



SAMSUNG ELECTRONICS Co., Ltd.,
Regulatory Compliance Group
IT R&D Center
416 Maetan3-Dong,
Yeongtong-gu, Suwon city,
Gyeonggi-Do, Korea 443-742

FCC CFR47 PART 22 & 24 SUBPART CERTIFICATION REPORT

Model Tested : **M8800C**
FCC ID(Requested) : **A3LSWDM8800C**
Report No : **FF-225-R1**
Job No : **FF-225**
Date issued : **October 20, 2008**

- Abstract -

All measurement reported herein accordance with FCC Rules, 47CFR Part2,
Part22, Part24.

Prepared By

KJ KWON – Test Engineer

Authorized By

WT JANG – Technical Manager

TABLE OF CONTENT

MEASUREMENT REPORT	Page
1. FCC CERTIFICATION INFORMATION	3
1.1. §2.1033 General Information	3
2. INTRODUCTION	4
2.1. General	4
3. MEASURING INSTRUMENT CALIBRATION	5
4. TEST EQUIPMENT LIST	6
5. DESCRIPTION OF TESTS	8
5.1. Effective Radiated Power / Equivalent Isotropic Radiated Power	8
5.2. Radiated Spurious & Harmonic Emission	9
5.3. Peak-Average Ratio	10
5.4. Occupied Bandwidth	11
5.5. Spurious and Harmonic Emission at Antenna Terminal	11
5.5.1. Occupied Bandwidth Emission Limits	11
5.5.2. Conducted Spurious Emission	13
5.6. Frequency Stability / Temperature Variation	14
6. TEST DATA	15
6.1. Effective Radiated Power (E.R.P.)	15
6.2. Equivalent Isotropic Radiated Power (E.I.R.P.)	16
6.3. GSM850 Radiated Spurious & Harmonic measurement	17
6.4. GSM1900 Radiated Spurious & Harmonic measurement	18
6.5. GSM850 Radiated Spurious & Harmonic Conversion Table	19
6.6. GSM1900 Radiated Spurious & Harmonic Conversion Table	20
6.7. Frequency Stability	21
6.7.1. GSM850 Frequency Stability Table	21
6.7.2. GSM850 Frequency Stability Graph	22
6.7.3. GSM1900 Frequency Stability Table	24
6.7.4. GSM1900 Frequency Stability Graph	25
7. CONCLUSION	27
8. TEST PLOTS	28



MEASUREMENT REPORT

1. FCC Certification Information

The following information is in accordance with FCC Rules, 47CFR Part2, Subpart J, Sections 2.1033 – 2.1055.

1.1. §2.1033 General Information

- Applicant Name : SAMSUNG ELECTRONICS CO., LTD.
- Address : 416 Maetan3-Dong, Yeongtong-gu, Suwon City
Gyeonggi-Do, Korea 443-742
- Attention : SungJoo KIM, Engineering Manager (QA Lab)
- FCC ID : A3LSWDM8800C
- Quantity : Quantity production is planned
- Emission Designators : 246KGXW(GSM850), 244KG7W(GSM850 EDGE)
245KGXW(GSM1900), 244KG7W(GSM1900 EDGE)
- Tx Freq. Range : 824.2 - 848.8MHz (GSM850)
1850.2MHz - 1909.8MHz (GSM1900)
- Rx Freq. Range : 869.2 - 893.8 MHz (GSM850)
1930.2MHz - 1989.8MHz (GSM1900)
- Max. Power Rating : 0.944 W ERP GSM850 (29.75 dBm)
1.081 W EIRP GSM1900 (30.34 dBm)
0.424 W ERP GSM850 EDGE(26.27dBm)
0.653 W EIRP GSM1900 EDGE(28.15dBm)
- FCC Classification(s) : PCS Licensed Portable Tx Held to Ear (PCE)
- Equipment (EUT) Type : 850/1900 GSM/EDGE Phone with Bluetooth
- Frequency Tolerance : $\pm 0.00025\%$ (2.5ppm)
- FCC Rule Part(s) : §24(E), §22(H), §2.
- Dates of Test : October 14 - 15, 2008
- Place of Test : SAMSUNG Lab,
- Test Report S/N : FF-225-R1

2. INTRODUCTION

2.1. General

These measurement test were conducted at **SAMSUNG ELECTRONICS CO., LTD(SUWON)**. The site address is 416 Maetan3-Dong, Yeongtong-gu, Suwon City, Gyeonggi-Do, Korea 443-742. The site have 1 Fully-anechoic chamber and measurement facility.



Figure1. Map of the Suwon City area.

Measurement Procedure

The radiated and spurious measurements were made Fully-anechoic chamber at a 3-meter test range (see Figure2). The equipment under testing was placed on the rotating device at the same height and at a distance of 3-meters from the receive antenna. The rotating device which can rotate horizontal axis was mounted on the turn unit to facilitate rotation around a vertical axis. The measurement was made for each horizontal/vertical position combination with receive antenna horizontally polarized. This measurement was repeated with receive antenna vertically polarized. The substitution antenna will replace the EUT antenna at the same position and in vertical polarization. The frequency of the signal generator shall be set to the frequencies that were measured on the EUT. The signal generator, output level, shall be adjusted until an equal or a known related level to what was measured from the EUT is obtained in the spectrum analyzer. This level was recorded. For readings above 1 GHz, the above procedure is repeated using horn antennas and the difference between the gain of the horn and an isotropic antenna are taken into consideration.




Figure2. Photograph of 3m Fully-Anechoic Chamber

3. MEASURING INSTRUMENT CALIBRATION

The measuring equipment, which was utilized in performing the tests documented herein, has been calibrated in accordance with the manufacturer's recommendations for utilizing calibration equipment, which is traceable to recognized national standards.

4. TEST EQUIPMENT LIST

Name Of Equipment	Model	Serial No.	Due Date
Spectrum Analyzer	ESI26	836119/010	2008-10-17
	E4440A(3Hz~26.5GHz)	MY46187454	2009-03-03
	E4440A(3Hz~26.5GHz)	MY41000236	2009-04-15
	E4440A(3Hz~26.5GHz)	MY41000233	2009-07-24
Signal Generator	SMR20	835197/030	2008-12-05
Network Analyzer	8753E	JP38160590	2009-06-20
Power Sensor	E9300H	MY41495838	2009-09-12
	8481B	3318A10325	2009-09-28
	8485A	3318A19924	2009-10-01
Power Meter	E4417A	MY45101042	2009-09-12
	E4419B	GB41293846	2009-09-12
Pre-Amplifier	8449B	3008A00691	2008-12-24
Communication test set	8960	MY47510060	2009-03-03
	8960	GB42230535	2009-01-02
	8960	GB42360886	2009-07-08
Controller	CO2000	CO2000/424	Not Required
Turn Unit	CT0800	CT0800/057	Not Required
Rotating Device	DE3600-RH-PR	DE3600-RH-PR/050	Not Required
Antenna Master	MA4000	MA4000/204	Not Required
Horn Antenna	HF906	100134	2009-10-24
	HF906	360306/011	2010-06-13
	BBHA9120	9120D-637	2009-10-24
Dipole Antenna	UHA 9105	9105-2412	2009-11-07
	UHA 9105	9105-2413	2010-06-13
	3121C-DB4	9007-587	2009-04-16
Communication test set	CMU200	109162	2008-10-17
Receive Antenna	HL040	353255/019	2009-10-29
	HL040	353255/020	2010-06-13
Power Supply	E3640A	MY40003594	2009-06-20
	E3640A	MY40003595	2009-05-22
	E3632A	MY40022438	2009-03-03
Divider	11636B	51946	Not Required

Name Of Equipment	Model	Serial No.	Due Date
	11636B	51942	Not Required
	11636B	56913	Not Required
	11636B	56918	Not Required
High Pass Filter	WHK1.0/15G-10SS	1	Not Required
	WHK/3.0/18G-10SS	492	Not Required
	WHK/3.5/18G-10SS	4	Not Required
Environmental Chamber	SH-241	92000549	2008-11-15
	SH-241	92000548	2008-11-15
Shielded Fully Anechoic Chamber	CHAMBER	ANT0001	Not Required

5. DESCRIPTION OF TESTS

5.1. Effective Radiated Power / Equivalent Isotropic Radiated Power

Test Set-up for the ERP/EIRP TEST

Effective Radiated Power Output and Equivalent Isotropic Radiated Power output Measurements by Substitution Method according to ANSI/TIA/EIA-603-C-2004




Figure 3. Diagram of ERP/EIRP test Set-up

The EUT was placed on the rotating device at 3-meters from the receive antenna. The turn unit and rotating device was adjusted for the highest reading on the receive spectrum analyzer. For GSM signals, an average detector is used, with RBW=VBW=3MHz, SPAN=10MHz. A half-wave dipole was substituted in place of the EUT. This dipole antenna was driven by a signal generator and the level of the signal generator was adjusted to obtain the same receive spectrum analyzer reading. The conducted power at the terminals of dipole is measured. The ERP and EIRP are recorded. For readings above 1GHz, the above procedure is repeated using horn antennas and the difference between the gain of the horn and an isotropic or dipole antenna are taken into consideration.

5.2. Radiated Spurious & Harmonic Emission

Test Set-up for the Radiated Emission TEST

Radiated Spurious Emission Measurements by Substitution Method according to ANSI/TIA/EIA-603-C-2004




Figure 4. Diagram of Radiated Spurious & Harmonic test Set-up

The EUT was placed on the rotating device at 3-meters from the receive antenna. The turn unit and rotating device was adjusted for the highest reading on the receive spectrum analyzer. The Spectrum was investigated from 30MHz to the 10th Harmonic of the fundamental. A peak detector is used, with RBW=VBW=1MHz. The value that we could measure was only reported. A half-wave dipole was substituted in place of the EUT. This dipole antenna was driven by a signal generator and the level of the signal generator was adjusted to obtain the same receive spectrum analyzer reading. This spurious level is recorded. For readings above 1GHz, the above procedure is repeated using horn antennas and the difference between the gain of the horn and an isotropic or dipole antenna are taken into consideration.

SAMPLE CALCULATION

Example: Channel 661 , Second Harmonic(3760.00MHz)

The receive analyzer reading at 3meters with the EUT on the turntable was -81.0dBm . The gain of the substituted antenna is 8.1dBi . The signal generator connected to the substituted antenna terminals is adjusted to produce a reading of -81.0dBm of the receive analyzer. The loss of the cable between the signal generator and the terminals of the substituted antenna is 2.0dB at 3760.00MHz . So 6.1dB is added to the signal generator reading of -30.9dBm yielding -24.8dBm . The fundamental EIRP was 25.5dBm so this harmonic was $25.5\text{dBm} - (-24.8) = 50.3\text{dBc}$.

5.3. Peak-Average Ratio

A peak to average ratio measurement is performed at the conducted port of the EUT. An average and a peak trace are used on a spectrum analyzer to determine the largest deviation between the average and the peak power of the EUT in a given bandwidth.

5.4.Occupied Bandwidth

Test Procedure

The EUT was setup to maximum output power at its lowest channel. The occupied bandwidth was measured using a spectrum analyzer. The measurements are repeated for the highest and a middle channel. The EUT's occupied bandwidth is measured as the width of the signal between two points, one below the carrier center frequency and one above the carrier frequency, outside of which all emissions are attenuated at least 26dB below the transmitter power.

Plots of the EUT's occupied bandwidth are shown herein.

5.5. Spurious and Harmonic Emission at Antenna Terminal

5.5.1. Occupied Bandwidth Emission Limits

- (a) On any frequency outside a licensee's frequency block, the power of any emission shall be attenuated below the transmitter power (P) by at least $43 + 10 \log(P)$ dB.
- (b) Compliance with these provisions is based on the use of measurement instrumentation employing a resolution bandwidth of 1 MHz or greater. However, in the 1MHz bands immediately outside and adjacent to the frequency block a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed. The emission bandwidth is defined as the width of the signal between two points, one below the carrier center frequency and one above the carrier center frequency, outside of which all emission are attenuated at least 26 dB below the transmitter power.
- (c) When measuring the emission limits, the nominal carrier frequency shall be adjusted as close to the licensee's frequency block edges, both upper and lower, as the design permits.
- (d) The measurement of emission power can be expressed in peak or average values, provided they are expressed in the same parameters as the transmitter power.

BLOCK	Freq. Range (MHz) Transmitter (Tx)	Freq. Range (MHz) Receiver (Rx)
A	1850 – 1865	1930 – 1945
B	1870 – 1885	1950 – 1965
C	1895 – 1910	1975 – 1990
D	1865 – 1870	1945 – 1950
E	1885 – 1890	1965 – 1970
F	1890 – 1895	1970 – 1975

Table 1. Broadband PCS Service Frequency Blocks

BLOCK	Freq. Range (MHz) Transmitter (Tx)	Freq. Range (MHz) Receiver (Rx)
A* Low + A	824 ~ 835	869 ~ 880
B	835 ~ 845	880 ~ 890
A* High	845 ~ 846.5	890 ~ 891.5
B*	846.5 ~ 849	891.5 ~ 894

Table 2. Cellular Service Frequency Blocks

5.5.2. Conducted Spurious Emission

Minimum standard:

On any frequency outside a license frequency block, the power of any emission shall be attenuated below the transmitter power(P) by at least $43+10\log(P)$ dB. Limit equivalent to -13dBm, calculation shown below.

$$43 + 10\log(0.944 \text{ W}) = 42.75 \text{ dB}$$

$$29.75 \text{ dBm} - 42.75 \text{ dB} = -13 \text{ dBm}$$

Compliance with the out-of-band emissions requirement is based on test being performed with an analyzer resolution bandwidth of 1MHz. However in the 1MHz band immediately outside and adjacent to the frequency block a resolution bandwidth of at least 1% of the fundamental emissions bandwidth may be employed.

In case of GSM : $0.01 * 273\text{KHz} = 2.73\text{KHz}$
A Resolution BW of 3KHz was used for measurement at the band edges.

Test Procedure:

The EUT was setup to maximum output power at its lowest channel. The Resolution BW of the analyzer is set to 1% of the emission bandwidth to show compliance with the -13dBm limit, in the 1MHz bands immediately outside and adjacent to the edge of the frequency block. The measurements are repeated for the EUT's highest channel. For the Out-of-Band measurements a 1MHz RBW was used to scan from 10MHz to 10GHz. (GSM1900 Mode : 10MHz to 20GHz). A display line was placed at -13dBm to show compliance. The high, lowest and a middle channel were tested for out of band measurements.

Plots are shown herein.

5.6. Frequency Stability / Temperature Variation

The frequency stability of the transmitter is measured by:

- a.) Temperature: The temperature is carried from -30°C to +60°C using an environmental chamber.
- b.) Primary Supply Voltage: The primary supply voltage is varied from 85% to 115% of the voltage normally at the input to the device or at the power supply terminals if cables are not normally supplied.

Specification- The frequency stability shall be sufficient to ensure that the fundamental emission stays within the authorized frequency block. The frequency stability of the transmitter shall be maintained within ± 0.00025 ($\pm 2.5\text{ppm}$) of the center frequency.

Time Period and Procedure:

1. The carrier frequency of the transmitter and the individual oscillators is measured at room temperature (25°C to 27°C to provide a reference).
2. The equipment is subjected to an overnight "soak" at -30°C without any power applied.
3. After the overnight "soak" at -30°C (Usually 14~16 hours), the equipment is turned on in a "standby" condition for one minute before applying power to the transmitter. Measurement of the carrier frequency of the transmitter and the individual oscillators is made within a three minute interval after applying to the transmitter.
4. Frequency measurements are made at 10°C interval up to room temperature. At least a period of one and one half-hour is provided to allow stabilization of the equipment at each temperature level.
5. Again the transmitter carrier frequency and the individual oscillators is measured at room temperature to begin measurement of the upper temperature levels.
6. Frequency measurements are at 10 intervals starting at -30°C up to +60°C allowing at least two hours at each temperature for stabilization. In all measurements the frequency is measured within three minutes after re-applying power to the transmitter.
7. The artificial load is mounted external to the temperature chamber.

NOTE : The EUT is tested down to the battery endpoint.

6. TEST DATA

6.1. Effective Radiated Power (E.R.P.)

Supply Voltage : 3.7VDC

Modulation : GSM850

■ Reference level

Frequency (MHz)	Output (dBm)	Polarization (H/V)	S/A (dBm)	Ant gain (dBd)	Ref level (dBm)
824.20	26.00	H	-11.30	-0.67	-10.63
		V	-11.56	-0.67	-10.89
836.60	29.00	H	-8.77	-0.73	-8.04
		V	-8.30	-0.73	-7.57
848.80	30.00	H	-9.63	-0.79	-8.84
		V	-8.50	-0.79	-7.71

■ Result

Frequency (MHz)	Tested level (dBm)	Polarization (H/V)	Azimuth (angle)	ERP (dBm)	ERP (W)	Battery
824.20	-10.11	H	279/80	26.52	0.449	Standard
836.60	-8.40	H	280/90	28.64	0.731	Standard
848.80	-9.09	H	282/80	29.75	0.944	Standard

■ EDGE Result

Frequency (MHz)	Tested level (dBm)	Polarization (H/V)	Azimuth (angle)	ERP (dBm)	ERP (W)	Battery
848.80	-12.69	H	282/80	26.27	0.424	Standard

NOTE : Standard batteries are the only battery options for this phone

- All modes of operation were investigated, and the worst-case results are reported.

Radiated measurements at 3 meters by Substitution Method

6.2. Equivalent Isotropic Radiated Power (E.I.R.P.)

Supply Voltage : 3.7VDC

Modulation : GSM 1900

■ Reference level

Frequency (MHz)	Output (dBm)	Polarization (H/V)	S/A (dBm)	Ant gain (dBi)	Ref level (dBm)
1850.20	28.00	H	-10.96	9.70	-20.66
		V	-11.22	9.70	-20.92
1880.00	30.00	H	-9.75	9.70	-19.45
		V	-9.43	9.70	-19.13
1909.80	30.00	H	-9.73	9.70	-19.43
		V	-9.59	9.70	-19.29

■ Result

Frequency (MHz)	Tested level (dBm)	Polarization (H/V)	Azimuth (angle)	EIRP (dBm)	EIRP (W)	Battery
1850.20	-21.05	H	289/180	27.61	0.577	Standard
1880.00	-18.79	V	329/110	30.34	1.081	Standard
1909.80	-19.42	V	255/80	29.87	0.971	Standard

■ EDGE Result

Frequency (MHz)	Tested level (dBm)	Polarization (H/V)	Azimuth (angle)	EIRP (dBm)	EIRP (W)	Battery
1880.00	-20.98	V	329/110	28.15	0.653	Standard

NOTE : Standard batteries are the only battery options for this phone

- All modes of operation were investigated, and the worst-case results are reported.

Radiated measurements at 3 meters by Substitution Method

6.3. GSM850 Radiated Spurious & Harmonic measurement

Operating Frequency : 824.20 MHz(Low), 836.60MHz(Middle), 848.80MHz(High)

Measured Output Power : 29.75 dBm = 0.944 W

Modulation Signal : GSM850

Limit : $43 + 10\log_{10}(P) = 42.75 \text{ dBc}$

■ Result

Channel	Harmonic	Frequency (MHz)	From EUT Tested level (dBm)	Result (dBc)	POL (H/V)
128	2	1648.40	-57.73	75.52	V
	3	2472.60	-61.43	74.87	V
	4	3296.80	-67.07	76.53	V
	5	4121.00	-	-	-
	6	4945.20	-	-	-
	7	5769.40	-	-	-
190	2	1673.20	-57.61	73.87	V
	3	2509.80	-61.43	74.35	H
	4	3346.40	-67.33	76.62	V
	5	4183.00	-	-	-
	6	5019.60	-	-	-
	7	5856.20	-	-	-
251	2	1697.60	-55.62	72.76	V
	3	2546.40	-58.66	71.85	H
	4	3395.20	-66.51	75.94	V
	5	4244.00	-	-	-
	6	5092.80	-	-	-
	7	5941.60	-	-	-

NOTE :

1. "-" Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. The spectrum is measured from 30MHz to the 10th harmonic and All modes of operation were investigated, and the worst-case results are reported..

Radiated Spurious Emission measurements at 3 meters by Substitution Method

6.4. GSM1900 Radiated Spurious & Harmonic measurement

Operating Frequency : 1850.2 MHz(Low), 1880.00 MHz(Middle), 1909.80 MHz(High)

Measured Output Power : 30.34 dBm = 1.081 W

Modulation Signal : GSM1900

Limit : $43 + 10\log_{10}(P) = 43.34$ dBc

■ Result

Channel	Harmonic	Frequency (MHz)	From EUT Tested level (dBm)	Result (dBc)	POL (H/V)
512	2	3700.40	-67.05	72.73	V
	3	5550.60	-65.32	66.40	H
	4	7400.80	-67.00	62.86	V
	5	9251.00	-	-	-
	6	11101.20	-	-	-
	7	12951.40	-	-	-
661	2	3760.00	-66.89	72.37	V
	3	5640.00	-66.71	67.02	V
	4	7520.00	-66.92	62.73	V
	5	9400.00	-	-	-
	6	11280.00	-	-	-
	7	13160.00	-	-	-
810	2	3819.60	-66.67	71.66	V
	3	5729.40	-64.29	64.24	V
	4	7639.20	-66.19	61.68	V
	5	9549.00	-	-	-
	6	11458.80	-	-	-
	7	13368.60	-	-	-

NOTE :

1. "-" Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. The spectrum is measured from 30MHz to the 10th harmonic and All modes of operation were investigated, and the worst-case results are reported.

Radiated Spurious Emission measurements at 3 meters by Substitution Method

6.5. GSM850 Radiated Spurious & Harmonic Conversion Table

Date : 2008. 10. 15

Test Engineer : KJ KWON

- ① Tx Cable loss
- ② Tx Horn Ant Gain
- ③ Tx Level to radiate - 13dBm
- ④ ESI Level received from Tx with - 13dBm
- ⑤ Tested Level from EUT
- ⑥ = ERP+2.14 - (-13 + ⑤ - ④)

CH	Har	Frequency (MHz)	① Tx C/L dB	②Tx Horn Gain dBi	③Tx Level dBm	④ ESI Level : H dBm	④ ESI Level : V dBm	⑤Tested EUT Level : H dBm	⑤Tested EUT Level : H dBm	⑥ Result EUT : H (dBc)	⑥ Result EUT : V (dBc)
128	2	1648.40	-9.15	9.50	-13.40	-25.78	-25.24	-58.16	-57.73	76.40	75.52
	3	2472.60	-11.48	10.70	-12.20	-30.65	-30.96	-61.48	-61.43	75.02	74.87
	4	3296.80	-13.42	12.30	-11.90	-34.30	-34.88	-67.26	-67.07	77.08	76.53
	5	4121.00	-14.84	12.50	-10.70	-37.37	-37.16	-	-	-	-
	6	4945.20	-16.67	12.70	-9.00	-39.95	-40.17	-	-	-	-
	7	5769.40	-18.06	12.90	-7.80	-42.25	-42.16	-	-	-	-
190	2	1673.20	-9.17	9.50	-13.30	-26.45	-26.15	-58.27	-57.61	76.12	73.87
	3	2509.80	-11.54	10.70	-12.20	-30.90	-30.96	-61.43	-62.91	74.35	76.16
	4	3346.40	-13.45	12.30	-11.80	-34.28	-34.36	-67.42	-67.33	77.19	76.62
	5	4183.00	-15.11	12.50	-10.40	-36.90	-37.13	-	-	-	-
	6	5019.60	-16.96	12.70	-8.70	-40.04	-40.64	-	-	-	-
	7	5856.20	-18.34	12.90	-7.60	-42.75	-42.94	-	-	-	-
251	2	1697.60	-9.21	9.50	-13.30	-26.64	-26.78	-57.33	-55.62	74.72	72.76
	3	2546.40	-11.56	10.70	-12.10	-30.32	-30.81	-58.66	-60.32	71.85	72.27
	4	3395.20	-13.35	12.30	-11.90	-34.25	-34.55	-67.28	-66.51	76.81	75.94
	5	4244.00	-15.26	12.50	-10.20	-37.07	-37.26	-	-	-	-
	6	5092.80	-17.03	12.70	-8.70	-40.12	-40.75	-	-	-	-
	7	5941.60	-18.49	12.90	-7.40	-43.10	-42.67	-	-	-	-

6.6. GSM1900 Radiated Spurious & Harmonic Conversion Table

Date : 2008. 10. 15

Test Engineer : KJ KWON

- ① Tx Cable loss
- ② Tx Horn Ant Gain
- ③ Tx Level to radiate - 13dBm
- ④ ESI Level received from Tx with - 13dBm
- ⑤ Tested Level from EUT
- ⑥ = EIRP - (-13 + ⑤ - ④)

CH	Har	Frequency (MHz)	① Tx C/L dB	②Tx Horn Gain dBi	③Tx Level dBm	④ ESI Level : H dBm	④ ESI Level : V dBm	⑤Tested EUT Level : H dBm	⑤Tested EUT Level : H dBm	⑥ Result EUT : H (dBc)	⑥ Result EUT : V (dBc)
512	2	3700.40	-14.12	12.40	-11.30	-37.56	-37.66	-68.54	-67.05	74.32	72.73
	3	5550.60	-17.80	12.90	-8.10	-42.26	-42.74	-65.32	-66.65	66.40	67.25
	4	7400.80	-20.57	10.50	-2.90	-47.18	-47.48	-68.29	-67.00	64.45	62.86
	5	9251.00	-23.73	11.20	-0.50	-51.10	-51.20	-	-	-	-
	6	11101.20	-26.86	11.60	2.30	-55.84	-55.59	-	-	-	-
	7	12951.40	-28.72	12.90	2.80	-58.86	-59.09	-	-	-	-
661	2	3760.00	-14.21	12.40	-11.20	-37.94	-37.86	-67.88	-66.89	73.28	72.37
	3	5640.00	-17.89	12.90	-8.00	-42.89	-43.03	-67.25	-66.71	67.70	67.02
	4	7520.00	-20.69	10.60	-2.90	-47.23	-47.53	-68.44	-66.92	64.55	62.73
	5	9400.00	-23.29	11.60	-1.30	-51.90	-51.21	-	-	-	-
	6	11280.00	-26.43	12.10	1.30	-56.00	-56.21	-	-	-	-
	7	13160.00	-28.29	12.80	2.50	-58.97	-59.23	-	-	-	-
810	2	3819.60	-14.27	12.40	-11.10	-38.02	-38.35	-67.55	-66.67	72.87	71.66
	3	5729.40	-17.95	13.00	-8.00	-43.49	-43.39	-66.34	-64.29	66.19	64.24
	4	7639.20	-21.02	11.20	-3.20	-47.61	-47.85	-68.41	-66.19	64.14	61.68
	5	9549.00	-23.65	11.70	-1.00	-52.29	-52.76	-	-	-	-
	6	11458.80	-26.89	11.70	2.20	-56.01	-56.16	-	-	-	-
	7	13368.60	-28.44	12.30	3.10	-59.88	-60.15	-	-	-	-

6.7. Frequency Stability

6.7.1. GSM850 Frequency Stability Table

Operating Frequency : 836,600,000 Hz

Channel : 190

Reference Voltage : 3.7VDC


Deviation Limit : ± 0.00025 % or 2.5ppm

Voltage (%)	Power (VDC)	Temp. (°C)	Frequency Error (Hz)	Frequency (Hz)	Deviation (%)	ppm
100%	3.70	+20(Ref)	-6.80	836,599,993	-0.000001	-0.008
100%		-30	27.40	836,600,027	0.000003	0.033
100%		-20	20.00	836,600,020	0.000002	0.024
100%		-10	-8.30	836,599,992	-0.000001	-0.010
100%		0	-23.40	836,599,977	-0.000003	-0.028
100%		+10	2.40	836,600,002	0.000000	0.003
100%		+20	-6.80	836,599,993	-0.000001	-0.008
100%		+30	-22.80	836,599,977	-0.000003	-0.027
100%		+40	2.90	836,600,003	0.000000	0.003
100%		+50	8.70	836,600,009	0.000001	0.010
100%		+60	-22.30	836,599,978	-0.000003	-0.027
85%	3.35	+20	-33.10	836,599,967	-0.000004	-0.040
115%	4.26	+20	15.10	836,600,015	0.000002	0.018
Batt.Endpoint	3.35	+20	-33.10	836,599,967	-0.000004	-0.040


Note : The temperature is varied from -30 °C to +60 °C using an environmental chamber.

The EUT is tested down to the battery end point.

6.7.2. GSM850 Frequency Stability Graph



Zoom IN



6.7.3. GSM1900 Frequency Stability Table

Operating Frequency : 1,880,000,000 Hz

Channel : 661

Reference Voltage : 3.7VDC


Deviation Limit : ± 0.00025 % or 2.5ppm

Voltage (%)	Power (VDC)	Temp. (°C)	Frequency Error (Hz)	Frequency (Hz)	Deviation (%)	ppm
100%	3.70	+20(Ref)	-16.70	1,879,999,983	-0.000001	-0.009
100%		-30	30.20	1,880,000,030	0.000002	0.016
100%		-20	-3.30	1,879,999,997	0.000000	-0.002
100%		-10	-14.00	1,879,999,986	-0.000001	-0.007
100%		0	-38.10	1,879,999,962	-0.000002	-0.020
100%		+10	36.30	1,880,000,036	0.000002	0.019
100%		+20	-16.70	1,879,999,983	-0.000001	-0.009
100%		+30	4.30	1,880,000,004	0.000000	0.002
100%		+40	12.00	1,880,000,012	0.000001	0.006
100%		+50	-33.00	1,879,999,967	-0.000002	-0.018
100%		+60	-1.50	1,879,999,999	0.000000	-0.001
85%	3.35	+20	-22.20	1,879,999,978	-0.000001	-0.012
115%	4.26	+20	28.70	1,880,000,029	0.000002	0.015
Batt.Endpoint	3.35	+20	-22.20	1,879,999,978	-0.000001	-0.012


Note : The temperature is varied from -30 °C to +60 °C using an environmental chamber.

The EUT is tested down to the battery end point.

6.7.4. GSM1900 Frequency Stability Graph



Zoom IN





7. CONCLUSION

The data collected shows that the SAMSUNG 850/1900 GSM/EDGE Phone with Bluetooth.
FCC ID : A3LSWDM8800C complies with all the requirements of Parts 2,22,24 of the FCC Rules.

8. TEST PLOTS



GSM850





Agilent

R T

Freq/Channel









Control	Transmit Power										TCH Parms																				
Transmit Power Setup ▾	<table><tr><td></td><td>Burst 1</td><td>Burst 2</td><td>Burst 3</td><td>Burst 4</td></tr><tr><td>Burst Power</td><td>32.37</td><td>----</td><td>----</td><td>----</td></tr><tr><td>Estimated Carrier Power</td><td>32.37</td><td>----</td><td>----</td><td>----</td></tr></table>											Burst 1	Burst 2	Burst 3	Burst 4	Burst Power	32.37	----	----	----	Estimated Carrier Power	32.37	----	----	----	Downlink Traffic Power					
												Burst 1	Burst 2	Burst 3	Burst 4																
											Burst Power	32.37	----	----	----																
	Estimated Carrier Power	32.37	----	----	----																										
	Traffic Band																														
GS1850																															
Single										Traffic Channel																					
										128																					
Phase & Frequency Error										MS TX Level																					
										5																					
Swap Window Positions	<table><tr><td></td><td>Peak Phase °</td><td>RMS Phase °</td><td>Frequency Hz</td></tr><tr><td>Minimum</td><td>2.40</td><td>1.06</td><td>-34.17</td></tr><tr><td>Maximum</td><td>5.66</td><td>1.40</td><td>-18.07</td></tr><tr><td>Average</td><td>4.10</td><td>1.22</td><td>-29.49</td></tr><tr><td>Pass/Fail</td><td>Pass</td><td>Pass</td><td>Pass</td></tr></table>											Peak Phase °	RMS Phase °	Frequency Hz	Minimum	2.40	1.06	-34.17	Maximum	5.66	1.40	-18.07	Average	4.10	1.22	-29.49	Pass/Fail	Pass	Pass	Pass	Channel Mode Setup
												Peak Phase °	RMS Phase °	Frequency Hz																	
											Minimum	2.40	1.06	-34.17																	
											Maximum	5.66	1.40	-18.07																	
											Average	4.10	1.22	-29.49																	
Pass/Fail	Pass	Pass	Pass																												
50 / 50 Single										Return																					
1 of 2			Active Cell Connected				Sys Type: GSM		1 of 2																						
			IntRef	Offset	R T																										


Control	Transmit Power										TCH Parms															
Transmit Power Setup ▾	<table><tr><td></td><td>Burst 1</td><td>Burst 2</td><td>Burst 3</td><td>Burst 4</td></tr><tr><td>Burst Power</td><td>32.27</td><td>----</td><td>----</td><td>----</td></tr><tr><td>Estimated Carrier Power</td><td>32.27</td><td>----</td><td>----</td><td>----</td></tr></table>											Burst 1	Burst 2	Burst 3	Burst 4	Burst Power	32.27	----	----	----	Estimated Carrier Power	32.27	----	----	----	Downlink Traffic Power
												Burst 1	Burst 2	Burst 3	Burst 4											
											Burst Power	32.27	----	----	----											
											Estimated Carrier Power	32.27	----	----	----											
	Traffic Band																									
GS1850																										
	Single										Traffic Channel															
											190															
											MS TX Level															
											5															
											Channel Mode Setup															
											Return															
	50 / 50 Single																									
			Active Cell Connected				Sys Type: GSM																			
1 of 2				IntRef	Offset	R T					1 of 2															

Control	Transmit Power								TCH Parms																									
Transmit Power Setup	<table border="1"> <thead> <tr> <th></th> <th>Burst 1</th> <th>Burst 2</th> <th>Burst 3</th> <th>Burst 4</th> </tr> </thead> <tbody> <tr> <td>Burst Power</td> <td>32.01</td> <td>----</td> <td>----</td> <td>----</td> </tr> <tr> <td>Estimated Carrier Power</td> <td>32.01</td> <td>----</td> <td>----</td> <td>----</td> </tr> </tbody> </table>									Burst 1	Burst 2	Burst 3	Burst 4	Burst Power	32.01	----	----	----	Estimated Carrier Power	32.01	----	----	----	Downlink Traffic Power										
									Burst 1	Burst 2	Burst 3	Burst 4																						
Burst Power									32.01	----	----	----																						
Estimated Carrier Power									32.01	----	----	----																						
	Traffic Band																																	
	GS1850																																	
	Traffic Channel																																	
	251																																	
	MS TX Level																																	
	5																																	
Swap Window Positions	<table border="1"> <thead> <tr> <th colspan="4">Phase & Frequency Error</th> </tr> <tr> <th></th> <th>Peak Phase °</th> <th>RMS Phase °</th> <th>Frequency Hz</th> </tr> </thead> <tbody> <tr> <td>Minimum</td> <td>2.42</td> <td>1.07</td> <td>-49.75</td> </tr> <tr> <td>Maximum</td> <td>5.10</td> <td>1.35</td> <td>-38.84</td> </tr> <tr> <td>Average</td> <td>4.16</td> <td>1.20</td> <td>-44.41</td> </tr> <tr> <td>Pass/Fail</td> <td>Pass</td> <td>Pass</td> <td>Pass</td> </tr> </tbody> </table>								Phase & Frequency Error					Peak Phase °	RMS Phase °	Frequency Hz	Minimum	2.42	1.07	-49.75	Maximum	5.10	1.35	-38.84	Average	4.16	1.20	-44.41	Pass/Fail	Pass	Pass	Pass	Channel Mode Setup	
Phase & Frequency Error																																		
									Peak Phase °	RMS Phase °	Frequency Hz																							
Minimum									2.42	1.07	-49.75																							
Maximum	5.10	1.35	-38.84																															
Average	4.16	1.20	-44.41																															
Pass/Fail	Pass	Pass	Pass																															
	Return																																	
	1 of 2																																	
	<table border="1"> <thead> <tr> <th colspan="4">Active Cell Connected</th> <th colspan="4">Sys Type: GSM</th> </tr> </thead> <tbody> <tr> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> </tbody> </table>								Active Cell Connected				Sys Type: GSM																					
Active Cell Connected				Sys Type: GSM																														
1 of 2				IntRef	Offset	R	T			1 of 2																								

Control	Power vs Time Graph								TCH Parms																	
Power vs Time Setup									Downlink Traffic Power																	
									Traffic Band																	
									GS1850																	
Change View									Traffic Channel																	
	128																									
	MS TX Level																									
	5																									
	Channel Mode Setup																									
	Return																									
	1 of 2																									
	<table border="1"> <thead> <tr> <th colspan="4">Active Cell Connected</th> <th colspan="4">Sys Type: GSM</th> </tr> </thead> <tbody> <tr> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> </tbody> </table>								Active Cell Connected				Sys Type: GSM													
Active Cell Connected				Sys Type: GSM																						
1 of 2				IntRef	Offset	R	T			1 of 2																







Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.128

Ref 33 dBm

Atten 40 dB

#Peak

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$\mathcal{E}(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center 1.255 GHz

Span 2.49 GHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 4.16 ms (601 pts)

Center Freq
1.25500000 GHz

Start Freq
10.0000000 MHz

Stop Freq
2.50000000 GHz

CF Step
249.000000 MHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.128

Mkr1 538.7 MHz

Ref 33 dBm

Atten 40 dB

-33.46 dBm

#Peak

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$\mathcal{E}(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center 414.6 MHz

Span 809.2 MHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 1.36 ms (601 pts)

Center Freq
414.600000 MHz

Start Freq
10.0000000 MHz

Stop Freq
819.200000 MHz

CF Step
80.9200000 MHz
Auto Man

Freq Offset
0.00000000 Hz


Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel



Center Freq
 1.66460000 GHz

Start Freq
 829.200000 MHz

Stop Freq
 2.50000000 GHz

CF Step
 167.080000 MHz
 Auto Man

Freq Offset
 0.00000000 Hz


Signal Track
 On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel



Center Freq
 6.25000000 GHz

Start Freq
 2.50000000 GHz

Stop Freq
 10.00000000 GHz

CF Step
 750.000000 MHz
 Auto Man

Freq Offset
 0.00000000 Hz

Signal Track
 On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.190

Ref 33 dBm

Atten 40 dB

#Peak

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$E(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center 1.255 GHz

Span 2.49 GHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 4.16 ms (601 pts)

Center Freq
1.25500000 GHz

Start Freq
10.0000000 MHz

Stop Freq
2.50000000 GHz

CF Step
249.000000 MHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.190

Mkr1 216.8 MHz

Ref 33 dBm

Atten 40 dB

-34.30 dBm

#Peak

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$E(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center 420.8 MHz

Span 821.6 MHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 1.4 ms (601 pts)

Center Freq
420.800000 MHz

Start Freq
10.0000000 MHz



Stop Freq
831.600000 MHz

CF Step
82.1600000 MHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved



Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.251

Ref 33 dBm

Atten 40 dB

#Peak

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$\mathcal{E}(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center 1.255 GHz

Span 2.49 GHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 4.16 ms (601 pts)

Center Freq
1.25500000 GHz

Start Freq
10.0000000 MHz

Stop Freq
2.50000000 GHz

CF Step
249.000000 MHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.251

Mkr1 736.8 MHz

Ref 33 dBm

Atten 40 dB

-33.83 dBm

#Peak

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$\mathcal{E}(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center 426.9 MHz

Span 833.8 MHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 1.4 ms (601 pts)

Center Freq
426.900000 MHz

Start Freq
10.0000000 MHz



Stop Freq
843.800000 MHz

CF Step
83.3800000 MHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved



Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.128

Ref 33 dBm

Atten 40 dB

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 824.000 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
824.000000 MHz

Start Freq
823.595000 MHz

Stop Freq
824.405000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.128

Mkr1 823.985 3 MHz

Ref 33 dBm

Atten 40 dB

-15.68 dBm

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 823.595 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
823.595000 MHz

Start Freq
823.190000 MHz

Stop Freq
824.000000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.251

Ref 33 dBm

Atten 40 dB

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$\mathcal{E}(f)$:

f>50k

Swp



Center 849.000 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
849.000000 MHz

Start Freq
848.595000 MHz

Stop Freq
849.405000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.251

Mkr1 849.010 7 MHz

Ref 33 dBm

Atten 40 dB

-16.90 dBm

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$\mathcal{E}(f)$:

f>50k

Swp



Center 849.405 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
849.405000 MHz

Start Freq
849.000000 MHz

Stop Freq
849.810000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz


Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

GSM1900


Agilent


R T



Agilent

R T





FCC ID : A3LSWDM8800C Transmit Power 512CH



Measurement/Instrument Screen																													
Control		Transmit Power						TCH Parms																					
Transmit Power Setup		<table><tr><td></td><td>Burst 1</td><td>Burst 2</td><td>Burst 3</td><td>Burst 4</td></tr><tr><td>Burst Power</td><td>29.20</td><td>----</td><td>----</td><td>----</td></tr><tr><td>Estimated Carrier Power</td><td>29.20</td><td>----</td><td>----</td><td>----</td></tr></table>							Burst 1	Burst 2	Burst 3	Burst 4	Burst Power	29.20	----	----	----	Estimated Carrier Power	29.20	----	----	----	Downlink Traffic Power						
	Burst 1							Burst 2	Burst 3	Burst 4																			
Burst Power	29.20							----	----	----																			
Estimated Carrier Power	29.20							----	----	----																			
Swap Window Positions		Traffic Band																											
		PCS																											
		Traffic Channel																											
		512																											
50 / 50		Phase & Frequency Error						RIS TX Level																					
		<table><tr><td></td><td>Peak Phase °</td><td>RMS Phase °</td><td>Frequency Hz</td></tr><tr><td>Minimum</td><td>3.47</td><td>1.22</td><td>-73.93</td></tr><tr><td>Maximum</td><td>7.27</td><td>1.77</td><td>-45.87</td></tr><tr><td>Average</td><td>5.03</td><td>1.51</td><td>-63.06</td></tr><tr><td>Pass/Fail</td><td>Pass</td><td>Pass</td><td>Pass</td></tr></table>							Peak Phase °	RMS Phase °	Frequency Hz	Minimum	3.47	1.22	-73.93	Maximum	7.27	1.77	-45.87	Average	5.03	1.51	-63.06	Pass/Fail	Pass	Pass	Pass	Channel Mode Setup	
									Peak Phase °	RMS Phase °	Frequency Hz																		
								Minimum	3.47	1.22	-73.93																		
Maximum	7.27							1.77	-45.87																				
Average	5.03	1.51	-63.06																										
Pass/Fail	Pass	Pass	Pass																										
1 of 2		Single						Return																					
		Background		Active Cell Connected			Sys Type: GSM																						
				IntRef Offset R T																									
								1 of 2																					



FCC ID : A3LSWDM8800C Transmit Power 661CH



Measurement/Instrument Screen																															
Control		Transmit Power						TCH Parms																							
Transmit Power Setup ▾		<table border="1"> <thead> <tr> <th></th> <th>Burst 1</th> <th>Burst 2</th> <th>Burst 3</th> <th>Burst 4</th> </tr> </thead> <tbody> <tr> <td>Burst Power</td> <td>29.38</td> <td>----</td> <td>----</td> <td>----</td> </tr> <tr> <td>Estimated Carrier Power</td> <td>29.38</td> <td>----</td> <td>----</td> <td>----</td> </tr> </tbody> </table>							Burst 1	Burst 2	Burst 3	Burst 4	Burst Power	29.38	----	----	----	Estimated Carrier Power	29.38	----	----	----	Downlink Traffic Power ▾								
									Burst 1	Burst 2	Burst 3	Burst 4																			
								Burst Power	29.38	----	----	----																			
								Estimated Carrier Power	29.38	----	----	----																			
Traffic Band																															
Swap Window Positions		Single <table border="1"> <thead> <tr> <th></th> <th>Peak Phase °</th> <th>RMS Phase °</th> <th>Frequency Hz</th> </tr> </thead> <tbody> <tr> <td>Minimum</td> <td>3.24</td> <td>1.15</td> <td>-86.60</td> </tr> <tr> <td>Maximum</td> <td>6.38</td> <td>1.83</td> <td>-65.93</td> </tr> <tr> <td>Average</td> <td>4.67</td> <td>1.49</td> <td>-78.13</td> </tr> <tr> <td>Pass/Fail</td> <td>Pass</td> <td>Pass</td> <td>Pass</td> </tr> </tbody> </table> 50 / 50 Single							Peak Phase °	RMS Phase °	Frequency Hz	Minimum	3.24	1.15	-86.60	Maximum	6.38	1.83	-65.93	Average	4.67	1.49	-78.13	Pass/Fail	Pass	Pass	Pass	Traffic Channel			
									Peak Phase °	RMS Phase °	Frequency Hz																				
								Minimum	3.24	1.15	-86.60																				
								Maximum	6.38	1.83	-65.93																				
Average	4.67	1.49	-78.13																												
Pass/Fail	Pass	Pass	Pass																												
661																															
MS TX Level																															
0																															
1 of 2		Background Active Cell Connected Sys Type: GSM IntRef Offset R T						Channel Mode Setup ▾																							
								Return																							
								1 of 2																							



FCC ID : A3LSWDM8800C Transmit Power 810CH

Measurement/Instrument Screen																															
Control		Transmit Power						TCH Parms																							
Transmit Power Setup ▾		<table border="1"> <thead> <tr> <th></th> <th>Burst 1</th> <th>Burst 2</th> <th>Burst 3</th> <th>Burst 4</th> </tr> </thead> <tbody> <tr> <td>Burst Power</td> <td>29.31</td> <td>----</td> <td>----</td> <td>----</td> </tr> <tr> <td>Estimated Carrier Power</td> <td>29.31</td> <td>----</td> <td>----</td> <td>----</td> </tr> </tbody> </table>							Burst 1	Burst 2	Burst 3	Burst 4	Burst Power	29.31	----	----	----	Estimated Carrier Power	29.31	----	----	----	Downlink Traffic Power ▾								
									Burst 1	Burst 2	Burst 3	Burst 4																			
								Burst Power	29.31	----	----	----																			
								Estimated Carrier Power	29.31	----	----	----																			
Traffic Band																															
Swap Window Positions		Single <table border="1"> <thead> <tr> <th></th> <th>Peak Phase °</th> <th>RMS Phase °</th> <th>Frequency Hz</th> </tr> </thead> <tbody> <tr> <td>Minimum</td> <td>3.55</td> <td>1.38</td> <td>-62.34</td> </tr> <tr> <td>Maximum</td> <td>8.51</td> <td>2.05</td> <td>-40.78</td> </tr> <tr> <td>Average</td> <td>5.06</td> <td>1.66</td> <td>-52.10</td> </tr> <tr> <td>Pass/Fail</td> <td>Pass</td> <td>Pass</td> <td>Pass</td> </tr> </tbody> </table> 50 / 50 Single							Peak Phase °	RMS Phase °	Frequency Hz	Minimum	3.55	1.38	-62.34	Maximum	8.51	2.05	-40.78	Average	5.06	1.66	-52.10	Pass/Fail	Pass	Pass	Pass	Traffic Channel			
									Peak Phase °	RMS Phase °	Frequency Hz																				
								Minimum	3.55	1.38	-62.34																				
								Maximum	8.51	2.05	-40.78																				
Average	5.06	1.66	-52.10																												
Pass/Fail	Pass	Pass	Pass																												
810																															
MS TX Level																															
0																															
1 of 2		Background Active Cell Connected Sys Type: GSM IntRef Offset R T						Channel Mode Setup ▾																							
								Return																							
								1 of 2																							










Agilent

R T

Freq/Channel



Center Freq
2.17885000 GHz

Start Freq
1.85770000 GHz

Stop Freq
2.50000000 GHz

CF Step
64.2300000 MHz
Auto Man

Freq Offset
0.00000000 Hz


Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel



Center Freq
11.2500000 GHz

Start Freq
2.50000000 GHz

Stop Freq
20.0000000 GHz

CF Step
1.75000000 GHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.661

Ref 30 dBm

Atten 40 dB

#Peak

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$\mathcal{E}(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center Freq

1.25500000 GHz

Start Freq

10.00000000 MHz

Stop Freq

2.50000000 GHz

CF Step

249.0000000 MHz

Auto

Man

Freq Offset

0.00000000 Hz

Signal Track

On

Off

Center 1.255 GHz

Span 2.49 GHz

#Res BW 1 MHz

#VBW 1 MHz

Sweep 4.16 ms (601 pts)

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Cond Spur Ch.661

Ref 30 dBm

Atten 40 dB

Mkr1 618 MHz

-32.19 dBm

#Peak

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

LgAv

M1 S2

S3 FC

$\mathcal{E}(f)$:

FTun

Swp

AC Coupled: unspecified below 20 MHz

Center Freq

941.250000 MHz

Start Freq

10.00000000 MHz

Stop Freq

1.87250000 GHz

CF Step

186.250000 MHz

Auto

Man

Freq Offset

0.00000000 Hz

Signal Track

On

Off

Center 941 MHz



Span 1.863 GHz



#Res BW 1 MHz



#VBW 1 MHz

Sweep 3.12 ms (601 pts)

File Operation Status, C:\TEMP.GIF file saved







Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.512

Ref 30 dBm

Atten 40 dB

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$\mathcal{E}(f)$:

f>50k

Swp



Center 1.850 000 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.85000000 GHz

Start Freq
1.84959500 GHz

Stop Freq
1.85040500 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.512

Mkr1 1.849 993 3 GHz

Ref 30 dBm

Atten 40 dB

-19.84 dBm

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$\mathcal{E}(f)$:

f>50k

Swp



Center 1.849 595 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.84959500 GHz

Start Freq
1.84919000 GHz

Stop Freq
1.85000000 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.810

Ref 30 dBm

Atten 40 dB

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$\mathcal{E}(f)$:

f>50k

Swp



Center 1.910 000 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.91000000 GHz

Start Freq
1.90959500 GHz

Stop Freq
1.91040500 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.810

Mkr1 1.910 014 8 GHz

Ref 30 dBm

Atten 40 dB

-17.77 dBm

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$\mathcal{E}(f)$:

f>50k

Swp



Center 1.910 405 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.91040500 GHz

Start Freq
1.91000000 GHz

Stop Freq
1.91081000 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

FCC ID:A3LSWDM8800C P.A.R Ch.661

▲ Mkr1 0 Hz

Ref 35.95 dBm

Atten 40 dB

-0.09 dB

#Avg

Log

10

dB/

Offst

8.71

dB

#LgAv

V1 V2

S3 FC

£(f):

FTun

Swp

Center 1.880 000 GHz

Span 5 MHz

#Res BW 3 MHz

VBW 3 MHz

Sweep 1 ms (601 pts)

Center Freq
1.88000000 GHz

Start Freq
1.87750000 GHz

Stop Freq
1.88250000 GHz

CF Step
500.000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off



Copyright 2000-2006 Agilent Technologies


EDGE850



Agilent

R T





FCC ID : A3LSWDM8800C Transmit Power 128CH EDGE

Measurement/Instrument Screen									
Control		EGPRS Transmit Power						PDCH Params	
EGPRS Transmit Power Setup ▾		EPSK Burst Power			EPSK Est Carrier Power			Downlink Traffic Power	
		Minimum		Maximum		Minimum		Maximum	
		25.64 dBm		26.70 dBm		26.26 dBm		26.28 dBm	
		Average		Std Dev		Average		Std Dev	
		26.21 dBm		0.21 dBm		26.27 dBm		0.00 dBm	
		200 / 200						Single	
								HS TX Level ▾	
								Modulation Coding Scheme ▾	
								Return	
				Active Cell Transferring			Sys Type: EGPRS		
1 of 2					IntRef	Offset	R	T	
							1 of 2		

Measurement/Instrument Screen												
Control		EGPRS Transmit Power								PDCH Parms		
EGPRS Transmit Power Setup ▾		EPSK Burst Power				EPSK Est Carrier Power				Downlink Traffic Power ▾		
		Minimum		Maximum		Minimum		Maximum		Traffic Band		
		25.44 dBm		26.72 dBm		26.19 dBm		26.21 dBm		GS1850		
		Average		Std Dev		Average		Std Dev		Traffic Channel		
		26.12 dBm		0.23 dBm		26.20 dBm		0.00 dBm		190		
		200 /200						Single				

Measurement/Instrument Screen												
Control		EGPRS Transmit Power								PDCH Parms		
EGPRS Transmit Power Setup ▾		EPSC Burst Power				EPSC Est Carrier Power				Downlink Traffic Power ▾		
		Minimum		Maximum		Minimum		Maximum		Traffic Band		
		25.30 dBm		26.53 dBm		26.00 dBm		26.02 dBm		GS1850		
		Average		Std Dev		Average		Std Dev		Traffic Channel		
		25.95 dBm		0.22 dBm		26.01 dBm		0.00 dBm		251		
		200 /200								Single		

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.128 EDGE

Ref 27 dBm

Atten 30 dB

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 824.000 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
824.000000 MHz

Start Freq
823.595000 MHz

Stop Freq
824.405000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.128 EDGE

Mkr1 823.977 3 MHz

Ref 27 dBm

Atten 30 dB

-22.98 dBm

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 823.595 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
823.595000 MHz

Start Freq
823.190000 MHz

Stop Freq
824.000000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.251 EDGE

Ref 27 dBm

Atten 30 dB

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 849.000 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
849.000000 MHz

Start Freq
848.595000 MHz

Stop Freq
849.405000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.251 EDGE

Mkr1 849.016 0 MHz

Ref 27 dBm

Atten 30 dB

-24.23 dBm

#Avg

Log

10

dB/

Offst

7.76

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 849.405 0 MHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
849.405000 MHz

Start Freq
849.000000 MHz

Stop Freq
849.810000 MHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz



Signal Track
On Off


File Operation Status, C:\TEMP.GIF file saved



Agilent

R T





FCC ID : A3LSWDM8800C Transmit Power 512CH EDGE

Measurement/Instrument Screen												
Control		EGPRS Transmit Power							PDCH Params			
EGPRS Transmit Power Setup ▾	EPSK Burst Power				EPSK Est Carrier Power			Downlink Traffic Power				
	Minimum		Maximum		Minimum		Maximum		Traffic Band			
	24.24 dBm		25.33 dBm		24.89 dBm		24.91 dBm		PCS			
	Average		Std Dev		Average		Std Dev		Traffic Channel			
	24.82 dBm		0.21 dBm		24.90 dBm		0.00 dBm		512			
	200 / 200				Single							
								MS TX Level				
							Modulation Coding Scheme					
							Return					
		Active Cell Transferring				Sys Type: EGPRS						
1 of 2						IntRef	Offset	R T			1 of 2	

Measurement/Instrument Screen												
Control		EGPRS Transmit Power								PDCH Params		
EGPRS Transmit Power Setup ▾		EPSK Burst Power				EPSK Est Carrier Power				Downlink Traffic Power		
		Minimum		Maximum		Minimum		Maximum		Traffic Band		
		24.46 dBm		25.58 dBm		25.07 dBm		25.10 dBm		PCS		
		Average		Std Dev		Average		Std Dev		Traffic Channel		
		25.02 dBm		0.23 dBm		25.08 dBm		0.01 dBm		661		
		200 / 200								Single		
										HS TX Level		
										Modulation Coding Scheme		
1 of 2				Active Cell Transferring				Sys Type: EGPRS			1 of 2	
				IntRef		Offset		R T				

Measurement/Instrument Screen										
Control	EGPRS Transmit Power								PDCH Params	
EGPRS Transmit Power Setup ▾	EP SK Burst Power				EP SK Est Carrier Power				Downlink Traffic Power	
	Minimum		Maximum		Minimum		Maximum		Traffic Band	
	24.43 dBm		25.63 dBm		24.98 dBm		25.00 dBm		PCS	
	Average		Std Dev		Average		Std Dev		Traffic Channel	
	24.93 dBm		0.21 dBm		24.99 dBm		0.00 dBm		810	
	200 / 200				Single					
									HS TX Level	
									Modulation Coding Scheme	
									Return	
			Active Cell Transferring				Sys Type: EGPRS			
1 of 2						IntRef	Offset	R	T	1 of 2

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.512 EDGE

Ref 26 dBm

Atten 30 dB

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

E(f):

f>50k

Swp



Center 1.850 000 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.85000000 GHz

Start Freq
1.84959500 GHz

Stop Freq
1.85040500 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.512 EDGE

Mkr1 1.849 975 9 GHz

Ref 26 dBm

Atten 30 dB

-22.42 dBm

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

E(f):

f>50k

Swp



Center 1.849 595 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.84959500 GHz

Start Freq
1.84919000 GHz

Stop Freq
1.85000000 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.810 EDGE

Ref 26 dBm

Atten 30 dB

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 1.910 000 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.91000000 GHz

Start Freq
1.90959500 GHz

Stop Freq
1.91040500 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

Agilent

R T

Freq/Channel

FCC ID:A3LSWDM8800C Band Edge Ch.810 EDGE

Mkr1 1.910 023 2 GHz

Ref 26 dBm

Atten 30 dB

-24.70 dBm

#Avg

Log

10

dB/

Offst

8.71

dB

DI

-13.0

dBm

PAvg


M1 S2

S3 FC

$E(f)$:

f>50k

Swp



Center 1.910 405 0 GHz

Span 810 kHz

#Res BW 3 kHz

#VBW 3 kHz

Sweep 343.2 ms (601 pts)

Center Freq
1.91040500 GHz

Start Freq
1.91000000 GHz

Stop Freq
1.91081000 GHz

CF Step
81.0000000 kHz
Auto Man

Freq Offset
0.00000000 Hz

Signal Track
On Off

File Operation Status, C:\TEMP.GIF file saved

