

**RadioShack, A Division of Tandy Corporation**

Application  
For  
Certification

900MHz Cordless Telephone

**(FCC ID: AAO4301101)**

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Limited

FCC ID: AAO4301101

WO# 98075262  
CKL/at  
September 9, 1998

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Limited

FCC ID: AAO4301101

**LIST OF EXHIBITS**

*INTRODUCTION*

|                   |                           |
|-------------------|---------------------------|
| <i>EXHIBIT 1:</i> | General Description       |
| <i>EXHIBIT 2:</i> | System Test Configuration |
| <i>EXHIBIT 3:</i> | Emission Results          |
| <i>EXHIBIT 4:</i> | Equipment Photographs     |
| <i>EXHIBIT 5:</i> | Product Labelling         |
| <i>EXHIBIT 6:</i> | Technical Specifications  |
| <i>EXHIBIT 7:</i> | Instruction Manual        |
| <i>EXHIBIT 8:</i> | Security Code Information |

---

## INTERTEK TESTING SERVICES

---

### MEASUREMENT/TECHNICAL REPORT

**RadioShack, A Division of Tandy Corporation - MODEL: 43-1101(XX)**  
**FCC ID: AAO4301101**

This report concerns (check one:)      Original Grant   X        Class II Change       

Equipment Type: Low Power Transmitter (example: computer, modem, transmitter, etc.)  
\_\_\_\_\_

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes             No   X  

If yes, defer until : \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.  
\_\_\_\_\_

Transition Rules Request per 15.37?      Yes             No   X  

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [10-1-96 Edition] provision.  
\_\_\_\_\_

Report prepared by:

C. K. Lam  
Intertek Testing Services.  
2/F., Garment Centre,  
576 Castle Peak Road,  
Kowloon, Hong Kong.  
Phone:      852-2746-8218  
Fax:      852-2785-5487

---

## INTERTEK TESTING SERVICES

---

### Table of Contents

|                                                                  |    |
|------------------------------------------------------------------|----|
| 1.0 <b><u>General Description</u></b> .....                      | 2  |
| 1.1 Product Description .....                                    | 2  |
| 1.2 Related Submittal(s) Grants .....                            | 3  |
| 1.3 Test Methodology .....                                       | 3  |
| 1.4 Test Facility .....                                          | 3  |
| 2.0 <b><u>System Test Configuration</u></b> .....                | 5  |
| 2.1 Justification .....                                          | 5  |
| 2.2 EUT Exercising Software .....                                | 5  |
| 2.3 Support Equipment List and Description .....                 | 6  |
| 2.4 Equipment Modification .....                                 | 7  |
| 3.0 <b><u>Emission Results</u></b> .....                         | 9  |
| 3.1 Field Strength Calculation .....                             | 10 |
| 3.2 Radiated Emission Configuration Photograph - Base Unit ..... | 11 |
| 3.3 Radiated Emission Data - Base Unit .....                     | 12 |
| 3.4 Radiated Emission Configuration Photograph - Handset .....   | 16 |
| 3.5 Radiated Emission Configuration Data - Handset .....         | 17 |
| 3.6 Radiated Emission on the bandedge .....                      | 21 |
| 3.7 Line Conducted Configuration Photograph - Base Unit .....    | 23 |
| 3.8 Line Conducted Data - Base Unit .....                        | 24 |
| 4.0 <b><u>Equipment Photographs</u></b> .....                    | 27 |
| 5.0 <b><u>Product Labelling</u></b> .....                        | 29 |
| 6.0 <b><u>Technical Specifications</u></b> .....                 | 31 |
| 7.0 <b><u>Instruction Manual</u></b> .....                       | 33 |
| 8.0 <b><u>Security Code Information</u></b> .....                | 35 |

---

## INTERTEK TESTING SERVICES

---

### List of attached file

| Exhibit type          | File Description               | filename                     |
|-----------------------|--------------------------------|------------------------------|
| Cover Letter          | Letter of Agency               | letter.pdf                   |
| Test Report           | Test Report                    | report.doc                   |
| Operation Description | Technical Description          | descri.pdf                   |
| Test Setup Photo      | Radiated Emission for Base     | base.jpg                     |
| Test Setup Photo      | Radiated Emission for Handset  | handset.jpg                  |
| Test Report           | Emission Plot                  | emission.pdf                 |
| Test Setup Photo      | Conducted Emission             | conduct1.pdf, conduct2.jpg   |
| Test Report           | conducted emission test result | conduct.pdf                  |
| External Photo        | External Photo                 | ophoto1.jpg, ophoto2 .jpg    |
| Internal Photo        | Internal Photo                 | iphoto1.jpg to iphoto16 .jpg |
| Block Diagram         | Block Diagram                  | block.pdf                    |
| Schematics            | Circuit Diagram                | circuit.pdf                  |
| ID Label/Location     | Label Artwork and Location     | label.pdf                    |
| User Manual           | User Manual                    | manual.pdf                   |

---

INTERTEK TESTING SERVICES

---

**EXHIBIT 1**  
**GENERAL DESCRIPTION**

## INTERTEK TESTING SERVICES

---

### 1.0 **General Description**

#### 1.1 Product Description

The 43-1101(XX) is a 900 MHz Cordless Phone. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The handset unit consists of a keypad with twelve standard keys (0,...9,\*,#), 6 function keys (Mute, Memory, Redial/Pause, Ringer Adjust, Flash & Intercom), and one channel switch key. A talk key is provided to control pick/release telephone line in a toggle base.

The base unit has a page key, which is used to page the handset unit.

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

## INTERTEK TESTING SERVICES

---

### 1.2 Related Submittal(s) Grants

This is an Application for Certification of a cordless telephone system. Two transmitters are included in this Application. This specific report details the emission characteristics of each transmitter. The receivers are subject to the verification authorization process, in accordance with 15.101(b). A verification report has been prepared for the receiver sections of each device. The device is also subject to Part 68 Registration.

### 1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

**EXHIBIT 2**  
**SYSTEM TEST CONFIGURATION**

### 2.0 **System Test Configuration**

#### 2.1 Justification

For emission testing, the equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). During testing, all cables were manipulated to produce worst case emissions. The handset was powered by a fully charged battery.

For the measurements, the EUT is attached to a cardboard box and placed on the wooden turntable. If the base unit attaches to peripherals, they are connected and operational (as typical as possible). The handset is remotely located as far from the antenna and the base as possible to ensure full power transmission from the base. Else, the base is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Detector function is in peak mode. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater. All emissions greater than 20 dB $\mu$ V/m are recorded.

Radiated emission measurement were performed from 30 MHz to tenth harmonics.

#### 2.2 EUT Exercising Software

The EUT exercise program used during radiated and conducted testing was designed to exercise the various system components in a manner similar to a typical use.

For emissions testing, the units were setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing.

## INTERTEK TESTING SERVICES

---

### 2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system (included inserted cards, which have grants) are:

#### *HARDWARE:*

The unit was operated standalone. An AC adapter (provided with the unit) was used to power the device. Its description is listed below.

- (1) AC adapter with two meter unshielded power cord permanently affixed.

#### *CABLES:*

- (1) Telecommunication cable with RJ11C connectors (1m, unshielded), terminated

#### *OTHERS:*

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by RadioShack, A Division of Tandy Corporation will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

*Confirmed by:*

*C. K. Lam  
Assistant Manager  
Intertek Testing Services  
Agent for RadioShack, A Division of Tandy Corporation*



\_\_\_\_\_  
Signature

\_\_\_\_\_  
October 13, 1998 Date

**EXHIBIT 3**  
**EMISSION RESULTS**

### 3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

---

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where            FS = Field Strength in dB $\mu$ V/m  
                    RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V  
                    CF = Cable Attenuation Factor in dB  
                    AF = Antenna Factor in dB  
                    AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where            FS = Field Strength in dB $\mu$ V/m  
                    RR = RA - AG in dB $\mu$ V  
                    LF = CF + AF in dB

Assume a receiver reading of 52.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

|                               |                      |
|-------------------------------|----------------------|
| RA = 52.0 dB $\mu$ V/m        |                      |
| AF = 7.4 dB                   | RR = 23.0 dB $\mu$ V |
| CF = 1.6 dB                   | LF = 9.0 dB          |
| AG = 29.0 dB                  |                      |
| FS = RR + LF                  |                      |
| FS = 23 + 9 = 32 dB $\mu$ V/m |                      |

Level in  $\mu$ V/m = Common Antilogarithm [(32 dB $\mu$ V/m)/20] = 39.8  $\mu$ V/m

## INTERTEK TESTING SERVICES

---

### 3.2 Radiated Emission Configuration Photograph - Base Unit

Worst Case Radiated Emission

at 902.805 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: base.jpg

---

## INTERTEK TESTING SERVICES

---

### 3.3 Radiated Emission Data - Base Unit

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 3.0 dB

\*\*\*\*\*

#### ***TEST PERSONNEL:***



---

*Tester Signature*

Wilson S. K. Loke, Engineer  
*Typed/Printed Name*

October 13, 1998  
*Date*

---

## INTERTEK TESTING SERVICES

---

Company: RadioShack, A Division of Tandy Corporation  
Model: 43-1101(XX)  
Mode : TX-Channel 1

Date of Test: Augsut 25, 1998

Table 1, Base unit

### Radiated Emissions

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Amp<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | L i m i t<br>(dB $\mu$ V /m ) | M a r g i n<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|--------------------------|----------------------------------|-------------------------------|----------------------|
| H        | 902.805              | 75.0                     | 32.0                       | 16                       | 91.0                             | 94                            | -3.0                 |
| V        | 1805.610             | 57.3                     | 26.5                       | 34                       | 49.8                             | 54                            | -4.2                 |
| V        | *2708.415            | 42.1                     | 29.1                       | 34                       | 37.2                             | 54                            | -16.8                |
| H        | *3611.220            | 32.1                     | 32.8                       | 34                       | 30.9                             | 54                            | -23.1                |

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative value in the margin column shows emission below limit.
- Horn antenna and average detector are used for the emission over 1000MHz.
- \* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Wilson S. K. Loke

---

## INTERTEK TESTING SERVICES

---

Company: RadioShack, A Division of Tandy Corporation  
Model: 43-1101(XX)  
Mode : TX-Channel 20

Date of Test: Augsut 25, 1998

Table 2, Base unit

### Radiated Emissions

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Amp<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | L i m i t<br>(dB $\mu$ V /m ) | M a r g i n<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|--------------------------|----------------------------------|-------------------------------|----------------------|
| H        | 903.755              | 74.1                     | 32.0                       | 16                       | 90.1                             | 94                            | -3.9                 |
| V        | 1807.510             | 56.7                     | 26.5                       | 34                       | 49.2                             | 54                            | -4.8                 |
| V        | *2711.265            | 40.1                     | 29.1                       | 34                       | 35.2                             | 54                            | -18.8                |
| V        | *3615.020            | 33.9                     | 32.8                       | 34                       | 32.7                             | 54                            | -21.3                |

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative value in the margin column shows emission below limit.
- Horn antenna and average detector are used for the emission over 1000MHz.
- \* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Wilson S. K. Loke

---

## INTERTEK TESTING SERVICES

---

Company: RadioShack, A Division of Tandy Corporation  
Model: 43-1101(XX)  
Mode : TX-Channel 40

Date of Test: Augsut 25, 1998

Table 3, Base unit

### Radiated Emissions

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Amp<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | L i m i t<br>(dB $\mu$ V /m ) | M a r g i n<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|--------------------------|----------------------------------|-------------------------------|----------------------|
| H        | 904.755              | 74.7                     | 32.0                       | 16                       | 90.7                             | 94                            | -3.3                 |
| V        | 1809.510             | 57.5                     | 26.5                       | 34                       | 50.0                             | 54                            | -4.0                 |
| H        | *2714.265            | 37.5                     | 29.1                       | 34                       | 32.6                             | 54                            | -21.4                |
| H        | *3619.020            | 38.0                     | 32.8                       | 34                       | 36.8                             | 54                            | -17.2                |

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative value in the margin column shows emission below limit.
- Horn antenna and average detector are used for the emission over 1000MHz.
- \* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Wilson S. K. Loke

## INTERTEK TESTING SERVICES

---

### 3.4 Radiated Emission Configuration Photograph - Handset

Worst Case Radiated Emission

at 925.300 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: handset.jpg

## INTERTEK TESTING SERVICES

---

### 3.5 Radiated Emission Data - Handset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 5.9 dB

\*\*\*\*\*

#### ***TEST PERSONNEL:***



---

*Tester Signature*

Wilson S. K. Loke, Engineer

*Typed/Printed Name*

October 13, 1998

*Date*

---

## INTERTEK TESTING SERVICES

---

Company: RadioShack, A Division of Tandy Corporation  
Model: 43-1101(XX)  
Mode : TX-Channel 1

Date of Test: Augsut 25, 1998

Table 6, Handset

### Radiated Emissions

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Amp<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | L i m i t<br>(dB $\mu$ V /m ) | M a r g i n<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|--------------------------|----------------------------------|-------------------------------|----------------------|
| V        | 925.300              | 70.5                     | 33.0                       | 16                       | 87.5                             | 94                            | -6.5                 |
| V        | 1850.600             | 40.2                     | 26.5                       | 34                       | 32.7                             | 54                            | -21.3                |
| V        | *2775.900            | 47.4                     | 29.1                       | 34                       | 42.5                             | 54                            | -11.5                |
| V        | *3701.200            | 36.8                     | 32.8                       | 34                       | 35.6                             | 54                            | -18.4                |

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative value in the margin column shows emission below limit.
- Horn antenna and average detector are used for the emission over 1000MHz.
- \* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Test Engineer

---

## INTERTEK TESTING SERVICES

---

Company: RadioShack, A Division of Tandy Corporation  
Model: 43-1101(XX)  
Mode : TX-Channel 20

Date of Test: Augsut 25, 1998

Table 7, Handset

### Radiated Emissions

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Amp<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | L i m i t<br>(dB $\mu$ V /m ) | M a r g i n<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|--------------------------|----------------------------------|-------------------------------|----------------------|
| V        | 926.250              | 70.8                     | 33.0                       | 16                       | 87.8                             | 94                            | -6.2                 |
| V        | 1852.500             | 42.6                     | 26.5                       | 34                       | 35.1                             | 54                            | -18.9                |
| V        | *2778.750            | 48.5                     | 29.1                       | 34                       | 43.6                             | 54                            | -10.4                |
| V        | *3705.000            | 38.6                     | 32.8                       | 34                       | 37.4                             | 54                            | -16.6                |

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna and average detector are used for the emission over 1000MHz.

\* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Wilson S. K. Loke

---

## INTERTEK TESTING SERVICES

---

Company: RadioShack, A Division of Tandy Corporation  
Model: 43-1101(XX)  
Mode : TX-Channel 40

Date of Test: Augsut 25, 1998

Table 8, Handset

### Radiated Emissions

| Polarity | Frequency<br>(M H z) | Reading<br>(dB $\mu$ V ) | Antenna<br>Factor<br>(dB ) | Pre-Amp<br>Gain<br>(dB ) | Net<br>at 3m<br>(dB $\mu$ V /m ) | L i m i t<br>(dB $\mu$ V /m ) | M a r g i n<br>(dB ) |
|----------|----------------------|--------------------------|----------------------------|--------------------------|----------------------------------|-------------------------------|----------------------|
| V        | 927.250              | 71.1                     | 33.0                       | 16                       | 88.1                             | 94                            | -5.9                 |
| V        | 1854.500             | 41.7                     | 26.5                       | 34                       | 34.2                             | 54                            | -19.8                |
| V        | *2781.750            | 48.2                     | 29.1                       | 34                       | 43.3                             | 54                            | -10.7                |
| V        | *3709.192            | 38.0                     | 32.8                       | 34                       | 36.8                             | 54                            | -17.2                |

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative value in the margin column shows emission below limit.
- Horn antenna and average detector are used for the emission over 1000MHz.
- \* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Wilson S. K. Loke

### 3.6 Radiated Emission on the bandedge

The plot on the following page shows the fundamental emission is confined in the specified band. And there shows that the emissions are at least 60 dB below the carrier level at the band edge (902 and 928 MHz). It meets the requirement of Section 15.249(c).

**Emission Plot**

For electronic filing, the emission plots are saved with filename: emission.pdf.

3.7 Line Conducted Configuration Photograph - Base Unit

Worst Case Line-Conducted Configuration

at 3.595 MHz

For electronic filing, the worst case line-conducted configuration is saved with filename:  
conduct1.jpg and conduct2.jpg

## INTERTEK TESTING SERVICES

---

### 3.8 Line Conducted Emission Configuration Data

The data on the following pages list the significant emission frequencies, the limit, and the margin of compliance.

Judgement : Passed by 16.3 dB

\* All readings are peak unless stated otherwise.

#### ***TEST PERSONNEL:***



---

*Tester Signature*

Wilson S. K. Loke, Engineer  
*Typed/Printed Name*

October 13, 1998  
*Date*

## INTERTEK TESTING SERVICES

---

Company: Integrated Display Technology Ltd.  
Model: 43-1101(XX)

Date of Test: Augsut 25, 1998

### **Conducted Emissions**

For electronic filing, the conducted emission test result are saved with filename: conduct.pdf

**EXHIBIT 4**  
**EQUIPMENT PHOTOGRAPHS**

### 4.0 **Equipment Photographs**

For electronic filing, the photographs are saved with filename: ophoto1.jpg to ophoto2.jpg and iphoto1.jpg to iphoto16.jpg.

**EXHIBIT 5**  
**PRODUCT LABELLING**

5.0 **Product Labelling**

For electronic filing, the FCC ID label and label location are saved with filename: label.pdf

**EXHIBIT 6**  
**TECHNICAL SPECIFICATIONS**

6.0 **Technical Specifications**

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf.

**EXHIBIT 7**  
**INSTRUCTION MANUAL**

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

Please note that the required FCC Information to the User can be found on Page 19 and 20 of this manual.

This manual will be provided to the end-user with each unit sold/leased in the United States.

**EXHIBIT 8**  
**SECURITY CODE INFORMATION**

## INTERTEK TESTING SERVICES

---

### 8.0 Security code information

The telephone has an internal security code with 65,536 possible combinations. Each time you place the HANDSET into the BASE, the code is randomly set to a new combination.