



EXHIBIT 2

Test Report Summary

Applicant: Nortel Networks

**For Class II Permissive Change
Certification on:**

AB6NT800SFRM



Test Report Summary for FCC Class II Permissive Change Equipment Authorization

FCC ID : AB6NT800SFRM Multi-carrier Flexible Radio Module

Document:	TRS_AB6NT800SFRM
Stream:	00
Issue:	03
Issue Date:	July 12, 2004
Security Status:	Nortel Networks Confidential
Author:	Thomas Wong

© 2002 Nortel Networks Limited

Disclaimer

The master of this document is stored on an electronic database and “write protected”. The protection can be altered by authorized persons only. Viewing of the master document electronically ensures access to the current issue. Any hardcopies must be regarded as uncontrolled copies.

Security Warning

The information disclosed herein is proprietary to Nortel Networks and not to be used by or disclosed by unauthorized persons without the written consent of Nortel Networks. The recipient of this document shall respect the security status of the information.

1 Introduction

This test report is submitted in accordance with the FCC Rules and Regulations, Part 2, Subpart J, Sections 2.1046 through 2.1057 for equipment authorization of Nortel Networks' CDMA 800 MHz Single-carrier Flexible Radio Module (SFRM). The 800 MHz_SFRM is intended for use in the Domestic Public Cellular Radio Telecommunications Service and is designed in accordance with the following standards:

- *CFR 47, Part 22, Subpart H, Subpart H, Cellular Radiotelephone Service[1]*
- *CFR 47, Part 2, Subpart J, Equipment Authorization Procedures - Equipment Authorization[2]*

1. Test Result Summary

Table 1 summarizes the measurement results for the CDMA 800 MHz SFRM.

Table 1: Test Results Summary


FCC Measurement Specification	FCC Limit Specification	Description	Results	Test(s) Conducted by	Remarks
2.1046		RF Output Power		Nortel Networks	See Exhibit 2A
2.1049		Occupied Bandwidth		Nortel Networks	See Exhibit 2A
2.1051, 2.1057	22.901, 22.917	Spurious Emission at Antenna Terminals	Compliant	Nortel Networks	See Exhibit 2A
2.1053, 2.1057	22.901, 22.917	Field Strength of Spurious Radiation	Compliant	Sanmina Canada ULC	See Exhibit 2B
2.1055	22.355	Frequency Stability	Compliant	Nortel Networks	See Exhibit 2A

2. Engineering Declaration

The CDMA 800 MHz Single-carrier Flexible Radio has been tested in accordance with the requirements contained in the Federal Communication Rules and Regulations Part 2 and 22.

To the best of my knowledge, these tests were performed in accordance with good engineering practices using measurement procedures consistent with industry or commission standards or previous Commission correspondence or guidance and demonstrate that this equipment complies with the appropriate standards. All tests (including tests performed by Sanmina Canada ULC) were conducted on a representative sample of the equipment for which type acceptance/certification is sought.

Report Prepared by



Signature

Thomas Wong
Regulatory Prime
Nortel Networks
Calgary, Alberta

3. Type Acceptance Application Requirements

3.1 Name of Applicant

The applicant is Nortel Networks Inc.

3.2 Identification of Equipment

The equipment in this application for type acceptance is the Nortel's CDMA 800 MHz Single-carrier Flexible Radio Module (SFRM). The 800MHz SFRM is marketed under the model name 800MHz SFRM. The FCC ID number sought is AB6NT800SFRM.

3.3 Quantity Production

The 800MHz SFRM will be produced in quantity.

3.4 Type of Emissions

The 800MHz SFRM Assembly is designed to operate in digital mode. The emission type is F9W for IS95 mode and D9W for IS856. The emission designator is 1M25F9W for IS95 and 1M25D9W for IS856. The emission designators were determined based on requirements of FCC Rule Part 2, Subpart C - Emissions, section 2.201 and Section 2.202.

3.5 Frequency Range

The 800 MHz MFRM operates in the 800 MHz cellular band where the operating frequency ranges are 824 – 849 MHz for the receiver and 869 - 894 MHz for the transmitter. The following table shows the CDMA channels within this band meeting FCC requirements.

Band	CDMA Channel Number	Transmitter Center Frequency Assignment for Base Station (MHz)	Channel Meeting FCC Requirements
A''	991-1023	869.040-870.000	Non-compliance
A	1-16	870.030-870.480	Non-compliance
	17-283	870.510-878.490	Compliance
	284-333	878.520-879.990	Non-compliance
B	334-383	881.020-881.490	Non-compliance
	384-616	881.520-888.480	Compliance
	617-666	888.510-889.980	Non-compliance
A'	667-716	890.010-891.480	Non-compliance
B'	717-799	891.510-893.970	Non-compliance

3.6 Range of Operating Power

The 800 MHz SFRM range of operating RF power is 30 dBm to 43 dBm . The maximum RF power output is 43.06 dBm..

3.7 Complete Circuit Diagrams

The RF chain of the 800 MHz SFRM is made up mainly of Nortel's TRM (Transmit/Receive Module), SCPA (Single Channel Power Amplifier) from Powerwave, and DPM (Duplexer Preselector Module). Exhibit 8 contains the schematics of the TRM and Exhibit 9 contains the parts lists of the TRM.

The OEM SCPA 800 MHz power amplifier is approved under FCC Tx ID E675JS0061.

3.8 Tune-up Procedure

The tune-up tests will be performed as part of the factory testing on the SFRM. This procedure includes power output levels, spurious emissions, and occupied bandwidth. There are no end-user adjustments that will have any effect on these settings. No tune-up testing is required in the field.

3.9 Circuit Description for Frequency Determining and Stabilizing

The Global Positioning Satellite Timing Module (GPSTM) is the primary clock source in the system. It consists of two outputs:

EVEN_SEC Clock and,
SYS_CLK (at 8fc or 9.8304 MHz)

In addition, the GPSTM has a 10 MHz reference output that can be used to synchronize external measurement equipment during system testing.

The GPSTM distributes the primary clock signals directly to the Control Module (CM) and the CORE modules (see Exhibit 3) which in-turn distribute the clock signals to the digital modules and to the SFRM via the high speed optical link.

The GPSTM has a frequency stability of better than 1.0 part per billion.

3.10 Circuit Description for Suppression of Spurious Radiation

The Tx band pass filter in the DPM provides out of band emission rejection and permits only signals in the Tx band to the antenna for emission.

3.11 Circuit Description for Limiting Modulation

This systems employs digital modulation techniques producing CDMA forward and reverse channel air interfaces which are compatible with IS95A and IS856 technical standards.

4. Test Method and Test Result

4.1 Tests performed by Nortel Networks

RF Power Output

The maximum measured RF output power for IS95 carrier was 42.87 dBm.

The maximum measured RF output power for IS856 carrier was 43.2 dBm.

Occupied Bandwidth

The average maximum measured occupied bandwidth for IS95 carrier was 1,263 KHz.

The average maximum measured occupied bandwidth for IS856 carrier was 1,254.6 KHz.

Spurious Emissions at Antenna Terminals

The minimum pass margin for spurious Emissions with IS95 carrier:

1 MHz upper and lower band edge measurement was 11.19 dB.
50 MHz to 10 GHz measurements was 13.48 dB.

The minimum pass margin for spurious Emissions with IS856 carrier:

1 MHz upper and lower band edge measurement was 8.83 dB.
10 kHz to 10 GHz measurements was 11.53 dB.

Frequency Stability

The GPS module has a frequency stability of 0.8 ppb over the range of -5°C to 70°C .

Please refer to the Exhibit 2A and Exhibit 2C for all test setups and results in details provided by Nortel Networks.

4.2 Tests performed by Sanmina Canada ULC

Radiated Emission Test Results from 30 MHz to 9 GHz

The minimum pass margin: 34.52 dB for H-Pol
31.98 dB for V-Pol

Please refer to the Exhibit 2B for all test setups and results in details provided by Sanmina Canada ULC.