

	 MS ISO/IEC 17025 TESTING SAMM No. 0825																												
MOTOROLA PENANG ADV. COMM. LABORATORY Motorola Solutions Malaysia Sdn Bhd Innoplex Plot 2A, Medan Bayan Lepas, Mukim 12 S.W.D, 11900 Bayan Lepas, Penang, Malaysia.	FCC / ISCED TEST REPORT Report Revision : Rev.A																												
<table><tr><td>Date/s Tested</td><td>: 12-NOV-2018 - 16-NOV-2018</td></tr><tr><td>Report Issue Date</td><td>: 18-DEC-2018</td></tr><tr><td>Manufacturer/Location</td><td>: Motorola Solutions Malaysia Sdn Bhd</td></tr><tr><td>Requestor</td><td>: TAI, WEN QI</td></tr><tr><td>Product Type</td><td>: Mobile</td></tr><tr><td>Model Number</td><td>: AAM28UMC9RA1AN</td></tr><tr><td>Frequency Band</td><td>: 806-870 / 896-941 MHz</td></tr><tr><td>Low / Max RF Output Power</td><td>: 6.3Watts / 10Watts / 36Watts / 42Watts</td></tr><tr><td>Application Name</td><td>: Motorola Solutions Inc</td></tr><tr><td>Manufacturer Address</td><td>: Plot 2, Bayan Lepas Technoplex, 11900 Bayan Lepas, Penang, Malaysia</td></tr><tr><td>ISED Registrations</td><td>: 109AK</td></tr><tr><td>FCC Registrations</td><td>: 461337</td></tr><tr><td>Firmware Version</td><td>: R02.09.01.0001</td></tr></table>  The equipment was tested accordance to the requirement listed below: <table><tr><td>(LMR) FCC 47 CFR Part 24 / 90 ISED RSS- Gen / 119 / 134</td><td>PASS</td></tr></table>		Date/s Tested	: 12-NOV-2018 - 16-NOV-2018	Report Issue Date	: 18-DEC-2018	Manufacturer/Location	: Motorola Solutions Malaysia Sdn Bhd	Requestor	: TAI, WEN QI	Product Type	: Mobile	Model Number	: AAM28UMC9RA1AN	Frequency Band	: 806-870 / 896-941 MHz	Low / Max RF Output Power	: 6.3Watts / 10Watts / 36Watts / 42Watts	Application Name	: Motorola Solutions Inc	Manufacturer Address	: Plot 2, Bayan Lepas Technoplex, 11900 Bayan Lepas, Penang, Malaysia	ISED Registrations	: 109AK	FCC Registrations	: 461337	Firmware Version	: R02.09.01.0001	(LMR) FCC 47 CFR Part 24 / 90 ISED RSS- Gen / 119 / 134	PASS
Date/s Tested	: 12-NOV-2018 - 16-NOV-2018																												
Report Issue Date	: 18-DEC-2018																												
Manufacturer/Location	: Motorola Solutions Malaysia Sdn Bhd																												
Requestor	: TAI, WEN QI																												
Product Type	: Mobile																												
Model Number	: AAM28UMC9RA1AN																												
Frequency Band	: 806-870 / 896-941 MHz																												
Low / Max RF Output Power	: 6.3Watts / 10Watts / 36Watts / 42Watts																												
Application Name	: Motorola Solutions Inc																												
Manufacturer Address	: Plot 2, Bayan Lepas Technoplex, 11900 Bayan Lepas, Penang, Malaysia																												
ISED Registrations	: 109AK																												
FCC Registrations	: 461337																												
Firmware Version	: R02.09.01.0001																												
(LMR) FCC 47 CFR Part 24 / 90 ISED RSS- Gen / 119 / 134	PASS																												
This report shall not be reproduced without written approval from an officially designated representative of the Motorola Penang Adv. Comm. Laboratory. The results and statements contained in this report pertain only to the device(s) evaluated.																													
Prepared By:  Khor Wei Loong Test Personnel	Approved By:  Vincent Foong Responsible Engineer																												

Table of Contents

Report Revision History	3
1.0 General Information.....	4
2.0 Summary of Test Results	5
3.0 Measurement Uncertainty	6
4.0 Equipment List.....	7
5.0 Test Condition.....	10
5.1. Transmitter Test Conditions	10
6.0 Transmitter Test Parameters	11
6.1. RF Output Power	11
6.1.1. Test Setup.....	11
6.1.2. Test Result	11
6.2. Frequency Stability	12
6.2.1. Test Setup.....	12
6.2.2. Test Result	13
6.2.3. Test Limit.....	18
6.3. Audio Frequency Response	19
6.3.1. Test Setup.....	19
6.3.2. Test Result	20
6.3.3. Test Limit.....	21
6.4. Audio Low Pass Filter Response	22
6.4.1. Test Setup.....	22
6.4.2. Test Result	23
6.4.3. Test Limit.....	25
6.5. Modulation Limiting	26
6.5.1. Test Setup.....	26
6.5.2. Test Result	27
6.5.3. Test Limit.....	28
6.6. Occupied Bandwidth.....	29
6.6.1. Test Setup (Analog)	29
6.6.2. Test Result (Analog).....	30
6.6.3. Test Setup (Digital).....	45
6.6.4. Test Result (Digital).....	46
6.6.5. Test Limit.....	76
6.7. Band Edge Conducted Spurious Emission (Part 22)	77
6.7.1. Test Setup (Analog)	77
6.7.2. Test Result (Analog).....	77
6.7.3. Test Setup (Digital).....	78
6.7.4. Test Result (Digital).....	78
6.7.5. Test Limit.....	78
6.8. Transient Frequency Behavior.....	79
6.8.1. Test Setup.....	79
6.8.2. Test Result	79
6.8.3. Test Limit.....	80

6.9.	Adjacent Channel Power.....	81
6.9.1.	Test Setup (Analog)	81
6.9.2.	Test Result	81
6.9.3.	Test Setup (Digital).....	82
6.9.4.	Test Result	82
6.10.	Conducted Spurious Emission	85
6.10.1.	Test Setup.....	85
6.10.2.	Test Result (Analog)	86
6.10.3.	Test Result (Digital).....	98
6.10.4.	Test Limit.....	110
6.11.	Radiated Spurious Emission	111
6.11.1.	Test Setup.....	111
6.11.2.	Test Result (Analog)	112
6.11.3.	Test Result (Digital).....	123
6.11.4.	Test Limit.....	136
6.12.	Effective Radiated Power (ERP)	137
6.12.1.	Test Setup.....	137
6.12.2.	Test Result	137
6.12.3.	Test Limit.....	138
6.13.	GNSS (EIRP for 1559 - 1610MHz).....	139
6.13.1.	Test Setup.....	139
6.13.1.	Test Result	139
6.13.2.	Test Limit.....	140

Report Revision History

Revision History	Description	Date	Originator
Rev. A	Initial Report	18-Dec-2018	Khor Wei Loong

1.0 General Information

EUT Description:

Technologies	Land Mobile Radio (LMR)
Modulation Type	Analog, 4FSK

General Description of Applied Standards

The EUT is a RF Product. According to the specifications of the manufacturer, the EUT is to comply with the requirements of the following standards:

ANSI C63.4-2014

ANSI C63.26-2015

2.0 Summary of Test Results

FCC General Rules Part (47CFR)	ISED General Rules Part	Test Item	Result	Remark
2.1046, 22.565, 74.461, 74.534	RSS-119	RF Power Output	Pass	-
2.1055, 90.213, 22.355, 74.464, 74.561	-	Frequency Stability	Pass	-
2.1047, 74.463, 80.213	RSS-119	Audio Frequency Response	Pass	-
2.1047, 74.463, 80.213	RSS-119	Audio Low Pass Filter Response	Pass	-
2.1047, 74.463, 80.213	RSS-119	Modulation limiting	Pass	-
2.1049, 90.210, 22.359, 74.462, 74.535, 80.211(c), 80.211(f)	RSS-119	Occupied Bandwidth	Pass	16K0F3E – 15.0819kHz 11K0F3E – 9.9225kHz 10K0F3E – 8.7522kHz 7K60F1D – 7.5822kHz 7K60F1E – 7.5981kHz 7K60F1W – 7.5763kHz
22.359	-	Band Edge Conducted Spurious Emission	Pass	-
90.214	-	Transient Frequency Behavior	Pass	-
-	-	Adjacent Channel Power	NA	-
2.1053, 90.210, 22.359, 74.461, 74.861	RSS-119	Conducted Spurious Emissions	Pass	Highest Spur Level -20.37dBm
2.1053, 90.210, 22.359, 74.461, 74.861	RSS-119	Radiated Spurious Emission	Pass	Highest Radiated Emission Level -31.37dBm
-	-	GNSS (EIRP for 1559 – 1610MHz)	NA	-
24.132	RSS-134	Effective Radiated Power (ERP)	Pass	-

NA → Not Applicable

3.0 Measurement Uncertainty

Measurement	Frequency	Expanded Uncertainty (k=1.96) (±)
AC Power Line Conducted Spurious Emission	150KHz ~ 30MHz	3.43
Radiated Emissions up to 1 GHz	30MHz ~ 200MHz	5.01
	200MHz ~ 1000MHz	5.01
Radiated Emissions above 1 GHz	1GHz ~ 18GHz	5.01
	18GHz ~ 25GHz	5.01

4.0 Equipment List

FCC Analog ATE#1: (SW version: 2.4.5 & FCC_Frequency Stability 1.0.3 rev.)

Description	Model	Serial Number	Calibration Date	Calibration Due Date
Audio Analyzer	8903B	3011A10475	9-Jul-18	9-Jul-19
SIGNAL GENERATOR	2042	203001/904	8-Mar-18	9-Mar-19
MODULATION ANALYZER	8901B	3538A03696	3-Apr-18	3-Apr-19
DSA	36570A	MY42506781	6-Jul-18	6-Jul-19
POWER SENSOR	E9031A	MY41498969	17-Apr-18	17-Apr-19
POWER METER	E4416A	MY45101016	16-Jan-18	16-Jan-19
POWER SUPPLY	6031A	2430A00146	09-Apr-18	09-Apr-19
CHAMBER	SH-641	92009188	3-Apr-18	3-Apr-19
N to N RF Cable # 1	M17/128-RG400	NA	NA	NA
BNC to N RF Cable # 1	RG 58	NA	NA	NA
BNC to BNC RF Cable # 1	RG 58	NA	NA	NA
BNC to BNC RF Cable # 2	RG 58	NA	NA	NA
BNC to BNC RF Cable # 3	RG 58	NA	NA	NA
BNC to BNC RF Cable # 4	RG 58	NA	NA	NA
BNC to BNC RF Cable # 5	RG 58	NA	NA	NA
BNC to BNC RF Cable # 6	RG 58	NA	NA	NA
BNC to BNC RF Cable # 7	RG 58	NA	NA	NA
N to SMA RF Cable # 1	RG 58	NA	NA	NA
N to SMA RF Cable # 2	RG 58	NA	NA	NA
N to SMA RF Cable # 3	RG 58	NA	NA	NA
Aeroflex Attenuator 30dB	49-30-34-LIM	NA	NA	NA

FCC Transient ATE #1: (SW version: FCC Transient ATE_R1.1.1)

Description	Model	Serial Number	Calibration Date	Calibration Due Date
POWER SUPPLY	6032A	2818A03549	11-Jul-18	11-Jul-19
POWER SENSOR	E4412A	MY50290007	27-Jul-18	27-Jul-19
POWER METER	E4416A	GB41293240	2-Mar-18	2-Mar-19
ATTENUATORS/SWITCH DRIVER	11713A	2508A10141	CNR	CNR
STEP ATTENUATOR/11dB	8494G	MY42143006	16-Apr-18	16-Apr-19
STEP ATTENUATOR/110dB	8496G	MY421430125	16-Apr-18	16-Apr-19
OSCILLOSCOPE	MSO8104A	MY45002372	26-Jun-18	26-Jun-19
AUDIO ANALYZER	8903B	3729A17409	18-Jul-18	18-Jul-19
AUDIO ANALYZER	8903B	3413A14586	5-Dec-17	5-Dec-18
MODULATION ANALYZER	8901B	3403A04772	31-Mar-18	31-Mar-19
SIGNAL GENERATOR	8657A	3039A3205	5-Jul-18	5-Jul-19
SPECTRUM ANALYZER	E4440A	MY46185415	16-Aug-17	16-Aug-19
N to N RF Cable # 1	SF126/11N/11N	NA	NA	NA
N to N RF Cable # 2	M17/128-RG400	NA	NA	NA
N to N RF Cable # 3	M17/128-RG400	NA	NA	NA
N to N RF Cable # 4	M17/128-RG400	NA	NA	NA
N to N RF Cable # 5	M17/128-RG400	NA	NA	NA
N to N RF Cable # 6	M17/128-RG400	NA	NA	NA
N to N RF Cable # 7	M17/128-RG400	NA	NA	NA
N to N RF Cable # 8	M17/128-RG400	NA	NA	NA
N to N RF Cable # 9	M17/128-RG400	NA	NA	NA
BNC to BNC RF Cable # 1	RG 58	NA	NA	NA
BNC to BNC RF Cable # 2	RG 58	NA	NA	NA
BNC to BNC RF Cable # 3	RG 58	NA	NA	NA
BNC to BNC RF Cable # 4	RG 58	NA	NA	NA
BNC to BNC RF Cable # 5	RG 58	NA	NA	NA
BNC to BNC RF Cable # 6	RG 58	NA	NA	NA
BNC to N RF Cable # 1	RG 58	NA	NA	NA
Aeroflex Attenuator 10dB	49-10-43-LIM	NA	NA	NA
Aeroflex Attenuator 10dB	33-10-34-LIM	NA	NA	NA
SWITCH CONTROL UNIT	3488A	2719A36210	CNR	CNR

CONDUCTED SPUR EMISSION ATE # 1 (SW version: Conducted Spur ATE_rev 1.23.01)

Description	Model	Serial Number	Calibration Date	Calibration Due Date
SWITCH CONTROL UNIT	3488A	2719A32735	CNR	CNR
PSA Series Spectrum Analyzer	E4445A	MY46181732	16-Feb-17	16-Feb-19
POWER SUPPLY	6032A	3232A08203	9-Apr-18	9-Apr-19
HIGH PASS FILTER SWITCH BOX	-	CS001	5-Jul-18	5-Jul-19
N to N RF Cable # 1	SF126/11N/11N	NA	NA	NA
N to N RF Cable # 2	SF126/11N/11N	NA	NA	NA
BNC to BNC RF Cable # 1	RG 58	NA	NA	NA
Aeroflex Attenuator 30dB	49-30-43-LIM	NA	NA	NA
Aeroflex Attenuator 10dB	33-10-34-LIM	NA	NA	NA
Vector Signal Generator	SMU200A	103537	22-Jul-17	22-Jul-20

EMC Chamber 1

DESCRIPTION	MODEL	SERIAL NUMBER	CALIBRATION DATE	CALIBRATION DUE DATE
DRG HORN FREQ.	SAS-571	719	18-Jul-17	18-Jul-19
DRG HORN FREQ.	SAS-571	720	2-Mar-17	2-Mar-19
POWER SUPPLY	6032A	2615A-01178	13-Jun-18	13-Jun-19
MICROWAVE SIGNAL GENERATOR	SMP04	100131	12-Jul-18	11-Jul-19
EMI TEST RECEIVER	ESIB26	100017	11-Apr-18	11-Apr-19
EMI TEST RECEIVER	ESW44	101750	25-Jun-18	25-Jun-19
5m Semi-anechoic Chamber	S800-HX	J2308	CNR	CNR
BILOG ANTENNA	CBL6112D	30991	23-Apr-18	23-Apr-19
BILOG ANTENNA	CBL6112B	2964	16-Feb-18	16-Feb-20
DATA LOGGER	SDL500	A.016776	18-Mar-17	18-Mar-19
SYSTEM CONTROLLER	SC104V	050806-1	CNR	CNR
TURNTABLE FLUSH MOUNT 2M	FM2011	NA	CNR	CNR
ANTENNA POSITIONING TOWER	TLT2	NA	CNR	CNR
18 - 40GHz PREAMPLIFIER	Miteq Hi Gain Sucoflex	002	CNR	CNR
PREAMPLIFIER	PAM-0118P	361	CNR	CNR
Test Software	EMC_FCC_IC_Bluetooth_RE_Test			
Version	EMC_FCC_RE_v1.5.1			

CNR → Calibration Not Require

5.0 Test Condition

5.1. Transmitter Test Conditions


Test Item, (Channel Spacing)	Power (W)	Modulation	Test Frequency (MHz)	Tested By
RF Output Power	Low & Max	Analog	806.0125, 814.9875, 823.9875, 851.0125, 860.0125, 868.8875, 896.0125, 900.9875, 935.0125, 939.9875, 901.5, 940.5	Khor Wei Loong
Frequency Stability	Max	Analog	823.9875, 896.0125, 940.5	Khor Wei Loong
Audio Frequency Response (12.5kHz / 25kHz)	Max	Analog	823.9875, 896.0125	Khor Wei Loong
Audio Low Pass Filter Response (12.5kHz / 25kHz)	Max	Analog	823.9875, 896.0125	Khor Wei Loong
Modulation limiting (12.5kHz / 25kHz)	Max	Analog	823.9875, 896.0125	Khor Wei Loong
Occupied Bandwidth (12.5kHz)	Max	Analog, 4FSK	806.0125, 814.9875, 823.9875, 851.0125, 853.9875, 860.0125, 868.8875, 896.0125, 900.9875, 935.0125, 939.9875, 901.5, 940.5	Khor Wei Loong
Band Edge Conducted Spurious Emissions (Part 22) (12.5kHz / 20kHz / 25kHz)	Max	Analog, 4FSK	NA	Khor Wei Loong
Transient Frequency Behavior (UHF & VHF Band) (12.5kHz / 25kHz)	Max	Analog	NA	Khor Wei Loong
Adjacent Channel Power (700MHz Band) (12.5kHz)	Max	Analog	NA	NA
Conducted Spurious Emissions- (12.5kHz / 25kHz)	Low / Max	Analog, 4FSK	806.0125, 814.9875, 823.9875, 851.0125, 860.0125, 868.8875, 896.0125, 900.9875, 935.0125, 939.9875, 901.5, 940.5	Khor Wei Loong
Radiated Spurious Emission (12.5kHz / 25kHz)	Low / Max	Analog, 4FSK	806.0125, 814.9875, 823.9875, 851.0125, 860.0125, 868.8875, 896.0125, 900.9875, 935.0125, 939.9875, 901.5, 940.5	Nazrin& Qawiman
GNSS (EIRP for 1559 - 1610MHz) (12.5kHz / 25kHz)	Max	Analog	NA	NA
Effective Radiated Power (ERP) (12.5kHz / 25kHz)	Max	Analog	901.5, 940.5	Nazrin& Qawiman

NA → Not Applicable

6.0 Transmitter Test Parameters

6.1 RF Output Power

6.1.1 Test Setup




- 1) The DUT transmitter connected to Power Meter using the 30 dB attenuator and power sensor with above setup.
- 2) Path loss for the measurement included.
- 3) All the measurement was done at low, mid, high frequency for each band.
- 4) Record the power into the test report.

6.1.2 Test Result

Temperature	25°C				Remarks
Voltage (V)	13.2V				
Frequency (MHz)	Low Power (W)	Current (A)	Max Power (W)	Current (A)	
806.0125	10.3	5.16	40.8	10.85	
814.9875	10.4	5.16	40.5	10.84	
823.9875	10.5	5.08	40.6	10.54	
851.0125	9.5	4.6	41	9.96	
860.0125	9.66	4.49	40.8	9.64	
868.8875	9.99	4.33	40.7	9.5	
896.0125	10.4	4.28	34.3	8.81	
900.9875	9.93	4.28	34.3	9.04	
935.0125	10.5	4.63	36	9.33	
939.9875	10.5	4.55	35.2	8.73	
901.5	-	-	6.29	3.35	
940.5	-	-	6.28	3.44	

6.2. Frequency Stability

6.2.1. Test Setup




- 1) The DUT transmitter output port was connected to Modulation / Spectrum Analyzer.
- 2) Path loss for the measurement included.
- 3) Transmit the DUT and record the freq in MCF_{MHz} .
- 4) Test in 2 conditions:
 - Temperature: The frequency of the transmitter was measured from -30°C to 50°C.
 - Supply Voltage:
 - Mobile: The frequency of the transmitter was measured from 85% to 115% of the nominal operating input voltage.
 - Portable: The frequency of the transmitter was measured from nominal $\pm x\%$ as specified by the manufacturer
- 5) Calculate the ppm frequency error by the following:


$$ppm\ error = \left(\frac{MCF_{MHz}}{ACF_{MHz}} - 1 \right) * 10^6$$

Where: MCF_{MHz} is the Measured Carrier Frequency in MHz
 ACF_{MHz} is the Assigned Carrier Frequency in MHz


6.2.2. Test Result




Frequency / Channel Spacing	823.9875 MHz / 12.5 kHz				
Temperature, °C	25				
Voltage %	Voltage, V	Frequency, MHz	Frequency Stability, PPM	Spec (low) PPM	Spec (high) PPM
-20	10.560	823.987200	-0.364	-0.500	0.500
-15	11.220	823.987210	-0.352	-0.500	0.500
-10	11.880	823.987210	-0.352	-0.500	0.500
-5	12.540	823.987240	-0.316	-0.500	0.500
0	13.200	823.987410	-0.109	-0.500	0.500
5	13.860	823.987390	-0.133	-0.500	0.500
10	14.520	823.987320	-0.218	-0.500	0.500
15	15.180	823.987300	-0.243	-0.500	0.500
20	15.840	823.987260	-0.291	-0.500	0.500




Frequency / Channel Spacing	823.9875 MHz / 12.5 kHz			
Voltage, V	13.2			
Temperature, °C	Frequency, MHz	Frequency Stability, PPM	Spec (low) PPM	Spec (high) PPM
-30	823.987420	-0.097	-0.500	0.500
-20	823.987460	-0.049	-0.500	0.500
-10	823.987710	0.255	-0.500	0.500
0	823.987710	0.255	-0.500	0.500
10	823.987650	0.182	-0.500	0.500
20	823.987510	0.012	-0.500	0.500
30	823.987450	-0.061	-0.500	0.500
40	823.987450	-0.061	-0.500	0.500
50	823.987450	-0.061	-0.500	0.500
60	823.987530	0.036	-0.500	0.500




Frequency / Channel Spacing	896.0125MHz / 12.5 kHz				
Temperature, °C	25				
Voltage %	Voltage, V	Frequency, MHz	Frequency Stability, PPM	Spec (low) PPM	Spec (high) PPM
-20	10.560	896.012170	-0.368	-0.500	0.500
-15	11.220	896.012180	-0.357	-0.500	0.500
-10	11.880	896.012180	-0.357	-0.500	0.500
-5	12.540	896.012210	-0.324	-0.500	0.500
0	13.200	896.012430	-0.078	-0.500	0.500
5	13.860	896.012370	-0.145	-0.500	0.500
10	14.520	896.012320	-0.201	-0.500	0.500
15	15.180	896.012270	-0.257	-0.500	0.500
20	15.840	896.012240	-0.290	-0.500	0.500



Frequency / Channel Spacing	896.0125 MHz / 12.5 kHz			
Voltage, V	13.2			
Temperature, °C	Frequency, MHz	Frequency Stability, PPM	Spec (low) PPM	Spec (high) PPM
-30	896.012460	-0.045	-0.500	0.500
-20	896.012470	-0.033	-0.500	0.500
-10	896.012710	0.234	-0.500	0.500
0	896.012740	0.268	-0.500	0.500
10	896.012650	0.167	-0.500	0.500
20	896.012480	-0.022	-0.500	0.500
30	896.012340	-0.179	-0.500	0.500
40	896.012310	-0.212	-0.500	0.500
50	896.012310	-0.212	-0.500	0.500
60	896.012250	-0.279	-0.500	0.500



Frequency / Channel Spacing	940.5MHz / 12.5 kHz				
Temperature, °C	25				
Voltage %	Voltage, V	Frequency, MHz	Frequency Stability, PPM	Spec (low) PPM	Spec (high) PPM
-20	10.560	940.499640	-0.383	-0.500	0.500
-15	11.220	940.499640	-0.383	-0.500	0.500
-10	11.880	940.499680	-0.340	-0.500	0.500
-5	12.540	940.499660	-0.362	-0.500	0.500
0	13.200	940.499940	-0.064	-0.500	0.500
5	13.860	940.499820	-0.191	-0.500	0.500
10	14.520	940.499830	-0.181	-0.500	0.500
15	15.180	940.499740	-0.276	-0.500	0.500
20	15.840	940.499750	-0.266	-0.500	0.500




Frequency / Channel Spacing	940.5 MHz / 12.5 kHz			
Voltage, V	13.2			
Temperature, °C	Frequency, MHz	Frequency Stability, PPM	Spec (low) PPM	Spec (high) PPM
-30	940.499960	-0.043	-0.500	0.500
-20	940.499970	-0.032	-0.500	0.500
-10	940.500190	0.202	-0.500	0.500
0	940.500230	0.245	-0.500	0.500
10	940.500160	0.170	-0.500	0.500
20	940.499950	-0.053	-0.500	0.500
30	940.499880	-0.128	-0.500	0.500
40	940.499880	-0.128	-0.500	0.500
50	940.499880	-0.128	-0.500	0.500
60	940.499750	-0.266	-0.500	0.500

6.2.3. Test Limit

As per manufacturer declared spec +/- 0.5ppm



6.3. Audio Frequency Response


6.3.1. Test Setup



- 1) The DUT transmitter output port was connected to Modulation Analyzer.
- 2) Path loss for the measurement included.
- 3) Set the audio bandwidth filter to 15 kHz and 50 kHz.
- 4) Transmit the radio and set the audio analyzer to 1 kHz audio frequency and 20% of the Full rated system deviation.
- 5) On audio analyzer, set the rated level as reference to zero.
- 6) Vary the audio frequency from 300 Hz to 3 kHz. Record the change in dB on the audio analyzer.


6.3.2. Test Result







6.4. Audio Low Pass Filter Response


6.4.1. Test Setup




- 1) The DUT transmitter output port was connected to Modulation Analyzer.
- 2) Path loss for the measurement included.
- 3) Press 23.1SPCL on modulation analyzer to enable the external LO from Sigen.
- 4) Set the Sigen frequency to $F_c + 1.5$ MHz, RF output level to 0dBm without modulation.
- 5) Transmit the radio and set the audio analyzer to 1 kHz audio frequency and 60% of the Full rated system deviation.
- 6) Up the amplitude by 20dB.
- 7) On DSA, get the reference point to 0dB.
- 8) Vary the frequency on audio analyzer from 3 kHz to 20 kHz, record the audio tone from DSA.

6.4.2. Test Result





6.4.3. Test Limit



For audio frequencies above 3000 Hz, the audio response of the post limiter low-pass filter shall meet or exceed the following requirements:

- a) For equipment operating on 20, 25 or 30 kHz channel bandwidth in the 25 MHz to 174 MHz range:

At frequencies from 3000 Hz through 15,000 Hz the attenuation shall be greater than the attenuation at 1000 Hz by at least: $40 \log_{10}(f/3000)$ dB

where: f is the audio frequency in Hz.

At frequencies above 15,000 Hz, the attenuation shall be greater than the attenuation at 1000 Hz, by at least: 28 dB.

- b) For equipment operating with 25 kHz bandwidth channels between 406 and 512 MHz through 896 MHz, and between 929 MHz through 930 MHz:

At frequencies from 3000 Hz through 20,000 Hz, the attenuation shall be greater than the attenuation at 1000 Hz by at least: $60 \log_{10}(f/3000)$ dB

where: f is the audio frequency in Hz.

At frequencies above 20,000 Hz the attenuation shall be greater than the attenuation at 1000 Hz by at least: 50 dB.


- c) For equipment operating on channels between 896 MHz through 901 MHz, between 935 MHz through 940 MHz, and 12.5 or 15 kHz spaced channels in the frequency range 138-174 MHz and 406-512 MHz.

At frequencies from 3000 Hz through 20,000 Hz the attenuation shall be greater than the attenuation at 1000 Hz by at least: $100 \log_{10}(f/3000)$ dB

where: f is the audio frequency in Hz.



6.5. Modulation Limiting


6.5.1. Test Setup



- 1) The DUT transmitter output port was connected to Modulation Analyzer.
- 2) Path loss for the measurement included.
- 3) Set the audio bandwidth filter to 15 kHz.
- 4) Transmit the radio and set the audio analyzer to 1 kHz audio frequency and 60% of the Full rated system deviation.
- 5) Record the frequency deviation as 0dB input level at 1kHz audio frequency.
- 6) Repeat the step and record the frequency deviation from -20 dB to 20dB by 5 dB increments and different audio freq 300 Hz, 2.5 kHz and 3 kHz.

6.5.2. Test Result






- 6.5.3. Test Limit**
Modulation Limiting shall not exceed 100 percent.

6.6. Occupied Bandwidth



6.6.1. Test Setup (Analog)







- 1) The DUT transmitter output port was connected to Modulation Analyzer.
- 2) Set the audio bandwidth filter to 15 kHz low pass filter and 50 kHz high pass filter.
- 3) Transmit the radio and set the audio analyzer to 2.5 kHz audio frequency and 50% of the rated deviation. Up the amplitude by 16 dB. Dekey the DUT.
- 4) Path loss for the measurement included.
- 5) Select the Occupied Bandwidth measurement for 99% Emissions Bandwidth Measurement.
- 6) Key in the F_c and Resolution Bandwidth (1 ~ 5 % of emission designator).
- 7) Transmit the DUT and record the occupied Bandwidth frequency.
- 8) Preset the spectrum analyzer for sideband spectrum measurement.
- 9) Set the span and Resolution Bandwidth (according to FCC/ ISED standard).
- 10) Save the screen shot as modulated signal
- 11) Remove the audio tone from audio analyzer to capture unmodulated signal.



* Only HPF added for Mask 80.211 measurement with attenuator.



6.6.2. Test Result (Analog)




















































6.6.3. Test Setup (Digital)







- 1) Program and set radio to operate in desire test frequency and digital mode with modulation. (*4FSK, C4FM or other digital modulation form).
- 2) Path loss for the measurement included.
- 3) Select the Occupied Bandwidth measurement for 99% Emissions Bandwidth Measurement.
- 4) Key in the Fc and Resolution Bandwidth (1 ~ 5 % of emission designator).
- 5) Transmit the DUT and record the occupied Bandwidth frequency.
- 6) Preset the spectrum analyzer for modulation emission spectrum measurement.
- 7) Set the span and Resolution Bandwidth (according to FCC/ ISED standard).
- 8) Capture the screen shot as modulated signal.



*Note:



- For Digital Modulation, 12.5 kHz Data F1D & FXD would be the same. Therefore only measurements with F1D modulation shown below.
- For Digital Modulation, 12.5 kHz Data F1E & FXE would be the same. Therefore only measurements with F1E modulation shown below.



6.6.4. Test Result (Digital)
















































































































6.6.5. Test Limit

The 99% occupied bandwidth is the width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage 0.5% of the total mean transmitted power.

6.7. Band Edge Conducted Spurious Emission (Part 22)

6.7.1. Test Setup (Analog)




- 1) The DUT transmitter output port was connected to Modulation Analyzer.
- 2) Set the audio bandwidth filter to 15 kHz low pass filter and 50 kHz high pass filter.
- 3) Transmit the radio and set the audio analyzer to 2.5 kHz audio frequency and 50% of the rated deviation. Up the amplitude by 16 dB. Dekey the DUT.
- 4) Path loss for the measurement included.
- 5) Select the Occupied Bandwidth measurement for 99% and 26dB Emissions Bandwidth Measurement.
- 6) Key in the Fc and Resolution Bandwidth.
- 7) Transmit the DUT and record the occupied Bandwidth frequencies.
- 8) Preset the spectrum analyzer for band edge measurement.
- 9) The band edges of lowest and highest channels were measured.
- 10) Key in the Lowest and highest channel frequency, span is 60 kHz and Resolution Bandwidth is at least 1% of Emission Bandwidth.
- 11) Save the screen shot as modulated signal.
- 12) Remove the audio tone from audio analyzer to capture unmodulated signal.

*Note:

- For emission designator ending with F3E, 16K0F3E is the worst case and therefore only 16K0F3E will be shown.

6.7.2. Test Result (Analog) NA → Not Applicable

6.7.3. Test Setup (Digital)



- 1) Program and set radio to operate in desire test frequency and digital mode with modulation. (*4FSK, C4FM or other digital modulation form).
- 2) Path loss for the measurement included.
- 3) Select the Occupied Bandwidth measurement for 99% and 26dB Emissions Bandwidth Measurement.
- 4) Key in the Fc and Resolution Bandwidth.
- 5) Transmit radio record the occupied Bandwidth frequencies.
- 6) Preset the spectrum analyzer for band edge measurement.
- 7) Key in the lowest and highest channels frequency, span is 60 kHz and Resolution Bandwidth is at least 1% of Emission Bandwidth.
- 8) Save the screen shot.

*Note:

- All digital modulation modes utilize the same high deviation test pattern, and they are therefore identical. Hence, only F1D plots will be shown.

6.7.4. Test Result (Digital) NA → Not Applicable

6.7.5. Test Limit

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB.

6.8.3. Test Limit

Transmitters designed to operate in the 150-174 MHz and 421-512 MHz frequency bands must maintain transient frequencies within the maximum frequency difference limits during the time intervals indicated:

Time intervals ^{1 2}	Maximum frequency difference ³	All equipment	
		150 to 174 MHz	421 to 512 MHz
Transient Frequency Behavior for Equipment Designed to Operate on 25 kHz Channels			
t ₁ ⁴	±25.0 kHz	5.0 ms	10.0 ms
t ₂	±12.5 kHz	20.0 ms	25.0 ms
t ₃ ⁴	±25.0 kHz	5.0 ms	10.0 ms
Transient Frequency Behavior for Equipment Designed to Operate on 12.5 kHz Channels			
t ₁ ⁴	±12.5 kHz	5.0 ms	10.0 ms
t ₂	±6.25 kHz	20.0 ms	25.0 ms
t ₃ ⁴	±12.5 kHz	5.0 ms	10.0 ms
Transient Frequency Behavior for Equipment Designed to Operate on 6.25 kHz Channels			
t ₁ ⁴	±6.25 kHz	5.0 ms	10.0 ms
t ₂	±3.125 kHz	20.0 ms	25.0 ms
t ₃ ⁴	±6.25 kHz	5.0 ms	10.0 ms

¹ t_{on} is the instant when a 1 kHz test signal is completely suppressed, including any capture time due to phasing.

t_1 is the time period immediately following t_{on} .

t_2 is the time period immediately following t_1 .

t_3 is the time period from the instant when the transmitter is turned off until t_{off} .

t_{off} is the instant when the 1 kHz test signal starts to rise.


² During the time from the end of t_2 to the beginning of t_3 , the frequency difference must not exceed the limits specified in §90.213.

³ Difference between the actual transmitter frequency and the assigned transmitter frequency.

⁴ If the transmitter carrier output power rating is 6 watts or less, the frequency difference during this time period may exceed the maximum frequency difference for this time period.

6.9. Adjacent Channel Power

6.9.1. Test Setup (Analog)




- 1) The DUT transmitter output port was connected to modulation analyzer.
- 2) Transmit the radio and turn on 1st audio analyzer with audio frequency 650Hz, 50% rated deviation, and record the amplitude value as AmpT1.
- 3) Turn off Audio analyzer 1 and turn on audio analyzer 2, set the audio frequency to 2.2 kHz and 50% deviation. Record the amplitude as AmpT2.
- 4) Turn both audio analyzers ON and up 10dB amplitude level.
- 5) Connect the output to PSA and set to assigned center frequency.
- 6) Set Span, Resolution Bandwidth and Video Bandwidth per rules part.
- 7) Transmit the radio and record the Adjacent Channel Power value in dBc.

6.9.2. Test Result

NA → Not Applicable

6.9.3. Test Setup (Digital)



- 1) Program and set radio to operate in desire test frequency and digital mode with modulation. (4FSK, C4FM or other digital modulation form).
- 2) Prepare setup as per picture.
- 3) Turn on the ACP Measurement – Press Measure, ACP.
- 4) Set Span, Resolution Bandwidth and Video Bandwidth as per rules part.
- 5) Transmit the radio and record the Adjacent Channel Power value in dBc.

6.9.4. Test Result

NA → Not Applicable

Test Limit

12.5 kHz MOBILE TRANSMITTER ACP REQUIREMENTS

Offset from center frequency (kHz)	Measurement bandwidth (kHz)	Maximum ACP relative (dBc)
9.375	6.25	-40
15.625	6.25	-60
21.875	6.25	-60
37.50	25.00	-60
62.50	25.00	-65
87.50	25.00	-65
150.00	100	-65
250.00	100	-65
350.00	100	-65
>400 to 12 MHz	30 (s)	-75
12 MHz to paired receive band	30 (s)	-75
In the paired receive band	30 (s)	-100

25 kHz MOBILE TRANSMITTER ACP REQUIREMENTS

Offset from center frequency (kHz)	Measurement bandwidth (kHz)	Maximum ACP relative (dBc)
15.625	6.25	-40
21.875	6.25	-60
37.50	25	-60
62.50	25	-65
87.50	25	-65
150.00	100	-65
250.00	100	-65
350.00	100	-65
>400 kHz to 12 MHz	30 (s)	-75
12 MHz to paired receive band	30 (s)	-75
In the paired receive band	30 (s)	-100

12.5 kHz BASE TRANSMITTER ACP REQUIREMENTS


Offset from center frequency (kHz)	Measurement bandwidth (kHz)	Maximum ACP (dBc)
9.375	6.25	-40
15.625	6.25	-60
21.875	6.25	-60
37.5	25	-60
62.5	25	-65
87.5	25	-65
150	100	-65
250	100	-65
350.00	100	-65
>400 kHz to 12 MHz	30 (s)	-80
12 MHz to paired receive band	30 (s)	-80
In the paired receive band	30 (s)	¹ -85

25 kHz BASE TRANSMITTER ACP REQUIREMENTS

Offset from center frequency (kHz)	Measurement bandwidth (kHz)	Maximum ACP (dBc)
15.625	6.25	-40
21.875	6.25	-60
37.5	25	-60
62.5	25	-65
87.5	25	-65
150	100	-65
250	100	-65
350	100.00	-65
>400 kHz to 12 MHz	30 (s)	-80
12 MHz to paired receive band	30 (s)	-80
In the paired receive band	30 (s)	¹ -85

6.10. Conducted Spurious Emission


6.10.1. Test Setup



- 1) The DUT transmitter output port was connected to Spectrum Analyzer with above setup.
- 2) Program and set radio to operate in desire test frequency and mode. (Analog / digital modulation form).
- 3) Path loss for the measurement included.
- 4) Set the PSA Resolution Bandwidth as per rules part.
- 5) Set the Ref offset from the pathloss offset calibration file.
- 6) Adjust the center frequency of the spectrum analyzer for incremental coverage of the range from:
 - a. 9 KHz to $F_c - \text{Test Bandwidth}$
 - b. $F_c + \text{Test Bandwidth}$ to $2F_c - 5\text{MHz}$.
- 7) Key up the DUT, Peak Search the highest Spur and record the levels of spurious emissions
- 8) Dekey the DUT.
- 9) Turn On High Pass Filter path and Key up the DUT.
- 10) Adjust the PSA Freq for incremental coverage of range from $2F_c$ to $10F_c$
- 11) Key up the DUT and record the highest spur levels of spurious emissions.


6.10.2. Test Result (Analog)

**Analog: 806.0125 MHz, 25.0kHz Channel Spacing, Max Power
FCC Part 90, RSS 119**




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.8150	-28.84	-13	PASS
(Fc + Test BW) to 1GHz	826.6200	-28.58	-13	PASS
1GHz to 2Fc	1274.9820	-54.04	-13	PASS
2Fc to 10Fc	7122.2420	-50.26	-13	PASS
	1612.0250	-54.86	-13	PASS
	2418.0370	-53.89	-13	PASS
	3224.0500	-51.58	-13	PASS
	4030.0620	-52.77	-13	PASS
	4836.0750	-53.73	-13	PASS
	5642.0870	-53.97	-13	PASS
	6448.1000	-53.69	-13	PASS
	7254.1130	-50.92	-13	PASS
	8060.1250	-51.58	-13	PASS

Analog: 814.9875 MHz, 25.0kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.8239	-31.57	-13	PASS
(Fc + Test BW) to 1GHz	878.2947	-26.76	-13	PASS
1GHz to 2Fc	1258.7400	-54.06	-13	PASS
2Fc to 10Fc	7051.3220	-50.38	-13	PASS
	1629.9750	-54.65	-13	PASS
	2444.9630	-53.90	-13	PASS
	3259.9500	-51.81	-13	PASS
	4074.9370	-52.67	-13	PASS
	4889.9250	-53.99	-13	PASS
	5704.9130	-53.59	-13	PASS
	6519.9000	-53.53	-13	PASS
	7334.8870	-51.19	-13	PASS
	8149.8750	-51.90	-13	PASS

**Analog: 823.9875 MHz, 25.0kHz Channel Spacing, Max Power
 FCC Part 90, RSS 119**




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.8329	-29.54	-13	PASS
(Fc + Test BW) to 1GHz	872.9551	-28.12	-13	PASS
1GHz to 2Fc	1244.9740	-54.02	-13	PASS
2Fc to 10Fc	7016.9220	-50.25	-13	PASS
	1647.9750	-54.76	-13	PASS
	2471.9630	-53.59	-13	PASS
	3295.9500	-51.77	-13	PASS
	4119.9370	-52.46	-13	PASS
	4943.9250	-53.84	-13	PASS
	5767.9130	-53.56	-13	PASS
	6591.9000	-53.27	-13	PASS
	7415.8870	-51.41	-13	PASS
	8239.8750	-51.81	-13	PASS

Analog: 851.0125 MHz, 25.0kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.8600	-29.91	-13	PASS
(Fc + Test BW) to 1GHz	868.6371	-26.01	-13	PASS
1GHz to 2Fc	1266.2640	-54.04	-13	PASS
2Fc to 10Fc	7124.2330	-50.08	-13	PASS
	1702.0250	-54.57	-13	PASS
	2553.0370	-53.48	-13	PASS
	3404.0500	-51.78	-13	PASS
	4255.0620	-53.37	-13	PASS
	5106.0750	-53.84	-13	PASS
	5957.0870	-53.73	-13	PASS
	6808.1000	-51.24	-13	PASS
	7659.1130	-51.05	-13	PASS
	8510.1250	-51.38	-13	PASS

Analog: 860.0125 MHz, 25.0kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.8690	-30.27	-13	PASS
(Fc + Test BW) to 1GHz	869.7182	-26.66	-13	PASS
1GHz to 2Fc	1684.2790	-54.06	-13	PASS
2Fc to 10Fc	7075.5230	-50.12	-13	PASS
	1720.0250	-54.64	-13	PASS
	2580.0370	-53.59	-13	PASS
	3440.0500	-51.87	-13	PASS
	4300.0620	-53.54	-13	PASS
	5160.0750	-53.79	-13	PASS
	6020.0870	-53.67	-13	PASS
	6880.1000	-51.57	-13	PASS
	7740.1130	-50.81	-13	PASS
	8600.1250	-51.48	-13	PASS

Analog: 868.8875 MHz, 25.0kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.8778	-30.55	-13	PASS
(Fc + Test BW) to 1GHz	985.0589	-26.38	-13	PASS
1GHz to 2Fc	1272.5920	-53.86	-13	PASS
2Fc to 10Fc	7037.1330	-50.08	-13	PASS
	1737.7750	-54.49	-13	PASS
	2606.6620	-53.38	-13	PASS
	3475.5500	-51.85	-13	PASS
	4344.4370	-53.08	-13	PASS
	5213.3250	-53.29	-13	PASS
	6082.2120	-53.27	-13	PASS
	6951.1000	-50.86	-13	PASS
	7819.9880	-51.08	-13	PASS
	8688.8750	-51.42	-13	PASS

Analog: 896.0125 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.9050	-30.96	-20	PASS
(Fc + Test BW) to 1GHz	923.3723	-26.10	-20	PASS
1GHz to 2Fc	1239.2560	-54.10	-20	PASS
2Fc to 10Fc	7034.2160	-50.39	-20	PASS
	1792.0250	-54.61	-20	PASS
	2688.0370	-53.57	-20	PASS
	3584.0500	-52.46	-20	PASS
	4480.0620	-53.65	-20	PASS
	5376.0750	-53.44	-20	PASS
	6272.0870	-53.44	-20	PASS
	7168.1000	-50.76	-20	PASS
	8064.1130	-51.54	-20	PASS
	8960.1250	-52.11	-20	PASS

Analog: 900.9875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.9100	-30.32	-20	PASS
(Fc + Test BW) to 1GHz	994.8521	-26.10	-20	PASS
1GHz to 2Fc	1290.1000	-43.12	-20	PASS
2Fc to 10Fc	7022.7350	-50.03	-20	PASS
	1801.9750	-54.08	-20	PASS
	2702.9630	-53.10	-20	PASS
	3603.9500	-52.39	-20	PASS
	4504.9370	-53.15	-20	PASS
	5405.9250	-53.28	-20	PASS
	6306.9130	-53.19	-20	PASS
	7207.9000	-50.38	-20	PASS
	8108.8870	-51.63	-20	PASS
	9009.8750	-51.66	-20	PASS

Analog: 935.0125 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.9440	-28.76	-20	PASS
(Fc + Test BW) to 1GHz	990.9039	-26.17	-20	PASS
1GHz to 2Fc	1725.7560	-50.78	-20	PASS
2Fc to 10Fc	7048.1740	-49.97	-20	PASS
	1870.0250	-54.36	-20	PASS
	2805.0370	-52.70	-20	PASS
	3740.0500	-52.18	-20	PASS
	4675.0620	-53.48	-20	PASS
	5610.0750	-53.46	-20	PASS
	6545.0870	-53.18	-20	PASS
	7480.1000	-51.02	-20	PASS
	8415.1120	-51.71	-20	PASS
	9350.1250	-51.78	-20	PASS

Analog: 939.9875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	0.9490	-28.19	-20	PASS
(Fc + Test BW) to 1GHz	963.5215	-26.30	-20	PASS
1GHz to 2Fc	1711.3550	-53.33	-20	PASS
2Fc to 10Fc	7108.2560	-50.08	-20	PASS
	1879.9750	-54.40	-20	PASS
	2819.9630	-52.68	-20	PASS
	3759.9500	-52.53	-20	PASS
	4699.9370	-53.86	-20	PASS
	5639.9250	-53.50	-20	PASS
	6579.9130	-53.37	-20	PASS
	7519.9000	-51.24	-20	PASS
	8459.8880	-51.62	-20	PASS
	9399.8750	-51.68	-20	PASS

Analog: 901.5 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 24, RSS 134



Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	877.1451	-27.87	-20	PASS
(Fc + Test BW) to 1GHz	928.8938	-27.79	-20	PASS
1GHz to 2Fc	1268.1280	-53.97	-20	PASS
2Fc to 10Fc	7084.5040	-49.95	-20	PASS
	1803.0000	-54.43	-20	PASS
	2704.5000	-53.33	-20	PASS
	3606.0000	-52.46	-20	PASS
	4507.5000	-53.31	-20	PASS
	5409.0000	-53.58	-20	PASS
	6310.5000	-53.54	-20	PASS
	7212.0000	-50.51	-20	PASS
	8113.5000	-51.78	-20	PASS
	9015.0000	-51.83	-20	PASS


Analog: 940.5 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 24, RSS 134



Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	873.7112	-29.19	-20	PASS
(Fc + Test BW) to 1GHz	996.9663	-24.87	-20	PASS
1GHz to 2Fc	1784.0200	-53.72	-20	PASS
2Fc to 10Fc	7066.9260	-49.83	-20	PASS
	1881.0000	-54.14	-20	PASS
	2821.5000	-52.37	-20	PASS
	3762.0000	-52.22	-20	PASS
	4702.5000	-53.47	-20	PASS
	5643.0000	-53.47	-20	PASS
	6583.5000	-52.91	-20	PASS
	7524.0000	-50.95	-20	PASS
	8464.5000	-51.35	-20	PASS
	9405.0000	-51.54	-20	PASS


6.10.3. Test Result (Digital)

Digital: 806.0125 MHz, 12.5kHz Channel Spacing, Max Power FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	346.5800	-22.62	-20	PASS
(Fc + Test BW) to 1GHz	818.8800	-20.84	-20	PASS
1GHz to 2Fc	1142.0380	-43.40	-20	PASS
2Fc to 10Fc	7736.0000	-40.39	-20	PASS
	1612.0250	-46.10	-20	PASS
	2418.0370	-43.09	-20	PASS
	3224.0500	-42.76	-20	PASS
	4030.0620	-43.78	-20	PASS
	4836.0750	-46.12	-20	PASS
	5642.0870	-45.14	-20	PASS
	6448.1000	-44.90	-20	PASS
	7254.1130	-42.04	-20	PASS
	8060.1250	-42.40	-20	PASS

Digital: 814.9875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	487.4000	-20.44	-20	PASS
(Fc + Test BW) to 1GHz	925.0950	-21.15	-20	PASS
1GHz to 2Fc	1338.7500	-44.05	-13	PASS
2Fc to 10Fc	7240.8000	-40.18	-20	PASS
	1629.9750	-45.76	-20	PASS
	2444.9630	-45.61	-20	PASS
	3259.9500	-42.56	-20	PASS
	4074.9370	-43.66	-20	PASS
	4889.9250	-44.39	-20	PASS
	5704.9130	-46.13	-20	PASS
	6519.9000	-44.29	-20	PASS
	7334.8870	-42.72	-20	PASS
	8149.8750	-42.78	-20	PASS

Digital: 823.9875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	463.1000	-21.66	-20	PASS
(Fc + Test BW) to 1GHz	875.9400	-20.50	-20	PASS
1GHz to 2Fc	1237.9100	-43.58	-20	PASS
2Fc to 10Fc	7776.0000	-40.14	-20	PASS
	1647.9750	-44.76	-20	PASS
	2471.9630	-43.59	-20	PASS
	3295.9500	-41.77	-20	PASS
	4119.9370	-42.46	-20	PASS
	4943.9250	-43.84	-20	PASS
	5767.9130	-43.56	-20	PASS
	6591.9000	-43.27	-20	PASS
	7415.8870	-41.41	-20	PASS
	8239.8750	-41.81	-20	PASS

Digital: 851.0125 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	459.5400	-22.01	-20	PASS
(Fc + Test BW) to 1GHz	879.6700	-20.99	-20	PASS
1GHz to 2Fc	1260.7000	-43.55	-20	PASS
2Fc to 10Fc	7049.0000	-40.28	-20	PASS
	1702.0250	-46.25	-20	PASS
	2553.0370	-45.26	-20	PASS
	3404.0500	-43.16	-20	PASS
	4255.0620	-44.15	-20	PASS
	5106.0750	-45.67	-20	PASS
	5957.0870	-44.83	-20	PASS
	6808.1000	-40.60	-20	PASS
	7659.1130	-42.54	-20	PASS
	8510.1250	-43.39	-20	PASS

Digital: 860.0125 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	407.6400	-21.81	-20	PASS
(Fc + Test BW) to 1GHz	967.2400	-20.96	-20	PASS
1GHz to 2Fc	1211.6400	-43.37	-20	PASS
2Fc to 10Fc	6765.3700	-40.50	-20	PASS
	1720.0250	-44.93	-20	PASS
	2580.0370	-45.29	-20	PASS
	3440.0500	-43.90	-20	PASS
	4300.0620	-44.63	-20	PASS
	5160.0750	-45.53	-20	PASS
	6020.0870	-44.73	-20	PASS
	6880.1000	-42.02	-20	PASS
	7740.1130	-42.69	-20	PASS
	8600.1250	-41.83	-20	PASS

Digital: 868.8875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	787.1000	-21.25	-20	PASS
(Fc + Test BW) to 1GHz	870.2300	-20.62	-20	PASS
1GHz to 2Fc	1520.3000	-42.91	-20	PASS
2Fc to 10Fc	7086.0000	-39.93	-20	PASS
	1737.7750	-45.91	-20	PASS
	2606.6620	-44.30	-20	PASS
	3475.5500	-43.62	-20	PASS
	4344.4370	-43.76	-20	PASS
	5213.3250	-44.53	-20	PASS
	6082.2120	-43.53	-20	PASS
	6951.1000	-42.27	-20	PASS
	7819.9880	-43.71	-20	PASS
	8688.8750	-42.37	-20	PASS

Digital: 896.0125 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	600.3000	-21.14	-20	PASS
(Fc + Test BW) to 1GHz	993.7700	-20.87	-20	PASS
1GHz to 2Fc	1024.3970	-43.97	-20	PASS
2Fc to 10Fc	7041.0000	-39.86	-20	PASS
	1792.0250	-46.63	-20	PASS
	2688.0370	-45.05	-20	PASS
	3584.0500	-44.04	-20	PASS
	4480.0620	-45.42	-20	PASS
	5376.0750	-45.75	-20	PASS
	6272.0870	-43.90	-20	PASS
	7168.1000	-42.01	-20	PASS
	8064.1130	-43.60	-20	PASS
	8960.1250	-44.50	-20	PASS

Digital: 900.9875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	484.7380	-20.61	-20	PASS
(Fc + Test BW) to 1GHz	966.4390	-20.37	-20	PASS
1GHz to 2Fc	1786.6000	-42.74	-20	PASS
2Fc to 10Fc	8733.0000	-40.18	-20	PASS
	1801.9750	-44.08	-20	PASS
	2702.9630	-43.10	-20	PASS
	3603.9500	-42.39	-20	PASS
	4504.9370	-43.15	-20	PASS
	5405.9250	-43.28	-20	PASS
	6306.9130	-43.19	-20	PASS
	7207.9000	-40.38	-20	PASS
	8108.8870	-41.63	-20	PASS
	9009.8750	-41.66	-20	PASS

Digital: 935.0125 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	913.4950	-22.21	-20	PASS
(Fc + Test BW) to 1GHz	961.1400	-20.80	-20	PASS
1GHz to 2Fc	1283.7200	-42.94	-20	PASS
2Fc to 10Fc	7137.9600	-39.13	-20	PASS
	1870.0250	-43.87	-20	PASS
	2805.0370	-43.56	-20	PASS
	3740.0500	-42.71	-20	PASS
	4675.0620	-44.56	-20	PASS
	5610.0750	-45.72	-20	PASS
	6545.0870	-45.28	-20	PASS
	7480.1000	-42.63	-20	PASS
	8415.1120	-43.14	-20	PASS
	9350.1250	-42.75	-20	PASS

Digital: 939.9875 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 90, RSS 119




Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	861.9800	-22.56	-20	PASS
(Fc + Test BW) to 1GHz	987.3400	-21.07	-20	PASS
1GHz to 2Fc	1231.0000	-43.33	-20	PASS
2Fc to 10Fc	7025.5200	-39.94	-20	PASS
	1879.9750	-45.77	-20	PASS
	2819.9630	-42.67	-20	PASS
	3759.9500	-43.75	-20	PASS
	4699.9370	-44.27	-20	PASS
	5639.9250	-42.48	-20	PASS
	6579.9130	-43.68	-20	PASS
	7519.9000	-42.35	-20	PASS
	8459.8880	-42.49	-20	PASS
	9399.8750	-42.37	-20	PASS

Digital: 901.5 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 24, RSS 134



Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	783.4000	-20.89	-20	PASS
(Fc + Test BW) to 1GHz	955.7802	-21.10	-20	PASS
1GHz to 2Fc	1774.8580	-42.83	-20	PASS
2Fc to 10Fc	1803.0000	-44.52	-20	PASS
	2704.5000	-43.75	-20	PASS
	3606.0000	-42.53	-20	PASS
	4507.5000	-44.20	-20	PASS
	5409.0000	-43.59	-20	PASS
	6310.5000	-43.55	-20	PASS
	7212.0000	-40.18	-20	PASS
	8113.5000	-42.08	-20	PASS
	9015.0000	-41.91	-20	PASS
	3213.5120	-39.16	-20	PASS

**Digital: 940.5 MHz, 12.5kHz Channel Spacing, Max Power
FCC Part 24, RSS 134**



Frequency Range	Highest Spur Frequency (MHz)	Spurious Level (dBm)	Failing Limit (dBm)	Results
FL to (Fc - Test BW)	504.1000	-20.46	-20	PASS
(Fc + Test BW) to 1GHz	988.2220	-21.64	-20	PASS
1GHz to 2Fc	1211.9920	-42.35	-20	PASS
2Fc to 10Fc	1881.0000	-43.00	-20	PASS
	2821.5000	-42.37	-20	PASS
	3762.0000	-42.92	-20	PASS
	4702.5000	-43.74	-20	PASS
	5643.0000	-43.53	-20	PASS
	6583.5000	-42.58	-20	PASS
	7524.0000	-40.93	-20	PASS
	8464.5000	-41.43	-20	PASS
	9405.0000	-41.92	-20	PASS
	7097.0620	-39.20	-20	PASS

6.10.4. Test Limit


Table below summarized the power of any emission outside a licensee's frequency block shall be attenuated below the transmitter power (P) by at least

Channel Spacing	Part 22	Part 24D	Part 74	Part 80	Part 90 (UHF, VHF, 800, 900)	Part 90 (700)
12.5kHz	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	Not Applicable	50 + log ₁₀ (P) (-20 dBm)	43 + log ₁₀ (P) (-13 dBm)
25kHz		Not Applicable		43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)

Channel Spacing	RSS 134	RSS 182	RSS 119 (UHF, VHF, 800, 900)	RSS 119 (700)
12.5kHz	43 + log ₁₀ (P) (-13 dBm)	Not Applicable	50 + log ₁₀ (P) (-20 dBm)	43 + log ₁₀ (P) (-13 dBm)
25kHz	Not Applicable	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)

6.11. Radiated Spurious Emission

6.11.1. Test Setup




- 1) The Resolution Bandwidth for scanning Radiated Emission below 1 GHz is 100 kHz with Video Bandwidth = 300 kHz and Resolution Bandwidth for above 1 GHz is 1 MHz with Video Bandwidth = 3 MHz. Detector mode is positive peak.
- 2) In the semi- anechoic chamber, setup as illustrated above the DUT placed on the 0.8m height (for frequencies < 1GHz) or 1.5m (for frequencies > 1GHz) of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The “Read Value” is the spectrum reading the maximum power value.
- 3) The substitution antenna is substituted for DUT at the same position and signals generator (S.G) export the CW signal to the substitution antenna via a TX cable. The receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum radiation power. Record the power level of maximum radiation power from spectrum. So, the measured substitution value = Ref level of S.G + TX cables loss – Substituted Antenna Gain.
- 4) Final Radiated Spurious Emission = “Read Value” + Measured substitution value.

6.11.2. Test Result (Analog)

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
806.012500 MHz 25 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1612.0250	-13.0000	-43.8500 *	-43.1800 *
2418.0375	-13.0000	-55.6230 **	-54.6098 **
3224.0500	-13.0000	-50.5322 **	-51.1852 **
4030.0625	-13.0000	-50.5412 **	-51.5901 **
4836.0750	-13.0000	-49.9055 **	-49.2284 **
5642.0875	-13.0000	-48.3671 **	-47.4871 **
6448.1000	-13.0000	-45.8986 **	-46.4461 **
7254.1125	-13.0000	-44.3578 **	-43.2239 **
8060.1250	-13.0000	-43.1846 **	-42.3830 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sat, Nov 17, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
814.987500 MHz 25 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1629.9750	-13.0000	-46.9100 *	-49.9900 *
2444.9625	-13.0000	-46.3500 *	-48.7000 *
3259.9500	-13.0000	-51.4731 **	-50.6810 **
4074.9375	-13.0000	-50.9187 **	-51.3894 **
4889.9250	-13.0000	-48.6635 **	-48.8101 **
5704.9125	-13.0000	-48.5702 **	-47.2759 **
6519.9000	-13.0000	-45.5133 **	-46.0928 **
7334.8875	-13.0000	-44.2399 **	-44.0578 **
8149.8750	-13.0000	-43.5497 **	-42.0379 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sat, Nov 17, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
823.987500 MHz 25 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1647.9750	-13.0000	-47.9800 *	-48.6400 *
2471.9625	-13.0000	-52.9344 **	-53.3474 **
3295.9500	-13.0000	-51.0173 **	-52.0814 **
4119.9375	-13.0000	-51.1907 **	-52.3528 **
4943.9250	-13.0000	-48.5015 **	-49.0362 **
5767.9125	-13.0000	-47.6983 **	-47.9985 **
6591.9000	-13.0000	-44.5611 **	-45.1728 **
7415.8875	-13.0000	-44.0999 **	-42.7604 **
8239.8750	-13.0000	-43.3946 **	-43.7393 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sat, Nov 17, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
851.012500 MHz 25 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1702.0250	-13.0000	-39.6700 *	-42.0900 *
2553.0375	-13.0000	-51.1810 **	-51.6076 **
3404.0500	-13.0000	-50.9385 **	-50.0546 **
4255.0625	-13.0000	-51.2672 **	-50.3812 **
5106.0750	-13.0000	-48.3959 **	-47.6071 **
5957.0875	-13.0000	-47.1368 **	-46.8781 **
6808.1000	-13.0000	-44.6526 **	-44.9751 **
7659.1125	-13.0000	-43.2040 **	-42.9554 **
8510.1250	-13.0000	-42.7196 **	-41.7985 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
860.012500 MHz 25 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1720.0250	-13.0000	-40.9600 *	-42.4400 *
2580.0375	-13.0000	-52.0400 **	-53.4139 **
3440.0500	-13.0000	-53.6077 **	-53.2004 **
4300.0625	-13.0000	-51.5352 **	-51.3229 **
5160.0750	-13.0000	-48.3488 **	-48.3616 **
6020.0875	-13.0000	-47.0082 **	-47.2343 **
6880.1000	-13.0000	-45.4020 **	-43.8283 **
7740.1125	-13.0000	-43.1343 **	-43.3129 **
8600.1250	-13.0000	-40.6056 **	-43.0126 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN **S/N:** 203TUV1654 **SR:**13928-EMC-00001
Battery Part No: NA **Accy Part No:** 2776-RMN5127C-3
Test Mode: TX Analog
868.887500 MHz **25 kHz** **42.000 Watt(s) /Max Power**

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1737.7750	-13.0000	-41.6600 *	-44.3900 *
2606.6625	-13.0000	-47.9500 *	-46.4800 *
3475.5500	-13.0000	-52.6402 **	-53.7818 **
4344.4375	-13.0000	-51.0245 **	-50.5763 **
5213.3250	-13.0000	-46.3653 **	-48.2927 **
6082.2125	-13.0000	-46.8690 **	-46.9278 **
6951.1000	-13.0000	-44.6889 **	-45.4057 **
7819.9875	-13.0000	-43.7835 **	-43.1000 **
8688.8750	-13.0000	-41.8802 **	-43.2600 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
 Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
 *Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
 Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
896.012500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1792.0250	-13.0000	-48.5100 *	-48.9600 *
2688.0375	-13.0000	-49.1100 *	-47.5600 *
3584.0500	-13.0000	-53.5284 **	-53.2388 **
4480.0625	-13.0000	-50.3290 **	-50.2661 **
5376.0750	-13.0000	-47.7336 **	-47.6624 **
6272.0875	-13.0000	-46.4030 **	-46.9127 **
7168.1000	-13.0000	-43.3591 **	-44.5307 **
8064.1125	-13.0000	-43.4827 **	-43.0211 **
8960.1250	-13.0000	-42.8805 **	-42.4226 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
900.987500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1801.9750	-13.0000	-50.2900 *	-48.7400 *
2702.9625	-13.0000	-31.3700	-34.8300 *
3603.9500	-13.0000	-53.8668 **	-52.0576 **
4504.9375	-13.0000	-51.1553 **	-50.2651 **
5405.9250	-13.0000	-48.3814 **	-47.8113 **
6306.9125	-13.0000	-46.8195 **	-46.4551 **
7207.9000	-13.0000	-44.4739 **	-43.7287 **
8108.8875	-13.0000	-44.1048 **	-43.9610 **
9009.8750	-13.0000	-40.1794 **	-41.1752 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
901.500000 MHz 12.5 kHz 10.000 Watt(s)

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1803.0000	-13.0000	-47.5700 *	-49.4700 *
2704.5000	-13.0000	-54.4253 **	-54.9201 **
3606.0000	-13.0000	-52.3642 **	-53.4397 **
4507.5000	-13.0000	-50.8025 **	-51.1978 **
5409.0000	-13.0000	-48.6801 **	-46.9896 **
6310.5000	-13.0000	-46.7946 **	-46.3139 **
7212.0000	-13.0000	-44.2142 **	-43.8080 **
8113.5000	-13.0000	-43.0614 **	-41.8901 **
9015.0000	-13.0000	-42.3991 **	-41.5740 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB


Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

***Radio tested at 10W to simulate worst case. Actual performance at part 24 frequency is 6.3W**

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
935.012500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1870.0250	-13.0000	-55.6625 **	-55.9934 **
2805.0375	-13.0000	-54.2734 **	-55.0858 **
3740.0500	-13.0000	-51.6939 **	-51.6208 **
4675.0625	-13.0000	-49.8208 **	-48.2879 **
5610.0750	-13.0000	-47.7032 **	-47.2740 **
6545.0875	-13.0000	-45.4800 **	-46.1288 **
7480.1000	-13.0000	-44.4776 **	-44.9515 **
8415.1125	-13.0000	-42.1377 **	-42.3784 **
9350.1250	-13.0000	-42.1854 **	-41.3624 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN **S/N:** 203TUV1654 **SR:**13928-EMC-00001
Battery Part No: NA **Accy Part No:** 2776-RMN5127C-3
Test Mode: TX Analog
939.987500 MHz **12.5 kHz** **36.000 Watt(s) /Max Power**

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1879.9750	-13.0000	-50.1600 *	-50.6200 *
2819.9625	-13.0000	-50.2300 *	-49.4500 *
3759.9500	-13.0000	-51.8235 **	-51.1470 **
4699.9375	-13.0000	-48.4431 **	-47.4921 **
5639.9250	-13.0000	-47.2462 **	-46.9905 **
6579.9125	-13.0000	-42.6184 **	-44.3511 **
7519.9000	-13.0000	-42.4423 **	-41.5973 **
8459.8875	-13.0000	-42.9006 **	-42.5602 **
9399.8750	-13.0000	-41.6304 **	-41.7995 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX Analog
940.500000 MHz 12.5 kHz 10.000 Watt(s)

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1881.0000	-13.0000	-57.5909 **	-56.8373 **
2821.5000	-13.0000	-54.2572 **	-54.9472 **
3762.0000	-13.0000	-53.4273 **	-52.7527 **
4702.5000	-13.0000	-48.8456 **	-49.7394 **
5643.0000	-13.0000	-47.1936 **	-47.0595 **
6583.5000	-13.0000	-45.8150 **	-45.5341 **
7524.0000	-13.0000	-43.1987 **	-42.6726 **
8464.5000	-13.0000	-43.1879 **	-41.7054 **
9405.0000	-13.0000	-42.3851 **	-41.4774 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:


Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

***Radio tested at 10W to simulate worst case. Actual performance at part 24 frequency is 6.3W**

6.11.3. Test Result (Digital)

SAC Transmitter Radiated Emission:
 Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
 Battery Part No: NA Accy Part No: 2776-RMN5127C-3
 Test Mode: TX PCR Digital 4FSK
 806.012500 MHz 12.5 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1612.0250	-13.0000	-42.7200 *	-41.0600 *
2418.0375	-13.0000	-49.1000 *	-49.7000 *
3224.0500	-13.0000	-47.4800 *	-45.3000 *
4030.0625	-13.0000	-49.7338 **	-48.6285 **
4836.0750	-13.0000	-44.7600 *	-44.4100 *
5642.0875	-13.0000	-48.2498 **	-45.2594 **
6448.1000	-13.0000	-41.1500 *	-41.3400 *
7254.1125	-13.0000	-42.8423 **	-41.9306 **
8060.1250	-13.0000	-43.5134 **	-43.5868 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
 Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.

*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
 Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX PCR Digital 4FSK
814.987500 MHz 12.5 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1629.9750	-13.0000	-48.2000 *	-47.6700 *
2444.9625	-13.0000	-45.6200 *	-47.6100 *
3259.9500	-13.0000	-48.1200 *	-46.7900 *
4074.9375	-13.0000	-49.8170 **	-47.0041 **
4889.9250	-13.0000	-44.1100 *	-44.0900 *
5704.9125	-13.0000	-48.2623 **	-47.6202 **
6519.9000	-13.0000	-41.1200 *	-41.7900 *
7334.8875	-13.0000	-42.4384 **	-41.6253 **
8149.8750	-13.0000	-43.1512 **	-42.4417 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------


SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK

823.987500 MHz 12.5 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1647.9750	-13.0000	-44.4000 *	-44.9300 *
2471.9625	-13.0000	-43.5500 *	-44.6300 *
3295.9500	-13.0000	-47.5300 *	-48.1000 *
4119.9375	-13.0000	-51.8200 **	-47.0817 **
4943.9250	-13.0000	-42.9700 *	-43.7300 *
5767.9125	-13.0000	-47.6626 **	-47.3229 **
6591.9000	-13.0000	-40.4100 *	-42.1000 *
7415.8875	-13.0000	-43.7561 **	-42.6117 **
8239.8750	-13.0000	-43.4454 **	-42.5119 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.

*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:
Model Number: AAM28UMN9RA1AN **S/N:** 203TUV1654 **SR:**13928-EMC-00001
Battery Part No: NA **Accy Part No:** 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK


851.012500 MHz

12.5 kHz

42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1702.0250	-13.0000	-41.1900 *	-40.1100 *
2553.0375	-13.0000	-43.3500 *	-43.4200 *
3404.0500	-13.0000	-41.7200 *	-38.1600 *
4255.0625	-13.0000	-51.7771 **	-51.4705 **
5106.0750	-13.0000	-47.8519 **	-48.3983 **
5957.0875	-13.0000	-46.9461 **	-45.1515 **
6808.1000	-13.0000	-45.7877 **	-45.3942 **
7659.1125	-13.0000	-43.2867 **	-42.3464 **
8510.1250	-13.0000	-43.1655 **	-43.4921 **

RADIATED SPURIOUS EMISSIONS



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
 Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.

*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
 Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------


SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK

860.012500 MHz 12.5 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1720.0250	-13.0000	-54.5600 *	-55.6100 *
1745.7600	-13.0000	-55.1700 *	-52.1000 *
2580.0375	-13.0000	-50.6600 *	-49.5100 *
3440.0500	-13.0000	-47.7400 *	-47.9900 *
4300.0625	-13.0000	-50.8901 **	-50.3051 **
5160.0750	-13.0000	-47.4660 **	-48.6542 **
6020.0875	-13.0000	-46.2958 **	-45.6266 **
6880.1000	-13.0000	-45.6175 **	-45.6122 **
7740.1125	-13.0000	-43.6425 **	-43.1753 **
8600.1250	-13.0000	-41.9353 **	-43.0304 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------


SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK

868.887500 MHz 12.5 kHz 42.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1737.7750	-13.0000	-33.6200 *	-36.2300 *
2606.6625	-13.0000	-36.9000 *	-34.5500 *
3475.5500	-13.0000	-51.2777 **	-50.2978 **
4344.4375	-13.0000	-50.0420 **	-51.6139 **
5213.3250	-13.0000	-47.3514 **	-48.5876 **
6082.2125	-13.0000	-46.8668 **	-45.1130 **
6951.1000	-13.0000	-43.7697 **	-44.2270 **
7819.9875	-13.0000	-43.8609 **	-43.8842 **
8688.8750	-13.0000	-42.4357 **	-42.7855 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.

*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------


SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK

896.012500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1792.0250	-13.0000	-42.2200 *	-44.6700 *
2688.0375	-13.0000	-33.8700 *	-37.6600 *
3584.0500	-13.0000	-53.8240 **	-53.3557 **
4480.0625	-13.0000	-50.7200 **	-49.8580 **
5376.0750	-13.0000	-48.9600 **	-47.9975 **
6272.0875	-13.0000	-46.4298 **	-46.0861 **
7168.1000	-13.0000	-44.3347 **	-44.0028 **
8064.1125	-13.0000	-43.0766 **	-43.0145 **
8960.1250	-13.0000	-42.7206 **	-42.7443 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3


System MU: 5.01 dB

Remarks: Passed Results Marginal Results Failed Results

SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX PCR Digital 4FSK
900.987500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1801.9750	-13.0000	-43.6000 *	-46.6600 *
2702.9625	-13.0000	-40.2800 *	-40.3700 *
3603.9500	-13.0000	-53.1900 **	-53.1593 **
4504.9375	-13.0000	-50.9788 **	-51.3283 **
5405.9250	-13.0000	-48.2557 **	-48.0764 **
6306.9125	-13.0000	-46.5884 **	-45.8518 **
7207.9000	-13.0000	-44.2543 **	-43.4333 **
8108.8875	-13.0000	-42.9106 **	-42.8628 **
9009.8750	-13.0000	-41.8991 **	-41.2010 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB


Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX PCR Digital 4FSK
901.500000 MHz 12.5 kHz 10.000 Watt(s)

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1803.0000	-13.0000	-44.6800 *	-47.8300 *
2704.5000	-13.0000	-43.0900 *	-41.8500 *
3606.0000	-13.0000	-54.1378 **	-53.0371 **
4507.5000	-13.0000	-51.2162 **	-50.5084 **
5409.0000	-13.0000	-48.0087 **	-47.7118 **
6310.5000	-13.0000	-44.4953 **	-46.7545 **
7212.0000	-13.0000	-44.1133 **	-44.0049 **
8113.5000	-13.0000	-43.5387 **	-42.8395 **
9015.0000	-13.0000	-41.6379 **	-41.7922 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.

*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks: Passed Results Marginal Results Failed Results

***Radio tested at 10W to simulate worst case. Actual performance at part 24 frequency is 6.3W**


SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK

935.012500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1870.0250	-13.0000	-48.6400 *	-46.6500 *
2805.0375	-13.0000	-43.5900 *	-45.6800 *
3740.0500	-13.0000	-52.5475 **	-52.1867 **
4675.0625	-13.0000	-50.0032 **	-48.7750 **
5610.0750	-13.0000	-47.9639 **	-48.6492 **
6545.0875	-13.0000	-45.2538 **	-44.8994 **
7480.1000	-13.0000	-43.8926 **	-43.9074 **
8415.1125	-13.0000	-41.1857 **	-42.0868 **
9350.1250	-13.0000	-42.6057 **	-41.5101 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------


SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3

Test Mode: TX PCR Digital 4FSK

939.987500 MHz 12.5 kHz 36.000 Watt(s) /Max Power

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1879.9750	-13.0000	-45.5800 *	-44.5600 *
2819.9625	-13.0000	-32.1700	-35.9800 *
3759.9500	-13.0000	-51.2819 **	-52.6636 **
4699.9375	-13.0000	-49.1665 **	-49.4692 **
5639.9250	-13.0000	-46.7806 **	-48.6370 **
6579.9125	-13.0000	-45.4663 **	-44.5791 **
7519.9000	-13.0000	-42.9214 **	-42.6585 **
8459.8875	-13.0000	-43.3930 **	-42.6807 **
9399.8750	-13.0000	-40.4331 **	-42.0852 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.
*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB


Remarks:

Passed Results	Marginal Results	Failed Results
----------------	------------------	----------------

SAC Transmitter Radiated Emission:

Model Number: AAM28UMN9RA1AN S/N: 203TUV1654 SR:13928-EMC-00001
Battery Part No: NA Accy Part No: 2776-RMN5127C-3
Test Mode: TX PCR Digital 4FSK
940.500000 MHz 12.5 kHz 10.000 Watt(s)

Frequency (MHz)	Limit	Horizontal Measured Emission Equiv Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into ideal Dipole (dBm)
1881.0000	-13.0000	-47.3600 *	-46.5000 *
2821.5000	-13.0000	-44.1400 *	-46.2300 *
3762.0000	-13.0000	-53.3379 **	-52.7843 **
4702.5000	-13.0000	-49.0175 **	-48.9933 **
5643.0000	-13.0000	-47.6190 **	-46.4741 **
6583.5000	-13.0000	-45.5205 **	-44.3755 **
7524.0000	-13.0000	-43.7070 **	-43.6660 **
8464.5000	-13.0000	-42.2862 **	-41.8887 **
9405.0000	-13.0000	-42.3516 **	-41.8694 **



The data presented here was taken using the substitution method as found in the ANSI C63.26-2015 document.
Motorola Penang EMC Lab - Test Performed by: Nazrin&Qawiman Sun, Nov 18, 2018

Remarks: ** Indicates the spurious emission could not be detected due to noise limitations or ambient.

*Pursuant to CFR 47 Part 2.1057 (c), emissions attenuated more than 20 dB below the permissible limit are not reported
Temp(Deg): 23.2 Hum(%RH): 69.3

System MU: 5.01 dB

Remarks: Passed Results Marginal Results Failed Results

***Radio tested at 10W to simulate worst case. Actual performance at part 24 frequency is 6.3W**

6.11.4. Test Limit


Table below summarized the power of any emission outside a licensee's frequency block shall be attenuated below the transmitter power (P) by at least

Channel Spacing	Part 22	Part 24D	Part 74	Part 80	Part 90 (UHF, VHF, 800, 900)	Part 90 (700)
12.5kHz	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	Not Applicable	50 + log ₁₀ (P) (-20 dBm)	43 + log ₁₀ (P) (-13 dBm)
25kHz		Not Applicable		43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)

Channel Spacing	RSS 134	RSS 182	RSS 119 (UHF, VHF, 800, 900)	RSS 119 (700)
12.5kHz	43 + log ₁₀ (P) (-13 dBm)	Not Applicable	50 + log ₁₀ (P) (-20 dBm)	43 + log ₁₀ (P) (-13 dBm)
25kHz	Not Applicable	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)	43 + log ₁₀ (P) (-13 dBm)

6.12. Effective Radiated Power (ERP)

6.12.1. Test Setup



- 1) The Resolution Bandwidth for Equivalent Radiated Power (ERP) below 1 GHz is 100 kHz with Video Bandwidth = 300 kHz and Resolution Bandwidth for EIRP above 1 GHz is 1 MHz with Video Bandwidth = 3 MHz. Detector Mode is RMS.
- 2) In the semi-anechoic chamber, setup as illustrated above the DUT placed on the 0.8m height of Turn Table, rotated the table 45 degree each interval to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power for each degree interval. The “Read Value” is the spectrum reading of maximum power value.
- 3) The substitution antenna is substituted for DUT at the same position and signals generator (S.G) export the CW signal to the substitution antenna via a TX cable. The receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum radiation power. Record the power level of maximum radiation power from spectrum. So, the Measured substitution value = Ref level of S.G + TX cables loss – Substituted Antenna Gain.

6.12.2. Test Result

S/N: 203TUV1654

Tx Power: 6.300 Watts

Channel Spacing : 12.5 kHz

Modulation: FM

Accessory: HAF4033A, 2776-RMN5127C-3

Antenna Polarization	Frequency (MHz)	EIRP (dBm)	ERP (dBm)
Horiz.	901.5000	30.97	28.82
Vert.	901.5000	40.29	38.14

S/N: 203TUV1654 **Tx Power:** 6.300 Watts
Channel Spacing : 12.5 kHz **Modulation:** FM
Accessory: HAF4033A, 2776-RMN5127C-3


Antenna Polarization	Frequency (MHz)	EIRP (dBm)	ERP (dBm)
Horiz.	940.5000	26.92	24.77
Vert.	940.5000	39.84	37.69

6.12.3. Test Limit

The maximum output power of the transmitter for mobile stations is 7 watts. Power is given in terms of effective radiated power (ERP).

6.13. GNSS (EIRP for 1559 - 1610MHz)

6.13.1. Test Setup



- 4) The Resolution Bandwidth for Equivalent Isotropically Radiated Power (EIRP) below 1 GHz is 100 kHz with Video Bandwidth = 300 kHz and Resolution Bandwidth for EIRP above 1 GHz is 1 MHz with Video Bandwidth = 3 MHz. Detector Mode is RMS.
- 5) In the semi-anechoic chamber, setup as illustrated above the DUT placed on the 0.8m height of Turn Table, rotated the table 45 degree each interval to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power for each degree interval. The “Read Value” is the spectrum reading of maximum power value.
- 6) The substitution antenna is substituted for DUT at the same position and signals generator (S.G) export the CW signal to the substitution antenna via a TX cable. The receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum radiation power. Record the power level of maximum radiation power from spectrum. So, the Measured substitution value = Ref level of S.G + TX cables loss – Substituted Antenna Gain.
- 7) $EIRP = \text{“Read Value”} + \text{Measured substitution value} + 2.15$.

6.13.1. Test Result

NA → Not Applicable

6.13.2. Test Limit

For operations in the 758-775 MHz and 788-805 MHz bands, all emissions including harmonics in the band 1559-1610 MHz shall be limited to -70 dBW/MHz equivalent isotropically radiated power (EIRP) for wideband signals, and -80 dBW EIRP for discrete emissions of less than 700 Hz bandwidth.

~ End of Report ~