

ANALOG Voice Encryption 20 kHz Channel Spacing 799.0875 MHz				
Offset (kHz)	Meas BW (kHz)	Lower	Upper	Spec (dBc)
15.625	6.25	-43.09	-44.32	-40
21.875	6.25	-65.47	-66.57	-60
37.5	25	-79.39	-79.74	-60
62.5	25	-83.59	-82.66	-65
87.5	25	-84.00	-84.00	-65
150	100	-77.19	-77.29	-65
250	100	-79.37	-79.46	-65
350	100	-80.43	-80.36	-65
400k - 12M	30 (swept)	-85.24	-85.17	-75
12M - RX	30 (swept)	-85.24	-85.17	-75
RX Band	30 (swept)	-105.17	-108.13	-100

Exhibit 6K - 27: Analog Voice Encryption ACCPR - Freq 799.0875 MHz, Ch Sp 20 kHz

ANALOG Voice Encryption 20 kHz Channel Spacing 804.9125 MHz				
Offset (kHz)	Meas BW (kHz)	Lower	Upper	Spec (dBc)
15.625	6.25	-43.61	-44.69	-40
21.875	6.25	-65.55	-66.19	-60
37.5	25	-79.57	-78.93	-60
62.5	25	-82.88	-82.96	-65
87.5	25	-83.85	-83.85	-65
150	100	-77.11	-77.07	-65
250	100	-79.08	-79.14	-65
350	100	-80.31	-80.28	-65
400k - 12M	30 (swept)	-86.24	-86.78	-75
12M - RX	30 (swept)	-86.24	-86.78	-75
RX Band	30 (swept)	-101.68	-100.51	-100

Exhibit 6K - 28: Analog Voice Encryption ACCPR - Freq 804.9125 MHz, Ch Sp 20 kHz

Exhibit 6L: List of Figures

EXHIBIT 6A- 1: CONDUCTED RF OUTPUT POWER.....	3
EXHIBIT 6B- 1: AUDIO RESPONSE - FREQUENCY 158.55 MHz, CH SP: 12.5 kHz	5
EXHIBIT 6B- 2: AUDIO RESPONSE - FREQUENCY 158.55 MHz, CH SP: 25 kHz	6
EXHIBIT 6B- 3: AUDIO RESPONSE - FREQUENCY 467.775 MHz, CH SP: 12.5 kHz	6
EXHIBIT 6B- 4: AUDIO RESPONSE - FREQUENCY 511.9875 MHz, CH SP: 25 kHz	7
EXHIBIT 6B- 5: AUDIO RESPONSE - FREQUENCY 769.0875 MHz, CH SP: 12.5 kHz	7
EXHIBIT 6B- 6: AUDIO RESPONSE - FREQUENCY 769.0875 MHz, CH SP: 25 kHz	8
EXHIBIT 6B- 7: AUDIO RESPONSE - FREQUENCY 823.9875 MHz, CH SP: 12.5 kHz	8
EXHIBIT 6B- 8: AUDIO RESPONSE - FREQUENCY 823.9875 MHz, CH SP: 25 kHz	9
EXHIBIT 6C- 1: AUDIO LOW PASS FILTER RESPONSE.....	10
EXHIBIT 6D- 1: PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 158.55 MHz, CH SP: 12.5 kHz.....	11
EXHIBIT 6D- 2 PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 467.775 MHz, CH SP: 12.5 kHz.....	12
EXHIBIT 6D- 3: PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 769.0875 MHz, CH SP: 12.5 kHz.....	13
EXHIBIT 6D- 4: PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 823.9875 MHz, CH SP: 12.5 kHz.....	14
EXHIBIT 6D- 5: PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 158.55 MHz, CH SP: 25 kHz.....	15
EXHIBIT 6D- 6: PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 511.9875 MHz, CH SP: 25 kHz.....	16
EXHIBIT 6D- 7: : PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 769.0875 MHz, CH SP: 25 kHz.....	17
EXHIBIT 6D- 8: PERCENTAGE MOD –VS- MOD FREQ AND INPUT LEVEL – FREQ 823.9875 MHz, CH SP: 25 kHz.....	18
EXHIBIT 6E- 1: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 138.0125 MHz, CH SP 12.5 kHz	20
EXHIBIT 6E- 2: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 158.55 MHz, CH SP 12.5 kHz	21
EXHIBIT 6E- 3: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 161.7 MHz, CH SP 12.5 kHz	22
EXHIBIT 6E- 4: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 173.3875 MHz, CH SP 12.5 kHz	23
EXHIBIT 6E- 5: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 406.2 MHz, CH SP 12.5 kHz	24
EXHIBIT 6E- 6: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 450.65 MHz, CH SP 12.5 kHz	25
EXHIBIT 6E- 7: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 467.775 MHz, CH SP 12.5 kHz	26
EXHIBIT 6E- 8: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 806.0125 MHz, CH SP 12.5 kHz	27
EXHIBIT 6E- 9: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 806.0125 MHz, CH SP 12.5 kHz	28
EXHIBIT 6E- 10: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 814.9875 MHz, CH SP 12.5 kHz	29
EXHIBIT 6E- 11: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 814.9875MHz, CH SP 12.5 kHz	30
EXHIBIT 6E- 12: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 823.9875 MHz, CH SP 12.5 kHz	31
EXHIBIT 6E- 13: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 851.0125 MHz, CH SP 12.5 kHz	32
EXHIBIT 6E- 14: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 853.9875 MHz, CH SP 12.5 kHz	33
EXHIBIT 6E- 15: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 860.0125 MHz, CH SP 12.5 kHz	34
EXHIBIT 6E- 16: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 860.0125 MHz, CH SP 12.5 kHz	35
EXHIBIT 6E- 17: OCCUPIED BANDWIDTH ANALOG VOICE 11K0F3E - FREQ 868.8875 MHz, CH SP 12.5 kHz	36
EXHIBIT 6E- 18: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 138.0125 MHz, CH SP 25 kHz	37
EXHIBIT 6E- 19: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 161.7 MHz, CH SP 25 kHz	38
EXHIBIT 6E- 20: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 173.3875 MHz, CH SP 25 kHz	39
EXHIBIT 6E- 21: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 450.65 MHz, CH SP 25 kHz	40
EXHIBIT 6E- 22: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 459.125 MHz, CH SP 25 kHz	41
EXHIBIT 6E- 23: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 467.775 MHz, CH SP 25 kHz	42
EXHIBIT 6E- 24: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 511.9875 MHz, CH SP 25 kHz	43
EXHIBIT 6E- 25: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 806.0125 MHz, CH SP 25 kHz	44
EXHIBIT 6E- 26: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 806.0125 MHz, CH SP 25 kHz	45
EXHIBIT 6E- 27: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 814.9875 MHz, CH SP 25 kHz	46
EXHIBIT 6E- 28: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 814.9875 MHz, CH SP 25 kHz	47
EXHIBIT 6E- 29: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 814.9875 MHz, CH SP 25 kHz	48
EXHIBIT 6E- 30: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 823.9875 MHz, CH SP 25 kHz	49
EXHIBIT 6E- 31: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 823.9875 MHz, CH SP 25 kHz	50

EXHIBIT 6E- 32: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 851.0125 MHz, Ch Sp 25 kHz	51
EXHIBIT 6E- 33: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 851.0125 MHz, Ch Sp 25 kHz	52
EXHIBIT 6E- 34: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 860.0125 MHz, Ch Sp 25 kHz	53
EXHIBIT 6E- 35: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 860.0125 MHz, Ch Sp 25 kHz	54
EXHIBIT 6E-36: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 860.0125 MHz, Ch Sp 25 kHz	55
EXHIBIT 6E- 37: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 868.8875 MHz, Ch Sp 25 kHz	56
EXHIBIT 6E- 38: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E - FREQ 868.8875 MHz, Ch Sp 25 kHz	57
EXHIBIT 6E- 39: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 138.0125 MHz, Ch Sp 12.5 kHz	58
EXHIBIT 6E- 40: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 158.55 MHz, Ch Sp 12.5 kHz	59
EXHIBIT 6E- 41: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 161.7 MHz, Ch Sp 12.5 kHz	60
EXHIBIT 6E- 42: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 173.3875 MHz, Ch Sp 12.5 kHz	61
EXHIBIT 6E- 43: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 406.2 MHz, Ch Sp 12.5 kHz	62
EXHIBIT 6E- 44: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 450.65 MHz, Ch Sp 12.5 kHz	63
EXHIBIT 6E- 45: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 459.125 MHz, Ch Sp 12.5 kHz	64
EXHIBIT 6E- 46: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 467.775 MHz, Ch Sp 12.5 kHz	65
EXHIBIT 6E- 47: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 806.0125 MHz, Ch Sp 12.5 kHz	66
EXHIBIT 6E- 48: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 806.0125 MHz, Ch Sp 12.5 kHz	67
EXHIBIT 6E- 49: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 814.9875 MHz, Ch Sp 12.5 kHz	68
EXHIBIT 6E- 50: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 814.9875 MHz, Ch Sp 12.5 kHz	69
EXHIBIT 6E- 51: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 823.9875 MHz, Ch Sp 12.5 kHz	70
EXHIBIT 6E- 52: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 851.0125 MHz, Ch Sp 12.5 kHz	71
EXHIBIT 6E- 53: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 853.9875 MHz, Ch Sp 12.5 kHz	72
EXHIBIT 6E- 54: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 860.0125 MHz, Ch Sp 12.5 kHz	73
EXHIBIT 6E- 55: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 860.0125 MHz, Ch Sp 12.5 kHz	74
EXHIBIT 6E- 56: OCCUPIED BANDWIDTH DIGITAL VOICE 8K10F1E - FREQ 868.8875 MHz, Ch Sp 12.5 kHz	75
EXHIBIT 6E- 57: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 138.0125 MHz, Ch Sp 12.5 kHz	76
EXHIBIT 6E- 58: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 158.55 MHz, Ch Sp 12.5 kHz	77
EXHIBIT 6E- 59: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 161.7 MHz, Ch Sp 12.5 kHz	78
EXHIBIT 6E- 60: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 173.3875 MHz, Ch Sp 12.5 kHz	79
EXHIBIT 6E- 61: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 406.2 MHz, Ch Sp 12.5 kHz	80
EXHIBIT 6E- 62: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 450.65 MHz, Ch Sp 12.5 kHz	81
EXHIBIT 6E- 63: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 459.125 MHz, Ch Sp 12.5 kHz ..	82
EXHIBIT 6E- 64: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 467.775 MHz, Ch Sp 12.5 kHz ..	83
EXHIBIT 6E- 65: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 806.0125 MHz, Ch Sp 12.5 kHz	84
EXHIBIT 6E- 66: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 806.0125 MHz, Ch Sp 12.5 kHz	85
EXHIBIT 6E- 67: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 814.9875 MHz, Ch Sp 12.5 kHz	86
EXHIBIT 6E- 68: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 814.9875 MHz, Ch Sp 12.5 kHz	87
EXHIBIT 6E- 69: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 823.9875 MHz, Ch Sp 12.5 kHz	88
EXHIBIT 6E- 70: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 851.0125 MHz, Ch Sp 12.5 kHz	89
EXHIBIT 6E- 71: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 853.9875 MHz, Ch Sp 12.5 kHz	90
EXHIBIT 6E- 72: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 860.0125 MHz, Ch Sp 12.5 kHz	91
EXHIBIT 6E- 73: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 860.0125 MHz, Ch Sp 12.5 kHz	92
EXHIBIT 6E- 74: OCCUPIED BANDWIDTH DIGITAL VOICE ENCRYPTION 8K10F1E - FREQ 868.8875 MHz, Ch Sp 12.5 kHz	93
EXHIBIT 6E- 75: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 138.0125 MHz, Ch Sp 12.5 kHz	94
EXHIBIT 6E- 76: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 158.55 MHz, Ch Sp 12.5 kHz	95
EXHIBIT 6E- 77: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 161.7 MHz, Ch Sp 12.5 kHz	96
EXHIBIT 6E- 78: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 173.3875 MHz, Ch Sp 12.5 kHz	97
EXHIBIT 6E- 79: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 406.2 MHz, Ch Sp 12.5 kHz	98
EXHIBIT 6E- 80: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 450.65 MHz, Ch Sp 12.5 kHz	99
EXHIBIT 6E- 81: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 459.125 MHz, Ch Sp 12.5 kHz	100
EXHIBIT 6E- 82: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 467.775 MHz, Ch Sp 12.5 kHz	101
EXHIBIT 6E- 83: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 806.0125 MHz, Ch Sp 12.5 kHz	102
EXHIBIT 6E- 84: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 806.0125 MHz, Ch Sp 12.5 kHz	103

EXHIBIT 6E- 85: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 814.9875 MHz, CH Sp 12.5 kHz	104
EXHIBIT 6E- 86: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 814.9875 MHz, CH Sp 12.5 kHz	105
EXHIBIT 6E- 87: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 823.9875 MHz, CH Sp 12.5 kHz	106
EXHIBIT 6E- 88: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 851.0125 MHz, CH Sp 12.5 kHz	107
EXHIBIT 6E- 89: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 853.9875 MHz, CH Sp 12.5 kHz	108
EXHIBIT 6E- 90: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 860.0125 MHz, CH Sp 12.5 kHz	109
EXHIBIT 6E- 91: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 860.0125 MHz, CH Sp 12.5 kHz	110
EXHIBIT 6E- 92: OCCUPIED BANDWIDTH DIGITAL DATA 8K10F1D - FREQ 868.8875 MHz, CH Sp 12.5 kHz	111
EXHIBIT 6E- 93: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 138.0125 MHz, CH Sp 12.5 kHz.....	112
EXHIBIT 6E- 94: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 158.55 MHz, CH Sp 12.5 kHz	113
EXHIBIT 6E- 95: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 161.7 MHz, CH Sp 12.5 kHz.....	114
EXHIBIT 6E- 96: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 173.3875 MHz, CH Sp 12.5 kHz.....	115
EXHIBIT 6E- 97: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 406.2 MHz, CH Sp 12.5 kHz.....	116
EXHIBIT 6E- 98: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 450.65 MHz, CH Sp 12.5 kHz.....	117
EXHIBIT 6E- 99: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 459.125 MHz, CH Sp 12.5 kHz.....	118
EXHIBIT 6E- 100: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 467.775 MHz, CH Sp 12.5 kHz.....	119
EXHIBIT 6E- 101: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 806.0125 MHz, CH Sp 12.5 kHz.....	120
EXHIBIT 6E- 102: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 806.0125 MHz, CH Sp 12.5 kHz.....	121
EXHIBIT 6E- 103: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 814.9875 MHz, CH Sp 12.5 kHz.....	122
EXHIBIT 6E- 104: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 814.9875 MHz, CH Sp 12.5 kHz.....	123
EXHIBIT 6E- 105: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 823.9875 MHz, CH Sp 12.5 kHz.....	124
EXHIBIT 6E- 106: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 851.0125 MHz, CH Sp 12.5 kHz.....	125
EXHIBIT 6E- 107: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 853.9875 MHz, CH Sp 12.5 kHz.....	126
EXHIBIT 6E- 108: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 860.0125 MHz, CH Sp 12.5 kHz.....	127
EXHIBIT 6E- 109: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 860.0125 MHz, CH Sp 12.5 kHz.....	128
EXHIBIT 6E- 110: OCCUPIED BANDWIDTH DIGITAL TDMA 8K10F1W - FREQ 868.8875 MHz, CH Sp 12.5 kHz.....	129
EXHIBIT 6E- 111: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 161.7 MHz, CH Sp 20 kHz.....	130
EXHIBIT 6E- 112: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 450.65 MHz, CH Sp 20 kHz...	131
EXHIBIT 6E- 113: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 511.9875 MHz, CH Sp 20 kHz132	
EXHIBIT 6E- 114: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 806.0125 MHz, CH Sp 20 kHz133	
EXHIBIT 6E- 115: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 806.0125 MHz, CH Sp 20 kHz134	
EXHIBIT 6E- 116: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 814.9875 MHz, CH Sp 20 kHz135	
EXHIBIT 6E- 117: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 814.9875 MHz, CH Sp 20 kHz136	
EXHIBIT 6E- 118: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 814.9875 MHz, CH Sp 20 kHz137	
EXHIBIT 6E- 119: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 823.9875 MHz, CH Sp 20 kHz138	
EXHIBIT 6E- 120: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 823.9875 MHz, CH Sp 20 kHz139	
EXHIBIT 6E- 121: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 851.0125 MHz, CH Sp 20 kHz140	
EXHIBIT 6E- 122: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 851.0125 MHz, CH Sp 20 kHz141	
EXHIBIT 6E- 123: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 860.0125 MHz, CH Sp 20 kHz142	
EXHIBIT 6E- 124: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 860.0125 MHz, CH Sp 20 kHz143	
EXHIBIT 6E- 125: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 860.0125 MHz, CH Sp 20 kHz144	
EXHIBIT 6E- 126: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 868.8875 MHz, CH Sp 20 kHz145	
EXHIBIT 6E- 127: OCCUPIED BANDWIDTH ANALOG VOICE ENCRYPTION 20K0F1E - FREQ 868.8875 MHz, CH Sp 20 kHz146	
EXHIBIT 6E- 128: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E (PART 22) - FREQ 158.55 MHz, CH Sp 20 kHz	147
EXHIBIT 6E- 129: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E (PART 80.211(F)) - FREQ 158.55.....	148
MHz, CH Sp 20 kHz	148
EXHIBIT 6E- 130: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E (PART 80.211(c)) - FREQ 158.55 MHz, CH Sp 20 kHz	
.....	149
EXHIBIT 6E- 131: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E (PART 22) - FREQ 459.125 MHz, CH Sp 20 kHz ...	150
EXHIBIT 6E- 132: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E (PART 80.211(F)) - FREQ 467.775 MHz, CH Sp 20 kHz	
.....	151
EXHIBIT 6E- 133: OCCUPIED BANDWIDTH ANALOG VOICE 16K0F3E (PART 80.211(c)) - FREQ 467.775 MHz, CH Sp 20	
kHz.....	152

EXHIBIT 6F- 1: TRSE DIGITAL C4FM – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	154
EXHIBIT 6F- 2: TRSE DIGITAL C4FM 1 WATT – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	155
EXHIBIT 6F- 3: TRSE DIGITAL C4FM – FREQ 158.55 MHz, Ch Sp 12.5 kHz	156
EXHIBIT 6F- 4: TRSE DIGITAL C4FM 1 WATT – FREQ 158.55 MHz, Ch Sp 12.5 kHz	157
EXHIBIT 6F- 5: TRSE DIGITAL C4FM – FREQ 161.7 MHz, Ch Sp 12.5 kHz	158
EXHIBIT 6F- 6: TRSE DIGITAL C4FM 1 WATT – FREQ 161.7 MHz, Ch Sp 12.5 kHz	159
EXHIBIT 6F- 7: TRSE DIGITAL C4FM – FREQ 173.3875 MHz, Ch Sp 12.5 kHz	160
EXHIBIT 6F- 8: TRSE DIGITAL C4FM 1 WATT – FREQ 173.3875 MHz, Ch Sp 12.5 kHz	161
EXHIBIT 6F- 9: TRSE PHASE II – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	162
EXHIBIT 6F- 10: TRSE PHASE II 1 WATT – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	163
EXHIBIT 6F- 11: TRSE PHASE II – FREQ 158.55 MHz, Ch Sp 12.5 kHz	164
EXHIBIT 6F- 12: TRSE PHASE II 1 WATT – FREQ 158.55 MHz, Ch Sp 12.5 kHz	165
EXHIBIT 6F- 13: TRSE PHASE II – FREQ 161.7 MHz, Ch Sp 12.5 kHz	166
EXHIBIT 6F- 14: TRSE PHASE II 1 WATT – FREQ 161.7 MHz, Ch Sp 12.5 kHz	167
EXHIBIT 6F- 15: TRSE PHASE II – FREQ 173.3875 MHz, Ch Sp 12.5 kHz	168
EXHIBIT 6F- 16: TRSE PHASE II 1 WATT – FREQ 173.3875 MHz, Ch Sp 12.5 kHz	169
EXHIBIT 6F- 17: TRSE DIGITAL C4FM – FREQ 380.0125 MHz, Ch Sp 12.5 kHz	170
EXHIBIT 6F- 18: TRSE DIGITAL C4FM 1 WATT– FREQ 380.0125 MHz, Ch Sp 12.5 kHz	171
EXHIBIT 6F- 19: TRSE DIGITAL C4FM – FREQ 406.2 MHz, Ch Sp 12.5 kHz	172
EXHIBIT 6F- 20: TRSE DIGITAL C4FM 1 WATT – FREQ 406.2 MHz, Ch Sp 12.5 kHz	173
EXHIBIT 6F- 21: TRSE DIGITAL C4FM – FREQ 450.65 MHz, Ch Sp 12.5 kHz	174
EXHIBIT 6F- 22: TRSE DIGITAL C4FM 1 WATT – FREQ 450.65 MHz, Ch Sp 12.5 kHz	175
EXHIBIT 6F- 23: TRSE DIGITAL C4FM – FREQ 459.125 MHz, Ch Sp 12.5 kHz	176
EXHIBIT 6F- 24: TRSE DIGITAL C4FM 1 WATT– FREQ 459.125 MHz, Ch Sp 12.5 kHz	177
EXHIBIT 6F- 25: TRSE DIGITAL C4FM – FREQ 467.775 MHz, Ch Sp 12.5 kHz	178
EXHIBIT 6F- 26: TRSE DIGITAL C4FM 1 WATT – FREQ 467.775 MHz, Ch Sp 12.5 kHz	179
EXHIBIT 6F- 27: TRSE DIGITAL C4FM – FREQ 482.0125 MHz, Ch Sp 12.5 kHz	180
EXHIBIT 6F- 28: TRSE DIGITAL C4FM 1 WATT– FREQ 482.0125 MHz, Ch Sp 12.5 kHz	181
EXHIBIT 6F- 29: TRSE DIGITAL C4FM – FREQ 511.9875 MHz, Ch Sp 12.5 kHz	182
EXHIBIT 6F- 30: TRSE DIGITAL C4FM 1 WATT – FREQ 511.9875 MHz, Ch Sp 12.5 kHz	183
EXHIBIT 6F- 31: TRSE DIGITAL C4FM – FREQ 519.9875 MHz, Ch Sp 12.5 kHz	184
EXHIBIT 6F- 32: TRSE DIGITAL C4FM 1 WATT– FREQ 519.9875 MHz, Ch Sp 12.5 kHz	185
EXHIBIT 6F- 33: TRSE PHASE II – FREQ 380.0125 MHz, Ch Sp 12.5 kHz	186
EXHIBIT 6F- 34: TRSE PHASE II 1 WATT– FREQ 380.0125 MHz, Ch Sp 12.5 kHz	187
EXHIBIT 6F- 35: TRSE PHASE II – FREQ 406.2 MHz, Ch Sp 12.5 kHz	188
EXHIBIT 6F- 36: TRSE PHASE II 1 WATT – FREQ 406.2 MHz, Ch Sp 12.5 kHz	189
EXHIBIT 6F- 37: TRSE PHASE II – FREQ 450.65 MHz, Ch Sp 12.5 kHz	190
EXHIBIT 6F- 38: TRSE PHASE II 1 WATT – FREQ 450.65 MHz, Ch Sp 12.5 kHz	191
EXHIBIT 6F- 39: TRSE PHASE II – FREQ 459.125 MHz, Ch Sp 12.5 kHz	192
EXHIBIT 6F- 40: TRSE PHASE II 1 WATT – FREQ 459.125 MHz, Ch Sp 12.5 kHz	193
EXHIBIT 6F- 41: TRSE PHASE II – FREQ 467.775 MHz, Ch Sp 12.5 kHz	194
EXHIBIT 6F- 42: TRSE PHASE II 1 WATT – FREQ 467.775 MHz, Ch Sp 12.5 kHz	195
EXHIBIT 6F- 43: TRSE PHASE II – FREQ 482.0125 MHz, Ch Sp 12.5 kHz	196
EXHIBIT 6F- 44: TRSE PHASE II 1 WATT – FREQ 482.0125 MHz, Ch Sp 12.5 kHz	197
EXHIBIT 6F- 45: TRSE PHASE II – FREQ 511.9875 MHz, Ch Sp 12.5 kHz	198
EXHIBIT 6F- 46: TRSE PHASE II 1 WATT – FREQ 511.9875 MHz, Ch Sp 12.5 kHz	199
EXHIBIT 6F- 47: TRSE PHASE II – FREQ 519.9875 MHz, Ch Sp 12.5 kHz	200
EXHIBIT 6F- 48: TRSE PHASE II 1 WATT – FREQ 519.9875 MHz, Ch Sp 12.5 kHz	201
EXHIBIT 6F- 49: TRSE ANALOG – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	202
EXHIBIT 6F- 50: TRSE ANALOG 1 WATT – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	203
EXHIBIT 6F- 51: TRSE ANALOG – FREQ 769.0125 MHz, Ch Sp 12.5 kHz	204
EXHIBIT 6F- 52: TRSE ANALOG – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	205
EXHIBIT 6F- 53: TRSE ANALOG 1 WATT – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	206

EXHIBIT 6F- 54: TRSE ANALOG – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	207
EXHIBIT 6F- 55: TRSE ANALOG 1 WATT – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	208
EXHIBIT 6F- 56: TRSE DIGITAL C4FM – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	209
EXHIBIT 6F- 57: TRSE DIGITAL C4FM 1 WATT – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	210
EXHIBIT 6F- 58: TRSE DIGITAL C4FM – FREQ 769.0125 MHz, Ch Sp 12.5 kHz	211
EXHIBIT 6F- 59: TRSE DIGITAL C4FM – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	212
EXHIBIT 6F- 60: TRSE DIGITAL C4FM 1 WATT – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	213
EXHIBIT 6F- 61: TRSE DIGITAL C4FM – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	214
EXHIBIT 6F- 62: TRSE DIGITAL C4FM 1 WATT – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	215
EXHIBIT 6F- 63: TRSE PHASE II – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	216
EXHIBIT 6F- 64: TRSE PHASE II 1 WATT – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	217
EXHIBIT 6F- 65: TRSE PHASE II – FREQ 769.0125 MHz, Ch Sp 12.5 kHz	218
EXHIBIT 6F- 66: TRSE PHASE II – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	219
EXHIBIT 6F- 67: TRSE PHASE II 1 WATT – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	220
EXHIBIT 6F- 68: TRSE PHASE II – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	221
EXHIBIT 6F- 69: TRSE PHASE II 1 WATT – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	222
EXHIBIT 6F- 70: TRSE DIGITAL C4FM – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	223
EXHIBIT 6F- 71: TRSE DIGITAL C4FM 1 WATT – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	224
EXHIBIT 6F- 72: TRSE DIGITAL C4FM – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	225
EXHIBIT 6F- 73: TRSE DIGITAL C4FM 1 WATT – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	226
EXHIBIT 6F- 74: TRSE DIGITAL C4FM – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	227
EXHIBIT 6F- 75: TRSE DIGITAL C4FM 1 WATT – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	228
EXHIBIT 6F- 76: TRSE DIGITAL C4FM – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	229
EXHIBIT 6F- 77: TRSE DIGITAL C4FM 1 WATT – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	230
EXHIBIT 6F- 78: TRSE DIGITAL C4FM – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	231
EXHIBIT 6F- 79: TRSE DIGITAL C4FM 1 WATT – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	232
EXHIBIT 6F- 80: TRSE DIGITAL C4FM – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	233
EXHIBIT 6F- 81: TRSE DIGITAL C4FM 1 WATT – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	234
EXHIBIT 6F- 82: TRSE PHASE II – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	235
EXHIBIT 6F- 83: TRSE PHASE II 1 WATT – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	236
EXHIBIT 6F- 84: TRSE PHASE II – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	237
EXHIBIT 6F- 85: TRSE PHASE II 1 WATT – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	238
EXHIBIT 6F- 86: TRSE PHASE II – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	239
EXHIBIT 6F- 87: TRSE PHASE II 1 WATT – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	240
EXHIBIT 6F- 88: TRSE PHASE II – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	241
EXHIBIT 6F- 89: TRSE PHASE II 1 WATT – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	242
EXHIBIT 6F- 90: TRSE PHASE II – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	243
EXHIBIT 6F- 91: TRSE PHASE II 1 WATT – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	244
EXHIBIT 6F- 92: TRSE PHASE II – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	245
EXHIBIT 6F- 93: TRSE PHASE II 1 WATT – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	246
EXHIBIT 6F- 94: TRSE ANALOG – FREQ 138.0125 MHz, Ch Sp 25 kHz	247
EXHIBIT 6F- 95: TRSE ANALOG 1 WATT – FREQ 138.0125 MHz, Ch Sp 25 kHz	248
EXHIBIT 6F- 96: TRSE ANALOG – FREQ 158.55 MHz, Ch Sp 20 kHz	249
EXHIBIT 6F- 97: TRSE ANALOG 1 WATT – FREQ 158.55 MHz, Ch Sp 20 kHz	250
EXHIBIT 6F- 98: TRSE ANALOG – FREQ 158.55 MHz, Ch Sp 25 kHz	251
EXHIBIT 6F- 99: TRSE ANALOG 1 WATT – FREQ 158.55 MHz, Ch Sp 25 kHz	252
EXHIBIT 6F- 100: TRSE ANALOG – FREQ 161.7 MHz, Ch Sp 20 kHz	253
EXHIBIT 6F- 101: TRSE ANALOG 1 WATT – FREQ 161.7 MHz, Ch Sp 20 kHz	254
EXHIBIT 6F- 102: TRSE ANALOG – FREQ 161.7 MHz, Ch Sp 25 kHz	255
EXHIBIT 6F- 103: TRSE ANALOG 1 WATT – FREQ 161.7 MHz, Ch Sp 25 kHz	256
EXHIBIT 6F- 104: TRSE ANALOG – FREQ 173.3875 MHz, Ch Sp 25 kHz	257
EXHIBIT 6F- 105: TRSE ANALOG 1 WATT – FREQ 173.3875 MHz, Ch Sp 25 kHz	258
EXHIBIT 6F- 106: TRSE ANALOG – FREQ 380.0125 MHz, Ch Sp 25 kHz	259

EXHIBIT 6F- 107: TRSE ANALOG 1 WATT – FREQ 380.0125 MHz, Ch Sp 25 kHz	260
EXHIBIT 6F- 108: TRSE ANALOG – FREQ 406.2 MHz, Ch Sp 25 kHz	261
EXHIBIT 6F- 109: TRSE ANALOG 1 WATT – FREQ 406.2 MHz, Ch Sp 25 kHz	262
EXHIBIT 6F- 110: TRSE ANALOG – FREQ 450.65 MHz, Ch Sp 25 kHz	263
EXHIBIT 6F- 111: TRSE ANALOG 1 WATT – FREQ 450.65 MHz, Ch Sp 25 kHz	264
EXHIBIT 6F- 112: TRSE ANALOG – FREQ 459.125 MHz, Ch Sp 20 kHz	265
EXHIBIT 6F- 113: TRSE ANALOG 1 WATT – FREQ 459.125 MHz, Ch Sp 20 kHz	266
EXHIBIT 6F- 114: TRSE ANALOG – FREQ 511.9875 MHz, Ch Sp 20 kHz	267
EXHIBIT 6F- 115: TRSE ANALOG 1 WATT – FREQ 511.9875 MHz, Ch Sp 20 kHz	268
EXHIBIT 6F- 116: TRSE ANALOG – FREQ 511.9875 MHz, Ch Sp 25 kHz	269
EXHIBIT 6F- 117: TRSE ANALOG 1 WATT – FREQ 511.9875 MHz, Ch Sp 25 kHz	270
EXHIBIT 6F- 118: TRSE ANALOG – FREQ 519.9875 MHz, Ch Sp 25 kHz	271
EXHIBIT 6F- 119: TRSE ANALOG 1 WATT – FREQ 519.9875 MHz, Ch Sp 25 kHz	272
EXHIBIT 6F- 120: TRSE ANALOG – FREQ 806.0125 MHz, Ch Sp 25 kHz	273
EXHIBIT 6F- 121: TRSE ANALOG 1 WATT – FREQ 806.0125 MHz, Ch Sp 25 kHz	274
EXHIBIT 6F- 122: TRSE ANALOG – FREQ 814.9875 MHz, Ch Sp 25 kHz	275
EXHIBIT 6F- 123: TRSE ANALOG 1 WATT – FREQ 814.9875 MHz, Ch Sp 25 kHz	276
EXHIBIT 6F- 124: TRSE ANALOG – FREQ 823.9875 MHz, Ch Sp 25 kHz	277
EXHIBIT 6F- 125: TRSE ANALOG 1 WATT – FREQ 823.9875 MHz, Ch Sp 25 kHz	278
EXHIBIT 6F- 126: TRSE ANALOG – FREQ 851.0125 MHz, Ch Sp 25 kHz	279
EXHIBIT 6F- 127: TRSE ANALOG 1 WATT – FREQ 851.0125 MHz, Ch Sp 25 kHz	280
EXHIBIT 6F- 128: TRSE ANALOG – FREQ 860.0125 MHz, Ch Sp 25 kHz	281
EXHIBIT 6F- 129: TRSE ANALOG 1 WATT – FREQ 860.0125 MHz, Ch Sp 25 kHz	282
EXHIBIT 6F- 130: TRSE ANALOG – FREQ 868.8875 MHz, Ch Sp 25 kHz	283
EXHIBIT 6F- 131: TRSE ANALOG 1 WATT – FREQ 868.8875 MHz, Ch Sp 25 kHz	284
EXHIBIT 6F- 132: TRSE ANALOG – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	285
EXHIBIT 6F- 133: TRSE ANALOG 1WATT – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	286
EXHIBIT 6F- 134: TRSE ANALOG – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	287
EXHIBIT 6F- 135: TRSE ANALOG 1 WATT – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	288
EXHIBIT 6F- 136: TRSE DIGITAL C4FM – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	289
EXHIBIT 6F- 137: TRSE DIGITAL C4FM 1 WATT – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	290
EXHIBIT 6F- 138: TRSE DIGITAL C4FM – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	291
EXHIBIT 6F- 139: TRSE DIGITAL C4FM 1 WATT – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	292
EXHIBIT 6F- 140: TRSE ANALOG – FREQ 467.775 MHz, Ch Sp 25 kHz	293
EXHIBIT 6F- 141: TRSE ANALOG 1 WATT – FREQ 467.775 MHz, Ch Sp 25 kHz	294
EXHIBIT 6F- 142: TRSE ANALOG – FREQ 482.0125 MHz, Ch Sp 20 kHz	295
EXHIBIT 6F- 143: TRSE ANALOG 1 WATT – FREQ 482.0125 MHz, Ch Sp 20 kHz	296
EXHIBIT 6F- 144: TRSE PHASE II – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	297
EXHIBIT 6F- 145: TRSE PHASE II 1 WATT – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	298
EXHIBIT 6F- 146: TRSE PHASE II – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	299
EXHIBIT 6F- 147: TRSE PHASE II 1 WATT – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	300
EXHIBIT 6F- 148: 1559 – 1610 MHz RADIATED EMISSIONS (GNSS), 799.0875 MHz	301
EXHIBIT 6F- 149: 1559 – 1610 MHz RADIATED EMISSIONS (GNSS), 804.9125 MHz	301
EXHIBIT 6G- 1: EFFECTIVE RADIATED POWER (ERP), 769.0125 MHz	302
EXHIBIT 6G- 2: EFFECTIVE RADIATED POWER (ERP), 769.0875 MHz	302
EXHIBIT 6G- 3: EFFECTIVE RADIATED POWER (ERP), 799.0125 MHz	303
EXHIBIT 6G- 4: EFFECTIVE RADIATED POWER (ERP), 804.9125 MHz	303
EXHIBIT 6H- 1: TCSE ANALOG HIGH POWER – FREQ 138.0125 MHz, Ch Sp 25 kHz	304
EXHIBIT 6H- 2: TCSE ANALOG LOW POWER – FREQ 138.0125 MHz, Ch Sp 25 kHz	305
EXHIBIT 6H- 3: TCSE APCO HIGH POWER – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	305
EXHIBIT 6H- 4: TCSE APCO LOW POWER – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	306
EXHIBIT 6H- 5: TCSE APCO PHASE II HIGH POWER – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	306
EXHIBIT 6H- 6: TCSE APCO PHASE II LOW POWER – FREQ 138.0125 MHz, Ch Sp 12.5 kHz	307

EXHIBIT 6H- 7: TCSE ANALOG HIGH POWER – FREQ 158.55 MHz, Ch Sp 20 kHz.....	307
EXHIBIT 6H- 8: TCSE ANALOG LOW POWER – FREQ 158.55 MHz, Ch Sp 20 kHz	308
EXHIBIT 6H- 9: TCSE ANALOG HIGH POWER – FREQ 158.55 MHz, Ch Sp 25 kHz.....	308
EXHIBIT 6H- 10: TCSE ANALOG LOW POWER – FREQ 158.55 MHz, Ch Sp 25 kHz	309
EXHIBIT 6H- 11: TCSE APCO HIGH POWER – FREQ 158.55 MHz, Ch Sp 12.5 kHz	309
EXHIBIT 6H- 12: TCSE APCO LOW POWER – FREQ 158.55 MHz, Ch Sp 12.5 kHz	310
EXHIBIT 6H- 13: TCSE APCO PHASE II HIGH POWER – FREQ 158.55 MHz, Ch Sp 12.5 kHz	310
EXHIBIT 6H- 14: TCSE APCO PHASE II LOW POWER – FREQ 158.55 MHz, Ch Sp 12.5 kHz.....	311
EXHIBIT 6H- 15: TCSE ANALOG HIGH POWER – FREQ 161.7 MHz, Ch Sp 20 kHz.....	311
EXHIBIT 6H- 16: TCSE ANALOG LOW POWER – FREQ 161.7 MHz, Ch Sp 20 kHz	312
EXHIBIT 6H- 17: TCSE ANALOG HIGH POWER – FREQ 161.7 MHz, Ch Sp 25 kHz.....	312
EXHIBIT 6H- 18: TCSE ANALOG LOW POWER – FREQ 161.7 MHz, Ch Sp 25 kHz	313
EXHIBIT 6H- 19: TCSE APCO HIGH POWER – FREQ 161.7 MHz, Ch Sp 12.5 kHz	313
EXHIBIT 6H- 20: TCSE APCO LOW POWER – FREQ 161.7 MHz, Ch Sp 12.5 kHz	314
EXHIBIT 6H- 21: TCSE APCO PHASE II HIGH POWER – FREQ 161.7 MHz, Ch Sp 12.5 kHz	314
EXHIBIT 6H- 22: TCSE APCO PHASE II LOW POWER – FREQ 161.7 MHz, Ch Sp 12.5 kHz.....	315
EXHIBIT 6H- 23: TCSE ANALOG HIGH POWER – FREQ 173.3875 MHz, Ch Sp 25 kHz.....	315
EXHIBIT 6H- 24: TCSE ANALOG LOW POWER – FREQ 173.3875 MHz, Ch Sp 25 kHz	316
EXHIBIT 6H- 25: TCSE APCO HIGH POWER – FREQ 173.3875 MHz, Ch Sp 12.5 kHz	316
EXHIBIT 6H- 26: TCSE APCO LOW POWER – FREQ 173.3875 MHz, Ch Sp 12.5 kHz.....	317
EXHIBIT 6H- 27: TCSE APCO PHASE II HIGH POWER – FREQ 173.3875 MHz, Ch Sp 12.5 kHz	317
EXHIBIT 6H- 28: TCSE APCO PHASE II LOW POWER – FREQ 173.3875 MHz, Ch Sp 12.5 kHz.....	318
EXHIBIT 6H- 29: TCSE ANALOG HIGH POWER – FREQ 380.0125 MHz, Ch Sp 25 kHz.....	318
EXHIBIT 6H- 30: TCSE ANALOG LOW POWER – FREQ 380.0125 MHz, Ch Sp 25 kHz	319
EXHIBIT 6H- 31: TCSE APCO HIGH POWER – FREQ 380.0125 MHz, Ch Sp 12.5 kHz	319
EXHIBIT 6H- 32: TCSE APCO LOW POWER – FREQ 380.0125 MHz, Ch Sp 12.5 kHz.....	320
EXHIBIT 6H- 33: TCSE APCO PHASE II HIGH POWER – FREQ 380.0125 MHz, Ch Sp 12.5 kHz	320
EXHIBIT 6H- 34: TCSE APCO PHASE II LOW POWER – FREQ 380.0125 MHz, Ch Sp 12.5 kHz.....	321
EXHIBIT 6H- 35: TCSE ANALOG HIGH POWER – FREQ 406.2 MHz, Ch Sp 25 kHz.....	321
EXHIBIT 6H- 36: TCSE ANALOG LOW POWER – FREQ 406.2 MHz, Ch Sp 25 kHz	322
EXHIBIT 6H- 37: TCSE APCO HIGH POWER – FREQ 406.2 MHz, Ch Sp 12.5 kHz	322
EXHIBIT 6H- 38: TCSE APCO LOW POWER – FREQ 406.2 MHz, Ch Sp 12.5 kHz	323
EXHIBIT 6H- 39: TCSE APCO PHASE II HIGH POWER – FREQ 406.2 MHz, Ch Sp 12.5 kHz.....	323
EXHIBIT 6H- 40: TCSE APCO PHASE II LOW POWER – FREQ 406.2 MHz, Ch Sp 12.5 kHz.....	324
EXHIBIT 6H- 41: TCSE ANALOG HIGH POWER – FREQ 450.65 MHz, Ch Sp 25 kHz.....	324
EXHIBIT 6H- 42: TCSE ANALOG LOW POWER – FREQ 450.65 MHz, Ch Sp 25 kHz	325
EXHIBIT 6H- 43: TCSE APCO HIGH POWER – FREQ 450.65 MHz, Ch Sp 12.5 kHz	325
EXHIBIT 6H- 44: TCSE APCO LOW POWER – FREQ 450.65 MHz, Ch Sp 12.5 kHz.....	326
EXHIBIT 6H- 45: TCSE APCO PHASE II HIGH POWER – FREQ 450.65 MHz, Ch Sp 12.5 kHz	326
EXHIBIT 6H- 46: TCSE APCO PHASE II LOW POWER – FREQ 450.65 MHz, Ch Sp 12.5 kHz.....	327
EXHIBIT 6H- 47: TCSE ANALOG HIGH POWER – FREQ 459.125 MHz, Ch Sp 20 kHz.....	327
EXHIBIT 6H- 48: TCSE ANALOG LOW POWER – FREQ 459.125 MHz, Ch Sp 20 kHz	328
EXHIBIT 6H- 49: TCSE APCO HIGH POWER – FREQ 459.125 MHz, Ch Sp 12.5 kHz	328
EXHIBIT 6H- 50: TCSE APCO LOW POWER – FREQ 459.125 MHz, Ch Sp 12.5 kHz.....	329
EXHIBIT 6H- 51: TCSE APCO PHASE II HIGH POWER – FREQ 459.125 MHz, Ch Sp 12.5 kHz	329
EXHIBIT 6H- 52: TCSE APCO PHASE II LOW POWER – FREQ 459.125 MHz, Ch Sp 12.5 kHz.....	330
EXHIBIT 6H- 53: TCSE ANALOG HIGH POWER – FREQ 467.775 MHz, Ch Sp 25 kHz.....	330
EXHIBIT 6H- 54: TCSE ANALOG LOW POWER – FREQ 467.775 MHz, Ch Sp 25 kHz	331
EXHIBIT 6H- 55: TCSE APCO HIGH POWER – FREQ 467.775 MHz, Ch Sp 12.5 kHz	331
EXHIBIT 6H- 56: TCSE APCO LOW POWER – FREQ 467.775 MHz, Ch Sp 12.5 kHz	332
EXHIBIT 6H- 57: TCSE APCO PHASE II HIGH POWER – FREQ 467.775 MHz, Ch Sp 12.5 kHz	332
EXHIBIT 6H- 58: TCSE APCO PHASE II LOW POWER – FREQ 467.775 MHz, Ch Sp 12.5 kHz.....	333
EXHIBIT 6H- 59: TCSE ANALOG HIGH POWER – FREQ 482.0125 MHz, Ch Sp 20 kHz.....	333

EXHIBIT 6H- 60: TCSE ANALOG LOW POWER – FREQ 482.0125 MHz, Ch Sp 20 kHz	334
EXHIBIT 6H- 61: TCSE APCO HIGH POWER – FREQ 482.0125 MHz, Ch Sp 12.5 kHz	334
EXHIBIT 6H- 62: TCSE APCO LOW POWER – FREQ 482.0125 MHz, Ch Sp 12.5 kHz.....	335
EXHIBIT 6H- 63: TCSE APCO PHASE II HIGH POWER – FREQ 482.0125 MHz, Ch Sp 12.5 kHz	335
EXHIBIT 6H- 64: TCSE APCO PHASE II LOW POWER – FREQ 482.0125 MHz, Ch Sp 12.5 kHz.....	336
EXHIBIT 6H- 65: TCSE ANALOG HIGH POWER – FREQ 511.9875 MHz, Ch Sp 20 kHz.....	336
EXHIBIT 6H- 66: TCSE ANALOG LOW POWER – FREQ 511.9875 MHz, Ch Sp 20 kHz	337
EXHIBIT 6H- 67: TCSE ANALOG HIGH POWER – FREQ 511.9875 MHz, Ch Sp 25 kHz.....	337
EXHIBIT 6H- 68: TCSE ANALOG LOW POWER – FREQ 511.9875 MHz, Ch Sp 25 kHz	338
EXHIBIT 6H- 69: TCSE APCO HIGH POWER – FREQ 511.9875 MHz, Ch Sp 12.5 kHz	338
EXHIBIT 6H- 70: TCSE APCO LOW POWER – FREQ 511.9875 MHz, Ch Sp 12.5 kHz.....	339
EXHIBIT 6H- 71: TCSE APCO PHASE II HIGH POWER – FREQ 511.9875 MHz, Ch Sp 12.5 kHz	339
EXHIBIT 6H- 72: TCSE APCO PHASE II LOW POWER – FREQ 511.9875 MHz, Ch Sp 12.5 kHz.....	340
EXHIBIT 6H- 73: TCSE ANALOG HIGH POWER – FREQ 519.9875 MHz, Ch Sp 25 kHz.....	340
EXHIBIT 6H- 74: TCSE ANALOG LOW POWER – FREQ 519.9875 MHz, Ch Sp 25 kHz	341
EXHIBIT 6H- 75: TCSE APCO HIGH POWER – FREQ 519.9875 MHz, Ch Sp 12.5 kHz	341
EXHIBIT 6H- 76: TCSE APCO LOW POWER – FREQ 519.9875 MHz, Ch Sp 12.5 kHz.....	342
EXHIBIT 6H- 77: TCSE APCO PHASE II HIGH POWER – FREQ 519.9875 MHz, Ch Sp 12.5 kHz	342
EXHIBIT 6H- 78: TCSE APCO PHASE II LOW POWER – FREQ 519.9875 MHz, Ch Sp 12.5 kHz.....	343
EXHIBIT 6H- 79: TCSE ANALOG HIGH POWER – FREQ 764.0125 MHz, Ch Sp 12.5 kHz.....	343
EXHIBIT 6H- 80: TCSE ANALOG LOW POWER – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	344
EXHIBIT 6H- 81: TCSE APCO HIGH POWER – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	344
EXHIBIT 6H- 82: TCSE APCO LOW POWER – FREQ 764.0125 MHz, Ch Sp 12.5 kHz.....	345
EXHIBIT 6H- 83: TCSE APCO PHASE II HIGH POWER – FREQ 764.0125 MHz, Ch Sp 12.5 kHz	345
EXHIBIT 6H- 84: TCSE APCO PHASE II LOW POWER – FREQ 764.0125 MHz, Ch Sp 12.5 kHz.....	346
EXHIBIT 6H- 85: TCSE ANALOG HIGH POWER – FREQ 769.0125 MHz, Ch Sp 12.5 kHz.....	346
EXHIBIT 6H- 86: TCSE ANALOG LOW POWER – FREQ 769.0125 MHz, Ch Sp 12.5 kHz	347
EXHIBIT 6H- 87: TCSE APCO HIGH POWER – FREQ 769.0125 MHz, Ch Sp 12.5 kHz	347
EXHIBIT 6H- 88: TCSE APCO LOW POWER – FREQ 769.0125 MHz, Ch Sp 12.5 kHz.....	348
EXHIBIT 6H- 89: TCSE APCO PHASE II HIGH POWER – FREQ 769.0125 MHz, Ch Sp 12.5 kHz	348
EXHIBIT 6H- 90: TCSE APCO PHASE II LOW POWER – FREQ 769.0125 MHz, Ch Sp 12.5 kHz.....	349
EXHIBIT 6H- 92: TCSE ANALOG LOW POWER – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	350
EXHIBIT 6H- 94: TCSE APCO LOW POWER – FREQ 769.0875 MHz, Ch Sp 12.5 kHz.....	351
EXHIBIT 6H- 96: TCSE APCO PHASE II LOW POWER – FREQ 769.0875 MHz, Ch Sp 12.5 kHz.....	352
EXHIBIT 6H- 97: TCSE ANALOG HIGH POWER – FREQ 774.8875 MHz, Ch Sp 12.5 kHz.....	352
EXHIBIT 6H- 98: TCSE ANALOG LOW POWER – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	353
EXHIBIT 6H- 99: TCSE APCO HIGH POWER – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	353
EXHIBIT 6H- 100: TCSE APCO LOW POWER – FREQ 774.8875 MHz, Ch Sp 12.5 kHz.....	354
EXHIBIT 6H- 101: TCSE APCO PHASE II HIGH POWER – FREQ 774.8875 MHz, Ch Sp 12.5 kHz	354
EXHIBIT 6H- 102: TCSE APCO PHASE II LOW POWER – FREQ 774.8875 MHz, Ch Sp 12.5 kHz.....	355
EXHIBIT 6H- 103: TCSE ANALOG HIGH POWER – FREQ 799.0875 MHz, Ch Sp 12.5 kHz.....	355
EXHIBIT 6H- 104: TCSE ANALOG LOW POWER – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	356
EXHIBIT 6H- 105: TCSE APCO HIGH POWER – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	356
EXHIBIT 6H- 106: TCSE APCO LOW POWER – FREQ 799.0875 MHz, Ch Sp 12.5 kHz.....	357
EXHIBIT 6H- 107: TCSE APCO PHASE II HIGH POWER – FREQ 799.0875 MHz, Ch Sp 12.5 kHz	357
EXHIBIT 6H- 108: TCSE APCO PHASE II LOW POWER – FREQ 799.0875 MHz, Ch Sp 12.5 kHz.....	358
EXHIBIT 6H- 109: TCSE ANALOG HIGH POWER – FREQ 804.9125 MHz, Ch Sp 12.5 kHz.....	358
EXHIBIT 6H- 110: TCSE ANALOG LOW POWER – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	359
EXHIBIT 6H- 111: TCSE APCO HIGH POWER – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	359
EXHIBIT 6H- 112: TCSE APCO LOW POWER – FREQ 804.9125 MHz, Ch Sp 12.5 kHz.....	360
EXHIBIT 6H- 113: TCSE APCO PHASE II HIGH POWER – FREQ 804.9125 MHz, Ch Sp 12.5 kHz	360
EXHIBIT 6H- 114: TCSE APCO PHASE II LOW POWER – FREQ 804.9125 MHz, Ch Sp 12.5 kHz.....	361
EXHIBIT 6H- 115: TCSE ANALOG HIGH POWER – FREQ 806.0125 MHz, Ch Sp 25 kHz.....	361

EXHIBIT 6H- 116: TCSE ANALOG LOW POWER – FREQ 806.0125 MHz, Ch Sp 25 kHz	362
EXHIBIT 6H- 117: TCSE APCO HIGH POWER – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	362
EXHIBIT 6H- 118: TCSE APCO LOW POWER – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	363
EXHIBIT 6H- 119: TCSE APCO PHASE II HIGH POWER – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	363
EXHIBIT 6H- 120: TCSE APCO PHASE II LOW POWER – FREQ 806.0125 MHz, Ch Sp 12.5 kHz	364
EXHIBIT 6H- 121: TCSE ANALOG HIGH POWER – FREQ 814.9875 MHz, Ch Sp 25 kHz	364
EXHIBIT 6H- 122: TCSE ANALOG LOW POWER – FREQ 814.9875 MHz, Ch Sp 25 kHz	365
EXHIBIT 6H- 123: TCSE APCO HIGH POWER – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	365
EXHIBIT 6H- 124: TCSE APCO LOW POWER – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	366
EXHIBIT 6H- 125: TCSE APCO PHASE II HIGH POWER – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	366
EXHIBIT 6H- 126: TCSE APCO PHASE II LOW POWER – FREQ 814.9875 MHz, Ch Sp 12.5 kHz	367
EXHIBIT 6H- 127: TCSE ANALOG HIGH POWER – FREQ 823.9875 MHz, Ch Sp 25 kHz	367
EXHIBIT 6H- 128: TCSE ANALOG LOW POWER – FREQ 823.9875 MHz, Ch Sp 25 kHz	368
EXHIBIT 6H- 129: TCSE APCO HIGH POWER – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	368
EXHIBIT 6H- 130: TCSE APCO LOW POWER – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	369
EXHIBIT 6H- 131: TCSE APCO PHASE II HIGH POWER – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	369
EXHIBIT 6H- 132: TCSE APCO PHASE II LOW POWER – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	370
EXHIBIT 6H- 133: TCSE ANALOG HIGH POWER – FREQ 851.0125 MHz, Ch Sp 25 kHz	370
EXHIBIT 6H- 134: TCSE ANALOG LOW POWER – FREQ 851.0125 MHz, Ch Sp 25 kHz	371
EXHIBIT 6H- 135: TCSE APCO HIGH POWER – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	371
EXHIBIT 6H- 136: TCSE APCO LOW POWER – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	372
EXHIBIT 6H- 137: TCSE APCO PHASE II HIGH POWER – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	372
EXHIBIT 6H- 138: TCSE APCO PHASE II LOW POWER – FREQ 851.0125 MHz, Ch Sp 12.5 kHz	373
EXHIBIT 6H- 139: TCSE ANALOG HIGH POWER – FREQ 860.0125 MHz, Ch Sp 25 kHz	373
EXHIBIT 6H- 140: TCSE ANALOG LOW POWER – FREQ 860.0125 MHz, Ch Sp 25 kHz	374
EXHIBIT 6H- 141: TCSE APCO HIGH POWER – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	374
EXHIBIT 6H- 142: TCSE APCO LOW POWER – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	375
EXHIBIT 6H- 143: TCSE APCO PHASE II HIGH POWER – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	375
EXHIBIT 6H- 144: TCSE APCO PHASE II LOW POWER – FREQ 860.0125 MHz, Ch Sp 12.5 kHz	376
EXHIBIT 6H- 145: TCSE ANALOG HIGH POWER – FREQ 868.8875 MHz, Ch Sp 25 kHz	376
EXHIBIT 6H- 146: TCSE ANALOG LOW POWER – FREQ 868.8875 MHz, Ch Sp 25 kHz	377
EXHIBIT 6H- 147: TCSE APCO HIGH POWER – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	377
EXHIBIT 6H- 148: TCSE APCO LOW POWER – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	378
EXHIBIT 6H- 149: TCSE APCO PHASE II HIGH POWER – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	378
EXHIBIT 6H- 150: TCSE APCO PHASE II LOW POWER – FREQ 868.8875 MHz, Ch Sp 12.5 kHz	379
EXHIBIT 6I- 1: VOLTAGE SUPPLY FREQUENCY STABILITY – FREQ 158.55 MHz, Ch Sp 12.5 kHz	380
EXHIBIT 6I- 2: TEMPERATURE FREQUENCY STABILITY – FREQ 158.55 MHz, Ch Sp 12.5 kHz	380
EXHIBIT 6I- 3: VOLTAGE SUPPLY FREQUENCY STABILITY – FREQ 467.775 MHz, Ch Sp 12.5 kHz	381
EXHIBIT 6I- 4: TEMPERATURE FREQUENCY STABILITY – FREQ 467.775 MHz, Ch Sp 12.5 kHz	381
EXHIBIT 6I- 5: VOLTAGE SUPPLY FREQUENCY STABILITY – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	382
EXHIBIT 6I- 6: TEMPERATURE FREQUENCY STABILITY – FREQ 769.0875 MHz, Ch Sp 12.5 kHz	382
EXHIBIT 6I- 7: VOLTAGE SUPPLY FREQUENCY STABILITY – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	383
EXHIBIT 6I- 8: TEMPERATURE FREQUENCY STABILITY – FREQ 823.9875 MHz, Ch Sp 12.5 kHz	383
EXHIBIT 6J- 1: ANALOG TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER ON – FREQ 158.55 MHz, Ch Sp 25 kHz	384
EXHIBIT 6J- 2: ANALOG TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER OFF – FREQ 158.55 MHz, Ch Sp 25 kHz	384
EXHIBIT 6J- 3: DIGITAL TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER ON – FREQ 158.55 MHz, Ch Sp 12.5 kHz	385
EXHIBIT 6J- 4: DIGITAL TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER OFF – FREQ 158.55 MHz, Ch Sp 25 kHz	385
EXHIBIT 6J- 5: ANALOG TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER ON – FREQ 467.775 MHz, Ch Sp 25 kHz	386
EXHIBIT 6J- 6: ANALOG TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER OFF – FREQ 467.775 MHz, Ch Sp 25 kHz	386
EXHIBIT 6J- 7: DIGITAL TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER ON – FREQ 467.775 MHz, Ch Sp 12.5 kHz	387
EXHIBIT 6J- 8: DIGITAL TRANSIENT FREQUENCY BEHAVIOR TRANSMITTER OFF – FREQ 467.775 MHz, Ch Sp 12.5 kHz ...	387
EXHIBIT 6K - 1: ANALOG ACCPR - FREQ 769.0875 MHz, Ch Sp 12.5 kHz	388
EXHIBIT 6K - 2: ANALOG ACCPR - FREQ 774.8875 MHz, Ch Sp 12.5 kHz	388

EXHIBIT 6K - 3: ANALOG ACCPR - FREQ 799.0875 MHz, CH SP 12.5 kHz	389
EXHIBIT 6K - 4: ANALOG ACCPR - FREQ 804.9125 MHz, CH SP 12.5 kHz	389
EXHIBIT 6K - 5: ANALOG ACCPR - FREQ 769.0875 MHz, CH SP 25 kHz	390
EXHIBIT 6K - 6: ANALOG ACCPR - FREQ 774.8875 MHz, CH SP 25 kHz	390
EXHIBIT 6K - 7: ANALOG ACCPR - FREQ 799.0875 MHz, CH SP 25 kHz	391
EXHIBIT 6K - 8: ANALOG ACCPR - FREQ 804.9125 MHz, CH SP 25 kHz	391
EXHIBIT 6K - 9: APCO DIGITAL VOICE ACCPR - FREQ 769.0875 MHz, CH SP 12.5 kHz	392
EXHIBIT 6K - 10: APCO DIGITAL VOICE ACCPR - FREQ 774.8875 MHz, CH SP 12.5 kHz	392
EXHIBIT 6K - 11: APCO DIGITAL VOICE ACCPR - FREQ 799.0875 MHz, CH SP 12.5 kHz	393
EXHIBIT 6K - 12: APCO DIGITAL VOICE ACCPR - FREQ 804.9125 MHz, CH SP 12.5 kHz	393
EXHIBIT 6K - 13: APCO DIGITAL VOICE ENCRYPTION ACCPR - FREQ 769.0875 MHz, CH SP 12.5 kHz	394
EXHIBIT 6K - 14: APCO DIGITAL VOICE ENCRYPTION ACCPR - FREQ 774.8875 MHz, CH SP 12.5 kHz	394
EXHIBIT 6K - 15: APCO DIGITAL VOICE ENCRYPTION ACCPR - FREQ 799.0875 MHz, CH SP 12.5 kHz	395
EXHIBIT 6K - 16: APCO DIGITAL VOICE ENCRYPTION ACCPR - FREQ 804.9125 MHz, CH SP 12.5 kHz	395
EXHIBIT 6K - 17: APCO DIGITAL DATA ACCPR - FREQ 769.0875 MHz, CH SP 12.5 kHz	396
EXHIBIT 6K - 18: APCO DIGITAL DATA ACCPR - FREQ 774.8875 MHz, CH SP 12.5 kHz	396
EXHIBIT 6K - 19: APCO DIGITAL DATA ACCPR - FREQ 799.0875 MHz, CH SP 12.5 kHz	397
EXHIBIT 6K - 20: APCO DIGITAL DATA ACCPR - FREQ 804.9125 MHz, CH SP 12.5 kHz	397
EXHIBIT 6K - 21: APCO DIGITAL F2 ACCPR - FREQ 769.0875 MHz, CH SP 12.5 kHz	398
EXHIBIT 6K - 22: APCO DIGITAL F2 ACCPR - FREQ 774.8875 MHz, CH SP 12.5 kHz	398
EXHIBIT 6K - 23: APCO DIGITAL F2 ACCPR - FREQ 799.0875 MHz, CH SP 12.5 kHz	399
EXHIBIT 6K - 24: APCO DIGITAL F2 ACCPR - FREQ 804.9125 MHz, CH SP 12.5 kHz	399
EXHIBIT 6K - 25: ANALOG VOICE ENCRYPTION ACCPR - FREQ 769.0875 MHz, CH SP 20 kHz	400
EXHIBIT 6K - 26: ANALOG VOICE ENCRYPTION ACCPR - FREQ 774.8875 MHz, CH SP 20 kHz	400
EXHIBIT 6K - 27: ANALOG VOICE ENCRYPTION ACCPR - FREQ 799.0875 MHz, CH SP 20 kHz	401
EXHIBIT 6K - 28: ANALOG VOICE ENCRYPTION ACCPR - FREQ 804.9125 MHz, CH SP 20 kHz	401