

Jeckson Electric Co., Ltd.

Application
For
Certification
(FCC ID: ELY547-47-1004-R)
Superregenerative Receiver

0616176
BC/ Sandy Lee
September 28, 2006

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

Intertek Testing Services Hong Kong Ltd.

2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.
Tel: (852) 2173 8888 Fax: (852) 2371 0521 Website: www.hk.intertek-etlsemko.com

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Jeckson Electric Co., Ltd. - MODEL: JECKERSON 47-1004F-R
JECKERSON 47-1004G-R
JECKERSON 47-1004H-R
Dimplex 47-1004F-R
Dimplex 47-1004G-R
Dimplex 47-1004H-R

FCC ID: ELY547-47-1004-R

This report concerns (check one:) Original Grant ☒ Class II Change ☐

Equipment Type: Superregenerative Receiver (example: computer, printer, modem, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes ☐ No ☒

If yes, defer until:
date

Company Name agrees to notify the Commission by:
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes ☐ No ☒

If no, assumed Part 15, Subpart B for unintentional radiator - the new 47 CFR [04-05-05 Edition] provision.

Report prepared by:

Chow Chi Ming, Billy
Intertek Testing Services Hong Kong Ltd.
2/F., Garment Centre,
576, Castle Peak Road,
Kowloon, Hong Kong.
Phone: 852-2173-8528
Fax: 852-2371-0521

INTERTEK TESTING SERVICES

Table of Contents

1.0	<u>General Description</u>	2
1.1	Product Description	2
1.2	Related Submittal(s) Grants.....	2
1.3	Test Methodology	3
1.4	Test Facility	3
2.0	<u>System Test Configuration</u>	5
2.1	Justification	5
2.2	EUT Exercising Software.....	5
2.3	Special Accessories	5
2.4	Equipment Modification	6
2.5	Measurement Uncertainty.....	6
2.6	Support Equipment List and Description	6
3.0	<u>Emission Results</u>	8
3.1	Field Strength Calculation.....	9
3.2	Radiated Emission Configuration Photograph.....	10
3.3	Radiated Emission Data	11
3.4	Conducted Emission Configuration Photograph.....	15
3.5	Conducted Emission Data	16
4.0	<u>Equipment Photographs</u>	18
5.0	<u>Product Labelling</u>	20
6.0	<u>Technical Specifications</u>	22
7.0	<u>Instruction Manual</u>	24
8.0	<u>Miscellaneous Information</u>	26
8.1	Stabilization Waveform	27
8.2	Discussion of Pulse Desensitization.....	28
8.3	Calculation of Average Factor.....	29
8.4	Emissions Test Procedures	30

INTERTEK TESTING SERVICES

List of attached file

Exhibit type	File Description	filename
Test Report	Test Report	report.pdf
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission	radiated photos.doc
Test Setup Photo	Conducted Emission	conducted photos.doc
Test Report	Conducted Emission Test Result	conducted.pdf
External Photo	External Photo	external photos.doc
Internal Photo	Internal Photo	internal photos.doc
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Test Report	Stabilization Waveform	superreg.pdf

INTERTEK TESTING SERVICES

EXHIBIT 1

GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 **General Description**

1.1 Product Description

The Equipment Under Test (EUT) is a Receiver operating at 433MHz. The EUT is powered by 120V a.c. It receive control signal from the corresponding transmitter and the device connected to it will be on/off accordingly.

Model differences/similarities are as follow:

1. The Model: Dimplex 47-1004F-R is the same as the Model: JECKSON 47-1004F-R in hardware aspect. The difference in trade name serves as marketing strategy.
2. The Model: Dimplex 47-1004G-R is the same as the Model: JECKSON 47-1004G-R in hardware aspect. The difference in trade name serves as marketing strategy.
3. The Model: Dimplex 47-1004H-R is the same as the Model: JECKSON 47-1004H-R in hardware aspect. The difference in trade name serves as marketing strategy.
4. The Model: JECKSON 47-1004G-R and JECKSON 47-1004H-R are the same as the Model: JECKSON 47-1004F-R in hardware aspect except that JECKSON 47-1004F-R is a bare board version and has no enclosure. Also, the receptacle is replaced by tabs.
5. Each model can have alternative relay.
Tyco, Model: T9AN1D12-24
Song Chuan, Model: 832-1A
Songle, Model: SLA-24VDC-L-A

Antenna Type : Internal, Integral

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

1.2 Related Submittal(s) Grants

This is an application for Certification of a receiver. The transmitter, associated with this receiver, has FCC ID: ELY547-47-1010-T and has been granted.

INTERTEK TESTING SERVICES

1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (2003). All radiated measurements were performed in an Open Area Test Site. Preliminary scans were performed in the Open Area Test Site only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the “**Justification Section**” of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been placed on file with the FCC.

INTERTEK TESTING SERVICES

EXHIBIT 2

SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 **System Test Configuration**

2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2003).

The device was powered from 120V a.c.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. The step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was mounted to a cardboard box, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

Model: JECKSON 47-1004F-R was used for testing. The test results on both relay versions are demonstrated on the report.

2.2 EUT Exercising Software

There was no special software to exercise the device. Once the unit is powered up, it received continuously.

2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

During test, 5 x 60W light bulbs and 7A resistive load was connected to the socket-outlet on the EUT.

INTERTEK TESTING SERVICES

2.4 Equipment Modification

Any modifications installed previous to testing by Jackson Electric Co., Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by Intertek Testing Services.

2.5 Measurement Uncertainty

When determining of the test conclusion, the Measurement Uncertainty of test has been considered.

2.6 Support Equipment List and Description

This product was tested in a configuration connected with 5 x 60W light bulbs and 7A resistive load.

All the items listed under section 2.0 of this report are

Confirmed by:

*Chow Chi Ming, Billy
Assistant Manager
Intertek Testing Services Hong Kong Ltd.
Agent for Jackson Electric Co., Ltd.*



Signature

September 28, 2006

Date

INTERTEK TESTING SERVICES

EXHIBIT 3

EMISSION RESULTS

INTERTEK TESTING SERVICES

3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB μ V/m
 RA = Receiver Amplitude (including preamplifier) in dB μ V
 CF = Cable Attenuation Factor in dB
 AF = Antenna Factor in dB
 AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:

$$FS = RR + LF$$

where FS = Field Strength in dB μ V/m
 RR = RA - AG in dB μ V
 LF = CF + AF in dB

Assume a receiver reading of 52.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB are added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

RA = 52.0 dB μ V/m	
AF = 7.4 dB	RR = 23.0 dB μ V
CF = 1.6 dB	LF = 9.0 dB
AG = 29.0 dB	
FS = RR + LF	
FS = 23 + 9 = 32 dB μ V/m	

Level in μ V/m = Common Antilogarithm [(32 dB μ V/m)/20] = 39.8 μ V/m

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission
at
430.605 MHz

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: radiated photos.doc.

INTERTEK TESTING SERVICES

3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 6.1 dB

TEST PERSONNEL:



Signature

Mark Cheung, Compliance Engineer
Typed/Printed Name

September 28, 2006
Date

INTERTEK TESTING SERVICES

Applicant: Jackson Electric Co., Ltd.

Date of Test: August 5, 2006

Model: JECKERSON 47-1004F-R

Mode: Rx (Sngle Relay)

Table 1

FCC Class B Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit at 3m (dB μ V/m)	Margin (dB)
H	414.860	22.0	25.0	16	31.0	46.0	-15.0
H	416.000	25.1	25.0	16	34.1	46.0	-11.9
H	418.250	26.4	25.0	16	35.4	46.0	-10.6
H	420.250	28.3	25.0	16	37.3	46.0	-8.7
H	427.001	28.9	25.0	16	37.9	46.0	-8.1
H	430.605	30.9	25.0	16	39.9	46.0	-6.1
H	431.250	25.0	25.0	16	34.0	46.0	-12.0
H	433.375	25.4	25.0	16	34.4	46.0	-11.6
H	436.870	24.0	26.0	16	34.0	46.0	-12.0
H	850.006	19.8	31.0	16	34.8	46.0	-11.2
H	853.550	19.7	31.0	16	34.7	46.0	-11.3
H	857.050	20.0	31.0	16	35.0	46.0	-11.0
H	1282.000	45.5	26.1	33	38.6	54.0	-15.4
H	1283.550	46.8	26.1	33	39.9	54.0	-14.1
H	1285.105	46.0	26.1	33	39.1	54.0	-14.9

NOTES: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative sign in the column shows value below limit.

4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Mark Cheung

INTERTEK TESTING SERVICES

Applicant: Jackson Electric Co., Ltd.

Date of Test: August 5, 2006

Model: JECKSON 47-1004F-R

Mode: Rx (Tyco Relay)

Table 2

FCC Class B Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit at 3m (dB μ V/m)	Margin (dB)
H	414.860	22.2	25.0	16	31.2	46.0	-14.8
H	416.001	25.3	25.0	16	34.3	46.0	-11.7
H	418.260	26.0	25.0	16	35.0	46.0	-11.0
H	420.260	27.9	25.0	16	36.9	46.0	-9.1
H	427.000	28.5	25.0	16	37.5	46.0	-8.5
H	430.600	30.5	25.0	16	39.5	46.0	-6.5
H	431.260	24.8	25.0	16	33.8	46.0	-12.2
H	433.365	25.4	25.0	16	34.4	46.0	-11.6
H	436.860	24.1	26.0	16	34.1	46.0	-11.9
H	850.001	19.0	31.0	16	34.0	46.0	-12.0
H	853.550	19.8	31.0	16	34.8	46.0	-11.2
H	857.060	19.7	31.0	16	34.7	46.0	-11.3
H	1282.000	44.9	26.1	33	38.0	54.0	-16.0
H	1283.560	46.7	26.1	33	39.8	54.0	-14.2
H	1285.105	45.9	26.1	33	39.0	54.0	-15.0

NOTES: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative sign in the column shows value below limit.

4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Mark Cheung

INTERTEK TESTING SERVICES

Applicant: Jackson Electric Co., Ltd.
Model: JECKSON 47-1004F-R
Mode: Rx (Song Chuan Relay)

Date of Test: August 5, 2006

Table 3

FCC Class B Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit at 3m (dB μ V/m)	Margin (dB)
V	414.860	22.8	25.0	16	31.8	46.0	-14.2
V	418.006	25.8	25.0	16	34.8	46.0	-11.2
V	420.710	26.5	25.0	16	35.5	46.0	-10.5
V	424.500	28.7	25.0	16	37.7	46.0	-8.3
V	426.860	29.0	25.0	16	38.0	46.0	-8.0
V	429.860	30.3	25.0	16	39.3	46.0	-6.7
V	431.210	25.8	25.0	16	34.8	46.0	-11.2
V	434.360	25.4	25.0	16	34.4	46.0	-11.6
V	437.360	24.0	26.0	16	34.0	46.0	-12.0
V	856.220	20.0	31.0	16	35.0	46.0	-11.0
V	860.110	19.8	31.0	16	34.8	46.0	-11.2
V	861.115	20.3	31.0	16	35.3	46.0	-10.7
V	1282.440	45.7	26.1	33	38.8	54.0	-15.2
V	1284.105	46.5	26.1	33	39.6	54.0	-14.4
V	1287.050	46.3	26.1	33	39.4	54.0	-14.6

- NOTES: 1. Peak Detector Data unless otherwise stated.
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative sign in the column shows value below limit.
4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Mark Cheung

INTERTEK TESTING SERVICES

3.4 Conducted Emission Configuration Photograph

Worst Case Conducted Emission
at
10.330 MHz

For electronic filing, the worst case conducted emission configuration photographs are saved with filename: conducted photos.doc.

INTERTEK TESTING SERVICES

3.5 Conducted Emission Data

For electronic filing, the graph and data table of conducted emission is saved with filename: conducted.pdf.

Judgement: Passed by 14.0 dB

TEST PERSONNEL:



Signature

Mark Cheung, Compliance Engineer
Typed/Printed Name

September 28, 2006
Date

INTERTEK TESTING SERVICES

EXHIBIT 4

EQUIPMENT PHOTOGRAPHS

INTERTEK TESTING SERVICES

4.0 **Equipment Photographs**

For electronic filing, the photographs are saved with filename: external photos.doc and internal photos.doc.

INTERTEK TESTING SERVICES

EXHIBIT 5

PRODUCT LABELLING

INTERTEK TESTING SERVICES

5.0 **Product Labelling**

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

INTERTEK TESTING SERVICES

EXHIBIT 6

TECHNICAL SPECIFICATIONS

INTERTEK TESTING SERVICES

6.0 **Technical Specifications**

For electronic filing, the block diagram and schematic of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

INTERTEK TESTING SERVICES

EXHIBIT 7

INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 **Instruction Manual**

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

INTERTEK TESTING SERVICES

EXHIBIT 8

MISCELLANEOUS INFORMATION

8.0 **Miscellaneous Information**

This miscellaneous information includes details of the stabilizing process (including a plot of the stabilized waveform), the test procedure and calculation of factors such as pulse desensitization and averaging factor.

INTERTEK TESTING SERVICES

8.1 Stabilization Waveform

Previous to the testing, the superregenerative receiver was stabilized as outlined in the test procedure. For the electronic filing, the plot saved with filename: superreg.pdf shows the fundamental emission when a signal generator was used to stabilize the receiver. Please note that the antenna was placed as close as possible to the EUT for clear demonstration of the waveform and that accurate readings are not possible from this plot.

INTERTEK TESTING SERVICES

8.2 Discussion of Pulse Desensitization

The determination of pulse desensitivity was made in accordance with Hewlett Packard Application Note 150-2, *Spectrum Analysis ... Pulsed RF*.

This device is a superregenerative receiver. The stabilized signals are continuous, and no desensitization of the measurement equipment occurs.

8.3 Calculation of Average Factor

The emission limits are specified using spectrum analyzers or receivers which incorporate quasi-peak detectors. Typical measurements are made using peak detectors, however, emissions which approach the respective emission limit are measured using a quasi-peak detector.

For measurements above 1 GHz, spectrum analyzers or receivers using average detectors are employed, or the appropriate average factor can be applied.

Measurements using spectrum analyzers with filters other than peak detectors are recorded in the data table section of this report.

This device is a superregenerative receiver.

It is not necessary to apply average factor to the measurement results.

8.4 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services Hong Kong Ltd. in the measurements of superregenerative receivers operating under the Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 2003. Superregenerative receivers are stabilized prior to measurement by generating a signal well above the receiver threshold whose frequency is tuned until the emissions stabilize into a line spectrum. The signal is usually generated as CW with a Marconi 2022D signal generator and a short whip antenna and is at a level of several hundred to several thousand mV/m. Plots of the stabilized signal will be shown. If a modulated signal is used, it will be noted.

The equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the groundplane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axis to obtain maximum emission levels. The antenna height and polarization are also varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings. A detailed description for the calculation of the average factor can be found in Exhibit 8.3.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower. For line conducted emissions, the range scanned is 150 kHz to 30 MHz.

INTERTEK TESTING SERVICES

8.4 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements were made as described in ANSI C63.4 - 2003.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater when frequency is below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.2). Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Measurements are normally conducted at a measurement distance of three meters. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.