

AXM-208I Specifications

RF Mouse Transmitter

Working frequency	27.045MHz
Channel numbers	1
ID numbers	256
RF output Power	-4dBm $\pm$ 2dBm
Deviation	6KHz $\pm$ 2 KHz
Modulation method	FSK
Power requirements	3.0V , (AAA size batteries 2 pieces)
Current Dissipation	30mA
Standby Mode Current	5 $\pm$ 1mA
Sleeping Mode Current	0.63mA
Transmitting Angle	360°
Working Distance	1.0 meters (Min.)
Low Battery	2.0V

RF Receiver

Working frequency	27 MHz
Channel numbers	1
ID numbers	256
Current Dissipation	15mA (Typ)
Working Distance	1.0 meters (Min)
Led Indicator	