

RF Exposure Report

(Part 0: SAR Char Evaluation)

APPLICANT : Motorola Mobility LLC
EQUIPMENT : Mobile Cellular Phone
BRAND NAME : Motorola
MODEL NAME : XT2203-1
FCC ID : IHDT56AE6
STANDARD : FCC 47 CFR Part 2 (2.1093)

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.

Tony Zhang

Reviewed by: Tony Zhang / Supervisor

Kat Yin

Approved by: Kat Yin / Manager



Sporton International Inc. (Kunshan)

**No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China**



Table of Contents

1. Introduction	4
2. Product Description	5
3. SAR Characterization.....	6
3.1 SAR design target and uncertainty.....	6
3.2 SAR Char Table	7

History of this test report

Report No.	Version	Description	Issued Date
FA1D2901B	01	Initial issue of report	Mar. 07, 2022
FA1D2901B	02	Updated relevant data of GSM1900 DSI 3 &6	Mar. 11, 2022



1. Introduction

The RF exposure limit is defined based on time-averaged RF exposure. The product implements Qualcomm Smart Transmit feature which controls the instantaneous transmitting power for WWAN transmitter to ensure the product in compliance with RF exposure limit over a defined time window, for SAR (transmit frequency $\leq$ 6GHz) and power density (transmit frequency $>$ 6GHz) to control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure is compliant to the regulation requirement. Cannot operate without SAR characterization at the device level, beforehand.

This report describes the procedures for the SAR char generation, and the parameters obtained from SAR characterization (referred to as SAR char, respectively) will be used as input for Smart Transmit. Both SAR char will be entered via the Embedded File System (EFS) to enable the Smart Transmit Feature.

Terminologies in this report

P_{limit}	The time-averaged RF power which corresponds to SAR_design_target.
P_{max}	Maximum target power level
SAR_design_target:	The design target for SAR compliance. It should be less than regulatory power density limit to account for all device design related uncertainties.
SAR char	P_{limit} for all the technologies/bands for all applicable DSI

2. Product Description

Product Feature & Specification	
Equipment Name	Mobile Cellular Phone
Brand Name	Motorola
Model Name	XT2203-1
FCC ID	IHDT56AE6
Wireless Technology and Frequency Range	GSM850: 824 MHz ~ 849 MHz GSM1900: 1850 MHz ~ 1910 MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 38: 2570 MHz ~ 2620 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 42: 3450 MHz ~ 3550MHz LTE Band 66: 1710 MHz ~ 1780 MHz 5G NR n2 : 1850 MHz ~ 1910 MHz 5G NR n5: 824 MHz ~ 849 MHz 5G NR n7: 2500 MHz ~ 2570 MHz 5G NR n38 : 2570 MHz ~ 2620 MHz 5G NR n66: 1710 MHz ~ 1780 MHz 5G NR n78: 3450 MHz ~ 3550 MHz WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz WLAN 6E U-NII-5: 5925 MHz ~ 6425 MHz WLAN 6E U-NII-6: 6425 MHz ~ 6525 MHz WLAN 6E U-NII-7: 6525 MHz ~ 6875 MHz WLAN 6E U-NII-8: 6875 MHz ~ 7125 MHz Bluetooth: 2402 MHz ~ 2480 MHz NFC: 13.56 MHz
Mode	GSM/GPRS/EGPRS RMC/AMR 12.2Kbps HSDPA HSUPA DC-HSDPA HSPA+(16QAM uplink is not supported) LTE: QPSK, 16QAM, 64QAM, 256QAM 5G NR : CP-OFDM / DFT-s-OFDM, PI/2 BPSK, QPSK, 16QAM, 64QAM, 256QAM WLAN 2.4GHz 802.11b/g/n HT20/HT40 WLAN 2.4GHz 802.11ax HE20/HE40 WLAN 5GHz 802.11a/n HT20/HT40 WLAN 5GHz 802.11ac/ax VHT20/VHT40/VHT80/VHT160/HE20/HE40/HE80/HE160 WLAN 6GHz 802.11a WLAN 6GHz 802.11ax HE20/HE40/HE80/HE160 Bluetooth BR/EDR/LE NFC: ASK

3. SAR Characterization

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for $f < 6$ GHz.

3.1 SAR design target and uncertainty

<SAR design target and uncertainty>:

	Uncertainty dB (k=2)
Total uncertainty	1.5

To account for total uncertainty, SAR_design_target should be determined as:

$$SAR_{design_target} < SAR_{regulatory_limit} \times 10^{\frac{-total\ uncertainty}{10}}$$

SAR design Target :

FCC SAR	Measure Distance	Standalone SAR (W/kg)	Simultaneous SAR (W/kg) For WWAN + Non DBS
		WWAN 2/3/4/5G Top and Bottom	SAR Limit WWAN 2/3/4/5G Top and Bottom
Body Worn (1g)	5 mm	1.00	0.75
Hotspot (1g)	5 mm		0.75
Head (1g)	touch&tilt 15deg	1.00	0.75
Extremity (10g)	0 mm	2.50	1.80

3.2 SAR Char Table

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for $f < 6$ GHz.

<P_{limit} for supported technologies and bands (P_{limit} in EFS file)>

Band	Antenna	Head DSI 2 Standalone	Head DSI 2 Simultaneous	Body Worn DSI 3 Standalone	Body Worn & Hotspot DSI 3 Simultaneous	Extremity DSI6 Standalone	Extremity DSI6 Simultaneous	Sensor Off DSI4	P _{max} *
GSM850(3 Tx slots)	Ant 0	32.1		24.4	23.1	26.1	24.6	25.7	25.7
GSM850(3 Tx slots)	Ant 1	21.9	20.6	23.7	22.4	28.0		25.7	25.7
GSM1900(3 Tx slots)	Ant 0	33.0		18.0	14.1	20.1	18.6	22.2	22.2
WCDMA II	Ant 0	33.3		18.4	13.8	19.4	17.9	23.0	23.0
WCDMA IV	Ant 0	30.9		17.5	13.6	18.2	16.7	23.0	23.0
WCDMA V	Ant 0	28.9		22.5	21.2	27.0		23.0	23.0
WCDMA V	Ant 1	21.3	20.0	22.4	21.1	22.9	21.4	23.0	23.0
LTE Band 2	Ant 0	31.8		18.1	12.8	19.5	18.0	23.0	23.0
LTE Band 2	Ant 1	17.6	16.3	18.1	16.8	21.1	19.6	23.0	23.0
LTE Band 7	Ant 0	29.0		17.8	14.2	20.3	18.8	23.0	23.0
LTE Band 7	Ant 1	17.7	16.4	19.6	16.3	20.4	18.9	23.0	23.0
LTE Band 12(17)	Ant 1	24.3	23.0	28.2		24.0		24.0	24.0
LTE Band 13	Ant 0	31.2		24.4	23.1	24.0		24.0	24.0
LTE Band 26(5)	Ant 1	20.9	19.6	21.5	20.2	22.7	21.2	23.0	23.0
LTE Band 66(4)	Ant 0	31.8		17.4	13.7	18.4	16.9	23.0	23.0
LTE Band 66(4)	Ant 1	17.8	16.5	16.6	15.3	20.9	19.4	23.0	23.0
LTE Band 38	Ant 1	18.1	16.8	18.9	15.7	19.2	17.7	23.0	23.0
LTE Band 41(38)	Ant 0	30.9		18.1	14.9	20.5	19.0	21.0	21.0
LTE Band 41(38) HPUE	Ant 0	30.9		18.1	14.9	20.5	19.0	22.4	22.4
LTE Band 42	Ant 4	13.5	12.2	15.8	14.5	19.1	17.6	21.0	21.0
5G NR n2	Ant 1	18.1	16.8	18.2	16.9	21.0	19.5	23.0	23.0
5G NR n5	Ant 1	21.8	20.5	22.5	21.2	23.2	21.7	23.0	23.0
5G NR n7	Ant 0	30.9		18.1	15.0	21.2	19.7	23.0	23.0
5G NR n66	Ant 0	31.2		17.9	14.3	18.1	16.6	23.0	23.0
5G NR n66	Ant 1	17.8	16.5	16.7	15.4	20.9	19.4	23.0	23.0
5G NR n38	Ant 0	31.6		17.9	14.5	21.3	19.8	23.0	23.0
5G NR n78-HPUE	Ant 2	12.3	11.0	15.4	14.1	16.9	15.4	16.9	23.0
5G NR n78-HPUE	Ant 4	14.3	13.0	15.7	14.4	19.3	17.8	26.0	26.0
5G NR n78-HPUE	Ant 7	29.2		18.5	17.2	19.5	18.0	19.5	23.0
5G NR n78-HPUE	Ant 8	20.2	18.9	13.7	12.4	19.2	17.7	19.2	24.5

Note: 1) *P_{max} is used for RF tune up procedure. The maximum allowed output power is equal to P_{max} + device uncertainty.

2) All P_{limit} power levels entered in the Table correspond to average power levels after accounting for duty cycle in the case TDD modulation schemes (for e.g., GSM & LTE TDD).

3) The max allowed output power is the P_{limit} + device uncertainty, and if P_{limit} is higher than P_{max}, the device output power will be P_{max} instead.

4) 5G NR n78 ant 2, ant 7 and ant 8 support SRS (Sounding Reference Signal) functionality.

5) LTE Band 2/7/38/66 ant 1 only for EN-DC combination, and LTE Band 4 ant 1 only for LTE inter-band uplink CA or EN-DC combination.

6) For Ant1 of LTE Band 2/4/7/38/66 test, using FTM (Factory Test Mode) to perform SAR with default 100% transmission.