

# RF Exposure Report

## (Part 0: SAR Char Evaluation)

APPLICANT : Motorola Mobility LLC  
EQUIPMENT : Mobile Cellular Phone  
BRAND NAME : Motorola  
MODEL NAME : XT2403-1, XT2403-2  
FCC ID : IHDT56AQ5  
STANDARD : FCC 47 CFR PART 2 (2.1093)

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures given in 47 CFR Part 2.1093 and FCC KDB and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.



Approved by: Si Zhang



**Sporton International Inc. (Kunshan)**

No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300  
People's Republic of China



## **Table of Contents**

|                                            |          |
|--------------------------------------------|----------|
| <b>1. Introduction .....</b>               | <b>4</b> |
| <b>2. Product Description .....</b>        | <b>5</b> |
| <b>3. SAR Characterization.....</b>        | <b>6</b> |
| 3.1 SAR design target and uncertainty..... | 6        |
| 3.2 SAR Char Table .....                   | 7        |

## History of this test report

| Report No. | Version | Description                                                                                 | Issued Date   |
|------------|---------|---------------------------------------------------------------------------------------------|---------------|
| FA3D1818D  | 01      | Initial issue of report                                                                     | Jan. 30, 2024 |
| FA3D1818D  | 02      | 1. Revised Frequency Range of WPT on page 5;<br>2. Updated 5GNR n77/78 at ant4 DSI2 Plimit. | Feb. 18, 2024 |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |
|            |         |                                                                                             |               |

## 1. Introduction

The 2nd generation of Smart Transmit (GEN2) operates based on pre-defined sub6 antenna groups (AG). This Device is enabled with the Qualcomm® Smart Transmit Gen2 feature. The RF exposure limit is defined based on time-averaged RF exposure. The RF exposure limit is defined based on time-averaged RF exposure. The product implements Qualcomm Smart Transmit feature which controls the instantaneous transmitting power for WWAN transmitter to ensure the product in compliance with RF exposure limit over a defined time window, for SAR (transmit frequency  $\leq 6\text{GHz}$ ) to control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure is compliant to the regulation requirement. Smart Transmit cannot operate without SAR characterization at the device level, beforehand.

This report describes the procedures for the SAR char generation, and the parameters obtained from SAR characterization (referred to as SAR char, respectively) will be used as input for Smart Transmit. Both SAR char will be entered via the Embedded File System (EFS) to enable the Smart Transmit GEN2 Feature.

### Terminologies in this report

|                    |                                                                                                                                                   |
|--------------------|---------------------------------------------------------------------------------------------------------------------------------------------------|
| $P_{\text{limit}}$ | The time-averaged RF power which corresponds to SAR_design_target.                                                                                |
| $P_{\text{max}}$   | Maximum target power level                                                                                                                        |
| SAR_design_target: | The design target for SAR compliance. It should be less than regulatory power density limit to account for all device design related uncertainty. |
| SAR char           | $P_{\text{limit}}$ for all the technologies/bands for all applicable DSI                                                                          |



## 2. Product Description

| Product Feature & Specification         |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|-----------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Equipment Name                          | Mobile Cellular Phone                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| Brand Name                              | Motorola                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Model Name                              | XT2403-1, XT2403-2                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| FCC ID                                  | IHDT56AQ5                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| Wireless Technology and Frequency Range | GSM850: 824 MHz ~ 849 MHz<br>GSM1900: 1850 MHz ~ 1910 MHz<br>WCDMA Band II: 1850 MHz ~ 1910 MHz<br>WCDMA Band IV: 1710 MHz ~ 1755 MHz<br>WCDMA Band V: 824 MHz ~ 849 MHz<br>LTE Band 2: 1850 MHz ~ 1910 MHz<br>LTE Band 4: 1710 MHz ~ 1755 MHz<br>LTE Band 5: 824 MHz ~ 849 MHz<br>LTE Band 7: 2500 MHz ~ 2570 MHz<br>LTE Band 12: 699 MHz ~ 716 MHz<br>LTE Band 13: 777 MHz ~ 787 MHz<br>LTE Band 17: 704 MHz ~ 716 MHz<br>LTE Band 26: 814 MHz ~ 849 MHz<br>LTE Band 38: 2570 MHz ~ 2620 MHz<br>LTE Band 41: 2496 MHz ~ 2690 MHz<br>LTE Band 42: 3450 MHz ~ 3550 MHz, 3550 MHz ~ 3600 MHz<br>LTE Band 43: 3600 MHz ~ 3700 MHz<br>LTE Band 48: 3550 MHz ~ 3700 MHz<br>LTE Band 66: 1710 MHz ~ 1780 MHz<br>5G NR n2: 1850 MHz ~ 1910 MHz<br>5G NR n5: 824 MHz ~ 849 MHz<br>5G NR n7: 2500 MHz ~ 2570 MHz<br>5G NR n26: 814 MHz ~ 849 MHz<br>5G NR n38: 2570 MHz ~ 2620 MHz<br>5G NR n41: 2496 MHz ~ 2690 MHz<br>5G NR n66: 1710 MHz ~ 1780 MHz<br>5G NR n77: 3700 MHz ~ 3980 MHz<br>5G NR n78: 3700 MHz ~ 3800 MHz<br>WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz<br>WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz<br>WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz<br>WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz<br>WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz<br>Bluetooth: 2402 MHz ~ 2480 MHz<br>NFC: 13.56 MHz<br>WPT: 110 kHz ~ 148 kHz |
| Mode                                    | GSM/GPRS/EGPRS<br>RMC/AMR 12.2Kbps<br>HSDPA<br>HSUPA<br>HSPA+(16QAM uplink is not supported)<br>LTE: QPSK, 16QAM, 64QAM, 256QAM<br>5G NR : CP-OFDM / DFT-s-OFDM, PI/2 BPSK, QPSK, 16QAM, 64QAM, 256QAM<br>WLAN 2.4GHz 802.11b/g/n HT20/HT40<br>WLAN 2.4GHz 802.11ax HE20/HE40<br>WLAN 5GHz 802.11a/n HT20/HT40<br>WLAN 5GHz 802.11ac/ax VHT20/VHT40/VHT80/VHT160/HE20/HE40/HE80/HE160<br>WLAN 6GHz 802.11a/ax HE20/HE40/HE80/HE160<br>Bluetooth BR/EDR/LE<br>NFC: ASK<br>WPT: ASK                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |

### **3. SAR Characterization**

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for  $f < 6$  GHz.

#### **3.1 SAR design target and uncertainty**

**SAR design Target :**

| Exposure conditions | Measure Distance | SAR (W/kg)<br>WWAN 2/3/4/5G<br>AG1 | SAR (W/kg)<br>WWAN 2/3/4/5G<br>AG0 |
|---------------------|------------------|------------------------------------|------------------------------------|
| Body Worn (1g)      | 5 mm             | 1.03                               | 0.71                               |
| Hotspot (1g)        | 5 mm             | 1.03                               | 0.50                               |
| Head (1g)           | touch&tilt 15deg | 1.03                               | 0.71                               |
| Extremity (10g)     | 0 mm             | 2.55                               | 1.98                               |

**Uncertainty:**

| Item              | Uncertainty dB (k=2) |
|-------------------|----------------------|
| Total uncertainty | 1.5                  |

To account for total uncertainty, SAR\_design\_target should be determined as:

$$SAR_{design\_target} < SAR_{regulatory\_limit} \times 10^{\frac{-total\ uncertainty}{10}}$$

**Antenna Group:**

|                       |                                   |
|-----------------------|-----------------------------------|
| Antenna Group 0 (AG0) | ANT1 & ANT4 & ANT5 & ANT7 & ANT10 |
| Antenna Group 1 (AG1) | ANT0 & ANT2 & ANT8                |

**3.2 SAR Char Table**

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for  $f < 6$  GHz.

**<P<sub>limit</sub> for supported technologies and bands (P<sub>limit</sub> in EFS file)>**

| Band                | Antenna | Head<br>DSI 2 | Body-Worn<br>DSI 3 | Hotspot<br>DSI 7 | Extremity<br>DSI 6 | Sensor off<br>DSI 4 | Pmax* |
|---------------------|---------|---------------|--------------------|------------------|--------------------|---------------------|-------|
| GSM850              | Ant 0   | 33.6          | 23.9               | 23.9             | 27.0               | 24.7                | 24.7  |
| GSM850              | Ant 1   | 21.5          | 23.4               | 21.8             | 24.5               | 24.5                | 24.5  |
| GSM1900             | Ant 1   | 14.6          | 15.1               | 13.3             | 17.0               | 19.7                | 19.7  |
| GSM1900             | Ant 2   | 32.3          | 20.7               | 19.4             | 21.7               | 20.7                | 20.7  |
| WCDMA II            | Ant 1   | 13.7          | 13.1               | 11.6             | 17.4               | 21.5                | 21.5  |
| WCDMA II            | Ant 2   | 30.9          | 20.4               | 19.0             | 21.8               | 22.0                | 22.0  |
| WCDMA IV            | Ant 1   | 14.3          | 14.7               | 13.3             | 18.9               | 21.5                | 21.5  |
| WCDMA IV            | Ant 2   | 32.1          | 19.1               | 18.2             | 21.8               | 22.0                | 22.0  |
| WCDMA V             | Ant 0   | 31.7          | 23.1               | 23.1             | 23.0               | 23.0                | 23.0  |
| WCDMA V             | Ant 1   | 20            | 23.0               | 20.3             | 23.0               | 23.0                | 23.0  |
| LTE Band 2          | Ant 1   | 13.8          | 12.6               | 12.2             | 16.0               | 21.5                | 21.5  |
| LTE Band 2          | Ant 2   | 32.1          | 20.9               | 19.5             | 23.0               | 23.0                | 23.0  |
| LTE Band 66(4)      | Ant 1   | 15.3          | 14.7               | 12.9             | 18.3               | 21.5                | 21.5  |
| LTE Band 66(4)      | Ant 2   | 33.5          | 20.0               | 18.9             | 21.9               | 23.0                | 23.0  |
| LTE Band 26(5)      | Ant 0   | 31.1          | 25.5               | 25.5             | 23.0               | 23.0                | 23.0  |
| LTE Band 26(5)      | Ant 1   | 20.1          | 23.7               | 21.9             | 23.0               | 23.0                | 23.0  |
| LTE Band 7          | Ant 0   | 29.7          | 21.5               | 20.9             | 21.1               | 21.5                | 21.5  |
| LTE Band 7          | Ant 1   | 12.7          | 16.1               | 12.2             | 17.6               | 21.5                | 21.5  |
| LTE Band 7          | Ant 2   | 31.6          | 21.1               | 19.4             | 20.8               | 23.0                | 23.0  |
| LTE Band 7          | Ant 10  | 21.9          | 18.6               | 17.0             | 18.6               | 18.6                | 23.0  |
| LTE Band 12(17)     | Ant 0   | 31.2          | 24.8               | 24.8             | 23.0               | 23.0                | 23.0  |
| LTE Band 12(17)     | Ant 1   | 21            | 23.1               | 22.0             | 23.0               | 23.0                | 23.0  |
| LTE Band 13         | Ant 0   | 30.8          | 24.8               | 24.8             | 23.0               | 23.0                | 23.0  |
| LTE Band 13         | Ant 1   | 20.2          | 23.0               | 21.8             | 23.0               | 23.0                | 23.0  |
| LTE Band 41(38)     | Ant 0   | 29.6          | 19.8               | 16.9             | 19.5               | 21.9                | 20.0  |
| LTE Band 41(38)HPUE | Ant 0   | 29.6          | 19.8               | 16.9             | 19.5               | 21.9                | 21.4  |
| LTE Band 41(38)     | Ant 1   | 12.8          | 15.4               | 10.9             | 17.5               | 21.9                | 20.0  |
| LTE Band 41(38)HPUE | Ant 1   | 12.8          | 15.4               | 10.9             | 17.5               | 21.9                | 21.4  |
| LTE Band 41(38)     | Ant 2   | 31            | 20.5               | 19.5             | 20.9               | 21.9                | 20.5  |
| LTE Band 41(38)HPUE | Ant 2   | 31            | 20.5               | 19.5             | 20.9               | 21.9                | 21.9  |
| LTE Band 41(38)     | Ant 10  | 20.3          | 19.0               | 16.2             | 19.0               | 19.0                | 21.0  |
| LTE Band 41(38)HPUE | Ant 10  | 20.3          | 19.0               | 16.2             | 19.0               | 19.0                | 22.4  |
| LTE Band 42 Part27Q | Ant 7   | 16.2          | 17.4               | 15.6             | 17.4               | 21.0                | 21.0  |
| LTE Band 48(42 43)  | Ant 7   | 16.2          | 17.4               | 15.6             | 17.4               | 21.0                | 21.0  |
| FR1 n2              | Ant 1   | 16.5          | 15.9               | 13.5             | 19.6               | 23.0                | 23.0  |
| FR1 n2 other PA     | Ant 1   | 16.5          | 15.9               | 13.5             | 19.6               | 22.0                | 22.0  |
| FR1 n2              | Ant 2   | 32.2          | 20.7               | 19.4             | 22.1               | 23.0                | 23.0  |
| FR1 n2 other PA     | Ant 2   | 32.2          | 20.7               | 19.4             | 22.1               | 22.0                | 22.0  |
| FR1 n26(5)          | Ant 0   | 32            | 25.4               | 25.4             | 23.0               | 23.0                | 23.0  |
| FR1 n26(5)          | Ant 1   | 22            | 23.1               | 22.0             | 23.0               | 23.0                | 23.0  |
| FR1 n7              | Ant 1   | 16            | 16.4               | 11.8             | 19.3               | 23.0                | 23.0  |
| FR1 n7 other PA     | Ant 1   | 16            | 16.4               | 11.8             | 19.3               | 21.5                | 21.5  |
| FR1 n7              | Ant 2   | 31.8          | 20.3               | 19.2             | 21.2               | 23.0                | 23.0  |
| FR1 n66             | Ant 1   | 15.9          | 15.8               | 14.0             | 18.9               | 23.0                | 23.0  |
| FR1 n66 other PA    | Ant 1   | 15.9          | 15.8               | 14.0             | 18.9               | 23.0                | 23.0  |
| FR1 n66             | Ant 2   | 32.7          | 20.9               | 19.2             | 22.3               | 23.0                | 23.0  |
| FR1 n66 other PA    | Ant 2   | 32.7          | 20.9               | 19.2             | 22.3               | 22.0                | 22.0  |

|                 |        |      |      |      |      |      |      |
|-----------------|--------|------|------|------|------|------|------|
| FR1 n41(38)     | Ant 0  | 27.4 | 19.8 | 18.6 | 20.3 | 21.0 | 21.0 |
| FR1 n41(38)     | Ant 1  | 13.8 | 16.3 | 12.5 | 19.6 | 21.5 | 21.5 |
| FR1 n41(38)     | Ant 2  | 31.6 | 20.1 | 18.5 | 19.8 | 23.0 | 23.0 |
| FR1 n41(38)     | Ant 10 | 25.5 | 23.0 | 20.3 | 23.0 | 23.0 | 23.0 |
| FR1 n77(78)     | Ant 4  | 18.0 | 18.0 | 16.5 | 23.7 | 23.0 | 23.0 |
| FR1 n77(78)HPUE | Ant 4  | 18.0 | 18.0 | 16.5 | 23.7 | 23.0 | 23.0 |
| FR1 n77(78)     | Ant 5  | 14.6 | 16.8 | 12.5 | 18.4 | 23.0 | 23.0 |
| FR1 n77(78)HPUE | Ant 5  | 14.6 | 16.8 | 12.5 | 18.4 | 23.0 | 23.0 |
| FR1 n77(78)     | Ant 7  | 16.7 | 18.5 | 14.4 | 18.5 | 23.0 | 23.0 |
| FR1 n77(78)HPUE | Ant 7  | 16.7 | 18.5 | 14.4 | 18.5 | 23.0 | 23.0 |
| FR1 n77(78)     | Ant 8  | 29.9 | 22.3 | 20.3 | 22.3 | 22.3 | 23.0 |
| FR1 n77(78)HPUE | Ant 8  | 29.9 | 22.3 | 20.3 | 22.3 | 22.3 | 23.0 |

Note: 1) \*P<sub>max</sub> is used for RF tune up procedure. The maximum allowed output power is equal to P<sub>max</sub> + 1.0 dB device uncertainty.

2) \*\*All P<sub>limit</sub> power levels entered in the Table correspond to average power levels after accounting for duty cycle in the case TDD modulation schemes (for e.g., GSM & LTE TDD & NR TDD).

3) The max allowed output power is the P<sub>limit</sub> + device uncertainty, and if P<sub>limit</sub> is higher than P<sub>max</sub>, the device output power

4) For 5G NR n77/n78 HPUE, 5G NR n77/n78 PC2 Maximum Duty Cycle is 50%, using FTM (Factory Test Mode) with 50% duty cycle is considered during SAR testing. For 5G NR other bands, using FTM to perform SAR with default 100% transmission.

5) The following table is duty cycle and factor used for calculating time average power.

| GSM/FDD/TDD | Duty Cycle | Time average calculation factor(dB) |
|-------------|------------|-------------------------------------|
| GSM 1TX     | 12.50%     | -9.0                                |
| GSM 2TX     | 25%        | -6.0                                |
| GSM 3TX     | 37.50%     | -4.3                                |
| GSM 4TX     | 50%        | -3.0                                |
| FDD LTE     | 100%       | 0.0                                 |
| TDD LTE     | 63.30%     | -2.0                                |
| TDD HPUE    | 43.30%     | -3.6                                |
| NR FDD/TDD  | 100%       | 0.0                                 |
| NR TDD HPUE | 50%        | -3.0                                |