

RF Exposure Report

(Part 0: SAR Char Evaluation)

APPLICANT : Motorola Mobility LLC
EQUIPMENT : Mobile Cellular Phone
BRAND NAME : Motorola
MODEL NAME : XT2605-3
FCC ID : IHDT56AW7
STANDARD : FCC 47 CFR PART 2 (2.1093)

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures given in 47 CFR Part 2.1093 and FCC KDB and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.



Approved by: Si Zhang

Sporton International Inc. (Kunshan)

No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China



Table of Contents

1. Introduction	4
2. Product Description	5
3. SAR Characterization.....	6
3.1 SAR design target and uncertainty.....	6
3.2 SAR Char Table	7



History of this test report

Report No.	Version	Description	Issued Date
FA5O2822-02C	01	Initial issue of report	Dec. 24, 2025

1. Introduction

The Qualcomm® Smart Transmit™ 3.0 of Smart Transmit (GEN2) Feature operates based on pre-defined sub6 antenna groups (AG). This Device is enabled with the Qualcomm® Smart Transmit Gen2 feature. The RF exposure limit is defined based on time-averaged RF exposure. The RF exposure limit is defined based on time-averaged RF exposure. The product implements Qualcomm Smart Transmit feature which controls the instantaneous transmitting power for WWAN to ensure the product in compliance with RF exposure limit over a defined time window. To control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure is compliant to the regulation requirement. Smart Transmit cannot operate without SAR characterization at the device level, beforehand.

This report describes the procedures for the SAR char generation, and the parameters obtained from SAR characterization (referred to as SAR char, respectively) will be used as input for Smart Transmit. Both SAR char will be entered via the Embedded File System (EFS) version 20 to enable the Smart Transmit GEN2 Feature.

Terminologies in this report

P_{limit}	The time-averaged RF power which corresponds to SAR_design_target.
P_{max}	Maximum target power level
SAR_design_target:	The design target for SAR compliance. It should be less than regulatory power density limit to account for all device design related uncertainty.
SAR char	P_{limit} for all the technologies/bands for all applicable DSI



2. Product Description

Product Feature & Specification	
Equipment Name	Mobile Cellular Phone
Brand Name	Motorola
Model Name	XT2605-3
FCC ID	IHDT56AW7
Wireless Technology and Frequency Range	GSM850: 824 MHz ~ 849 MHz GSM1900: 1850 MHz ~ 1910 MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 38: 2570 MHz ~ 2620 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 42: 3450 MHz ~ 3550 MHz LTE Band 66: 1710 MHz ~ 1780 MHz 5G NR n2: 1850 MHz ~ 1910 MHz 5G NR n7: 2500 MHz ~ 2570 MHz 5G NR n38: 2570 MHz ~ 2620 MHz 5G NR n41: 2496 MHz ~ 2690 MHz 5G NR n66: 1710 MHz ~ 1780 MHz 5G NR n77: 3700 MHz ~ 3980 MHz 5G NR n78: 3700 MHz ~ 3800 MHz WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz WLAN U-NII 5: 5925 MHz ~ 6425 MHz WLAN U-NII 6: 6425 MHz ~ 6525 MHz WLAN U-NII 7: 6525 MHz ~ 6875 MHz WLAN U-NII 8: 6875 MHz ~ 7125 MHz Bluetooth: 2402 MHz ~ 2480 MHz NFC: 13.56 MHz
Mode	GSM/GPRS/EGPRS RMC/AMR 12.2Kbps HSDPA/HSUPA DC-HSDPA HSPA+(16QAM uplink is supported) LTE: QPSK, 16QAM, 64QAM, 256QAM 5G NR: DFT-s-OFDM/CP-OFDM, Pi/2 BPSK/QPSK/16QAM/64QAM/256QAM WLAN 2.4GHz 802.11b/g/n HT20/HT40 WLAN 2.4GHz 802.11ax HE20/HE40 WLAN 5GHz 802.11a/n HT20/HT40 WLAN 5GHz 802.11ac VHT20/VHT40/VHT80 WLAN 5GHz 802.11ax HE20/HE40/HE80 WLAN 6GHz 802.11a/ax HE20/HE40/HE80 Bluetooth BR/EDR/LE NFC: ASK

3. SAR Characterization

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for $f < 6$ GHz.

3.1 SAR design target and uncertainty

SAR design Target :

Exposure Condition	Measure Distance	SAR (W/kg)	
		AG0	AG1
Body Worn (1g)	5 mm	1.03	0.71
Hotspot (1g)	5 mm	1.03	0.50
Head (1g)	touch&tilt 15deg	1.03	0.71
Extremity (10g)	0 mm	2.55	1.98

Uncertainty:

Item	Uncertainty dB (k=2)
Total uncertainty	1.5

To account for total uncertainty, SAR_design_target should be determined as:

$$SAR_{design_target} < SAR_{regulatory_limit} \times 10^{\frac{-total\ uncertainty}{10}}$$

Antenna Group:

Antenna Group 0 (AG0)	ANT0 & ANT2& ANT8
Antenna Group 1 (AG1)	ANT1 & ANT4& ANT5& ANT9& ANT7

**3.2 SAR Char Table**

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for $f < 6$ GHz.

<P_{limit} for supported technologies and bands (P_{limit} in EFS file)>

Band	Antenna	Head DSI2	Body worn DSI3	Hotspot DSI7	Extremity DSI6	Sensor off DSI4	Pmax*
GSM850	Ant0	33.7	24.2	24.2	28.1	31.2	24.7
GSM850	Ant1	21.2	20.3	18.5	24.7	31.5	24.7
GSM1900	Ant1	16.3	15.7	14.9	20.9	23.9	19.7
GSM1900	Ant2	34.3	24.2	24.2	21.7	24.1	21.7
WCDMA II	Ant1	14.8	15.8	14.0	20.5	24.1	23.0
WCDMA II	Ant2	31.9	22.5	22.5	24.0	27.5	23.0
WCDMA IV	Ant1	17.4	16.5	14.9	21.0	26.1	23.0
WCDMA IV	Ant2	31.6	21.6	21.1	23.2	27.2	23.0
WCDMA V	Ant0	31.0	23.3	23.3	25.5	29.4	23.0
WCDMA V	Ant1	22.8	20.1	18.5	24.9	29.2	23.0
LTE Band 2	Ant0	32.6	17.5	17.3	20.5	24.1	22.0
LTE Band 2	Ant1	16.6	16.1	14.5	21.0	23.7	23.0
LTE Band 2	Ant2	32.7	22.7	21.7	26.4	28.1	23.0
LTE Band 2	Ant9	23.5	19.9	15.6	20.1	20.1	23.0
LTE Band 7	Ant0	34.7	20.0	20.0	21.0	28.9	23.0
LTE Band 7	Ant1	15.5	15.5	13.7	19.9	24.3	23.0
LTE Band 7	Ant2	30.4	22.1	21.1	23.2	29.4	23.0
LTE Band 7	Ant9	20.5	17.4	11.9	18.0	18.0	23.0
LTE Band 12(17)	Ant0	34.6	26.8	26.8	23.0	23.0	23.0
LTE Band 12(17)	Ant1	23.5	22.2	19.8	23.0	31.8	23.0
LTE Band 13	Ant0	31.1	24.7	24.1	23.0	23.0	23.0
LTE Band 13	Ant1	22.7	20.1	18.4	23.0	29.6	23.0
LTE Band 26(5)	Ant0	32.3	23.0	23.0	23.0	23.0	23.0
LTE Band 26(5)	Ant1	23.7	21.0	18.7	23.9	30.2	23.0
LTE Band 66(4)	Ant1	17.4	17.0	15.3	21.0	23.7	23.0
LTE Band 66(4)	Ant2	32.4	22.0	20.9	23.4	27.6	23.0
LTE Band 41(38)	Ant0	33.0	18.7	18.7	20.7	27.9	21.0
LTE Band 41(38)	Ant1	15.1	15.5	13.7	20.0	24.8	21.0
LTE Band 41(38)	Ant2	31.2	21.1	20.8	22.1	28.1	21.0
LTE Band 41(38)	Ant9	20.4	18.2	12.7	18.5	18.5	21.0
LTE Band 42	Ant4	18.2	17.5	15.1	18.0	30.4	18.0
LTE Band 42	Ant7	16.1	16.9	15.1	20.5	23.2	21.0
FR1 n2	Ant1	17.3	16.6	14.7	20.3	25.2	23.0
FR1 n2	Ant2	34.0	22.5	22.7	23.0	29.3	23.0
FR1 n7	Ant1	15.7	16.6	14.5	21.7	25.5	23.0
FR1 n7	Ant2	30.3	22.3	21.8	23.0	29.9	23.0
FR1 n66	Ant1	19.1	18.5	16.4	21.3	26.8	23.0
FR1 n66	Ant2	32.4	23.5	22.4	23.0	23.0	23.0
FR1 n38	Ant0	31.9	18.8	19.5	20.5	20.5	20.5
FR1 n38	Ant2	30.5	22.4	21.0	21.7	23.0	23.0
FR1 n41	Ant0	31.9	20.0	20.6	20.5	28.9	20.5
FR1 n41(38)	Ant1	15.7	17.0	15.4	20.3	26.0	21.5
FR1 n41	Ant2	30.5	22.1	21.0	23.0	28.5	23.0
FR1 n41(38)	Ant9	19.9	18.2	12.4	20.2	20.2	23.0
FR1 n77(78)	Ant4	15.5	18.8	13.3	17.7	26.9	21.5
FR1 n77(78)	Ant5	16.5	17.4	15.0	22.0	26.7	22.0
FR1 n77(78)	Ant7	19.2	19.2	17.6	21.5	24.7	23.0



FR1 n77(78)	Ant8	31.7	26.3	22.9	23.0	23.0	23.0
-------------	------	------	------	------	------	------	------

Note: 1) *P_{max} is used for RF tune up procedure. The maximum allowed output power is equal to P_{max} +total uncertainty.

2) All P_{limit} power levels entered in the Table correspond to average power levels after accounting for duty cycle in the case TDD modulation schemes (for e.g., GSM & LTE TDD & NR TDD).

2) If DSI's P_{limit} is higher than P_{max}, then P_{limit} is operate as P_{max} power.

3) The following table is duty cycle and factor used for calculating time average power.

GSM/FDD/TDD	Duty Cycle	Time average calculation factor(dB)
GSM 1TX	12.50%	-9.0
GSM 2TX	25%	-6.0
GSM 3TX	37.50%	-4.3
GSM 4TX	50%	-3.0
FDD LTE	100%	0.0
TDD LTE	63.30%	-2.0
NR FDD/TDD	100%	0.0

-----THE END-----