



FCC RF Test Report

APPLICANT : Motorola Mobility LLC
EQUIPMENT : Mobile Cellular Phone
BRAND NAME : Motorola
MODEL NAME : XT2605-3
FCC ID : IHDT56AW7
STANDARD : FCC Part 15 Subpart E §15.407
CLASSIFICATION : 15E 6 GHz Low Power Indoor Client (6XD)
TEST DATE(S) : Nov. 15, 2025 ~ Dec. 17, 2025

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.

Jason Jia

Approved by: Jason Jia



Sporton International Inc. (Kunshan)

***No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China***



Table of Contents

1	General Description	5
1.1	Applicant	5
1.2	Manufacturer	5
1.3	Product Feature of Equipment Under Test.....	5
1.4	Product Specification of Equipment Under Test.....	6
1.5	Modification of EUT	7
1.6	Specification of Accessory	7
1.7	Testing Location	8
1.8	Test Software	8
1.9	Applicable Standards	8
2	Test Configuration of Equipment Under Test	9
2.1	Carrier Frequency and Channel	9
2.2	Test Mode	11
2.3	Connection Diagram of Test System	12
2.4	Support Unit used in test configuration and system	13
2.5	EUT Operation Test Setup	14
2.6	Measurement Results Explanation Example	14
3	Test Result	15
3.1	26dB & 99% Occupied Bandwidth Measurement	15
3.2	Maximum conducted Output Power and Fundamental Maximum EIRP Measurement	16
3.3	Fundamental Power Spectral Density Measurement	17
3.4	In-Band Emissions (Channel Mask)	19
3.5	Contention Based Protocol	21
3.6	Unwanted Emissions Measurement	30
3.7	AC Conducted Emission Measurement	34
3.8	Antenna Requirements	36
4	List of Measuring Equipment	37
5	Measurement Uncertainty	38
Appendix A. Conducted Test Results		
Appendix B. AC Conducted Emission Test Result		
Appendix C. Radiated Spurious Emission		
Appendix D. Duty Cycle Plots		
Appendix E. Setup Photographs		



History of this test report

Report No.	Version	Description	Issued Date
FR5O2822-02F	01	Initial issue of report	Dec. 23, 2025



Summary of Test Result

Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
3.1	15.407(a)(11)	26dB Emission Bandwidth	Pass	-
3.1	2.1049	99% Occupied Bandwidth	Pass	-
3.2	15.407(a)(8)	Maximum Conducted Output Power	Reporting only	-
3.2	15.407(a)(8)	Fundamental Maximum EIRP	Pass	-
3.3	15.407(a)(8)	Fundamental Power Spectral Density	Pass	-
3.4	15.407(b)(7)	In-Band Emissions (Channel Mask)	Pass	-
3.5	15.407(d)(6)	Contention Based Protocol	Pass	
3.6	15.407(b)	Unwanted Emissions	Pass	Under limit 3.69 dB at 5924.82 MHz
3.7	15.207	AC Conducted Emission	Pass	Under limit 14.03 dB at 0.510 MHz
3.8	15.203 15.407(a)	Antenna Requirement	Pass	-

Conformity Assessment Condition:

1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacture who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
2. The measurement uncertainty please refer to each test result in the section "Measurement Uncertainty"

Disclaimer:

The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.



1 General Description

1.1 Applicant

Motorola Mobility LLC

222 W,Merchandise Mart Plaza, Chicago IL 60654 USA

1.2 Manufacturer

Motorola Mobility LLC

222 W,Merchandise Mart Plaza, Chicago IL 60654 USA

1.3 Product Feature of Equipment Under Test

Product Feature	
Equipment	Mobile Cellular Phone
Brand Name	Motorola
Model Name	XT2605-3
FCC ID	IHDT56AW7
IMEI Code	Conducted: 356194350011533/356194350011541 Radiation: 356194350014016/356194350014024 Conduction: 356194350014115/356194350014123 CBP: 356194350011590/356194350011608
HW Version	DVT2
SW Version	W2WE36.39
EUT Stage	Identical Prototype

Remark: The above EUT's information was declared by manufacturer. Please refer to the specifications or user's manual for more detailed description.

1.4 Product Specification of Equipment Under Test

Standards-related Product Specification	
Tx/Rx Frequency Range	U-NII-5: 5925 MHz ~ 6425 MHz U-NII-6: 6425 MHz ~ 6525 MHz U-NII-7: 6525 MHz ~ 6875 MHz U-NII-8: 6875 MHz ~ 7125 MHz
Maximum EIRP	<5925 MHz ~ 7125 MHz > <SISO Ant. 4> 802.11a : 7.50 dBm / 0.0056 W 802.11ax HE20 : 7.74 dBm / 0.0059 W 802.11ax HE40 : 10.45 dBm / 0.0111 W 802.11ax HE80 : 12.38 dBm / 0.0173 W <SISO Ant. 6> 802.11a : 7.72 dBm / 0.0059 W 802.11ax HE20 : 8.14 dBm / 0.0065 W 802.11ax HE40 : 12.03 dBm / 0.0160 W 802.11ax HE80 : 11.75 dBm / 0.0150 W
99% Occupied Bandwidth	<SISO Ant. 4> 802.11a : 16.754 MHz 802.11ax HE20 : 19.267 MHz 802.11ax HE40 : 51.937 MHz 802.11ax HE80 : 87.12 MHz <SISO Ant. 6> 802.11a : 16.545 MHz 802.11ax HE20 : 18.981 MHz 802.11ax HE40 : 45.769 MHz 802.11ax HE80 : 78.515 MHz
Antenna Type / Gain	<5925 MHz ~ 6425 MHz > <Ant. 4> : PIFA Antenna with gain -5.1 dBi <Ant. 6> : PIFA Antenna with gain -6.6 dBi <6425 MHz ~ 6525 MHz > <Ant. 4> : PIFA Antenna with gain -5.9 dBi <Ant. 6> : PIFA Antenna with gain -6.8 dBi <6525 MHz ~ 6875 MHz > <Ant. 4> : PIFA Antenna with gain -5.5 dBi <Ant. 6> : PIFA Antenna with gain -6.7 dBi <6875 MHz ~ 7125 MHz > <Ant. 4> : PIFA Antenna with gain -6.3 dBi <Ant. 6> : PIFA Antenna with gain -7.3 dBi
Type of Modulation	802.11a: OFDM (BPSK / QPSK / 16QAM / 64QAM) 802.11ax: OFDM (BPSK / QPSK / 16QAM / 64QAM / 256QAM / 1024QAM)

Remark:

1. 802.11ax support full RU tone and partial RU tone, both full RU and partial RU-left (for low CH) and partial RU-right (for high CH) are tested for conducted power/PSD/Channel Mask in appendix A, all the other test case were performed with full RU with its maximum power/PSD.
2. The EUT does not support channel puncturing mode.
3. The device does not support UNII-8 CH233 (BW=20M, Center Frequency = 7115MHz).



4. CBP test with antenna path of minimum gain (Antenna 6, Minimum gain= -7.3 dBi).

1.5 Modification of EUT

No modifications are made to the EUT during all test items.

1.6 Specification of Accessory

Specification of Accessory				
AC Adapter 1(US)	Brand Name	Motorola(Chenyang)	Model Name	MC-681N
AC Adapter 1(EU)	Brand Name	Motorola(Chenyang)	Model Name	MC-682N
AC Adapter 1(AR)	Brand Name	Motorola(Chenyang)	Model Name	MC-686N
AC Adapter 1(BR)	Brand Name	Motorola(Chenyang)	Model Name	MC-687N
AC Adapter 1(CHILE)	Brand Name	Motorola(Chenyang)	Model Name	MC-689N
AC Adapter 2(US)	Brand Name	Motorola(Acbel)	Model Name	MC-681N
AC Adapter 2(EU)	Brand Name	Motorola(Acbel)	Model Name	MC-682N
AC Adapter 2(AR)	Brand Name	Motorola(Acbel)	Model Name	MC-686N
AC Adapter 2(BR)	Brand Name	Motorola(Acbel)	Model Name	MC-687N
AC Adapter 2(CHILE)	Brand Name	Motorola(Acbel)	Model Name	MC-689N
Battery 1	Brand Name	Motorola(AmpereX)	Model Name	SA52
Battery 2	Brand Name	Motorola(Veken)	Model Name	SA52
USB Cable 1	Brand Name	Motorola(SAIBAO)	Model Name	SC18D71644
USB Cable 2	Brand Name	Motorola(Luxshare)	Model Name	SC18E08104
USB Cable 3	Brand Name	Motorola(SAIBAO)	Model Name	SC18D86731
USB Cable 4	Brand Name	Motorola(Luxshare)	Model Name	SC18E08103



1.7 Testing Location

Sporton International Inc. (Kunshan) is accredited to ISO/IEC 17025:2017 by American Association for Laboratory Accreditation with Certificate Number 5145.02.

Test Firm	Sporton International Inc. (Kunshan)		
Test Site Location	No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300 People's Republic of China TEL : +86-512-57900158		
Test Site No.	Sporton Site No.	FCC Designation No.	FCC Test Firm Registration No.
	CO01-KS 03CH05-KS TH01-KS DFS01-KS	CN1257	314309

1.8 Test Software

Item	Site	Manufacture	Name	Version
1.	03CH05-KS	AUDIX	E3	6.2009-8-24
2.	CO01-KS	AUDIX	E3	6.2009-8-24

1.9 Applicable Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ FCC Part 15 Subpart E
- ♦ FCC KDB 987594 D02 U-NII 6 GHz EMC Measurement v03
- ♦ FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01.
- ♦ FCC KDB 414788 D01 Radiated Test Site v01r01.
- ♦ FCC KDB 662911 D01 Multiple Transmitter Output v02r01.
- ♦ ANSI C63.10-2020

Remark:

1. All test items were verified and recorded according to the standards and without any deviation during the test.
2. This EUT has also been tested and complied with the requirements of FCC Part 15, Subpart B, recorded in a separate test report.

2 Test Configuration of Equipment Under Test

- a. The EUT has been associated with peripherals and configuration operated in a manner tended to maximize its emission characteristics in a typical application. Frequency range investigated: conduction emission (150 kHz to 30 MHz), radiation emission (9 kHz to the 10th harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower). For radiated measurement, pre-scanned in three orthogonal panels, X, Y, Z. The worst cases (X plane) were recorded in this report.
- b. AC power line Conducted Emission was tested under maximum output power.

2.1 Carrier Frequency and Channel

<U-NII-5, 6, 7, 8>

BW 20M	Channel	-	1	5	9	13	17	21	25	29
	Freq. (MHz)	-	5955	5975	5995	6015	6035	6055	6075	6095
BW 40M	Channel	3			11		19		27	
	Freq. (MHz)	5965			6005		6045		6085	
BW 80M	Channel	7					23			
	Freq. (MHz)	5985					6065			

BW 20M	Channel	33	37	41	45	49	53	57	61
	Freq. (MHz)	6115	6135	6155	6175	6195	6215	6235	6255
BW 40M	Channel	35		43		51		59	
	Freq. (MHz)	6125		6165		6205		6245	
BW 80M	Channel	39					55		
	Freq. (MHz)	6145					6225		

BW 20M	Channel	65	69	73	77	81	85	89	93
	Freq. (MHz)	6275	6295	6315	6335	6355	6375	6395	6415
BW 40M	Channel	67		75		83		91	
	Freq. (MHz)	6285		6325		6365		6405	
BW 80M	Channel	71					87		
	Freq. (MHz)	6305					6385		

BW 20M	Channel	97	101	105	109	113	117	121	125
	Freq. (MHz)	6435	6455	6475	6495	6515	6535	6555	6575
BW 40M	Channel	99		107		115		123	
	Freq. (MHz)	6445		6485		6525		6565	
BW 80M	Channel	103					119		
	Freq. (MHz)	6465					6545		



BW 20M	Channel	129	133	137	141	145	149	153	157
	Freq. (MHz)	6595	6615	6635	6655	6675	6695	6715	6735
BW 40M	Channel	131		139		147		155	
	Freq. (MHz)	6605		6645		6685		6725	
BW 80M	Channel	135				151			
	Freq. (MHz)	6625				6705			

BW 20M	Channel	161	165	169	173	177	181	185	189
	Freq. (MHz)	6755	6775	6795	6815	6835	6855	6875	6895
BW 40M	Channel	163		171		179		187	
	Freq. (MHz)	6765		6805		6845		6885	
BW 80M	Channel	167				183			
	Freq. (MHz)	6785				6865			

BW 20M	Channel	193	197	201	205	209	213	217	221
	Freq. (MHz)	6915	6935	6955	6975	6995	7015	7035	7055
BW 40M	Channel	195		203		211		219	
	Freq. (MHz)	6925		6965		7005		7045	
BW 80M	Channel	199				215			
	Freq. (MHz)	6945				7025			

BW 20M	Channel	225			229		-
	Freq. (MHz)	7075			7095		-
BW 40M	Channel	227					
	Freq. (MHz)	7085					

2.2 Test Mode

Final test modes are considering the modulation and worse data rates as below table.

Modulation	Data Rate
802.11a	6 Mbps
802.11ax HE20	MCS0
802.11ax HE40	MCS0
802.11ax HE80	MCS0

Test Cases	
AC Conducted Emission	Mode 1 : GSM 850 Idle + BT Link + WLAN(6G) Link + USB Cable 1(Charging From Adapter 1)+ Battery
Remark: For Radiated Test Cases, the tests were performed with Adapter 1 and USB Cable 1.	

Ch. #		5925-6425 MHz UNII-5	6425-6525 MHz UNII-6	6525-6875 MHz UNII-7	6875-7125 MHz UNII-8
		802.11ax HE20	802.11ax HE20	802.11ax HE20	802.11ax HE20
L	Low	001	097	117	189
M	Middle	045	105	149	209
H	High	093	113	181	229
Straddle		-	-	-	185

Ch. #		5925-6425 MHz UNII-5	6425-6525 MHz UNII-6	6525-6875 MHz UNII-7	6875-7125 MHz UNII-8
		802.11ax HE40	802.11ax HE40	802.11ax HE40	802.11ax HE40
L	Low	003	099	123	195
M	Middle	043	-	147	203
H	High	091	107	179	227
Straddle		-	115	-	187


Ch. #		5925-6425 MHz UNII-5	6425-6525 MHz UNII-6	6525-6875 MHz UNII-7	6875-7125 MHz UNII-8
		802.11ax HE80	802.11ax HE80	802.11ax HE80	802.11ax HE80
L	Low	007	103	135	199
M	Middle	039		151	-
H	High	087		167	215
Straddle		-	119	183	-

Ch. #		5925-6425 MHz UNII-5	6425-6525 MHz UNII-6	6525-6875 MHz UNII-7	6875-7125 MHz UNII-8
		802.11ax HE160	802.11ax HE160	802.11ax HE160	802.11ax HE160
L	Low	015	-	143	207
M	Middle	047			
H	High	079			
Straddle		-	111	175	-


Remark: For radiation spurious emission, the final modulation and the worst data rate was reference the max RF conducted power.

2.3 Connection Diagram of Test System

For AC Conducted Emission



For Radiated Emission



2.4 Support Unit used in test configuration and system

Item	Equipment	Brand Name	Model Name	FCC ID	Data Cable	Power Cord
1.	LTE Base Station	Anritus	MT8821C	N/A	N/A	Unshielded,1.8m
2.	5GNR Base Station	Anritus	MT8000A	N/A	N/A	Unshielded,1.8m
3.	Vector Signal Generator	R&S	SMBV100A	258305	N/A	N/A
4.	Bluetooth Earphone	Lenovo	thinkplus-BH3	N/A	N/A	N/A
5.	WLAN AP	D-link	DIR-655	KA21R655B1	N/A	Unshielded,1.8m
6.	Notebook	Lenovo	G480	QDS-BRCM1050I	N/A	AC I/P: Unshielded, 1.8 m DC O/P: Shielded, 1.8 m
7.	Hard Disk	Lenovo	F310	DoC	Shielded, 1.2m	N/A



2.5 EUT Operation Test Setup

For WLAN RF test items, an engineering test program (QRCT TX Tool) was provided and enabled to make EUT continuously transmit.

For AC power line conducted emissions, the EUT was set to connect with the WLAN AP under large package sizes transmission.

2.6 Measurement Results Explanation Example

For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

Example :

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

Offset = RF cable loss + attenuator factor.

Following shows an offset computation example with cable loss 5.25 dB and 20dB attenuator.

$$\begin{aligned}\text{Offset(dB)} &= \text{RF cable loss(dB)} + \text{attenuator factor(dB)} \\ &= 5.25 + 20 = 25.25 \text{ (dB)}\end{aligned}$$

3 Test Result

3.1 26dB & 99% Occupied Bandwidth Measurement

3.1.1 CFR 15.407 (a)(11)

The maximum transmitter channel bandwidth for U-NII devices in the 5.925-7.125 GHz band is 320 megahertz.


3.1.2 Measuring Instruments

See list of measuring equipment of this test report.

3.1.3 Test Procedures

1. The testing follows FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01. Section C) Emission bandwidth
2. Set RBW = approximately 1% of the emission bandwidth.
3. Set the VBW > RBW.
4. Detector = Peak.
5. Trace mode = max hold
6. Measure the maximum width of the emission that is 26 dB down from the peak of the emission. Compare this with the RBW setting of the analyzer. Readjust RBW and repeat measurement as needed until the RBW/EBW ratio is approximately 1%.
7. For 99% Bandwidth Measurement, the spectrum analyzer's resolution bandwidth (RBW) is set 1-5% of the emission bandwidth and set the Video bandwidth (VBW) $\geq 3 * RBW$.
8. Measure and record the results in the test report.

3.1.4 Test Setup



3.1.5 Test Result of 26dB & 99% Occupied Bandwidth

Please refer to Appendix A.

3.2 Maximum conducted Output Power and Fundamental Maximum EIRP Measurement

3.2.1 Limit of Fundamental Maximum EIRP

<FCC CFR 15.407>

(a)(8) For client devices operating under the control of an indoor access point in the 5.925-7.125 GHz bands, the maximum e.i.r.p. over the frequency band of operation must not exceed 24 dBm.

3.2.2 Measuring Instruments

See list of measuring equipment of this test report.


3.2.3 Test Procedures

The testing follows Method PM of FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01.

Method PM (Measurement using an RF average power meter):

1. Measurement is performed using a wideband RF power meter.
2. The EUT is configured to transmit continuously with a consistent duty cycle at its maximum power control level.
3. Measure the average power of the transmitter, and the average power is corrected with duty factor, $10 \log(1/x)$, where x is the duty cycle.

3.2.4 Test Setup



3.2.5 Test Result of Fundamental Maximum EIRP

Please refer to Appendix A.

3.3 Fundamental Power Spectral Density Measurement

3.3.1 Limit of Fundamental Power Spectral Density

<FCC CFR 15.407>

(a)(8) For client devices operating under the control of an indoor access point in the 5.925-7.125 GHz bands, the maximum power spectral density must not exceed -1 dBm e.i.r.p. in any 1-megahertz band.

3.3.2 Measuring Instruments

See list of measuring equipment of this test report.

3.3.3 Test Procedures


The testing follows FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01.
Section F) Maximum power spectral density.

Method SA-2

(trace averaging across on and off times of the EUT transmissions, followed by duty cycle correction).

- Measure the duty cycle.
 - Set span to encompass the entire emission bandwidth (EBW) of the signal.
 - Set RBW = 1 MHz.
 - Set VBW $\geq$ 3 MHz.
 - Number of points in sweep $\geq$ 2 Span / RBW.
 - Sweep time = auto.
 - Detector = RMS
 - Trace average at least 100 traces in power averaging mode.
 - Add $10 \log(1/x)$, where x is the duty cycle, to the measured power in order to compute the average power during the actual transmission times. For example, add $10 \log(1/0.25) = 6$ dB if the duty cycle is 25 percent.
1. The RF output of EUT was connected to the spectrum analyzer by a low loss cable.
 2. Each plot has already offset with cable loss, attenuator loss and duty factor. Measure the PSD and record it.

3.3.4 Test Setup



3.3.5 Test Result of Power Spectral Density

Please refer to Appendix A.

3.4 In-Band Emissions (Channel Mask)

3.4.1 Limit of Unwanted Emissions

<FCC CFR 15.407>

(b)(7) For transmitters operating within the 5.925-7.125 GHz bands: Power spectral density must be suppressed by 20 dB at 1 MHz outside of channel edge, by 28 dB at one channel bandwidth from the channel center, and by 40 dB at one- and one-half times the channel bandwidth away from channel center. At frequencies between one megahertz outside an unlicensed device's channel edge and one channel bandwidth from the center of the channel, the limits must be linearly interpolated between 20 dB and 28 dB suppression, and at frequencies between one and one- and one-half times an unlicensed device's channel bandwidth, the limits must be linearly interpolated between 28 dB and 40 dB suppression. Emissions removed from the channel center by more than one- and one-half times the channel bandwidth must be suppressed by at least 40 dB.

3.4.2 Measuring Instruments

See list of measuring equipment of this test report.

3.4.3 Test Procedures


The testing follows FCC KDB 987594 D02 U-NII 6GHz EMC Measurement.

Section J) In-Band Emissions.

1. Take nominal bandwidth as reference channel bandwidth provided that 26 dB emission bandwidth is always larger than nominal bandwidth
2. Measure the power spectral density (which will be used for emissions mask reference) using the following procedure:
 - a) Set the span to encompass the entire 26 dB EBW of the signal.
 - b) Set RBW = same RBW used for 26 dB EBW measurement.
 - c) Set VBW $\geq 3 \times$ RBW
 - d) Number of points in sweep $\geq [2 \times \text{span} / \text{RBW}]$.
 - e) Sweep time = auto.
 - f) Detector = RMS (i.e., power averaging)
 - g) Trace average at least 100 traces in power averaging (rms) mode.
 - h) Use the peak search function on the instrument to find the peak of the spectrum.
3. Using the measuring equipment limit line function, develop the emissions mask based on the following requirements. The emissions power spectral density must be reduced below the peak power spectral density (in dB) as follows:
 - a. Suppressed by 20 dB at 1 MHz outside of the channel edge.
 - b. Suppressed by 28 dB at one channel bandwidth from the channel center.

- c. Suppressed by 40 dB at one- and one-half times the channel bandwidth from the channel center.
4. Adjust the span to encompass the entire mask as necessary.
5. Clear trace.
6. Trace average at least 100 traces in power averaging (rms) mode.
7. Adjust the reference level as necessary so that the crest of the channel touches the top of the emission mask.

3.4.4 Test Setup



3.4.5 Test Result

Please refer to Appendix A.

3.5 Contention Based Protocol

3.5.1 Limit of Contention Based Protocol

<FCC CFR 15.407>

(d)(6) All U-NII transmitters, except for standard power access points and fixed client devices, operating in the 5.925-7.125 GHz band must employ a contention-based protocol.

Unlicensed low-power indoor devices must detect co-channel radio frequency power that is at least -62 dBm or lower. Upon detection of energy in the band, unlicensed low power indoor devices must vacate the channel and stay off the channel as long as detected radio frequency power is equal to or greater than the threshold (-62 dBm). The -62 dBm (or lower) threshold is referenced to a 0 dBi antenna gain. To ensure incumbent operations are reliably detected in the band, low power indoor devices must detect RF energy throughout their intended operating channel. For example, an 802.11 device that plans to transmit a 40 MHz- wide signal (on a primary 20 MHz channel and a secondary 20 MHz channel) must detect energy throughout the entire 40 MHz channel. Additionally, low-power indoor devices must detect co-channel energy with 90% or greater certainty.

Table 1. Criteria to determine number of times detection threshold test may be performed

If	Number of Tests	Placement of Incumbent Transmission
$BW_{EUT} \leq BW_{Inc}$	Once	Tune incumbent and EUT transmissions ($f_{c1} = f_{c2}$)
$BW_{Inc} < BW_{EUT} \leq 2BW_{Inc}$	Once	Incumbent transmission is contained within BW_{EUT}
$2BW_{Inc} < BW_{EUT} \leq 4BW_{Inc}$	Twice. Incumbent transmission is contained within BW_{EUT}	Incumbent transmission is located as closely as possible to the lower edge and upper edge, respectively, of the EUT channel
$BW_{EUT} > 4BW_{Inc}$	Three times	Incumbent transmission is located as closely as possible to the lower edge of the EUT channel, in the middle of EUT channel, and as closely as possible to the upper edge of the EUT channel


where:

BW_{EUT} : Transmission bandwidth of EUT signal

BW_{Inc} : Transmission bandwidth of the simulated incumbent signal (10 MHz wide AWGN signal)

f_{c1} : Center frequency of EUT transmission

f_{c2} : Center frequency of simulated incumbent signal



3.5.2 Measuring Instruments

See list of measuring equipment of this test report.


3.5.3 Test Procedures

1. To ensure EUT reliably detects an incumbent signal in both scenarios shown in Figure 1, the detection threshold test may be repeated more than once with the incumbent signal (having center frequency f_{c2}) tuned to different center frequencies within the UT transmission bandwidth. The criteria specified in Table 1 determines how many times the detection threshold test must be performed
2. Using an AWGN signal source, generate (but do not transmit, i.e., RF OFF) a 10 MHz-wide AWGN signal. Use Table 1 to determine the center frequency of the 10 MHz AWGN signal relative to the EUT's channel bandwidth and center frequency.
3. Monitor the signal analyzer to verify if the AWGN signal has been detected and the EUT has ceased transmission. If the EUT continues to transmit, then incrementally increase the AWGN signal power level until the EUT stops transmitting.
4. (Including all losses in the RF paths) Determine and record the AWGN signal power level (at the EUT's antenna port) at which the EUT ceased transmission. Repeat the procedure at least 10 times to verify the EUT can detect an AWGN signal with 90% (or better) level of certainty.
5. Refer to Table 1 to determine number of times the detection threshold testing needs to be repeated. If testing is required more than once, then go back to step 2, choose a different center

frequency for the AWGN signal and repeat the process.

6. EUT was driven in MIMO mode, the interferer signal was injected to both chains to monitor the performance, while the interferer level is determined according to the lowest antenna gain among both antennas.

3.5.4 Test Setup



3.5.5 Support Unit used in test configuration and system

Instrument	Brand Name	Model No.	Characteristics
Signal Generator	Keysight	5182B/5182BX07	9KHz~7.2GHz
Spectrum Analyzer	R&S	FSV40	10kHz~40GHz
Terminal (NB Server)	DELL	P78G	LAN
Combiner (splitter1)	Tojoin	N/A	2G~8GHz
Combiner (splitter2)	MTJ Cooperation	MTJ7144-M	0.5GHz~18GHz
Attenuator	Keysight	8494B	0-110dBm
WLAN AP	ASUS	GT-AXE11000	Dual Band AP

3.5.6 Test Summary of Contention Based Protocol Test

Band	Channel Freq. (MHz)	Channel BW (MHz)	Incumbent freq. (MHz)	Injected AWGN Level (dBm)	Detection Rate (%)	Regulated Threshold level (dBm)	Adjusted Power (dBm)	Margin (dB)
UNII Band 5	6135	20	6415	-76.59	100	-62	-69.29	7.29
					Result: Stop Transmission			
				-77.59	< 90	-62	-70.29	8.29
					Result: Minimal Operation			
				-78.90	0	-62	-71.6	9.6
					Result: Normal Operation			
	6145	80	6030	-75.94	100	-62	-68.64	6.64
					Result: Stop Transmission			
				-76.94	< 90	-62	-69.64	7.64
					Result: Minimal Operation			
				-77.67	0	-62	-70.37	8.37
					Result: Normal Operation			
			6065	-75.67	100	-62	-68.37	6.37
					Result: Stop Transmission			
				-76.67	< 90	-62	-69.37	7.37
					Result: Minimal Operation			
				-77.22	0	-62	-69.92	7.92
					Result: Normal Operation			
			6100	-76.26	100	-62	-68.96	6.96
					Result: Stop Transmission			
				-77.26	< 90	-62	-69.96	7.96
					Result: Minimal Operation			
				-77.68	0	-62	-70.38	8.38
					Result: Normal Operation			

Note 1: Adjusted Power = Injected AWGN Level - minimum antenna gain (Antenna 6, gain = -7.3dBi)

Note 2: Path Loss between antenna and RF connector is negligible. (0 dB)

Note 3: Margin = Regulated Threshold level - Adjusted Power



Band	Channel Freq. (MHz)	Channel BW (MHz)	Incumbent freq. (MHz)	Injected AWGN Level (dBm)	Detection Rate (%)	Regulated Threshold level (dBm)	Adjusted Power (dBm)	Margin (dB)
UNII Band 6/7	6455	20	6475	-77.64	100	-62	-70.34	8.34
					Result: Stop Transmission			
				-78.64	< 90	-62	-71.34	9.34
					Result: Minimal Operation			
				-79.37	0	-62	-72.07	10.07
					Result: Normal Operation			
	6465	80	6510	-77.90	100	-62	-70.6	8.6
					Result: Stop Transmission			
				-78.90	< 90	-62	-71.6	9.6
					Result: Minimal Operation			
				-79.09	0	-62	-71.79	9.79
					Result: Normal Operation			
			6545	-76.64	100	-62	-69.34	7.34
					Result: Stop Transmission			
				-77.64	< 90	-62	-70.34	8.34
					Result: Minimal Operation			
				-78.43	0	-62	-71.13	9.13
					Result: Normal Operation			
			6580	-77.87	100	-62	-70.57	8.57
					Result: Stop Transmission			
				-78.87	< 90	-62	-71.57	9.57
					Result: Minimal Operation			
				-79.05	0	-62	-71.75	9.75
					Result: Normal Operation			

Note 1: Adjusted Power = Injected AWGN Level - minimum antenna gain (Antenna 6, gain = -7.3dBi)

Note 2: Path Loss between antenna and RF connector is negligible. (0 dB)

Note 3: Margin = Regulated Threshold level - Adjusted Power



Band	Channel Freq. (MHz)	Channel BW (MHz)	Incumbent freq. (MHz)	Injected AWGN Level (dBm)	Detection Rate (%)	Regulated Threshold level (dBm)	Adjusted Power (dBm)	Margin (dB)
UNII Band 7/8	6695	20	6695	-78.09	100	-62	-70.79	8.79
					Result: Stop Transmission			
				-79.09	< 90	-62	-71.79	9.79
					Result: Minimal Operation			
				-79.23	0	-62	-71.93	9.93
					Result: Normal Operation			
	6705	80	6830	-76.64	100	-62	-69.34	7.34
					Result: Stop Transmission			
				-77.64	< 90	-62	-70.34	8.34
					Result: Minimal Operation			
				-77.95	0	-62	-70.65	8.65
					Result: Normal Operation			
			6865	-76.72	100	-62	-69.42	7.42
					Result: Stop Transmission			
				-77.72	< 90	-62	-70.42	8.42
					Result: Minimal Operation			
				-77.93	0	-62	-70.63	8.63
					Result: Normal Operation			
			6900	-77.00	100	-62	-69.7	7.7
					Result: Stop Transmission			
				-78.00	< 90	-62	-70.7	8.7
					Result: Minimal Operation			
				-78.22	0	-62	-70.92	8.92
					Result: Normal Operation			

Note 1: Adjusted Power = Injected AWGN Level - minimum antenna gain (Antenna 6, gain = -7.3dBi)

Note 2: Path Loss between antenna and RF connector is negligible. (0 dB)

Note 3: Margin = Regulated Threshold level - Adjusted Power



Band	Channel Freq. (MHz)	Channel BW (MHz)	Incumbent freq. (MHz)	Injected AWGN Level (dBm)	Detection Rate (%)	Regulated Threshold level (dBm)	Adjusted Power (dBm)	Margin (dB)
UNII Band 8	7015	20	6955	-77.85	100	-62	-70.55	8.55
					Result: Stop Transmission			
				-78.85	< 90	-62	-71.55	9.55
					Result: Minimal Operation			
				-78.89	0	-62	-71.59	9.59
					Result: Normal Operation			
	7025	80	6990	-74.80 (worst)	100	-62	-67.5	5.5
					Result: Stop Transmission			
				-75.80	< 90	-62	-68.5	6.5
					Result: Minimal Operation			
				-76.89	0	-62	-69.59	7.59
					Result: Normal Operation			
			7025	-76.65	100	-62	-69.35	7.35
					Result: Stop Transmission			
				-77.65	< 90	-62	-70.35	8.35
					Result: Minimal Operation			
				-78.26	0	-62	-70.96	8.96
					Result: Normal Operation			
			7060	-77.30	100	-62	-70	8
					Result: Stop Transmission			
				-78.30	< 90	-62	-71	9
					Result: Minimal Operation			
				-78.50	0	-62	-71.2	9.2
					Result: Normal Operation			

Note 1: Adjusted Power = Injected AWGN Level - minimum antenna gain (Antenna 6, gain = -7.3dBi)

Note 2: Path Loss between antenna and RF connector is negligible. (0 dB)

Note 3: Margin = Regulated Threshold level - Adjusted Power




3.5.7 Worst Case Plots of Contention Based Protocol

Contention Based Protocol Result Plots on U-NII 8 (AWGN Interference)


802.11ax (HE80) / 6990MHz (Lower edge)

Threshold Level (TL) = -74.80 dBm




802.11ax (HE80) / CH201 (Lower edge)

Test result is pass due to no transmission occur.




802.11ax (HE80) / 6990MHz (Lower edge)

Threshold Level (TL) = -75.80 dBm



802.11ax (HE80) / CH201 (Lower edge)

Transmit when the interferer is 1dB lower.




Remark: M1: Injection of AWGN signal, D1: Removal of AWGN signal



3.5.8 Worst Case of Contention Based Protocol Transmission Bandwidth

Verify transmission absence when Incumbent signal at different frequency (frequency domain plots).

1. When Incumbent Signal inject at lowest frequency, the transmission bandwidth reduced to 20MHz;
2. When Incumbent Signal inject at middle frequency, the whole 80MHz bandwidth stop transmission;
3. When Incumbent Signal inject at highest frequency, the transmission bandwidth reduced to 40MHz;
4. This device does not support channel puncturing mode for incumbent avoidance but bandwidth reduction mechanism is supported.



3.6 Unwanted Emissions Measurement

This section is to measure unwanted emissions through radiated measurement for band edge spurious emissions and out of band emissions measurement.

3.6.1 Limit of Unwanted Emissions

- (1) For transmitters operating within the 5.925-7.125 GHz band: Any emissions outside of the 5.925-7.125 GHz band must not exceed an e.i.r.p. of -27 dBm/MHz.

EIRP (dBm)	Field Strength at 3m (dBμV/m)
- 27 (RMS)	68.2
- 7 (Peak)	88.2

Unwanted emissions outside of restricted bands are measured with a RMS detector.

In addition, 15.35(b) applies where the peak emissions must be limited to no more than 20 dB above the average limit

- (2) Unwanted spurious emissions fallen in restricted bands shall comply with the general field strength limits as below table:

Frequency (MHz)	Field Strength (microvolts/meter)	Measurement Distance (meters)
0.009 – 0.490	2400/F(kHz)	300
0.490 – 1.705	24000/F(kHz)	30
1.705 – 30.0	30	30
30 – 88	100	3
88 – 216	150	3
216 - 960	200	3
Above 960	500	3

Note: The following formula is used to convert the EIRP to field strength.

$$E = \frac{1000000\sqrt{30P}}{3} \mu\text{V/m, where P is the eirp (Watts)}$$

3.6.2 Measuring Instruments


See list of measuring equipment of this test report.

3.6.3 Test Procedures


1. The testing follows FCC KDB 789033 D02 General UNII Test Procedures New Rules v02r01.
Section G) Unwanted emissions measurement.
 - (1) Procedure for Unwanted Emissions Measurements Below 1000MHz
 - RBW = 120 kHz
 - VBW = 300 kHz
 - Detector = Peak
 - Trace mode = max hold
 - (2) Procedure for Peak Unwanted Emissions Measurements Above 1000 MHz
 - RBW = 1 MHz
 - VBW $\geq$ 3 MHz
 - Detector = Peak
 - Sweep time = auto
 - Trace mode = max hold
 - (3) Procedures for Average Unwanted Emissions Measurements Above 1000MHz
 - RBW = 1 MHz
 - VBW = 10 Hz, when duty cycle is no less than 98 percent.
 - VBW $\geq$ 1/T, when duty cycle is less than 98 percent where T is the minimum transmission duration over which the transmitter is on and is transmitting at its maximum power control level for the tested mode of operation.
2. The EUT was placed on a turntable with 0.8 meter for frequency below 1GHz and 1.5 meter for frequency above 1GHz respectively above ground.
3. The EUT was set 3 meters from the interference receiving antenna which was mounted on the top of a variable height antenna tower.
4. The antenna is a broadband antenna and its height is adjusted between one meter and four meters above ground to find the maximum value of the field strength for both horizontal polarization and vertical polarization of the antenna.
5. For each suspected emission, the EUT was arranged to its worst case and then adjust the antenna tower (from 1 m to 4 m) and turntable (from 0 degree to 360 degrees) to find the maximum reading.
6. For testing below 1GHz, if the emission level of the EUT in peak mode was 3 dB lower than the limit specified, then peak values of EUT will be reported, otherwise, the emissions will be repeated one by one using the CISPR quasi-peak method and reported.
7. For testing above 1GHz, the emission level of the EUT in peak mode was 20dB lower than average limit (that means the emission level in average mode also complies with the limit in average mode), then peak values of EUT will be reported, otherwise, the emissions will be measured in average mode again and reported.

3.6.4 Test Setup


For radiated emissions below 30MHz



For radiated emissions from 30MHz to 1GHz



For radiated emissions above 1GHz



3.6.5 Test Results of Radiated Spurious Emissions (9 kHz ~ 30 MHz)

The low frequency, which started from 9 kHz to 30MHz, was pre-scanned and the result which was 20dB lower than the limit line was not reported.

There is adequate comparison measurement of both open-field test site and alternative test site - semi-Anechoic chamber according to 414788 D01 Radiated Test Site v01r01, and the result came out very similar.

3.6.6 Test Result of Radiated Spurious at Band Edges

Please refer to Appendix C

3.6.7 Duty Cycle

Please refer to Appendix D.

3.6.8 Test Result of Radiated Spurious Emissions (30MHz ~ 10th Harmonic)

Please refer to Appendix C.

The emission level above 18GHz is checked that the emission level is noise floor only, so it is not reflected in the report.

3.7 AC Conducted Emission Measurement

3.7.1 Limit of AC Conducted Emission

For equipment that is designed to be connected to the public utility (AC) power line, the radio frequency voltage that is conducted back onto the AC power line on any frequency or frequencies within the band 150 kHz to 30 MHz shall not exceed the limits in the following table.

Frequency of emission (MHz)	Conducted limit (dBμV)	
	Quasi-peak	Average
0.15-0.5	66 to 56*	56 to 46*
0.5-5	56	46
5-30	60	50

*Decreases with the logarithm of the frequency.


3.7.2 Measuring Instruments

See list of measuring equipment of this test report.

3.7.3 Test Procedures

1. The EUT was placed 0.4 meter from the conducting wall of the shielding room was kept at least 80 centimeters from any other grounded conducting surface.
2. Connect EUT to the power mains through a line impedance stabilization network (LISN).
3. All the support units are connecting to the other LISN.
4. The LISN provides 50 ohm coupling impedance for the measuring instrument.
5. The FCC states that a 50 ohm, 50 microhenry LISN should be used.
6. Both sides of AC line were checked for maximum conducted interference.
7. The frequency range from 150 kHz to 30 MHz was searched.
8. Set the test-receiver system to Peak Detect Function and specified bandwidth with Maximum Hold Mode.

3.7.4 Test Setup



3.7.5 Test Result of AC Conducted Emission

Please refer to Appendix B.



3.8 Antenna Requirements

3.8.1 Standard Applicable

§15.203: An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the provisions of this section.

3.8.2 Antenna Anti-Replacement Construction

An embedded-in antenna design is used. The EUT complies with the requirement of 15.203.

3.8.3 Antenna Gain

The antenna peak gain of EUT is less than 6 dBi. Therefore, it is not necessary to reduce maximum peak output power limit.



4 List of Measuring Equipment

Instrument	Brand Name	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Spectrum Analyzer	R&S	FSV40	101040	10Hz~40GHz	Jul. 07, 2025	Nov. 28, 2025~ Dec. 05, 2025	Jul. 06, 2026	Conducted (TH01-KS)
Pulse Power Sensor	Anritsu	MA2411B	0917070	300MHz~40GHz	Jan. 02, 2025	Nov. 28, 2025~ Dec. 05, 2025	Jan. 01, 2026	Conducted (TH01-KS)
Power Meter	Anritsu	ML2495A	1005002	50MHz Bandwidth	Jan. 02, 2025	Nov. 28, 2025~ Dec. 05, 2025	Jan. 01, 2026	Conducted (TH01-KS)
EMI Test Receiver	Keysight	N9038A	MY57290151	3Hz~8.5GHz; Max 30dBm	Jul. 02, 2025	Dec. 08, 2025	Jul. 01, 2026	Radiation (03CH05-KS)
EXA Spectrum Analyzer	Keysight	N9010B	MY60242126	10Hz~44GHz, MAX 30dB	Oct. 10, 2025	Dec. 08, 2025	Oct. 10, 2026	Radiation (03CH05-KS)
Active loop antenna	R&S	HFH2-Z2E	101125	9kHz~30MHz	Aug. 10, 2025	Dec. 08, 2025	Aug. 09, 2026	Radiation (03CH05-KS)
Bilog Antenna	TeseQ	CBL6111D	49921	30MHz~1GHz	Mar. 24, 2025	Dec. 08, 2025	Mar. 23, 2026	Radiation (03CH05-KS)
Double Ridge Horn Antenna	ETS-Lindgren	3117	00218642	1GHz~18GHz	Apr. 14, 2025	Dec. 08, 2025	Apr. 13, 2026	Radiation (03CH05-KS)
SHF-EHF Horn	Com-power	AH-840	101115	18GHz~40GHz	Oct. 18, 2025	Dec. 08, 2025	Oct. 19, 2026	Radiation (03CH05-KS)
Amplifier	SONOMA	310N	380827	9KHz~1GHz	Jul. 03, 2025	Dec. 08, 2025	Jul. 02, 2026	Radiation (03CH05-KS)
Amplifier	EM	EM18G40GA	060851	18~40GHz	Jan. 02, 2025	Dec. 08, 2025	Jan. 01, 2026	Radiation (03CH05-KS)
high gain Amplifier	EM	EM01G18GA	060843	1Ghz~18Ghz	Jan. 02, 2025	Dec. 08, 2025	Jan. 01, 2026	Radiation (03CH05-KS)
Amplifier	EM	EM01G18GA	060833	1Ghz~18Ghz	Jan. 02, 2025	Dec. 08, 2025	Jan. 01, 2026	Radiation (03CH05-KS)
AC Power Source	Chroma	61601	F104090004	N/A	NCR	Dec. 08, 2025	NCR	Radiation (03CH05-KS)
Turn Table	ChamPro	EM 1000-T	060762-T	0~360 degree	NCR	Dec. 08, 2025	NCR	Radiation (03CH05-KS)
Antenna Mast	ChamPro	EM 1000-A	060762-A	1 m~4 m	NCR	Dec. 08, 2025	NCR	Radiation (03CH05-KS)
EMI Receiver	R&S	ESC17	100768	9kHz~7GHz;	Apr. 16, 2025	Nov. 15, 2025	Apr. 15, 2026	Conduction (CO01-KS)
AC LISN (for auxiliary equipment)	MessTec	AN3016	060103	9kHz~30MHz	Jul. 03, 2025	Nov. 15, 2025	Jul. 02, 2026	Conduction (CO01-KS)
AC LISN	MessTec	AN3016	060105	9kHz~30MHz	Dec. 24, 2024	Nov. 15, 2025	Dec. 23, 2025	Conduction (CO01-KS)
AC Power Source	Ouhan	APW-130NYT	202201040060	AC 0V~300V, 45Hz~1000Hz	Apr. 16, 2025	Nov. 15, 2025	Apr. 15, 2026	Conduction (CO01-KS)
Signal Analyzer	R&S	FSV7	101472	10Hz~7GHz	Jan. 02, 2025	Dec. 17, 2025	Jan. 01, 2026	CBP (DFS01-KS)
MXG-B RF Vector Signal Generator	Keysight	5182B /5182BX07	MY56200417 /MY59360210	9kHz~7.2GHz	Apr. 16, 2025	Dec. 17, 2025	Apr. 15, 2026	CBP (DFS01-KS)
Vector Signal Generator	R&S	SMJ100A	101908	100kHz~6GHz	Jan. 02, 2025	Dec. 17, 2025	Jan. 01, 2026	CBP (DFS01-KS)
Combiner	MTJ Cooperation	MTJ7112	N/A	0.4-6GHz	NCR	Dec. 17, 2025	NCR	CBP (DFS01-KS)

NCR: No Calibration Required

5 Measurement Uncertainty

Uncertainty of Conducted Measurement

Conducted Spurious Emission & Bandedge	±2.00 dB
Occupied Channel Bandwidth	±0.384%
Conducted Power	±0.90 dB
Conducted Power Spectral Density	±0.90 dB
Frequency	±0.38 Hz
Conducted Generated signal Levels	±0.56 dB
Conducted Time	0.44%

Uncertainty of AC Conducted Emission Measurement (0.15 MHz ~ 30 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	2.84dB
---	--------

Uncertainty of Radiated Emission Measurement (9 KHz ~ 30 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	3.3dB
---	-------

Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	6.18dB
---	--------

Uncertainty of Radiated Emission Measurement (1 GHz ~ 18 GHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	4.88dB
---	--------

Uncertainty of Radiated Emission Measurement (18 GHz ~ 40 GHz)

Measuring Uncertainty for a Level of Confidence of 95% (U = 2Uc(y))	5.36dB
---	--------

----- THE END -----



Appendix A. Conducted Test Results

TEST RESULTS DATA																
Average Output Power																
Mode							Power Setting	Power Setting	Average Conducted Power with duty factor(dBm)		Gain(dBi)		EIRP Power (dBm)		EIRP Power Limit (dBm)	Pass/Fail
Band	SISO	N _{TX}	Channel	Freq (MHz)	Data Rate	RU Config			Ant 4	Ant 6	Ant 4	Ant 6	Ant 4	Ant 6		
11a	SISO	1	1	5955	6Mbps	-	12.50	14.00	12.26	13.60	-5.10	-6.60	7.16	7.00	24	Pass
11a	SISO	1	49	6195	6Mbps	-	12.50	15.00	12.09	13.16	-5.10	-6.60	6.99	6.56	24	Pass
11a	SISO	1	93	6415	6Mbps	-	13.00	14.50	11.86	13.38	-5.10	-6.60	6.76	6.78	24	Pass
HE20	SISO	1	1	5955	MCS0	Full	13.00	14.50	12.65	13.87	-5.10	-6.60	7.55	7.27	24	Pass
HE20	SISO	1	1	5955	MCS0	RU 26/0	3.50	4.50	4.35	5.57	-5.10	-6.60	-0.75	-1.03	24	Pass
HE20	SISO	1	1	5955	MCS0	RU 52/37	6.50	7.50	7.29	8.53	-5.10	-6.60	2.19	1.93	24	Pass
HE20	SISO	1	1	5955	MCS0	RU 106/53	9.50	11.00	10.18	11.82	-5.10	-6.60	5.08	5.22	24	Pass
HE20	SISO	1	49	6195	MCS0	Full	13.00	16.00	12.38	13.95	-5.10	-6.60	7.28	7.35	24	Pass
HE20	SISO	1	93	6415	MCS0	Full	13.50	15.00	12.11	13.71	-5.10	-6.60	7.01	7.11	24	Pass
HE40	SISO	1	3	5965	MCS0	Full	15.50	17.00	14.97	16.26	-5.10	-6.60	9.87	9.66	24	Pass
HE40	SISO	1	51	6205	MCS0	Full	16.00	18.00	15.07	15.96	-5.10	-6.60	9.97	9.36	24	Pass
HE40	SISO	1	91	6405	MCS0	Full	16.50	18.00	15.42	16.96	-5.10	-6.60	10.32	10.36	24	Pass
HE80	SISO	1	7	5985	MCS0	Full	18.00	18.00	17.48	17.12	-5.10	-6.60	12.38	10.52	24	Pass
HE80	SISO	1	55	6225	MCS0	Full	18.00	18.00	16.83	16.71	-5.10	-6.60	11.73	10.11	24	Pass
HE80	SISO	1	87	6385	MCS0	Full	18.00	18.00	16.04	16.85	-5.10	-6.60	10.94	10.25	24	Pass

TEST RESULTS DATA																
Average Output Power																
Mode							Power Setting	Power Setting	Average Conducted Power with duty factor(dBm)		Gain(dBi)		EIRP Power (dBm)		EIRP Power Limit (dBm)	Pass/Fail
Band	SISO	N _{TX}	Channel	Freq (MHz)	Data Rate	RU Config			Ant 4	Ant 6	Ant 4	Ant 6	Ant 4	Ant 6		
11a	SISO	1	97	6435	6Mbps	-	14.00	15.50	12.42	13.69	-5.90	-6.80	6.52	6.89	24	Pass
11a	SISO	1	105	6475	6Mbps	-	14.50	15.50	12.70	13.90	-5.90	-6.80	6.80	7.10	24	Pass
11a	SISO	1	113	6515	6Mbps	-	14.00	15.00	12.36	13.69	-5.90	-6.80	6.46	6.89	24	Pass
HE20	SISO	1	97	6435	MCS0	Full	14.50	15.50	12.68	13.58	-5.90	-6.80	6.78	6.78	24	Pass
HE20	SISO	1	97	6435	MCS0	RU 26/0	5.50	6.00	4.74	5.46	-5.90	-6.80	-1.16	-1.34	24	Pass
HE20	SISO	1	97	6435	MCS0	RU 52/37	8.50	9.00	7.68	8.35	-5.90	-6.80	1.78	1.55	24	Pass
HE20	SISO	1	97	6435	MCS0	RU 106/53	11.50	12.00	10.62	11.27	-5.90	-6.80	4.72	4.47	24	Pass
HE20	SISO	1	105	6475	MCS0	Full	15.50	16.00	13.52	14.54	-5.90	-6.80	7.62	7.74	24	Pass
HE20	SISO	1	113	6515	MCS0	Full	14.50	15.50	12.63	13.91	-5.90	-6.80	6.73	7.11	24	Pass
HE40	SISO	1	99	6445	MCS0	Full	18.00	18.00	15.82	16.72	-5.90	-6.80	9.92	9.92	24	Pass
HE40	SISO	1	107	6485	MCS0	Full	18.00	18.00	15.80	16.86	-5.90	-6.80	9.90	10.06	24	Pass
HE40	SISO	1	115	6525	MCS0	Full	17.00	17.50	15.76	16.48	-5.90	-6.80	9.86	9.68	24	Pass
HE80	SISO	1	103	6465	MCS0	Full	18.00	18.00	15.87	16.62	-5.90	-6.80	9.97	9.82	24	Pass
HE80	SISO	1	119	6545	MCS0	Full	18.00	18.00	15.81	17.03	-5.90	-6.80	9.91	10.23	24	Pass

TEST RESULTS DATA Average Output Power																
Mode							Power Setting	Power Setting	Average Conducted Power with duty factor(dBm)		Gain(dBi)		EIRP Power (dBm)		EIRP Power Limit (dBm)	Pass/Fail
Band	SISO	N _{TX}	Channel	Freq (MHz)	Data Rate	RU Config			Ant 4	Ant 6	Ant 4	Ant 6	Ant 4	Ant 6		
11a	SISO	1	117	6535	6Mbps	-	14.00	15.00	12.48	13.82	-5.50	-6.70	6.98	7.12	24	Pass
11a	SISO	1	149	6695	6Mbps	-	14.00	15.00	12.41	13.70	-5.50	-6.70	6.91	7.00	24	Pass
11a	SISO	1	181	6855	6Mbps	-	14.00	14.50	11.85	12.92	-5.50	-6.70	6.35	6.22	24	Pass
11a	SISO	1	185	6875	6Mbps	-	14.50	14.50	12.31	13.35	-5.50	-6.70	6.81	6.65	24	Pass
HE20	SISO	1	117	6535	MCS0	Full	14.50	15.50	12.72	13.98	-5.50	-6.70	7.22	7.28	24	Pass
HE20	SISO	1	117	6535	MCS0	RU 26/0	5.00	6.00	4.18	5.91	-5.50	-6.70	-1.32	-0.79	24	Pass
HE20	SISO	1	117	6535	MCS0	RU 52/37	8.00	8.50	7.05	8.26	-5.50	-6.70	1.55	1.56	24	Pass
HE20	SISO	1	117	6535	MCS0	RU 106/53	11.00	11.50	10.04	11.16	-5.50	-6.70	4.54	4.46	24	Pass
HE20	SISO	1	149	6695	MCS0	Full	14.50	15.50	12.69	13.97	-5.50	-6.70	7.19	7.27	24	Pass
HE20	SISO	1	181	6855	MCS0	Full	14.50	15.00	12.06	13.23	-5.50	-6.70	6.56	6.53	24	Pass
HE20	SISO	1	185	6875	MCS0	Full	15.00	15.00	12.82	13.86	-5.50	-6.70	7.32	7.16	24	Pass
HE40	SISO	1	123	6565	MCS0	Full	17.00	17.50	15.42	16.22	-5.50	-6.70	9.92	9.52	24	Pass
HE40	SISO	1	147	6685	MCS0	Full	18.00	17.50	15.95	16.45	-5.50	-6.70	10.45	9.75	24	Pass
HE40	SISO	1	179	6845	MCS0	Full	18.00	17.50	15.74	16.16	-5.50	-6.70	10.24	9.46	24	Pass
HE40	SISO	1	187	6885	MCS0	Full	18.00	17.50	15.93	16.77	-5.50	-6.70	10.43	10.07	24	Pass
HE80	SISO	1	135	6625	MCS0	Full	18.00	18.00	15.96	17.29	-5.50	-6.70	10.46	10.59	24	Pass
HE80	SISO	1	151	6705	MCS0	Full	18.00	18.00	15.94	17.27	-5.50	-6.70	10.44	10.57	24	Pass
HE80	SISO	1	167	6785	MCS0	Full	18.00	18.00	15.64	17.07	-5.50	-6.70	10.14	10.37	24	Pass
HE80	SISO	1	183	6865	MCS0	Full	18.00	18.00	16.15	17.26	-5.50	-6.70	10.65	10.56	24	Pass

TEST RESULTS DATA																
Average Output Power																
Mode							Power Setting	Power Setting	Average Conducted Power with duty factor(dBm)		Gain(dBi)		EIRP Power (dBm)		EIRP Power Limit (dBm)	Pass/Fail
Band	SISO	N _{TX}	Channel	Freq (MHz)	Data Rate	RU Config			Ant 4	Ant 6	Ant 4	Ant 6	Ant 4	Ant 6		
11a	SISO	1	189	6895	6Mbps	-	15.00	14.50	12.89	13.67	-6.30	-7.30	6.59	6.37	24	Pass
11a	SISO	1	209	6995	6Mbps	-	15.00	13.50	12.85	13.92	-6.30	-7.30	6.55	6.62	24	Pass
11a	SISO	1	229	7095	6Mbps	-	15.00	13.50	13.80	15.02	-6.30	-7.30	7.50	7.72	24	Pass
-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
HE20	SISO	1	189	6895	MCS0	Full	15.00	15.00	12.76	14.17	-6.30	-7.30	6.46	6.87	24	Pass
HE20	SISO	1	209	6995	MCS0	Full	15.50	14.00	13.21	14.21	-6.30	-7.30	6.91	6.91	24	Pass
HE20	SISO	1	229	7095	MCS0	Full	15.50	14.00	14.04	15.44	-6.30	-7.30	7.74	8.14	24	Pass
HE20	SISO	1	229	7095	MCS0	RU 26/8	6.50	5.00	6.07	7.17	-6.30	-7.30	-0.23	-0.13	24	Pass
HE20	SISO	1	229	7095	MCS0	RU 52/40	9.50	8.00	8.85	10.09	-6.30	-7.30	2.55	2.79	24	Pass
HE20	SISO	1	229	7095	MCS0	RU 106/54	12.50	11.00	11.55	12.86	-6.30	-7.30	5.25	5.56	24	Pass
-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	--
HE40	SISO	1	195	6925	MCS0	Full	18.00	17.50	15.99	17.55	-6.30	-7.30	9.69	10.25	24	Pass
HE40	SISO	1	211	7005	MCS0	Full	18.00	17.50	16.18	17.87	-6.30	-7.30	9.88	10.57	24	Pass
HE40	SISO	1	227	7085	MCS0	Full	17.50	18.00	16.23	19.33	-6.30	-7.30	9.93	12.03	24	Pass
HE80	SISO	1	199	6945	MCS0	Full	18.00	18.00	16.32	18.44	-6.30	-7.30	10.02	11.14	24	Pass
HE80	SISO	1	215	7025	MCS0	Full	18.00	18.00	16.85	19.05	-6.30	-7.30	10.55	11.75	24	Pass



Emission Bandwidth

Test Result

TestMode	Antenna	Freq(MHz)	26dB EBW [MHz]	FL[MHz]	FH[MHz]	Limit[MHz]	Verdict
11A	Ant4	5955	19.9	5944.81	5964.71	≤320	PASS
		6195	20.1	6184.67	6204.76	≤320	PASS
		6415	20.19	6404.67	6424.86	≤320	PASS
		6435	20.05	6424.76	6444.81	≤320	PASS
		6475	19.95	6464.76	6484.71	≤320	PASS
		6515	20.62	6504.76	6525.38	≤320	PASS
		6535	20.14	6524.57	6544.71	≤320	PASS
		6695	20.1	6684.62	6704.71	≤320	PASS
		6855	19.95	6844.67	6864.62	≤320	PASS
		6875	20.48	6864.71	6885.19	≤320	PASS
		6895	20.52	6884.95	6905.48	≤320	PASS
		6995	20.05	6984.57	7004.62	≤320	PASS
		7095	20.38	7084.48	7104.86	≤320	PASS
	Ant6	5955	20.14	5944.67	5964.81	≤320	PASS
		6195	19.95	6184.81	6204.76	≤320	PASS
		6415	19.95	6404.67	6424.62	≤320	PASS
		6435	20.14	6424.71	6444.86	≤320	PASS
		6475	20.24	6464.62	6484.86	≤320	PASS
		6515	19.86	6504.71	6524.57	≤320	PASS
		6535	20	6524.71	6544.71	≤320	PASS
		6695	19.95	6684.71	6704.67	≤320	PASS
		6855	19.71	6844.9	6864.62	≤320	PASS
		6875	19.9	6864.76	6884.67	≤320	PASS
		6895	20.1	6884.81	6904.9	≤320	PASS
		6995	19.62	6984.76	7004.38	≤320	PASS
		7095	20.05	7084.71	7104.76	≤320	PASS
11AX20SISO	Ant4	5955	21.52	5944.33	5965.86	≤320	PASS
		6195	21.1	6184.43	6205.52	≤320	PASS
		6415	21.29	6404.33	6425.62	≤320	PASS
		6435	21.29	6424.29	6445.57	≤320	PASS
		6475	21.43	6464.29	6485.71	≤320	PASS
		6515	21.24	6504.38	6525.62	≤320	PASS
		6535	21.29	6524.38	6545.67	≤320	PASS




		6695	21.38	6684.33	6705.71	≤320	PASS
		6855	21	6844.48	6865.48	≤320	PASS
		6875	21.52	6864.19	6885.71	≤320	PASS
		6895	21.38	6884.29	6905.67	≤320	PASS
		6995	21.29	6984.14	7005.43	≤320	PASS
		7095	27.71	7080.52	7108.24	≤320	PASS
	Ant6	5955	21.29	5944.38	5965.67	≤320	PASS
		6195	21.19	6184.43	6205.62	≤320	PASS
		6415	21.14	6404.38	6425.52	≤320	PASS
		6435	21	6424.52	6445.52	≤320	PASS
		6475	21.14	6464.43	6485.57	≤320	PASS
		6515	21.1	6504.48	6525.57	≤320	PASS
		6535	21.33	6524.33	6545.67	≤320	PASS
		6695	21.33	6684.33	6705.67	≤320	PASS
		6855	21.33	6844.24	6865.57	≤320	PASS
		6875	21.14	6864.38	6885.52	≤320	PASS
		6895	21.14	6884.48	6905.62	≤320	PASS
		6995	21.19	6984.38	7005.57	≤320	PASS
		7095	21.62	7084.24	7105.86	≤320	PASS
		11AX40SISO	Ant4	5965	40.29	5944.81	5985.1
6205	40.19			6184.81	6225	≤320	PASS
6405	40.19			6384.9	6425.1	≤320	PASS
6445	40.19			6424.81	6465	≤320	PASS
6485	40.29			6464.71	6505	≤320	PASS
6525	40.67			6504.52	6545.19	≤320	PASS
6565	40.67			6544.62	6585.29	≤320	PASS
6685	40.57			6664.81	6705.38	≤320	PASS
6845	40.38			6824.62	6865	≤320	PASS
6885	46.95			6858.24	6905.19	≤320	PASS
6925	49.43			6895.67	6945.1	≤320	PASS
7005	58.76			6967.38	7026.14	≤320	PASS
7085	85.81			7041.67	7127.48	≤320	PASS
Ant6	5965		40.1	5944.9	5985	≤320	PASS
	6205		40.38	6184.9	6225.29	≤320	PASS
	6405		40.19	6384.9	6425.1	≤320	PASS
	6445		40.19	6424.81	6465	≤320	PASS
	6485		40.19	6465	6505.19	≤320	PASS
	6525		40.48	6504.81	6545.29	≤320	PASS
	6565		40.19	6544.71	6584.9	≤320	PASS
6685	40.38	6664.81	6705.19	≤320	PASS		



11AX80SISO		6845	40.38	6824.81	6865.19	≤320	PASS
		6885	40.48	6864.71	6905.19	≤320	PASS
		6925	48.57	6896.43	6945	≤320	PASS
		7005	61.24	6967.86	7029.1	≤320	PASS
		7085	83.33	7041.95	7125.29	≤320	PASS
	Ant4	5985	81.9	5943.86	6025.76	≤320	PASS
		6225	81.14	6184.24	6265.38	≤320	PASS
		6385	81.52	6344.43	6425.95	≤320	PASS
		6465	81.71	6424.05	6505.76	≤320	PASS
		6545	82.1	6504.05	6586.14	≤320	PASS
		6625	82.29	6584.05	6666.33	≤320	PASS
		6705	81.52	6664.05	6745.57	≤320	PASS
		6785	81.9	6744.05	6825.95	≤320	PASS
		6865	81.33	6824.24	6905.57	≤320	PASS
		6945	81.9	6904.24	6986.14	≤320	PASS
		7025	139.62	6944.24	7083.86	≤320	PASS
	Ant6	5985	81.71	5943.86	6025.57	≤320	PASS
		6225	81.14	6184.43	6265.57	≤320	PASS
		6385	82.1	6344.24	6426.33	≤320	PASS
		6465	82.1	6424.05	6506.14	≤320	PASS
		6545	81.52	6504.05	6585.57	≤320	PASS
		6625	82.1	6584.24	6666.33	≤320	PASS
		6705	81.9	6664.24	6746.14	≤320	PASS
		6785	81.52	6743.86	6825.38	≤320	PASS
		6865	82.1	6824.05	6906.14	≤320	PASS
		6945	84.95	6901.95	6986.9	≤320	PASS
		7025	126.86	6947.86	7074.71	≤320	PASS




Test Graphs






11A_Ant4_6415




11A_Ant4_6435






11A_Ant4_6475




11A_Ant4_6515






11A_Ant4_6535



Date: 28.NOV.2025 05:52:21


11A_Ant4_6695



Date: 28.NOV.2025 05:53:49




11A_Ant4_6855



Date: 28.NOV.2025 05:55:16


11A_Ant4_6875




Date: 28.NOV.2025 05:56:45




11A_Ant4_6895




11A_Ant4_6995








11AX20SISO_Ant4_5955




11AX20SISO_Ant4_6195






11AX20SiSO_Ant4_6415




11AX20SiSO_Ant4_6435






11AX20SISO_Ant4_6475



Date: 28.NOV.2025 06:16:04


11AX20SISO_Ant4_6515




Date: 28.NOV.2025 06:17:32



11AX20SiSO_Ant4_6535




11AX20SiSO_Ant4_6695






11AX20SISO_Ant4_6855




11AX20SISO_Ant4_6875







11AX20SISO_Ant4_6895




11AX20SISO_Ant4_6995








11AX40SISO_Ant4_5965



Date: 28.NOV.2025 06:34:47


11AX40SISO_Ant4_6205




Date: 28.NOV.2025 06:39:51



11AX40SiSO_Ant4_6405




11AX40SiSO_Ant4_6445






11AX40SISO_Ant4_6485



Date: 28.NOV.2025 06:51:16


11AX40SISO_Ant4_6525



Date: 28.NOV.2025 06:52:55




11AX40SISO_Ant4_6565



Date: 28.NOV.2025 06:54:36


11AX40SISO_Ant4_6685




Date: 28.NOV.2025 06:56:16



11AX40SiSO_Ant4_6845




11AX40SiSO_Ant4_6885






11AX40SISO_Ant4_6925




11AX40SISO_Ant4_7005






11AX40SISO_Ant4_7085



Date: 28.NOV.2025 07:08:27


11AX80SISO_Ant4_5985




Date: 28.NOV.2025 07:10:19



11AX80SISO_Ant4_6225




11AX80SISO_Ant4_6385






11AX80SISO_Ant4_6465




11AX80SISO_Ant4_6545






11AX80SISO_Ant4_6625




11AX80SISO_Ant4_6705






11AX80SISO_Ant4_6785




11AX80SISO_Ant4_6865






11AX80SISO_Ant4_6945



Date: 28.NOV.2025 07:28:42


11AX80SISO_Ant4_7025



Date: 28.NOV.2025 07:31:39




11A_Ant6_5955



Date: 28.NOV.2025 21:48:41


11A_Ant6_6195



Date: 28.NOV.2025 21:50:14




11A_Ant6_6415



Date: 28.NOV.2025 21:51:38


11A_Ant6_6435



Date: 28.NOV.2025 22:04:11




11A_Ant6_6475



Date: 28.NOV.2025 22:05:39

11A_Ant6_6515



Date: 28.NOV.2025 22:07:05