

DFS Test Report

Report No.: RF130710E11H-3

FCC ID: MCLT77H462

Test Model: T77H462

Received Date: Oct. 14, 2015

Test Date: Dec. 04, 2015

Issued Date: Dec. 14, 2015

Applicant: Hon Hai PRECISION IND.CO.,LTD

Address: 5F-1,5 Hsin-An Road Hsinchu, Science-Based Industrial Park Taiwan,
R.O.C.

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch
Hsin Chu Laboratory

Lab Address: E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,
Taiwan R.O.C.

Test Location (1): E-2, No.1, Li Hsin 1st Road, Hsinchu Science Park, Hsinchu City 300,
Taiwan R.O.C.

Test Location (2): No. 49, Ln. 206, Wende Rd., Shangshan Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by TAF or any government agencies.

Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 EUT Information	5
2.1 Operating Frequency Bands and Mode of EUT	5
2.2 EUT Software and Firmware Version	5
2.3 Description of Available Antennas to the EUT	6
2.4 EUT Maximum Conducted Power	8
2.5 EUT Maximum EIRP Power	9
2.6 Transmit Power Control (TPC)	10
2.7 Statement of Manufacturer	10
3. U-NII DFS Rule Requirements	11
3.1 Working Modes and Required Test Items	11
3.2 Test Limits and Radar Signal Parameters	12
4. Test & Support Equipment List	15
4.1 Test Instruments	15
4.2 Description of Support Units	15
5. Test Procedure	16
5.1 DFS Measurement System	16
5.2 Calibration of DFS Detection Threshold Level	17
5.3 Deviation from Test Standard	18
5.4 Conducted Test Setup Configuration	18
5.4.1 Client without Radar Detection Mode	18
6. Test Results	19
6.1 Summary of Test Results	19
6.2 Test Results	20
6.2.1 Test Mode: Device Operating In Client without Radar Detection Mode	20
6.2.2 Channel Closing Transmission and Channel Move Time	21
6.2.3 Non-Occupancy Period	22
6.2.4 Non-Associated Test	24
6.2.5 Non- Co-Channel Test	24
APPENDIX-A	25
Appendix B – Information on the Testing Laboratories	26



A D T

Release Control Record

Issue No.	Description	Date Issued
RF130710E11H-3	Original release.	Dec. 14, 2015

1 Certificate of Conformity

Product: 802.11abgn+BT4.0 module

Brand: FOXCONN

Test Model: T77H462

Sample Status: ENGINEERING SAMPLE

Applicant: Hon Hai PRECISION IND.CO.,LTD


Test Date: Dec. 04, 2015

Standards: FCC Part 15, Subpart E (Section 15.407)

KDB 905462 D02 UNII DFS Compliance Procedures New Rules v01r02

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by :



Date:

Dec. 14, 2015

Midoli Peng / Specialist

Approved by :



Date:

Dec. 14, 2015

May Chen / Manager

2 EUT Information

2.1 Operating Frequency Bands and Mode of EUT

Table 1: Operating Frequency Bands and Mode of EUT

Operational Mode	Operating Frequency Range	
	5250~5350MHz	5470~5725MHz
Client without radar detection and ad hoc function	✓	✓

2.2 EUT Software and Firmware Version

Table 2: The EUT Software/Firmware Version

No.	Product	Model No.	Software/Firmware Version
1	802.11abgn+BT4.0 module	T77H462	Broadcom 2013/5/6 6.10.197.39

2.3 Description of Available Antennas to the EUT

Table 3: Antenna List

Antenna Set 1							
Transmitter Circuit	Brand	Model	Antenna Type	Antenna Gain (dBi)	Frequency range (MHz to MHz)		Connector Type
Chain (0)	Foxconn	T77H462	PIFA	-0.6	2400~2500		MHF4
				-2.3	5150~5850		
Chain (1)	Foxconn	T77H462	PIFA	-0.6	2400~2500		MHF4
				-2.3	5150~5850		
Antenna Set 2							
Transmitter Circuit	Brand	Model	Antenna Type	Antenna Gain (dBi) <Including cable loss>	Frequency range (MHz to MHz)	Cable Length (mm)	Connector Type
Chain (0) & Chain (1)	Wistron Neweb Corporation	DC33001GL00	PIFA	1.32	2400~2500	55	MHF4 (i-pex)
				1.62	5150-5350		
				-1.84	5470-5725		
				-2.12	5725-5850		
Antenna Set 3							
Transmitter Circuit	Brand	Model	Antenna Type	Antenna Gain (dBi) <Including cable loss>	Frequency range (MHz to MHz)	Cable Length (mm)	Connector Type
Chain (0) & Chain (1)	Wistron Neweb Corporation	DC33001GL10	PIFA	0.48	2400~2500	239	MHF4 (i-pex)
				-2.19	5150-5350		
				-2.70	5470-5725		
				-1.77	5725-5850		
Antenna Set 4							
Transmitter Circuit	Antenna P/N	Manufacturer	Antenna Type	Cable Assembly P/N and Information	Frequency range (MHz to MHz)	Antenna Gain (dBi) <Including cable loss>	Antenna Gain (dBi) <Excluding cable loss>
Chain (0)	Main Antenna (P/N: LA22RF754-1H)	LUXSHARE-ICT Co., Ltd.	PIFA	50 ohm coaxial cable Cable length:750 mm Diameter: Lowloss 1.13mm	2400-2500	0.43	2.68
					5150-5350	-8.70	-5.15
					5470-5725	-8.82	-5.15
					5725-5850	-8.98	-5.25
Chain (1)	Auxiliary Antenna (P/N: LA22RF755-1H)	LUXSHARE-ICT Co., Ltd.	PIFA	50 ohm coaxial cable Cable length: 750 mm Diameter: Lowloss1.13 mm	2400-2500	0.43	2.68
					5150-5350	-8.70	-5.15
					5470-5725	-8.82	-5.15
					5725-5850	-8.98	-5.25



Antenna Set 5									
Transmitter Circuit	Antenna P/N	Manufacturer	Antenna Type	Cable Assembly P/N and Information	Frequency range (MHz to MHz)	Antenna Gain (dBi) <Including cable loss>	Antenna Gain (dBi) <Excluding cable loss>	Cable loss max.(dB)	VSWR
Chain (0)	Main Antenna (P/N: LA22RF764-1H)	LUXSHARE -ICT Co., Ltd.	PIFA	50 ohm coaxial cable Cable length:220 mm Diameter:1.13mm	2400-2500	2.34	3.0	0.66	2.5 max
					5150-5350	0.67	1.71	1.04	2.5 max
					5470-5725	0.15	1.22	1.07	2.5 max
					5725-5850	-0.54	0.55	1.09	2.5 max
Chain (1)	Auxiliary Antenna (P/N: LA22RF765-1H)	LUXSHARE -ICT Co., Ltd.	PIFA	50 ohm coaxial cable Cable length: 250 mm Diameter:1.13 mm	2400-2500	0.83	1.58	0.75	2.5 max
					5150-5350	2.05	3.23	1.18	2.5 max
					5470-5725	0.61	1.84	1.23	2.5 max
					5725-5850	0.61	1.85	1.24	2.5 max
Antenna Set 6									
Transmitter Circuit	Antenna P/N	Manufacturer	Antenna Type	Cable Assembly P/N and Information	Frequency range (MHz to MHz)	Antenna Gain (dBi) <Including cable loss>			
Chain (0)	Main Antenna (P/N: 1415-04LN000)	WNC	PIFA	Black 1.13(dia) x 50mm	2400-2500	0.72			
					5150-5350	1.75			
					5470-5725	1.55			
					5725-5850	0.41			
Chain (1)	Auxiliary Antenna (P/N: 1415-04LP000)	WNC	PIFA	White 1.13(dia) x 190mm	2400-2500	-0.41			
					5150-5350	-1.00			
					5470-5725	0.77			
					5725-5850	0.04			
Antenna Set 7									
Transmitter Circuit	Antenna P/N	Manufacturer	Antenna Type	Cable Assembly P/N and Information	Frequency range (MHz to MHz)	Antenna Gain (dBi) <Including cable loss>			
Chain (0)	Main Antenna (P/N: 1415-04LR000)	WNC	PIFA	Black 1.13(dia) x 120mm	2400-2500	0.67			
					5150-5350	0.6			
					5470-5725	-0.75			
					5725-5850	1.25			
Chain (1)	Auxiliary Antenna (P/N: 1415-04LQ000)	WNC	PIFA	White 1.13(dia) x 143mm	2400-2500	-1.59			
					5150-5350	1.12			
					5470-5725	0.82			
					5725-5850	0.33			

2.4 EUT Maximum Conducted Power

Table 4: The Measured Conducted Output Power

802.11a

FREQUENCY BAND (MHz)	MAX. POWER	
	OUTPUT POWER(dBm)	OUTPUT POWER(mW)
5250~5350	18.65	73.282
5470~5725	15.71	37.239

802.11n (HT20)

FREQUENCY BAND (MHz)	MAX. POWER	
	OUTPUT POWER(dBm)	OUTPUT POWER(mW)
5250~5350	19.89	97.486
5470~5725	19.19	83.079

802.11n (HT40)

FREQUENCY BAND (MHz)	MAX. POWER	
	OUTPUT POWER(dBm)	OUTPUT POWER(mW)
5250~5350	18.60	72.483
5470~5725	18.96	78.62

2.5 EUT Maximum EIRP Power

Table 5: The EIRP Output Power List

802.11a

FREQUENCY BAND (MHz)	MAX. POWER	
	OUTPUT POWER(dBm)	OUTPUT POWER(mW)
5250~5350	20.70	117.489
5470~5725	17.26	53.211

802.11n (HT20)

FREQUENCY BAND (MHz)	MAX. POWER	
	OUTPUT POWER(dBm)	OUTPUT POWER(mW)
5250~5350	21.94	156.294
5470~5725	20.74	118.711

802.11n (HT40)

FREQUENCY BAND (MHz)	MAX. POWER	
	OUTPUT POWER(dBm)	OUTPUT POWER(mW)
5250~5350	20.65	116.208
5470~5725	20.51	112.340

2.6 Transmit Power Control (TPC)

U-NII devices operating in the 5.25-5.35 GHz band and the 5.47-5.725 GHz band shall employ a TPC mechanism. The U-NII device is required to have the capability to operate at least 6 dB below the mean EIRP value of 30 dBm. A TPC mechanism is not required for systems with an e.i.r.p. of less than 500 mW.

Maximum EIRP of this device is 156.294mW which less than 500mW, therefore it's not require TPC function.

2.7 Statement of Manufacturer

Manufacturer statement confirming that information regarding the parameters of the detected Radar Waveforms is not available to the end user. **And the device doesn't have Ad Hoc mode on DFS frequency band.**

3. U-NII DFS Rule Requirements

3.1 Working Modes and Required Test Items

The manufacturer shall state whether the UUT is capable of operating as a Master and/or a Client. If the UUT is capable of operating in more than one operating mode then each operating mode shall be tested separately. See tables 6 and 7 for the applicability of DFS requirements for each of the operational modes.

Table 6: Applicability of DFS Requirements Prior To Use a Channel

Requirement	Operational Mode		
	Master	Client without radar detection	Client with radar detection
Non-Occupancy Period	✓	Not required	✓
DFS Detection Threshold	✓	Not required	✓
Channel Availability Check Time	✓	Not required	Not required
U-NII Detection Bandwidth	✓	Not required	✓

Table 7: Applicability of DFS Requirements During Normal Operation.

Requirement	Operational Mode	
	Master or Client with radar detection	Client without radar detection
DFS Detection Threshold	✓	Not required
Channel Closing Transmission Time	✓	✓
Channel Move Time	✓	✓
U-NII Detection Bandwidth	✓	Not required

Additional requirements for devices with multiple bandwidth modes	Master or Client with radar detection	Client without radar detection
U-NII Detection Bandwidth and Statistical Performance Check	All BW modes must be tested	Not required
Channel Move Time and Channel Closing Transmission Time	Test using widest BW mode available	Test using the widest BW mode available for the link
All other tests	Any single BW mode	Not required

Note: Frequencies selected for statistical performance check (Section 7.8.4) should include several frequencies within the radar detection bandwidth and frequencies near the edge of the radar detection bandwidth. For 802.11 devices it is suggested to select frequencies in each of the bonded 20 MHz channels and the channel center frequency.

3.2 Test Limits and Radar Signal Parameters

Detection Threshold Values

Table 8: DFS Detection Thresholds for Master Devices and Client Devices With Radar Detection

Maximum Transmit Power	Value (See Notes 1, 2, and 3)
EIRP $\geq$ 200 milliwatt	-64 dBm
EIRP < 200 milliwatt and power spectral density < 10 dBm/MHz	-62 dBm
EIRP < 200 milliwatt that do not meet the power spectral density requirement	-64 dBm

Note 1: This is the level at the input of the receiver assuming a 0 dBi receive antenna.

Note 2: Throughout these test procedures an additional 1 dB has been added to the amplitude of the test transmission waveforms to account for variations in measurement equipment. This will ensure that the test signal is at or above the detection threshold level to trigger a DFS response.

Note3: EIRP is based on the highest antenna gain. For MIMO devices refer to KDB Publication 662911 D01.

Table 9: DFS Response Requirement Values

Parameter	Value
Non-occupancy period	Minimum 30 minutes
Channel Availability Check Time	60 seconds
Channel Move Time	10 seconds See Note 1.
Channel Closing Transmission Time	200 milliseconds + an aggregate of 60 milliseconds over remaining 10 second period. See Notes 1 and 2.
U-NII Detection Bandwidth	Minimum 100% of the U-NII 99% transmission power bandwidth. See Note 3

Note 1: Channel Move Time and the Channel Closing Transmission Time should be performed with Radar Type 0. The measurement timing begins at the end of the Radar Type 0 burst.

Note 2: The Channel Closing Transmission Time is comprised of 200 milliseconds starting at the beginning of the Channel Move Time plus any additional intermittent control signals required to facilitate a Channel move (an aggregate of 60 milliseconds) during the remainder of the 10 second period. The aggregate duration of control signals will not count quiet periods in between transmissions.

Note 3: During the U-NII Detection Bandwidth detection test, radar type 0 should be used. For each frequency step the minimum percentage of detection is 90 percent. Measurements are performed with no data traffic.

Parameters of DFS Test Signals

Step intervals of 0.1 microsecond for Pulse Width, 1 microsecond for PRI, 1 MHz for chirp width and 1 for the number of pulses will be utilized for the random determination of specific test waveforms.

Table 10: Short Pulse Radar Test Waveforms

Radar Type	Pulse Width (μsec)	PRI (μsec)	Number of Pulses	Minimum Percentage of Successful Detection	Minimum Number of Trials
0	1	1428	18	See Note 1	See Note 1
1	1	Test A: 15 unique PRI values randomly selected from the list of 23 PRI values in Table 5a ----- Test B: 15 unique PRI values randomly selected within the range of 518-3066 μsec, with a minimum increment of 1 μsec, excluding PRI values selected in Test A	$\text{Roundup} \left\{ \left\{ \frac{1}{360} \right\} \cdot \left\{ \frac{19 \cdot 10^6}{\text{PRI}_{\mu\text{sec}}} \right\} \right\}$	60%	30
2	1-5	150-230	23-29	60%	30
3	6-10	200-500	16-18	60%	30
4	11-20	200-500	12-16	60%	30
Aggregate (Radar Types 1-4)				80%	120
Note 1: Short Pulse Radar Type 0 should be used for the detection bandwidth test, channel move time, and channel closing time tests.					

Table 11: Long Pulse Radar Test Waveform

Radar Type	Pulse Width (μsec)	Chirp Width (MHz)	PRI (μsec)	Number Of Pulses Per Burst	Number Of Bursts	Minimum Percentage Of Successful Detection	Minimum Number Of Trials
5	50-100	5-20	1000-2000	1-3	8-20	80%	30

Table 12: Frequency Hopping Radar Test Waveform

Radar Type	Pulse Width (μsec)	PRI (μsec)	Pulses per Hop	Hopping Rate (kHz)	Hopping Sequence Length (msec)	Minimum Percentage Of Successful Detection	Minimum Number Of Trials
6	1	333	9	0.333	300	70%	30

4. Test & Support Equipment List

4.1 Test Instruments

Table 13: Test Instruments List

Description & Manufacturer	Model No.	Brand	Date Of Calibration	Due Date Of Calibration
Spectrum Analyzer R&S	FSP40	100036	Jan. 22, 2015	Jan. 21, 2016
Vector Signal Generator Agilent	N5182B	MY53051263	Aug. 10, 2015	Aug. 09, 2016

4.2 Description of Support Units

Table 14: Support Unit Information.

No.	Product	Brand	Model No.	Fcc Id	SPEC.
1	11n Access-Point	MOTOROLA	AP-7131N	UZ7AP7131N	The maximum EIRP is 13.6 dBm, Antenna Gain is -3.38dBi

NOTE: This device was functioned as a ☒ Master ☐ Slave device during the DFS test.

Table 15: Software/Firmware Information.


No.	Product	Model No.	Software/Firmware Version
1.	11n Access-Point	AP-7131N	4.1.5.0-004R

5. Test Procedure

5.1 DFS Measurement System

A complete DFS Measurement System consists of Radar signal generate system to generating the radar waveforms in Table 10, 11 and 12. The traffic monitoring system is specified to the type of unit under test (UUT).

Conducted Setup Configuration of DFS Measurement System



Channel Loading

System testing will be performed with channel-loading using means appropriate to the data types that are used by the unlicensed device. The following requirements apply:


a)	The data file must be of a type that is typical for the device (i.e., MPEG-2, MPEG-4, WAV, MP3, MP4, AVI, etc.) and must generally be transmitting in a streaming mode.	
b)	Software to ping the client is permitted to simulate data transfer but must have random ping intervals.	
c)	Timing plots are required with calculations demonstrating a minimum channel loading of approximately 17% or greater.	✓
d)	Unicast or Multicast protocols are preferable but other protocols may be used. The appropriate protocol used must be described in the test procedures.	

5.3 Deviation from Test Standard

No deviation.

5.4 Conducted Test Setup Configuration

5.4.1 Client without Radar Detection Mode



The UUT is a U-NII Device operating in Client mode without radar detection. The radar test signals are injected into the Master Device.

6. Test Results

6.1 Summary of Test Results

CLAUSE	TEST PARAMETER	REMARKS	PASS/FAIL
15.407	DFS Detection Threshold	Not Applicable	NA
15.407	Channel Availability Check Time	Not Applicable	NA
15.407	Channel Move Time	Applicable	Pass
15.407	Channel Closing Transmission Time	Applicable	Pass
15.407	Non- Occupancy Period	Applicable	Pass
15.407	U-NII Detection Bandwidth	Not Applicable	NA
15.407	Non-associated test	Applicable	Pass
15.407	Non-Co-Channel test	Applicable	Pass

6.2 Test Results

6.2.1 Test Mode: Device Operating In Client without Radar Detection Mode.

The radar test signals are injected into the Master Device.


This test was investigated for different bandwidth (20MHz - 40MHz).

The following plots was done on 40MHz as a representative

DFS Detection Threshold

The Required detection threshold is -64.38dBm ($= -62 + 1 - 3.38$).


The conducted radar burst level is lower than -64.38dBm.



Radar Signal 0


6.2.2 Channel Closing Transmission and Channel Move Time

Channel Closing Transmission Time & Channel Move Time @ CH102 - 5510MHz



NOTE: T1 denotes the start of Channel Move Time upon the end of the last Radar burst. T2 denotes the data transmission time of 200ms from T1. T4 denotes the 10 second from T1 to observe the aggregate duration of transmissions.

Channel Closing Transmission Time & Channel Move Time @ CH102 - 5510MHz




NOTE: An expanded plot for the device vacates the channel in the required 500ms.

6.2.3 Non-Occupancy Period


ASSOCIATED TEST

1) Test results demonstrating an associated client link is established with the master on a test frequency.



EUT (Client) links with master on 5510MHz

2) The client and DFS-certified master device are associated, and system testing will be performed with channel-loading for a non-occupancy period test.



Client performed with channel-loading via master.

The screenshot displays the Pulse Editor and Spectrum Analyzer in Keysight ADS. The Pulse Editor shows a pulse with a delay of 0.000 ns, rise time of 0.000 ns, fall time of 0.000 ns, and a pulse width of 1428.000 ns. The Spectrum Analyzer shows a single sharp peak at 5.5 GHz with a power level of approximately -1.0 dBm. The plot is labeled 'Pulse' and 'Spectrum'.


The graph displays the SNR over a 32-hour period. The signal starts at approximately -38 dB at 00:00. At 01:00, there is a sharp drop in SNR, indicated by two red arrows. One arrow points to the drop and is labeled "Injected into Radar". The other arrow points to the drop and is labeled "Traffic Signal". After the drop, the signal remains relatively stable, fluctuating around -72 dB for the remainder of the 32-hour period.

6.2.4 Non-Associated Test

Master was off.

During the 30 minutes observation time, The UUT did not make any transmissions in the DFS band after UUT power up.

Non - Associated Test @ CH102 - 5510MHz




6.2.5 Non- Co-Channel Test

The UUT was investigated after radar was detected the channel and made sure no co-channel operation with radars.

APPENDIX-A

NON BEACON ON DFS BAND

- 1) Test results demonstrating no any beacon on DFS band after power up.
- 2) Observation time is 10min after power up.



Appendix B – Information on the Testing Laboratories

We, Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch, were founded in 1988 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

If you have any comments, please feel free to contact us at the following:

Linko EMC/RF Lab:

Tel: 886-2-26052180

Fax: 886-2-26051924

Hsin Chu EMC/RF/Telecom Lab:

Tel: 886-3-6668565

Fax: 886-3-6668323

Hwa Ya EMC/RF/Safety Lab:

Tel: 886-3-3183232

Fax: 886-3-3270892

Email: service.adt@tw.bureauveritas.com

Web Site: www.bureauveritas-adt.com

The address and road map of all our labs can be found in our web site also.

--- END ---