


LTE Band 38


LTE Band 38, Channel Bandwidth 5MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
37775	2572.5	3.71	6.06	5.99
38000	2595.0	4.07	6.48	6.31
38225	2617.5	8.35	5.28	5.89
LTE Band 38, Channel Bandwidth 10MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
37800	2575.0	3.66	6.16	5.84
38000	2595.0	4.07	5.92	5.87
38200	2615.0	3.75	5.66	5.47
LTE Band 38, Channel Bandwidth 15MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
37825	2577.5	4.27	5.84	5.64
38000	2595.0	4.98	6.37	5.49
38175	2612.5	4.58	5.46	4.97
LTE Band 38, Channel Bandwidth 20MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
37850	2580.0	4.61	5.98	5.75
38000	2595.0	4.77	6.21	5.76
38150	2610.0	4.55	5.74	5.40

Spectrum Plot of Worst Value


5MHz / 16QAM




10MHz / 16QAM



15MHz / 16QAM



20MHz / 16QAM



LTE Band 41

LTE Band 41, Channel Bandwidth 5MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
40065	2537.5	3.98	6.12	6.48
40445	2575.5	4.09	5.69	6.37
40825	2613.5	3.99	5.19	6.15
41215	2652.5	3.61	4.60	6.26
LTE Band 41, Channel Bandwidth 10MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
40090	2540.0	4.05	6.34	6.03
40450	2576.0	4.13	5.90	6.30
40820	2613.0	4.01	5.12	6.21
41190	2650.0	3.22	5.71	4.52
LTE Band 41, Channel Bandwidth 15MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
40115	2542.5	4.61	5.90	6.35
40465	2577.5	4.31	5.70	6.36
40815	2612.5	3.81	4.90	6.49
41165	2647.5	3.75	5.24	4.87
LTE Band 41, Channel Bandwidth 20MHz				
Channel	Frequency (MHz)	Peak To Average Ratio (dB)		
		QPSK	16QAM	64QAM
40140	2545.0	4.47	5.79	5.80
40470	2578.0	4.00	6.09	6.24
40810	2612.0	3.92	4.97	6.10
41140	2645.0	4.09	5.22	5.05

Spectrum Plot of Worst Value


5MHz / 64QAM



10MHz / 16QAM



15MHz / 64QAM



20MHz / 64QAM



4.7 Conducted Spurious Emissions

4.7.1 Limits of Conducted Spurious Emissions Measurement


For WCDMA Band 4, LTE Band 4

In the FCC 27.53(m)(4), On any frequency outside a licensee's frequency block, The power of any emission shall be attenuated below the transmitter power (P) by at least $43 + 10 \log (P)$ dB. The emission limit equal to -13dBm .

For LTE Band 7, 38, 41

In the FCC 27.53(m)(4), On any frequency outside a licensee's frequency block, The power of any emission shall be attenuated below the transmitter power (P) by at least $55 + 10 \log (P)$ dB. The emission limit equal to -25dBm .

4.7.2 Test Setup



4.7.3 Test Procedure

- All measurements were done at 3 channels: low, middle and high operational frequency range.
- When the spectrum scanned from 9kHz to 26.5GHz or 27GHz, it shall be connected to the attenuator with the carried frequency.


4.7.4 Test Results

WCDMA Band 4


WCDMA

Channel 1312 (1712.4MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




WCDMA

Channel 1413 (1732.6MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




WCDMA

Channel 1513 (1752.6MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




HSDPA

Channel 1312 (1712.4MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




HSDPA

Channel 1413 (1732.6MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




HSDPA

Channel 1513 (1752.6MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




HSUPA

Channel 1312 (1712.4MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




HSUPA

Channel 1413 (1732.6MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz




Frequency Range : 10GHz~26.5GHz




HSUPA

Channel 1513 (1752.6MHz)


Frequency Range : 9kHz~3GHz



Frequency Range : 3GHz~10GHz



Frequency Range : 10GHz~26.5GHz




LTE Band 4


Channel Bandwidth: 1.4MHz

Channel 19957 (1710.7MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 1.4MHz

Channel 20175 (1732.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 1.4MHz

Channel 20393 (1754.3MHz)



Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 3MHz

Channel 19965 (1711.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 3MHz

Channel 20175 (1732.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 3MHz

Channel 20385 (1753.5MHz)



Frequency Range : 9kHz~1GHz




Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz



*The 9kHz signal over the limit is from Spectrum.




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 5MHz

Channel 20175 (1732.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 5MHz

Channel 20375 (1752.5MHz)



Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 10MHz

Channel 20000 (1715.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 10MHz

Channel 20175 (1732.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 10MHz

Channel 20350 (1750.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 15MHz

Channel 20025 (1717.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 15MHz

Channel 20175 (1732.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 15MHz

Channel 20325 (1747.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 20MHz

Channel 20050 (1720.0MHz)



Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 20MHz

Channel 20175 (1732.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Bandwidth: 20MHz

Channel 20300 (1745.0MHz)



Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~10GHz



Frequency Range : 10GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.

LTE Band 7


Channel Band width: 5MHz

Channel 20775(2502.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 5MHz

Channel 21100(2535MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 5MHz

Channel 21425(2567.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 10MHz

Channel 20800(2505MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 10MHz

Channel 21100(2535MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 10MHz

Channel 21400(2565MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 15MHz

Channel 20825(2507.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 15MHz

Channel 21100(2535MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 15MHz

Channel 21375(2562.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 20MHz

Channel 20850(2510MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 20MHz

Channel 21100(2535MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.


Channel Band width: 20MHz

Channel 21350(2560MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




*The 9kHz signal over the limit is from Spectrum.

LTE Band 38


Channel Band width: 5MHz

Channel 37775(2572.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 5MHz

Channel 38000(2595.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 5MHz

Channel 38225(2617.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 10MHz

Channel 37800(2575.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 10MHz

Channel 38000(2595.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 10MHz

Channel 38200(2615.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 15MHz

Channel 37825(2577.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 15MHz

Channel 38000(2595.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 15MHz

Channel 38175(2612.5MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 20MHz

Channel 37850(2580.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 20MHz

Channel 38000(2595.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Band width: 20MHz

Channel 38150(2610.0MHz)


Frequency Range : 9kHz~1GHz



Frequency Range : 1GHz~3GHz



Frequency Range : 3GHz~27GHz




LTE Band 41


Channel Bandwidth: 5MHz

Channel 40065(2537.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 5MHz

Channel 40445(2575.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 5MHz

Channel 40825(2613.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 5MHz

Channel 41215(2652.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 10MHz

Channel 40090(2540.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 10MHz

Channel 40450(2576.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 10MHz

Channel 40820(2613.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 10MHz

Channel 41190(2650.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 15MHz

Channel 40115(2542.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 15MHz

Channel 40465(2577.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 15MHz

Channel 40815(2612.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 15MHz

Channel 41165(2647.5MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 20MHz

Channel 40140(2545.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 20MHz

Channel 40470(2578.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 20MHz

Channel 40810(2612.0MHz)

Frequency Range : 30kHz~3GHz




Frequency Range : 3GHz~27GHz




Channel Bandwidth: 20MHz

Channel 41140(2645.0MHz)

Frequency Range : 30kHz~3GHz



Frequency Range : 3GHz~27GHz



4.8 Radiated Emission Measurement

4.8.1 Limits of Radiated Emission Measurement

For WCDMA Band 4, LTE Band 4

According to FCC 27.53(h) for operations in the 1695-1710 MHz, 1710-1755 MHz, 1755-1780 MHz, 1915-1920 MHz, 1995-2000 MHz, 2000-2020 MHz, 2110-2155 MHz, 2155-2180 MHz, and 2180-2200 bands, the power of any emission outside a licensee's frequency block shall be attenuated below the transmitter power (P) in watts by at least $43 + 10 \log (P)$ dB.

For LTE Band 7, 38, 41

In the FCC 27.53(m) (4)(6), On any frequency outside a licensee's frequency block, The power of any emission shall be attenuated below the transmitter power (P) by at least $55 + 10 \log (P)$ dB. The emission limit equal to -25dBm .

4.8.2 Test Procedure

- a. The power was measured with R&S Spectrum Analyzer. All measurements were done at 3 channels (low, middle and high channel of operational frequency range.)
- b. Substitution method is used for E.I.R.P measurement. In the semi-anechoic chamber, EUT placed on the 0.8m height of Turn Table, rotated the table around 360 degrees to search the maximum radiation power and receiver antenna shall be rotated vertical and horizontal polarization and moved height from 1m to 4m to find the maximum polar radiated power. The "Read Value" is the spectrum reading the maximum power value.
- c. The substitution antenna is substituted for EUT at the same position and signals generator export the CW signal to the substitution antenna via a TX cable. Rotated the Turn Table and moved receiving antenna to find the maximum radiation power. Adjust output power level of S.G to get a Value of spectrum reading equal to "Read Value" of step b. Record the power level of S.G
- d. $\text{EIRP} = \text{Output power level of S.G} - \text{TX cable loss} + \text{Antenna gain of substitution antenna}$.


Note: The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 1MHz/3MHz.

4.8.3 Deviation from Test Standard


No deviation.

4.8.4 Test Setup

For radiated emission 30MHz to 1GHz



For radiated emission above 1GHz



For the actual test configuration, please refer to the attached file (Test Setup Photo).

4.8.5 Test Results


Below 1GHz
WCDMA Band 4

Mode	TX channel 1513 (1752.6MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	46.49	-62.90	-52.50	-9.90	-62.40	-13.00	-49.40
2	67.83	-57.10	-62.80	-1.00	-63.80	-13.00	-50.80
3	78.50	-57.50	-63.20	0.60	-62.60	-13.00	-49.60
4	107.60	-57.70	-63.30	-2.30	-65.60	-13.00	-52.60
5	202.66	-57.20	-63.10	-2.10	-65.20	-13.00	-52.20
6	355.92	-63.00	-70.00	4.00	-66.00	-13.00	-53.00

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




Mode	TX channel 1513 (1752.6MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	46.49	-48.10	-46.40	-9.90	-56.30	-13.00	-43.30
2	68.80	-54.00	-59.80	-0.80	-60.60	-13.00	-47.60
3	94.99	-50.20	-57.00	-0.90	-57.90	-13.00	-44.90
4	193.93	-65.40	-64.10	-2.60	-66.70	-13.00	-53.70
5	275.41	-68.70	-64.00	-1.60	-65.60	-13.00	-52.60
6	359.80	-64.40	-68.80	4.00	-64.80	-13.00	-51.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




LTE Band 4, Channel Bandwidth: 1.4MHz

Mode	TX channel 19957 (1710.7MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	74.62	-59.50	-65.40	0.10	-65.30	-13.00	-52.30
2	189.08	-59.90	-65.50	-2.80	-68.30	-13.00	-55.30
3	288.02	-67.10	-68.90	-1.80	-70.70	-13.00	-57.70
4	375.32	-67.30	-72.80	3.70	-69.10	-13.00	-56.10
5	411.21	-68.60	-72.10	3.30	-68.80	-13.00	-55.80
6	544.10	-69.70	-73.00	3.80	-69.20	-13.00	-56.20

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




Mode	TX channel 19957 (1710.7MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	62.01	-50.60	-54.40	-3.00	-57.40	-13.00	-44.40
2	80.44	-57.10	-62.30	0.50	-61.80	-13.00	-48.80
3	188.11	-67.30	-66.80	-2.70	-69.50	-13.00	-56.50
4	278.32	-70.90	-66.00	-1.60	-67.60	-13.00	-54.60
5	324.88	-66.20	-70.50	4.10	-66.40	-13.00	-53.40
6	460.68	-66.40	-69.80	3.40	-66.40	-13.00	-53.40

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




LTE Band 7, Channel Bandwidth: 5MHz

Mode	TX channel 20775 (2502.5MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	31.94	-54.40	-32.70	-18.30	-51.00	-25.00	-26.00
2	74.62	-57.60	-63.50	0.10	-63.40	-25.00	-38.40
3	144.46	-61.60	-63.50	-3.20	-66.70	-25.00	-41.70
4	289.96	-61.70	-63.40	-1.70	-65.10	-25.00	-40.10
5	397.63	-61.50	-65.50	3.30	-62.20	-25.00	-37.20
6	519.85	-62.20	-65.70	3.80	-61.90	-25.00	-36.90

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




Mode	TX channel 20775 (2502.5MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	31.94	-42.20	-34.40	-18.30	-52.70	-25.00	-27.70
2	62.01	-50.90	-54.70	-3.00	-57.70	-25.00	-32.70
3	78.50	-55.30	-61.10	0.60	-60.50	-25.00	-35.50
4	142.52	-62.60	-61.70	-3.10	-64.80	-25.00	-39.80
5	197.81	-62.90	-61.30	-2.40	-63.70	-25.00	-38.70
6	276.38	-62.80	-57.90	-1.60	-59.50	-25.00	-34.50

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




LTE Band 38, Channel Bandwidth: 5MHz

Mode	TX channel 37775 (2572.5MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	73.65	-58.40	-64.30	0.10	-64.20	-25.00	-39.20
2	155.13	-67.90	-69.50	-2.90	-72.40	-25.00	-47.40
3	188.11	-60.90	-66.40	-2.70	-69.10	-25.00	-44.10
4	290.93	-67.10	-68.80	-1.90	-70.70	-25.00	-45.70
5	323.91	-66.30	-74.30	4.10	-70.20	-25.00	-45.20
6	407.33	-67.50	-71.30	3.30	-68.00	-25.00	-43.00

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




Mode	TX channel 37775 (2572.5MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	52.31	-39.60	-39.80	-6.80	-46.60	-25.00	-21.60
2	75.59	-54.60	-60.60	0.20	-60.40	-25.00	-35.40
3	127.00	-62.70	-65.10	-3.30	-68.40	-25.00	-43.40
4	188.11	-68.50	-68.00	-2.70	-70.70	-25.00	-45.70
5	279.29	-71.30	-66.40	-1.60	-68.00	-25.00	-43.00
6	434.49	-65.90	-69.60	3.60	-66.00	-25.00	-41.00

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




LTE Band 41, Channel Bandwidth: 5MHz

Mode	TX channel 40065 (2537.5MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 71%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	70.74	-55.80	-61.60	-0.40	-62.00	-25.00	-37.00
2	153.19	-68.70	-70.00	-2.90	-72.90	-25.00	-47.90
3	189.08	-60.40	-66.00	-2.80	-68.80	-25.00	-43.80
4	289.96	-67.20	-68.90	-1.70	-70.60	-25.00	-45.60
5	328.76	-66.90	-74.80	4.10	-70.70	-25.00	-45.70
6	405.39	-67.30	-71.20	3.30	-67.90	-25.00	-42.90

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).




Mode	TX channel 40065 (2537.5MHz)	Frequency Range	Below 1000 MHz
Environmental Conditions	25deg. C, 71%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	77.53	-51.60	-57.60	0.50	-57.10	-25.00	-32.10
2	189.08	-68.40	-67.80	-2.80	-70.60	-25.00	-45.60
3	277.35	-70.70	-65.80	-1.60	-67.40	-25.00	-42.40
4	319.06	-66.90	-71.00	4.00	-67.00	-25.00	-42.00
5	423.82	-67.20	-70.90	3.40	-67.50	-25.00	-42.50
6	478.14	-66.60	-70.50	3.70	-66.80	-25.00	-41.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).



Above 1GHz
WCDMA Band 4

Mode	TX channel 1312 (1712.4MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3424.80	-60.70	-52.10	1.30	-50.80	-13.00	-37.80
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3424.80	-62.20	-54.10	1.30	-52.80	-13.00	-39.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1413 (1732.6MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.20	-60.60	-52.20	1.40	-50.80	-13.00	-37.80
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.20	-62.40	-54.60	1.40	-53.20	-13.00	-40.20

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 1513 (1752.6MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3505.20	-59.80	-51.60	1.50	-50.10	-13.00	-37.10
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3505.20	-61.70	-54.10	1.50	-52.60	-13.00	-39.60

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4, Channel Bandwidth: 1.4MHz

Mode	TX channel 19957 (1710.7MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3421.40	-75.60	-71.40	7.10	-64.30	-13.00	-51.30
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3421.40	-76.20	-69.70	7.10	-62.60	-13.00	-49.60

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175 (1732.5MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.00	-75.30	-70.40	7.10	-63.30	-13.00	-50.30
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.00	-76.40	-69.60	7.10	-62.50	-13.00	-49.50

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20393 (1754.3MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3508.60	-75.60	-70.10	7.20	-62.90	-13.00	-49.90
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3508.60	-76.20	-69.30	7.20	-62.10	-13.00	-49.10

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4, Channel Bandwidth: 5MHz

Mode	TX channel 19975 (1712.5MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3425.00	-73.20	-69.00	7.10	-61.90	-13.00	-48.90
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3425.00	-76.30	-69.80	7.10	-62.70	-13.00	-49.70

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175 (1732.5MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.00	-75.20	-70.30	7.10	-63.20	-13.00	-50.20
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.00	-74.50	-67.70	7.10	-60.60	-13.00	-47.60

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20375 (1752.5MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3505.00	-75.60	-70.10	7.20	-62.90	-13.00	-49.90
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3505.00	-76.50	-69.50	7.20	-62.30	-13.00	-49.30

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 4, Channel Bandwidth: 20MHz

Mode	TX channel 20050 (1720.0MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3440.00	-72.80	-68.30	7.10	-61.20	-13.00	-48.20
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3440.00	-75.30	-68.70	7.10	-61.60	-13.00	-48.60

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20175 (1732.5MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.00	-75.30	-70.40	7.10	-63.30	-13.00	-50.30
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3465.00	-74.20	-67.40	7.10	-60.30	-13.00	-47.30

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 20300 (1745.0MHz)	Frequency Range	1GHz ~ 20GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3490.00	-75.90	-70.60	7.20	-63.40	-13.00	-50.40
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	3490.00	-76.20	-69.30	7.20	-62.10	-13.00	-49.10

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7, Channel Bandwidth: 5MHz

Mode	TX channel 20775 (2502.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5005.00	-64.70	-54.20	6.60	-47.60	-25.00	-22.60
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5005.00	-61.50	-50.80	6.60	-44.20	-25.00	-19.20

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100 (2535MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5070.00	-64.30	-53.00	6.60	-46.40	-25.00	-21.40
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5070.00	-61.20	-50.40	6.60	-43.80	-25.00	-18.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21425 (2567.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5135.00	-64.30	-52.40	6.60	-45.80	-25.00	-20.80
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5135.00	-61.50	-50.90	6.60	-44.30	-25.00	-19.30

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 7, Channel Bandwidth: 20MHz

Mode	TX channel 20850 (2510MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5020.00	-64.90	-54.20	6.60	-47.60	-25.00	-22.60
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5020.00	-62.00	-51.30	6.60	-44.70	-25.00	-19.70

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21100 (2535MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5070.00	-64.30	-53.00	6.60	-46.40	-25.00	-21.40
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5070.00	-60.60	-49.80	6.60	-43.20	-25.00	-18.20

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 21350 (2560MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5120.00	-63.90	-52.10	6.60	-45.50	-25.00	-20.50
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5120.00	-61.20	-50.50	6.60	-43.90	-25.00	-18.90

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38, Channel Bandwidth: 5MHz

Mode	TX channel 37775 (2572.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5145.00	-64.20	-54.40	6.60	-47.80	-25.00	-22.80
Antenna Polarity & Test Distance: Vertical at 3 m							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5145.00	-63.90	-55.50	6.60	-48.90	-25.00	-23.90

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000 (2595.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5190.00	-63.80	-53.90	6.70	-47.20	-25.00	-22.20
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5190.00	-63.90	-55.80	6.70	-49.10	-25.00	-24.10

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38225 (2617.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5235.00	-63.40	-53.60	6.60	-47.00	-25.00	-22.00
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5235.00	-64.00	-55.60	6.60	-49.00	-25.00	-24.00

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 38, Channel Bandwidth: 20MHz

Mode	TX channel 37850 (2580.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5160.00	-63.20	-53.50	6.70	-46.80	-25.00	-21.80
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5160.00	-64.20	-55.90	6.70	-49.20	-25.00	-24.20

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38000 (2595.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5190.00	-64.20	-54.40	6.70	-47.70	-25.00	-22.70
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5190.00	-64.50	-56.50	6.70	-49.80	-25.00	-24.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 38150 (2610.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5220.00	-64.70	-54.90	6.70	-48.20	-25.00	-23.20
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5220.00	-63.90	-55.60	6.70	-48.90	-25.00	-23.90

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41, Channel Bandwidth: 5MHz

Mode	TX channel 40065 (2537.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5075.00	-64.80	-55.50	6.60	-48.90	-25.00	-23.90
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5075.00	-63.40	-54.70	6.60	-48.10	-25.00	-23.10

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40445 (2575.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5151.00 (PK)	-65.00	-53.10	6.70	-46.40	-25.00	-21.40
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5151.00 (PK)	-63.50	-53.10	6.70	-46.40	-25.00	-21.40

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40825 (2613.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5227.00 (PK)	-65.10	-53.10	6.60	-46.50	-25.00	-21.50
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5227.00 (PK)	-63.30	-52.80	6.60	-46.20	-25.00	-21.20

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41215 (2652.5MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5305.00	-65.00	-55.80	6.70	-49.10	-25.00	-24.10
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5305.00	-63.80	-54.50	6.70	-47.80	-25.00	-22.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

LTE Band 41, Channel Bandwidth: 20MHz

Mode	TX channel 40140 (2545.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5090.00	-64.00	-54.60	6.60	-48.00	-25.00	-23.00
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5090.00	-64.00	-55.40	6.60	-48.80	-25.00	-23.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40470 (2578.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5156.00 (PK)	-65.20	-53.30	6.70	-46.60	-25.00	-21.60
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5156.00 (PK)	-63.80	-53.40	6.70	-46.70	-25.00	-21.70

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 40810 (2612.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5224.00 (PK)	-65.00	-53.10	6.70	-46.40	-25.00	-21.40
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5224.00 (PK)	-63.50	-53.10	6.70	-46.40	-25.00	-21.40

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

Mode	TX channel 41140 (2645.0MHz)	Frequency Range	1GHz ~ 27GHz
Environmental Conditions	25deg. C, 70%RH	Input Power	120Vac, 60Hz
Tested By	Noah Chang		

Antenna Polarity & Test Distance: Horizontal at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5290.00	-64.50	-55.20	6.70	-48.50	-25.00	-23.50
Antenna Polarity & Test Distance: Vertical at 3 M							
No.	Freq. (MHz)	Reading (dBm)	S.G Power Value (dBm)	Correction Factor (dB)	EIRP (dBm)	Limit (dBm)	Margin (dB)
1	5290.00	-64.50	-55.50	6.70	-48.80	-25.00	-23.80

Remarks:

1. EIRP (dBm) = S.G Value (dBm) + Correction Factor (dB).
2. Correction Factor (dB) = Substitution Antenna Gain (dB) + Cable Loss (dB).

5 Pictures of Test Arrangements

Please refer to the attached file (Test Setup Photo).

Appendix – Information of the Testing Laboratories

We, Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch, were founded in 1988 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are FCC recognized accredited test firms and accredited and approved according to ISO/IEC 17025.

If you have any comments, please feel free to contact us at the following:

Lin Kou EMC/RF Lab

Tel: 886-2-26052180

Fax: 886-2-26051924

Hsin Chu EMC/RF/Telecom Lab

Tel: 886-3-6668565

Fax: 886-3-6668323

Hwa Ya EMC/RF/Safety Lab

Tel: 886-3-3183232

Fax: 886-3-3270892

Email: service.adt@tw.bureauveritas.com

Web Site: www.bureauveritas-adt.com

The address and road map of all our labs can be found in our web site also.

--- END ---