

Uni-Art Precise Products Ltd.

Application
For
Certification

900MHz Cordless Headset Telephone

(FCC ID: MVABE-900-001FA)

WO# 9809516
CKL/at
December 30, 1998

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Limited

FCC ID: MVABE-900-001FA

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Security Code Information

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Uni-Art Precise Products Ltd - MODEL: Bell Equipment Sonacor BE900FA
TT Systems TT900FA
FCC ID: MVABE-900-001FA

This report concerns (check one): Original Grant X Class II Change

Equipment Type: Low Power Transmitter (example: computer, modem, transmitter, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes No X

If yes, defer until : _____
date

Company Name agrees to notify the Commission by: _____
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes No X

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [10-1-96 Edition] provision.

Report prepared by:

Alfred Lo
Intertek Testing Services.
2/F., Garment Centre,
576 Castle Peak Road,
Kowloon, Hong Kong.
Phone: 852-2746-8217
Fax: 852-2785-5487

INTERTEK TESTING SERVICES

Table of Contents

1.0 <u>General Description</u>	2
1.1 Product Description	2
1.2 Related Submittal(s) Grants	3
1.3 Test Methodology	3
1.4 Test Facility	3
2.0 <u>System Test Configuration</u>	5
2.1 Justification.....	5
2.2 EUT Exercising Software	5
2.3 Support Equipment List and Description	6
2.4 Equipment Modification	7
3.0 <u>Emission Results</u>	9
3.1 Field Strength Calculation.....	10
3.2 Radiated Emission Configuration Photograph - Base Unit.....	11
3.3 Radiated Emission Data - Base Unit.....	12
3.4 Radiated Emission Configuration Photograph - Headset.....	17
3.5 Radiated Emission Configuration Data - Headset	18
3.6 Radiated Emission on the band edge.....	21
3.7 Line Conducted Configuration Photograph - Base Unit	23
3.8 Line Conducted Data - Base Unit	27
4.0 <u>Equipment Photographs</u>	26
5.0 <u>Product Labelling</u>	28
6.0 <u>Technical Specifications</u>	30
7.0 <u>Instruction Manual</u>	32
8.0 <u>Security Code Information</u>	34

INTERTEK TESTING SERVICES

List of attached file

Exhibit type	File Description	filename
Cover Letter	Letter of Agency	letter.pdf
Test Report	Test Report	report.doc
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission for Base	base.jpg
Test Setup Photo	Radiated Emission for Headset	headset.jpg
Test Report	Emission Plot	emission.pdf
Test Setup Photo	Conducted Emission	conduct1.jpg, conduct2.jpg
Test Report	Conducted Emission Test Result	conduct.pdf
External Photo	External Photo	ophoto1.jpg, ophoto2.jpg
Internal Photo	Internal Photo	iphoto1.jpg to iphoto13.jpg
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf

INTERTEK TESTING SERVICES

EXHIBIT 1
GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 **General Description**

1.1 Product Description

The Bell Equipment Sonacor BE900FA is a 900MHz Cordless Headset Telephone. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The TT Systems TT900FA is identical to Bell Equipment Sonacor BE900FA as far as hardware, software, features and functionality. The additional model number is for marketing purposes only.

The headset unit consists of a keypad with twelve standard keys (0,...9,*,#), four function keys Memo, Redial, Pause, Flash, and one channel switch key. A talk key is provided to control pick/release telephone line in a toggle base.

The base unit has a page key, which is used to page the headset unit. The "MIC" and "SPEAKER" jacks of the telephone are for Internet phone applications and this mode is achieved by moving the switch in front of the base unit from "TELEPHONE" to "COMPUTER".

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

INTERTEK TESTING SERVICES

1.2 Related Submittal(s) Grants

This is an Application for Certification of a cordless telephone system. Two transmitters are included in this Application. This specific report details the emission characteristics of each transmitter. The receivers are subject to the verification authorization process, in accordance with 15.101(b). A verification report has been prepared for the receiver sections of each device. The device is also subject to Part 68 Registration.

1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

EXHIBIT 2
SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 **System Test Configuration**

2.1 Justification

For emission testing, the equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). During testing, all cables were manipulated to produce worst case emissions. The handset was powered by a fully charged battery.

For the measurements, the EUT is attached to a cardboard box and placed on the wooden turntable. If the base unit attaches to peripherals, they are connected and operational (as typical as possible). The headset is remotely located as far from the antenna and the base as possible to ensure full power transmission from the base. Else, the base is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Detector function is in peak mode. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater. All emissions greater than 20 dB μ V/m are recorded.

Radiated emission measurement were performed from 30 MHz to tenth harmonics.

2.2 EUT Exercising Software

The EUT exercise program used during radiated and conducted testing was designed to exercise the various system components in a manner similar to a typical use.

For emissions testing, the units were setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing.

INTERTEK TESTING SERVICES

2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system (included inserted cards, which have grants) are:

HARDWARE:

The unit was operated standalone. An AC adapter (provided with the unit) was used to power the device. Its description is listed below.

- (1) AC adapter with two meter unshielded power cord permanently affixed.

CABLES:

- (1) Telecommunication cable with RJ11C connectors (1m, unshielded), terminated
- (2) 1 set of unshielded audio cable which connected to the Speaker jack.
- (3) 1 set of shielded audio cable which connected to the Mic jack.

OTHERS:

1. Audio Signal Generator.
2. Resistive Load.

INTERTEK TESTING SERVICES

2.4 Equipment Modification

Any modifications installed previous to testing by Uni-Art Precise Products Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

Confirmed by:

*Alfred Lo
Technical Supervisor
Intertek Testing Services
Agent for Uni-Art Precise Products Ltd.*



Signature

December 30, 98 _____
Date

EXHIBIT 3
EMISSION RESULTS

3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB μ V/m
 RA = Receiver Amplitude (including preamplifier) in dB μ V
 CF = Cable Attenuation Factor in dB
 AF = Antenna Factor in dB
 AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where FS = Field Strength in dB μ V/m
 RR = RA - AG in dB μ V
 LF = CF + AF in dB

Assume a receiver reading of 52.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

RA = 52.0 dB μ V/m	
AF = 7.4 dB	RR = 23.0 dB μ V
CF = 1.6 dB	LF = 9.0 dB
AG = 29.0 dB	
FS = RR + LF	
FS = 23 + 9 = 32 dB μ V/m	

Level in μ V/m = Common Antilogarithm [(32 dB μ V/m)/20] = 39.8 μ V/m

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph - Base Unit

Worst Case Radiated Emission

at 3608.667 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: base.jpg

INTERTEK TESTING SERVICES

3.3 Radiated Emission Data - Base Unit

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 6.0 dB

TEST PERSONNEL:



Tester Signature

H. Y. Vu, Engineer

Typed/Printed Name

December 30, 98

Date

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA
Mode : TX-Channel 1

Date of Test: December 16, 1998

Table 1, Base unit

Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit (dB μ V/m)	Margin (dB)
V	902.127	70.4	32.0	16	86.4	94	-7.6
H	451.084	28.8	25.0	16	37.8	46	-8.2
H	468.434	28.9	26.0	16	38.9	46	-7.1
H	1804.254	53.6	26.5	34	46.1	54	-7.9
H	*2706.381	40.3	29.1	34	35.4	54	-18.6
H	*3608.508	49.2	32.8	34	48.0	54	-6.0
H	*4510.635	42.6	34.0	34	42.6	54	-11.4
H	*5412.762	41.9	35.2	34	43.1	54	-10.9

NOTES: 1. Peak Detector data

- All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
- Negative value in the margin column shows emission below limit.
- Horn antenna and average detector are used for the emission over 1000MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA
Mode : TX-Channel 40

Date of Test: December 16, 1998

Table 3, Base unit

Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit (dB μ V/m)	Margin (dB)
V	902.300	71.0	32.0	16	87.0	94	-7.0
H	451.667	28.2	25.0	16	37.2	46	-8.8
H	469.020	26.9	26.0	16	36.9	46	-9.1
H	1804.600	46.0	26.5	34	38.5	54	-15.5
H	*2706.900	45.0	29.1	34	40.1	54	-13.9
H	*3609.200	47.9	32.8	34	46.7	54	-7.3
H	*4511.500	41.2	34.0	34	41.2	54	-12.8
H	*5413.800	41.1	35.2	34	42.3	54	-11.7

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna and average detector are used for the emission over 1000MHz.

* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA
Mode : Stand by

Date of Test: December 16, 1998

Table 4, Base unit

Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit (dB μ V/m)	Margin (dB)
H	468.649	27.7	25	16	36.7	46	-9.3

- NOTES:
1. Peak Detector data
 2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
 3. Negative value in the margin column shows emission below limit.
 4. Horn antenna and average detector are used for the emission over 1000MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA
Mode : Charging

Date of Test: December 16, 1998

Table 5, Base unit

Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit (dB μ V/m)	Margin (dB)
H	468.649	27.7	25	16	36.7	46	-9.3

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: H. Y. Vu

INTERTEK TESTING SERVICES

3.4 Radiated Emission Configuration Photograph - Handset

Worst Case Radiated Emission

at 463.083 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: handset.pdf

INTERTEK TESTING SERVICES

3.5 Radiated Emission Data - Headset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 6.5 dB

TEST PERSONNEL:



Tester Signature

H. Y. Vu, Engineer
Typed/Printed Name

December 30, 98
Date

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA
Mode : TX-Channel 1

Date of Test: December 16, 1998

Table 6, Headset

Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit (dB μ V/m)	Margin (dB)
V	926.127	65.8	33	16	82.8	94	-11.2
H	463.083	29.5	26	16	39.5	46	-6.5
H	1852.254	46.4	26.5	34	38.9	54	-15.1
H	*2778.381	44.3	29.1	34	39.4	54	-14.6
H	*3704.508	39.7	32.8	34	38.5	54	-15.5

NOTES: 1. Peak Detector data

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
 3. Negative value in the margin column shows emission below limit.
 4. Horn antenna and average detector are used for the emission over 1000MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: H.Y. Vu

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA
Mode : TX-Channel 40

Date of Test: December 16, 1998

Table 7, Headset

Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit (dB μ V/m)	Margin (dB)
V	927.297	64.6	33.0	16	81.6	94	-12.4
H	463.669	29.4	26.0	16	39.4	46	-6.6
H	1854.594	45.1	26.5	34	37.6	54	-16.4
V	*2781.891	46.5	29.1	34	41.6	54	-12.4
H	*3709.188	38.1	32.8	34	36.9	54	-17.1

- NOTES: 1. Peak Detector data
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: H. Y. Vu

3.6 Radiated Emission on the band edge

From the following plots, they show that the fundamental emissions are confined in the specified band and the emissions are at least 60 dB below the carrier level at band edge (902 and 928 MHz). It meets the requirement of section 15.249(c).

Emission Plot

For electronic filing, the emission plots are saved with filename: emission.pdf

INTERTEK TESTING SERVICES

3.7 Line Conducted Configuration Photograph - Base Unit

Worst Case Line-Conducted Configuration

For electronic filing, the worst case line conducted configuration photograph are saved with filename: conduct1.pdf and conduct2.pdf

INTERTEK TESTING SERVICES

3.8 Line Conducted Emission Configuration Data

The data on the following pages list the significant emission frequencies, the limit, and the margin of compliance.

Judgement : Passed by more than 20 dB

TEST PERSONNEL:



Tester Signature

H. Y. Vu, Engineer

Typed/Printed Name

December 30, 98

Date

INTERTEK TESTING SERVICES

Company: Uni-Art Precise Products Ltd.
Model: Bell Equipment Sonacor BE900FA

Date of Test: December 16, 1998

Conducted Emissions

For electronic filing, the conducted emission test result is saved with filename: conduct.pdf

EXHIBIT 4
EQUIPMENT PHOTOGRAPHS

4.0 **Equipment Photographs**

For electronic filing, the photographs are saved with filename: ophoto1.jpg to ophoto2.jpg & iphoto1.jpg to iphoto13.jpg

EXHIBIT 5
PRODUCT LABELLING

5.0 **Product Labelling**

For electronic filing, the FCC ID label artwork and location is saved with filename: label.pdf

EXHIBIT 6
TECHNICAL SPECIFICATIONS

6.0 **Technical Specifications**

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf respectively.

EXHIBIT 7
INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

Please note that the required FCC Information to the User can be found on Page 17 and 18 of this manual.

This manual will be provided to the end-user with each unit sold/leased in the United States.

In addition, the Instruction Manual will also include the following statement :

Shielded cables must be used with the “MIC” jack of the unit to ensure compliance with FCC Part 15 limits.

EXHIBIT 8
SECURITY CODE INFORMATION

INTERTEK TESTING SERVICES

8.0 Security code information

The telephone has an internal security code with 65,536 possible combinations. Each time you pick up the HEADSET, the code is randomly set to a new combination.

Communication between HEADSET and BASE UNIT may not be possible in any of the following situation:

1. After a power failure.
2. After relocation the BASE UNIT by disconnecting the AC adaptor.
3. After replacing the HEADSET battery.

To reset, place the HEADSET on the BASE UNIT for 2 to 5 seconds.