

1. Turn off the power of your computer. Disconnect another mouse installed and locate an empty 9-pin RS-232 port (or the USB mouse port). The port(s) is usually on the back of the computer. See the user's manual came with your computer, if you have problem to find the port.
2. Connect the 9-pin D-sub connector from AQMouse (serial mouse) to the RS-232 port, or connect the USB port connector from AQMouse USB mouse to the USB mouse port.
3. Tighten the screws and secure the connection.
4. Turn the power on to start your computer.

(C) **Driver Install (After finish the "Hardware Install" as showed above.)**

It's recommended that you remove other mouse control program and reboot your computer before following installation steps.

• **Windows 3.1**

1. Start Windows (C:\>WIN.)
2. Open the "Program Manager" window (Alt + TAB).
3. Pull down the "File" menu (Alt + F), and type R to open RUN dialog box.
4. Insert the AQMouse Driver disk to you driver A (or B).
5. Type A:\WINDOWS\SETUP in the command line and press ENTER(↵).
6. Follow the directions / steps on the screen and use default settings by just pressing ENTER. Change the settings if necessary.
7. Be sure to remove the disk from the driver as the install program indicates.
8. The install program will restart your computer and then the AQMouse works.

• **Windows 95**

1. Start Windows 95.
2. Pull-up "Start" menu (Ctrl + ESC).
3. Select "RUN" by arrow keys (↑) or type R.
4. Insert the AQMouse Driver disk to you driver A (or B).
5. Type A:\WINDOWS\SETUP in the command line and press ENTER(↵).
6. Follow the directions / steps on the screen and use default settings by just pressing ENTER. Change the settings if necessary.
7. Be sure to remove the disk from the driver as the install program indicates.
8. The install program will restart your computer and then the AQMouse works.

**Canadian Department Of Communication Notice**

The Canadian Department Of Communications (DOC) label identifies certified equipment. This certification means that the equipment meets certain Department does not guarantee the equipment will operate to the user's satisfaction.

**Copyright**

This manual is copyrighted with all rights reserved. No portion of this manual may be copied or reproduced by any means. While every precaution has been taken in the preparation of this manual, no responsibility for errors or omissions is assumed. Neither is any liability assumed for damages resulting from the use of the information contained herein.

**Installation**

Mouse model : S3C800A and A3C800A

**A) System Requirement**

IBM PC or compatible computer with a RS-232 (or PS2), USB port and a 3 1/2" floppy driver.

All brand names and registered trademarks mentioned are property of their respective owners.

FCC ID: N1Y53C800A