

Lelux Electronics Ltd.

Application
For
Certification

46/49MHz 10 Channel Analog Modulation Cordless Phone with Caller ID

(FCC ID: NS3650D)

WO# 01133351
TL/at Ann Choy
January 14, 2002

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer to deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited

FCC ID: NS3650D

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1;</i>	General Description
<i>EXHIBIT 2;</i>	System Test Configuration
<i>EXHIBIT 3;</i>	Emission Results
<i>EXHIBIT 4;</i>	Frequency Deviation
<i>EXHIBIT 5;</i>	Operating Bandwidth
<i>EXHIBIT 6;</i>	Equipment Photographs
<i>EXHIBIT 7;</i>	Product Labelling
<i>EXHIBIT 8;</i>	Technical Specifications
<i>EXHIBIT 9;</i>	Instruction Manual
<i>EXHIBIT 10;</i>	Security Code Information

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Lelux Electronics Ltd. - MODEL: Lelux 650D
FCC ID: NS3650D

This report concerns (check one:) Original Grant X Class II Change _____

Equipment Type: Cordless Telephone (example: computer, modem, transmitter, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes _____ No X _____

If yes, defer until: _____
date

Company Name agrees to notify the Commission by: _____
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes _____ No X _____

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [5-24-01 Edition] provision.

Report prepared by:

Tommy Leung
Intertek Testing Services.
2/F., Garment Centre,
576 Castle Peak Road,
Kowloon, Hong Kong.
Phone: 852-2173-8575
Fax: 852-2741-1693

INTERTEK TESTING SERVICES

List of attached file

Exhibit type	File Description	filename
Test Report	Test Report	report.doc
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission for Base	config photos.doc
Test Setup Photo	Radiated Emission for Handset	config photos.doc
Test Report	Conducted Emission Test Result	conduct.pdf
Test Report	Base Bandwidth Plot	bsbw.pdf
Test Report	Handset Bandwidth Plot	hsbw.pdf
External Photo	External Photo	external photos.doc
Internal Photo	Internal Photo	internal photos.doc
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
User Manual	FCC Information	fcc information.pdf

INTERTEK TESTING SERVICES

Table of Contents

1.0 General Description	2
1.1 Product Description	2
1.2 Related Submittal(s) Grants	3
1.3 Test Methodology	3
1.4 Test Facility	3
2.0 System Test Configuration	5
2.1 Justification	5
2.2 EUT Exercising Software	5
2.3 Support Equipment List and Description	6
2.4 Measurement Uncertainty	7
2.5 Equipment Modification	7
3.0 Emission Results	9
3.1 Field Strength Calculation	10
3.2 Radiated Emission Configuration Photograph - Base Unit	11
3.3 Radiated Emission Data - Base Unit	12
3.4 Radiated Emission Configuration Photograph - Handset	14
3.5 Radiated Emission Data - Handset	15
3.6 Line Conducted Configuration Photograph - Base Unit	17
3.7 Line Conducted Configuration Data - Base Unit	18
4.0 Frequency Deviation	21
4.1 Base Unit	22
4.2 Handset	24
5.0 Operating Bandwidth	27
5.1 Base Unit	28
5.2 Handset	30
6.0 Equipment Photographs	33
7.0 Product Labelling	35
8.0 Technical Specifications	37
9.0 Instruction Manual	39
10.0 Security Code Information	41

INTERTEK TESTING SERVICES

EXHIBIT 1 GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 **General Description**

1.1 Product Description

The Lelux 650D is a 46/49MHz 10 Channel Analog Modulation Cordless Phone with Caller ID. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The handset unit consists of a keypad with twelve standard keys (0,...9,*,#), six function keys (Prog, Volume Up, Volume Down, Ex, Rdl/P, F), and one channel switch key. A Talk key is provided to control pick/release telephone line in a toggle base.

The base unit has a page key, which is used to page the handset unit.

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

INTERTEK TESTING SERVICES

1.2 Related Submittal(s) Grants

This is an Application for Certification of a cordless telephone system. Two transmitters are included in this Application. This specific report details the emission characteristics of each transmitter. The receivers are subject to the verification authorization process, in accordance with 15.101(b). A verification report has been prepared for the receiver sections of each device. The device is also subject to Part 68 Registration.

1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

INTERTEK TESTING SERVICES

EXHIBIT 2 SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 System Test Configuration

2.1 Justification

For emission testing, the equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). During testing, all cables were manipulated to produce worst case emissions. The handset was powered by a fully charged battery.

For the measurements, the EUT is attached to a cardboard box if necessary and placed on the wooden turntable. If the base unit attaches to peripherals, they are connected and operational (as typical as possible). The handset is remotely located as far from the antenna and the base as possible to ensure full power transmission from the base. Else, the base is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Detector function is in peak mode. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater. All emissions greater than 20 dB μ V/m are recorded.

2.2 EUT Exercising Software

The EUT exercise program used during radiated and conducted testing was designed to exercise the various system components in a manner similar to a typical use.

For emissions testing, the units were setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing.

INTERTEK TESTING SERVICES

2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system (included inserted cards, which have grants) are:

HARDWARE:

The unit was operated standalone. An AC adapter (provided with the unit) was used to power the device. Its description is listed below.

- (1) AC adapter (120VAC to 9VAC 300mA) with two meter unshielded power cord permanently affixed.

CABLES:

- (1) Telecommunication cable with RJ11C connectors (1m, unshielded), terminated

OTHERS:

- (1) A headset for telephone use with 1.2m unshielded cable permanently affixed.

INTERTEK TESTING SERVICES

2.4 Measurement Uncertainty

When determining of the test conclusion, the Measurement Uncertainty of test has been considered.

2.5 Equipment Modification

Any modifications installed previous to testing by Lelux Electronics Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

Confirmed by:

*Tommy Leung
Assistant Supervisor
Intertek Testing Services
Agent for Lelux Electronics Ltd.*



Signature

January 14, 2002 Date

INTERTEK TESTING SERVICES

EXHIBIT 3 EMISSION RESULTS

3.0 **Emission Results**

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in dB μ V/m
 RA = Receiver Amplitude (including preamplifier) in dB μ V
 CF = Cable Attenuation Factor in dB
 AF = Antenna Factor in dB
 AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where FS = Field Strength in dB μ V/m
 RR = RA - AG in dB μ V
 LF = CF + AF in dB

Assume a receiver reading of 52.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

RA = 52.0 dB μ V/m	
AF = 7.4 dB	RR = 23.0 dB μ V
CF = 1.6 dB	LF = 9.0 dB
AG = 29.0 dB	
FS = RR + LF	
FS = 23 + 9 = 32 dB μ V/m	

Level in mV/m = Common Antilogarithm [(32 dB μ V/m)/20] = 39.8 μ V/m

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph - Base Unit

Worst Case Radiated Emission

at 46.730 MHz

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: config photos.doc


INTERTEK TESTING SERVICES

3.3 Radiated Emission Data - Base Unit

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 0.5 dB

TEST PERSONNEL:



Tester Signature

Yvonne Leung, Engineer
Typed/Printed Name

January 14, 2002
Date

INTERTEK TESTING SERVICES

Company: Lelux Electronics Ltd.
Model: Lelux 650D
Mode : TX-Channel 5

Date of Test: November 16, 2001

Table 1, Base unit

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Am p Gain (dB)	Net at 3m (dB μ V /m)	L i n i t (dB μ V /m)	M a g i n (dB)
V	46.730	83.6	11.9	16	79.5	80.0	-0.5
H	93.460	40.7	9.4	16	34.1	43.5	-9.4
H	140.190	35.7	11.7	16	31.4	43.5	-12.1
H	186.920	30.5	16.7	16	31.2	43.5	-12.3
H	233.650	35.4	11.4	16	30.8	46.0	-15.2

- NOTES:
1. Quasi-peak detector is used for the emission below or equal to 1000 MHz.
 2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
 3. Negative value in the margin column shows emission below limit.
 4. Horn antenna and average detector are used for the emission over 1000MHz.
 5. Radiated emission measurement were performed the lowest radio frequency signal generated in the device which is greater than 9kHz to 500MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Yvonne Leung

INTERTEK TESTING SERVICES

3.4 Radiated Emission Configuration Photograph - Handset

Worst Case Radiated Emission

at 49.875 MHz

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: config photos.doc


INTERTEK TESTING SERVICES

3.5 Radiated Emission Data - Handset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 6.4 dB

TEST PERSONNEL:



Tester Signature

Yvonne Leung, Engineer
Typed/Printed Name

January 14, 2002
Date

INTERTEK TESTING SERVICES

Company: Lelux Electronics Ltd.
Model: Lelux 650D
Mode : TX-Channel 5

Date of Test: November 16, 2001

Table 2, Handset

Radiated Emissions

Polarity	Frequency (M H z)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Am p Gain (dB)	Net at 3m (dB μ V /m)	Lim it (dB μ V /m)	M agin (dB)
V	49.875	77.7	11.9	16	73.6	80.0	-6.4
H	99.750	40.6	10.6	16	35.2	43.5	-8.3
H	149.625	37.6	11.6	16	33.2	43.5	-10.3
H	199.500	31.5	17.3	16	32.8	43.5	-10.7
H	*249.375	35.1	11.4	16	30.5	46.0	-15.5

- NOTES:
1. Quasi-peak detector is used for the emission below or equal to 1000 MHz.
 2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
 3. Negative value in the margin column shows emission below limit.
 4. Horn antenna and average detector are used for the emission over 1000MHz.
 5. Radiated emission measurement were performed the lowest radio frequency signal generated in the device which is greater than 9kHz to 500MHz.
- * Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Yvonne Leung

INTERTEK TESTING SERVICES

3.6 Line Conducted Configuration Photograph - Base Unit

Worst Case Line-Conducted Configuration

at 22.300 MHz

For electronic filing, the worst case line conducted configuration photographs are saved with filename: config photos.doc


INTERTEK TESTING SERVICES

3.7 Line Conducted Emission Configuration Data

The data on the following pages list the significant emission frequencies, the limit, and the margin of compliance.

Judgement : Passed by 12.2 dB

TEST PERSONNEL:



Tester Signature

Yvonne Leung, Engineer
Typed/Printed Name

January 14, 2002
Date

INTERTEK TESTING SERVICES

Company: Lelux Electronics Ltd.
Model: Lelux 650D

Date of Test: November 16, 2001

Conducted Emissions

For electronic filing, the conducted emission test result is saved with filename: conduct.pdf

INTERTEK TESTING SERVICES

EXHIBIT 4
FREQUENCY DEVIATION

INTERTEK TESTING SERVICES

4.0 Frequency Deviation

Two stability tests were performed -- Frequency stability versus input voltage and frequency stability versus temperature. For both measurements, a 1 GHz frequency counter with temperature controlled time base is used.

The counter is coupled to the transmitter by coiling a pickup wire over the transmitter antenna or directly attaching it to the antenna, assuming a 50 Ω antenna is used.

The frequency stability is measured at room temperature by varying the supply voltage (AC or DC, as required) from 85% through 115% of normal operating voltage. This test is not applicable if the unit uses battery power. For battery powered equipment, the batteries are new and fully charged.

Stability versus temperature testing is carried out with the aid of a Tabai Espec Corp, Model PR-3F(W) environmental chamber. The following procedure is followed during testing:

1. Cool the device to -20°C and allow it to stabilize for 30 minutes. Record the frequency.
2. Heat the oven to +50°C and allow it to stabilize for 30 minutes. Record the frequency of operation.
3. Compare the measurements and a room temperature measurement against the assigned frequency tolerance.

The frequency tolerance of the carrier signal shall be maintained within $\pm 0.01\%$ of the operating frequency.

INTERTEK TESTING SERVICES

4.1.1 Measurement Data - Base Unit

Channel Frequency

Channel	Assigned Frequency (MHz)	Measured Frequency (MHz)	Tolerance %
1	46.61000	46.60975	-0.00054
2	46.63000	46.62975	-0.00054
3	46.67000	46.66976	-0.00052
4	46.71000	46.70981	-0.00040
5	46.73000	46.72974	-0.00055
6	46.77000	46.76976	-0.00052
7	46.83000	46.82978	-0.00048
8	46.87000	46.86977	-0.00048
9	46.93000	46.92975	-0.00054
10	46.97000	46.96976	-0.00050

4.1.2 Measurement Data - Base Unit - Channel 5

FCC ID: NS3650D

INTERTEK TESTING SERVICES

Frequency Stability

Frequency Stability versus Source Voltage

	Voltage (Vac)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance % ($\times 10^{-3}$)
Nominal	120.0	46730.00	46729.74	-0.26	-0.55
85 %	102.0	46730.00	46729.80	-0.21	-0.44
115 %	138.0	46730.00	46729.79	-0.21	-0.45

Frequency Stability versus Temperature

Temperature (°C)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance (%) ($\times 10^{-3}$)
-20	46730.00	46730.58	0.58	1.24
25	46730.00	46729.74	-0.26	-0.55
50	46730.00	46729.15	-0.85	-1.81

Test Results: Form the above sets of table for base unit, the largest deviation for nominal frequency was -850Hz, which was -0.00181% compared to the standard test frequency. The required minimum standard is $\pm 0.01\%$ in §15.233(g).

INTERTEK TESTING SERVICES

4.2.1 Measurement Data - Handset Unit

Channel Frequency

Channel	Assigned Frequency (MHz)	Measured Frequency (MHz)	Tolerance %
1	49.67000	49.67016	0.00031
2	49.84500	49.84520	0.00040
3	49.86000	49.86033	0.00066
4	49.77000	49.77041	0.00083
5	49.87500	49.87517	0.00034
6	49.83000	49.83025	0.00050
7	49.89000	49.89037	0.00074
8	49.93000	49.93057	0.00113
9	49.99000	49.99021	0.00041
10	49.97000	49.97036	0.00072

INTERTEK TESTING SERVICES

4.2.2 Measurement Data - Handset - Channel 5

Frequency Stability

Frequency Stability versus Temperature

Temperature (°C)	Assigned Frequency (kHz)	Measured Frequency (kHz)	Frequency deviation (kHz)	Tolerance (%) (x 10 ⁻³)
-20	49875.000	49877.471	2.47	4.95
25	49875.000	49875.171	0.17	0.34
50	49875.000	49873.688	-1.31	-2.63

Test Results: Form the above table for handset unit, the largest deviation for nominal frequency was 2470Hz, which was 0.00495% compared to the standard test frequency. The required minimum standard is $\pm 0.01\%$ in §15.233(g).

INTERTEK TESTING SERVICES

EXHIBIT 5
OPERATING BANDWIDTH

INTERTEK TESTING SERVICES

5.0 Operating Bandwidth

For measurements of bandwidth, the following procedure was followed by the test engineer:

- (1) Set up the equipment such that the antenna is located close enough to give a full scale deflection of the unmodulated carrier.
- (2) Plot the unmodulated carrier. Any residual guard tones should be left in place, as these will be present at all times in actual operation.
- (3) Plot the bandwidth with all alerting tones active. These include ringing and "call" signals from the base, and any intercom functions available in the handset.
- (4) Determine the worst case bandwidth using the following procedure:
 - (a) Disable all internal modulations, if possible.
 - (b) Apply a 2500 Hz signal to the audio input.
 - (c) Vary the input signal level and observe on the spectrum analyzer the waveform. Vary unit until a maximum deflection is observed. Record the input signal level. Record and plot the bandwidth deflection (100% modulation) measured at -26 dB below the carrier.
 - (d) **FOR A DEVICE WITH MODULATION LIMITING:**

Apply a 2500 Hz signal with the input level 16 dB greater than the level which produces 50% modulation. Plot and record the bandwidth.
 - (e) **FOR A DEVICE WITHOUT MODULATION LIMITING:**

Apply a 2500 Hz signal with the input level set for 85% modulation. If not possible, maximize the modulation percentage. Plot and record bandwidth.
- (5) Complete the tables on the following pages.

INTERTEK TESTING SERVICES

5.1 Base Unit - Channel 5

Operating Bandwidth

kHz from Carrier	Amplitude Down from Carrier (dB)	Limit (kHz)
-8.38	26.00	-10
8.75	26.00	10
-20.00	58.48	N/A
20.00	57.02	N/A

Test Result: From the above table for Base Unit - Channel 5, the modulated signal from base unit closest to band edge was 1.25kHz below the upper band edge 46.740MHz according to §15.233(d).

INTERTEK TESTING SERVICES

Bandwidth Plot - Base Unit

For electronic filing, the bandwidth plot is saved with filename: bsbw.pdf

INTERTEK TESTING SERVICES

5.2 Handset - Channel 5

Operating Bandwidth

kHz from Carrier	Amplitude Down from Carrier (dB)	Limit (kHz)
-8.38	26.00	-10
8.25	26.00	10
-20.00	60.58	N/A
20.00	56.86	N/A

Test Result: From the above table for Handset - Channel 5, the modulated signal from handset closest to band edge was 1.62kHz above the lower band edge 49.865MHz according to §15.233(d).

INTERTEK TESTING SERVICES

Bandwidth Plot - Handset

For electronic filing, the bandwidth plot is saved with filename: hsbw.pdf

INTERTEK TESTING SERVICES

EXHIBIT 6 EQUIPMENT PHOTOGRAPHS

6.0 Equipment Photographs

FCC ID: NS3650D

INTERTEK TESTING SERVICES

For electronic filing, the photographs are saved with filename: external photos.doc & internal photos.doc

INTERTEK TESTING SERVICES

EXHIBIT 7
PRODUCT LABELLING

INTERTEK TESTING SERVICES

7.0 **Product Labelling**

For electronic filing, the FCC ID label artwork and location is saved with filename:
label.pdf

INTERTEK TESTING SERVICES

EXHIBIT 8 TECHNICAL SPECIFICATIONS

8.0 Technical Specifications

INTERTEK TESTING SERVICES

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf respectively.

EXHIBIT 9 INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

9.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

Please note that the required FCC Information to the User is saved with filename: fcc information.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

INTERTEK TESTING SERVICES

EXHIBIT 10
SECURITY CODE INFORMATION

INTERTEK TESTING SERVICES

10.0 Security code information

The telephone has an internal security code with 64,000 possible combinations. Each time you pick up the HANDSET, the code is randomly set to a new combination.