



**Technical Report to the FCC
Gentex Corporation**

**Model: UAHL50
FCC ID: NZLUAHL50
ISED: 4112A-UAHL50**

11/8/2022

A report concerning approval for Gentex Corporation model UAHL50
Please issue grant immediately upon review.

Measurements Made by:

Bolay Pannell Digitally signed by Bolay Pannell
Date: 2022.12.08 15:36:15 -05'00'

Bolay Pannell
Laboratory Validation Engineer III
Gentex Corporation

Measurements Reviewed by:

Daniel Brasier Digitally signed by Daniel
Brasier
Date: 2022.12.12 15:50:34
-05'00'

Dan Brasier
Laboratory Development Engineer II
Gentex Corporation

Report Prepared by:

Patricia Klawitter Digitally signed by Patricia
Klawitter
Date: 2022.12.08 15:33:52 -05'00'

Patricia Klawitter
Laboratory Validation Engineer I
Gentex Corporation

Report Approved by:

Jason Vargo Digitally signed by Jason
Vargo Laboratory Lab Manager
I
Date: 2022.12.12 12:19:07
-05'00'

Jason Vargo
Laboratory Manager I
Gentex Corporation

Report Prepared, and Submitted by:

Brian Miller Digitally signed by Brian
Miller
Date: 2022.12.09 10:06:28
-05'00'

Brian Miller
Laboratory Group Leader – Regulatory II
Gentex Corporation

Test Report Revision

REV Number	Date	Author	Description
1.0	11/8/2022	Patricia Klawitter	Initial Release
2.0	12/8/2022	Patricia Klawitter	Revised data table per ACB comments

Results relate only to the items tested as received.

Compliance has been evaluated based on the Lab Manual section 7.6.2. The decision rule used regarding measurement uncertainty was to determine results solely on whether the measured values met the defined acceptance criteria without factoring in measurement uncertainty values.

1. General Information

1.1. Product Description

The Gentex Corporation HomeLink OEM device that is installed into a rearview mirror. The installation is provided by trained technicians during the manufacture of the automobile. It is powered by the 12 Volt system of the automobile.

The unit is supplied to the automobile manufacturer without harness. For testing purposes, a typical assembly and 2-conductor cable harness were used to power to the unit.

The antenna system is an integral part of the unit. It cannot be altered nor replaced by the user. Service of this system is only available from the Automobile Manufacturer's Dealerships and Gentex Corporation.

1.2. Related Grants

This device will have functionality that is covered under 47 CFR Part 15.231 and ISED Canada RSS-210. The device will have FCC ID # of NZLUAHL50 and ISED ID # of 4112A-UAHL50.

1.3. Test Methodology

Radiated Emissions testing was performed according to ANSI C63.4:2014. The power source for this product is a 12V automotive vehicle battery, thus conducted emissions measurements are not required. The DUT was tested by placing it in RX mode with a signal generator transmitting to a loop antenna within proximity of the DUT. The emissions sweeps were performed with the signal generator transmitting a CW signal at the low, mid, and high frequency of the intentional radiator frequency bands.

The unit is supplied to the automobile manufacturer without harness. For testing purposes, a 2-conductor cable harness was used to interface to the unit.

The DUT was tested in receive mode only.

1.4. Test Facility

The 3-meter semi-anechoic chamber where these measurements were taken is located on the grounds of Gentex Corporation's Corporate Labs, in the city of Zeeland, county of Ottawa, state of Michigan, United States of America.

For radiated measurements above 1 GHz, RF absorbing material is placed between the antenna and EUT in accordance with ANSI C63.4:2014 Section 5.5 and chamber manufacturer's instructions.

Tabletop testing was conducted on a 3m turntable described in the site recertification report. The 3m chamber has been added to our A2LA scope of accreditation on 4/18/2019 and includes accreditation to ANSI C63.4:2014, ANSI C63.10:2013, and C63.26:2015. Our 3m chamber is registered with the ISED under Site# 4112A-2 and FCC under registration number 357351.

Corporate Mailing/Shipping Address

Gentex Corporation
600 N. Centennial Street
Zeeland, MI 49464

Site Address

Gentex Corporation
380 Riley Street
Zeeland, MI 49464

1.5. Accreditation

The Gentex Corporate EMC Lab is accredited to ISO/IEC 17025 by the American Association for Laboratory Accreditation (A2LA). Our laboratory scope and accreditation certificate #[2529.01](#) are available from their web site www.a2la.org. Our scope of accreditation covers ANSI C63.4:2014, ANSI C63.10:2013, ANSI C63.26:2015 and Radiated Emissions at 3m, FCC 47 CFR Part 90, ISSED RSS-137.

2. Product Labeling

2.1. Identifiers

The FCC Identifier assigned is FCC ID: NZLUAHL5O. The ISSED certification number is 4112A-UAHL5O. These identifiers will be labeled on the product housing.

The label will be printed on a label, which will be placed on the exterior of the housing and permanently affixed.

Because of the small size of the device and because the installation is inside a portion of the automobile, the following statements will appear in the user's manual. Refer to attachment "Users Manual.pdf" for the entire text of the user's manual.

"The receiver portion of the device complies with FCC rule Part 15. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference,
- (2) This device must accept any interference that may be received including interference that may cause undesired operation.

WARNING: The transmitter has been tested and complies with FCC and ISSED rules. Changes or modifications not expressly approved by the party responsible for the compliance could void the user's authority to operate the device."

This equipment complies with FCC and ISSED radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must be at least 20cm from the user and must not be co-located or operating in conjunction with any other antenna or transmitter.

The term "ISSED:" before the certification/registration number only signifies that ISSED technical specifications were met.

ISSED: 4112A-UAHL5O FCC ID: NZLUAHL5O

2.2. Label Drawing and Location on Product

The label drawing is included in the "Label.pdf" attachment.

A diagram showing the location of the label on the assembly is included in the "Label Location.pdf" attachment.

3. Test Configuration

Radiated Emission measurements presented in the report were made in accordance with ANSI C63.4-2014. The EUT was placed on a 1 x 1.5m non-metallic table elevated 80cm above a conducting ground plane for all measurements. The harness was run straight down from the center of the turntable to a power supply connection sitting at the base of the table. The power supply is located beneath the floor of the chamber.

For radiated measurements above 1 GHz, RF absorbing material is placed between the antenna and EUT in accordance with ANSI C63.4:2014 Section 5.5 and chamber manufacturer's instructions.

4. Conducted Emissions Measurements

Conducted Measurements are not required for this product.

5. Radiated Emissions Data

5.1. Date(s) Tested: 11/4/2022-11/7/2022

5.2. Test Method Deviations: None

5.3. Temperature and Humidity conditions

	Measured Value	Unit
Temperature	25.3	°C
Humidity	36.70	%R.H.

5.4. Summary of Results

Measurement		Margin	Frequency
Worst case Digital Emission	24.06 dBuV/m	15.94 dB	78 MHz

- **Measurement Uncertainty:** The standard uncertainty of measurement has been determined in accordance with the ISO Guide to the Expression of Uncertainty in Measurements. The estimation of measurement uncertainty reported is the expanded uncertainty for a coverage factor of $k=2.26$ and confidence interval of approximately 95%.

Expanded Uncertainty $U_{(k=2.26)}$ is as follows:

- Radiated Emissions – Bicon (30-250 MHz): 4.7 dB
- Radiated Emissions – LPA (250-1000 MHz): 5.6 dB
- Radiated Emissions – DRWG (26.5 GHz): 4.9 dB
- Frequency: 0.12ppm

5.5. Test Equipment Setup and Procedure

5.5.1. Test Equipment Used

Description	Model #	ID Number	Cal Due
EMCO Biconical Antenna [30-250 MHz]	3110B	H6189	5/6/2024
EMCO LPA Antenna [250-1000MHz]	3148	H6192	5/3/2024
Com-Power Double Ridged Waveguide [1-18GHz]	AHA-118	8893	11/25/2024
Rohde & Schwarz EMI Receiver	ESR26	6595	10/11/2023
Cables, attenuator and port feed through	various	CF GCL	4/30/2023
3m Chamber SW	N/A	SW30	3/31/2023
Gentex Emissions SW	N/A	SW48	3/31/2023
Sonoma Pre-Amplifier	310N	273123	12/31/2022
Rohde & Schwarz Signal Generator	SMB100A	6368	9/18/2023

EMI Receiver Settings Emissions:

Detector Function: Quasi-Peak
Resolution Bandwidth: 120 kHz (below 1GHz)
1MHz (above 1GHz)

For the testing, the EUT was placed at the center of a non-conducting table 80cm above the ground plane pursuant to ANSI C63.4:2014 for stand-alone equipment. The 2-conductor harness was run straight down from the center of the turntable to a power supply sitting at the base of the table.

Equipment is placed in one of the three orthogonal orientations, End, Side, and Flat where applicable. The DUT was tested in in-vehicle position only similar to the flat orientation, see test setup photos for details. These orientations are described below in Figure 6.2.1.




Figure 6.2.1 EUT Orthogonal Orientations

While in the prescribed orientation, the vertical antenna positioner sweeps in elevation from 1 to 4m in height until the operator finds the peak. The 3m turntable is then rotated through 360 degrees until a peak is found. The table is stopped at the peak location and the peak in elevation re-verified. Procedure is repeated for applicable orientations/measurement antenna polarizations.

6. Class B Emissions

The transmitter spurious radiation emissions were measured in a 3m semi-anechoic chamber. The design utilizes permanently attached antenna system and offers no provision antenna replacement. The DUT was placed on a turntable elevated as required above the ground plane at a distance of 3 meters from the measurement antenna. For RX mode, emissions sweeps were performed with a loop antenna in proximity of the DUT and connected to a signal generator. An emissions sweep was performed with the signal generator transmitting a CW signal for each low, mid, and high frequency of the intentional radiator frequency range to be certified.

The turntable was rotated through 360 degrees to locate the position registering the maximum amplitude emission. The frequency spectrum was then searched for spurious emissions generated from the transmitter. Raising and lowering the measurement antenna and rotating the turntable to maximize the emission. A Biconical Antenna was used for measuring emissions from for 30-300 MHz, Log Antenna for 300-1000 MHz, and Double Ridge Wave Guide Horn for 1-9 GHz. Emissions were measured in dBuV/m at 3 meters.

Data was taken per 47CFR Part 2.1051 and applicable parts of 47CFR Part 15B. The DUT demonstrated compliance with the specifications of Paragraphs 47CFR 2.1051, 2.1057.

7. Formula and Sample Calculation

The EMI Receiver used for making the measurements in this report automatically corrects for cable correction and antenna factors using values stored in memory taken from the most recent calibration (in the case of antenna factors), periodic cable loss measurements, and preamplifier gain.

Formula 1: $FS(dBuV/m) = M(dBuV) + AF(dB/m) + CF(dB) - AG(dB)$

The presented field strength is computed by the EMI Receiver by taking the measured level and adding to it the antenna factor and cable loss corrections. The measurements presented were gathered using the EMI Receiver's peak-hold capability.

8. Measurement Settings

30 - 200MHz:

Sweep 1: QuasiPeak - 120 kHz

Segment: 1

Start Frequency: 30 MHz

End Frequency: 88 MHz

Band: Band 1

Detector: QuasiPeak

Sweep Mode: FFT

Attenuator: 5 dB

Pre-Amp: Off

Max Hold Trace Mode: Off

Bandwidth Filter: EMI (6dB)

RBW: 120 kHz

Step Size: AUTO (30 kHz)

Dwell Time: 1000ms

Sweep 1: QuasiPeak - 120 kHz

Segment: 2

Start Frequency: 88 MHz

End Frequency: 200 MHz

Band: Band 2

Detector: QuasiPeak

Sweep Mode: FFT

Attenuator: 5 dB

Pre-Amp: Off

Max Hold Trace Mode: Off

Bandwidth Filter: EMI (6dB)

RBW: 120 kHz

Step Size: AUTO (30 kHz)

Dwell Time: 1000ms

200 - 1000MHz:

Sweep 1: QuasiPeak - 120 kHz

Segment: 1

Start Frequency: 200 MHz

End Frequency: 216 MHz

Band: Band 2

Detector: QuasiPeak

Sweep Mode: FFT

Attenuator: 5 dB

Pre-Amp: Off

Max Hold Trace Mode: Off

Bandwidth Filter: EMI (6dB)

RBW: 120 kHz

Step Size: AUTO (30 kHz)

Dwell Time: 1000ms

Sweep 1: QuasiPeak - 120 kHz

Segment: 2

Start Frequency: 216 MHz

End Frequency: 960 MHz

Band: Band 3

Detector: QuasiPeak

Sweep Mode: FFT

Attenuator: 5 dB

Pre-Amp: Off

Max Hold Trace Mode: Off

Bandwidth Filter: EMI (6dB)

RBW: 120 kHz

Step Size: AUTO (30 kHz)

Dwell Time: 1000ms

Sweep 1: QuasiPeak - 120 kHz

Segment: 3

Start Frequency: 960 MHz

End Frequency: 1000 MHz

Band: Band 4

Detector: QuasiPeak

Sweep Mode: FFT

Attenuator: 5 dB

Pre-Amp: Off

Max Hold Trace Mode: Off

Bandwidth Filter: EMI (6dB)

RBW: 120 kHz

Step Size: AUTO (30 kHz)

Dwell Time: 1000ms

1000-5000MHz:

Sweep 2: CISPR Average - 1000 kHz

Segment: 1

Start Frequency: 1000 MHz

End Frequency: 5000 MHz

Band: Band 5

Detector: CISPR Average

Sweep Mode: FFT

Attenuator: 5 dB

Pre-Amp: Off

Max Hold Trace Mode: Off

Bandwidth Filter: EMI (6dB)

RBW: 1000 kHz

Step Size: AUTO (250 kHz)

Dwell Time: 5ms

GENTEX CORPORATION

Test Mode	Detector	Frequency (MHz)		Worst-Case Orientation	Antenna Polarization	Frequencies (MHz)	Emission (dBuV/m)	Limit (dBuV/m)	Margin (dB)
		Start	Stop						
RX	Quasi-Peak	30	88	Flat	V	54	11.4	40	-28.6
RX	Quasi-Peak	30	88	Side	V	66	20.29	40	-19.71
RX	Quasi-Peak	30	88	Flat	V	74.55	21.76	40	-18.24
RX	Quasi-Peak	30	88	Flat	V	77.19	24	40	-16
RX	Quasi-Peak	30	88	Flat	V	78	24.06	40	-15.94
RX	Quasi-Peak	30	88	Flat	V	81	21.62	40	-18.38
RX	Quasi-Peak	88	216	Flat	V	89	21.75	43.5	-21.75
RX	Quasi-Peak	88	216	Side	V	90	15.67	43.5	-27.83
RX	Quasi-Peak	88	216	Flat	V	141	10.96	43.5	-32.54
RX	Quasi-Peak	216	1000	Flat	V	250	10.96	46	-35.04
RX	Quasi-Peak	216	1000	Side	H	312	19.53	46	-26.47
RX	Quasi-Peak	216	1000	End	V	400	21.77	46	-24.23
RX	Quasi-Peak	216	1000	End	V	480	22.1	46	-23.9
RX	Quasi-Peak	216	1000	Side	V	500	27.12	46	-18.88
RX	Quasi-Peak	216	1000	End	V	528	20.09	46	-25.91
RX	Quasi-Peak	216	1000	End	V	552	21.15	46	-24.85
RX	Quasi-Peak	216	1000	End	V	576	22.14	46	-23.86
RX	Quasi-Peak	216	1000	End	V	600	20.22	46	-25.78
RX	Quasi-Peak	216	1000	End	V	730	19.73	46	-26.27
RX	Quasi-Peak	216	1000	Side	V	750	27.2	46	-18.8
RX	Quasi-Peak	216	1000	Flat	V	827.5	20.7	46	-25.3
RX	Quasi-Peak	216	1000	Side	V	937.5	24.38	46	-21.62
RX	Peak	1000	5000	Side	V	1062	22.76	74	-51.24
RX	Peak	1000	5000	Flat	V	1101	15.99	74	-58.01
RX	Peak	1000	5000	Flat	V	1200	24.04	74	-49.96
RX	Peak	1000	5000	Flat	V	1248	22.79	74	-51.21
RX	Peak	1000	5000	Flat	V	1562.5	24.72	74	-49.28
RX	Peak	1000	5000	Side	V	1812.5	23.48	74	-50.52
RX	Peak	1000	5000	Flat	V	2000	24.78	74	-49.22
RX	Peak	1000	5000	Side	H	4421.25	36.49	74	-37.51
RX	Average	1000	5000	Side	V	1062	18.83	54	-35.17
RX	Average	1000	5000	Flat	V	1101	9	54	-45
RX	Average	1000	5000	Flat	V	1200	20.61	54	-33.39
RX	Average	1000	5000	Flat	V	1248	19.58	54	-34.42
RX	Average	1000	5000	Flat	V	1562.5	19.7	54	-34.3
RX	Average	1000	5000	Side	V	1812.5	18.56	54	-35.44
RX	Average	1000	5000	Flat	V	2000	19.77	54	-34.23
RX	Average	1000	5000	Side	H	4421.25	29.52	54	-24.48