


14.2 BLOCK DIAGRAM OF TEST SETUP



14.3 PROCEDURE

- For below 1GHz, the EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 or 10 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.
- For above 1GHz, the EUT was placed on the top of a rotating table 1.5 meters above the ground at a 3 meter fully-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.
- The EUT was set 3 or 10 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
- The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.
- If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

- h. Test the EUT in the lowest channel, the middle channel, the Highest channel.
- i. The radiation measurements are performed in X, Y, Z axis positioning for Transmitting mode, and found the X axis positioning which it is the worst case.
- j. Repeat above procedures until all frequencies measured was complete.


Remark 1: $\text{Level} = \text{Read Level} + \text{Cable Loss} + \text{Antenna Factor} - \text{Preamp Factor}$

Remark 2: For frequencies above 1GHz, the field strength limits are based on average limits. However, the peak field strength of any emission shall not exceed the maximum permitted average limits specified above by more than 20 dB under any condition of modulation. For the emissions whose peak level is lower than the average limit, only the peak measurement is shown in the report.

14.4 TEST DATA

Remark: During the test, pre-scan the BLE 1M, BLE 2M, and found the BLE 1M which it is worse case.

[TestMode: TX low channel]; [Polarity: Horizontal]




*:Maximum data x:Over limit !:over margin (Reference Only)

Receiver: ESR_1 Spectrum Analyzer: FSP40

Antenna: EZ 9120D 1G-18G Engineer Signature:

Test Result: Pass

[TestMode: TX low channel]; [Polarity: Vertical]




Site	Polarization: Vertical	Temperature: (C)
Limit: FCC Part15 (PK)	Power:	Humidity: %RH
EUT: TLSR9528BDK104D		
M/N: TLSR9528BDK104D		
Mode: TX-2402		
Note:		

No. Mk.	Freq.	Reading Level	Correct Factor	Measure-ment	Limit	Over		
	MHz	dBuV	dB	dBuV/m	dBuV/m	dB	Detector	Comment
1	2310.000	41.24	-2.89	38.35	74.00	-35.65	peak	
2 *	2353.985	45.80	-2.78	43.02	74.00	-30.98	peak	
3	2390.000	42.95	-2.70	40.25	74.00	-33.75	peak	

*:Maximum data x:Over limit !:over margin				(Reference Only)	
Receiver:	ESR_1	Spectrum Analyzer:	FSP40		
Antenna:	EZ 9120D 1G-18G	Engineer Signature:			

Test Result: Pass

[TestMode: TX high channel]; [Polarity: Horizontal]




*:Maximum data x:Over limit !:over margin (Reference Only)

Receiver: ESR_1 Spectrum Analyzer: FSP40
Antenna: EZ 9120D 1G-18G Engineer Signature:

Test Result: Pass

[TestMode: TX high channel]; [Polarity: Vertical]



*:Maximum data x:Over limit !:over margin (Reference Only)

Receiver: ESR_1 Spectrum Analyzer: FSP40
Antenna: EZ 9120D 1G-18G Engineer Signature:

Test Result: Pass

Remark:

1. Final Level = Receiver Read level + Correct factor
2. Correct factor = Antenna Factor + Cable Loss – Preamplifier Factor
3. The emission levels of other frequencies are very lower than the limit and not show in test report.

BlueAsia


15 CONDUCTED SPURIOUS EMISSIONS

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	ANSI C63.10 (2013) Section 7.8.6 & Section 11.11
Test Mode (Pre-Scan)	TX
Test Mode (Final Test)	TX
Tester	Jozu
Temperature	25°C
Humidity	60%

15.1 LIMITS

Limit:	In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.209(a) (see §15.205(c)).
---------------	--

15.2 BLOCK DIAGRAM OF TEST SETUP



15.3 TEST DATA

Pass: Please Refer To Appendix: Appendix1 For Details


16 POWER SPECTRUM DENSITY

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	ANSI C63.10 (2013) Section 11.10.2
Test Mode (Pre-Scan)	TX
Test Mode (Final Test)	TX
Tester	Jozu
Temperature	25°C
Humidity	60%

16.1 LIMITS

Limit: $\leq 8\text{dBm}$ in any 3 kHz band during any time interval of continuous transmission

16.2 BLOCK DIAGRAM OF TEST SETUP



16.3 TEST DATA

Pass: Please Refer To Appendix: Appendix1 For Details


17 CONDUCTED PEAK OUTPUT POWER

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	ANSI C63.10 (2013) Section 7.8.5
Test Mode (Pre-Scan)	TX
Test Mode (Final Test)	TX
Tester	Jozu
Temperature	25°C
Humidity	60%

17.1 LIMITS

Frequency range(MHz)	Output power of the intentional radiator(watt)
902-928	1 for ≥ 50 hopping channels
	0.25 for $25 \leq \text{hopping channels} < 50$
	1 for digital modulation
2400-2483.5	1 for ≥ 75 non-overlapping hopping channels
	0.125 for all other frequency hopping systems
	1 for digital modulation
5725-5850	1 for frequency hopping systems and digital modulation

17.2 BLOCK DIAGRAM OF TEST SETUP



17.3 TEST DATA

Pass: Please Refer To Appendix: Appendix1 For Details


18 MINIMUM 6DB BANDWIDTH

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	ANSI C63.10 (2013) Section 11.8.1
Test Mode (Pre-Scan)	TX
Test Mode (Final Test)	TX
Tester	Jozu
Temperature	25℃
Humidity	60%

18.1 LIMITS

Limit:	≥ 500 kHz
--------	----------------

18.2 BLOCK DIAGRAM OF TEST SETUP



18.3 TEST DATA

Pass: Please Refer To Appendix: Appendix1 For Details

19 ANTENNA REQUIREMENT

Test Standard	47 CFR Part 15, Subpart C 15.247
Test Method	N/A

19.1 CONCLUSION

15.203 requirement:

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator, the manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited.

15.247(c) (1)(i) requirement:

(i) Systems operating in the 2400-2483.5 MHz band that is used exclusively for fixed. Point-to-point operations may employ transmitting antennas with directional gain greater than 6dBi provided the maximum conducted output power of the intentional radiator is reduced by 1 dB for every 3 dB that the directional gain of the antenna exceeds 6dBi.

Evaluation Information:

Product uses uniquely coupled antenna with intentional radiator, detachable non-standard jack antenna, it is reverse polarity, connector is RP-SMA, female screw. full the requirement of this section.

EUT Antenna:

The best case gain of the antenna is 3dBi.




20 APPENDIX1


Maximum Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	4.714	30	Pass
NVNT	BLE 1M	2442	Ant1	4.099	30	Pass
NVNT	BLE 1M	2480	Ant1	4.671	30	Pass
NVNT	BLE 2M	2402	Ant1	4.72	30	Pass
NVNT	BLE 2M	2442	Ant1	3.889	30	Pass
NVNT	BLE 2M	2480	Ant1	4.43	30	Pass


Power NVNT BLE 1M 2402MHz Ant1




Power NVNT BLE 1M 2442MHz Ant1




Power NVNT BLE 1M 2480MHz Ant1




Power NVNT BLE 2M 2402MHz Ant1



Power NVNT BLE 2M 2442MHz Ant1




Power NVNT BLE 2M 2480MHz Ant1




-6dB Bandwidth

Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	BLE 1M	2402	Ant1	0.663	0.5	Pass
NVNT	BLE 1M	2442	Ant1	0.663	0.5	Pass
NVNT	BLE 1M	2480	Ant1	0.698	0.5	Pass
NVNT	BLE 2M	2402	Ant1	1.35	0.5	Pass
NVNT	BLE 2M	2442	Ant1	1.378	0.5	Pass
NVNT	BLE 2M	2480	Ant1	1.377	0.5	Pass


-6dB Bandwidth NVNT BLE 1M 2402MHz Ant1




-6dB Bandwidth NVNT BLE 1M 2442MHz Ant1




-6dB Bandwidth NVNT BLE 1M 2480MHz Ant1




-6dB Bandwidth NVNT BLE 2M 2402MHz Ant1



-6dB Bandwidth NVNT BLE 2M 2442MHz Ant1




-6dB Bandwidth NVNT BLE 2M 2480MHz Ant1




Occupied Channel Bandwidth

Condition	Mode	Frequency (MHz)	Antenna	99% OBW (MHz)
NVNT	BLE 1M	2402	Ant1	1.0334
NVNT	BLE 1M	2442	Ant1	1.0173
NVNT	BLE 1M	2480	Ant1	1.0223
NVNT	BLE 2M	2402	Ant1	2.0259
NVNT	BLE 2M	2442	Ant1	2.0186
NVNT	BLE 2M	2480	Ant1	2.0200


OBW NVNT BLE 1M 2402MHz Ant1




OBW NVNT BLE 1M 2442MHz Ant1




OBW NVNT BLE 1M 2480MHz Ant1




OBW NVNT BLE 2M 2402MHz Ant1



OBW NVNT BLE 2M 2442MHz Ant1




OBW NVNT BLE 2M 2480MHz Ant1




Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Max PSD (dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	-7.008	8	Pass
NVNT	BLE 1M	2442	Ant1	-7.97	8	Pass
NVNT	BLE 1M	2480	Ant1	-4.838	8	Pass
NVNT	BLE 2M	2402	Ant1	-9.086	8	Pass
NVNT	BLE 2M	2442	Ant1	-10.195	8	Pass
NVNT	BLE 2M	2480	Ant1	-9.696	8	Pass


PSD NVNT BLE 1M 2402MHz Ant1




PSD NVNT BLE 1M 2442MHz Ant1




PSD NVNT BLE 1M 2480MHz Ant1




PSD NVNT BLE 2M 2402MHz Ant1



PSD NVNT BLE 2M 2442MHz Ant1




PSD NVNT BLE 2M 2480MHz Ant1




Band Edge

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-58.96	-20	Pass
NVNT	BLE 1M	2480	Ant1	-60.12	-20	Pass
NVNT	BLE 2M	2402	Ant1	-58.55	-20	Pass
NVNT	BLE 2M	2480	Ant1	-56.13	-20	Pass

Band Edge NVNT BLE 1M 2402MHz Ant1 Ref



Band Edge NVNT BLE 1M 2402MHz Ant1 Emission



Band Edge NVNT BLE 1M 2480MHz Ant1 Ref



Band Edge NVNT BLE 1M 2480MHz Ant1 Emission