

Band: GSM850								
ENV	Mode		Frequency (MHz)	Conducted Power (dBm)	Gain (dbi)	ERP (dBm)		Verdict
	Network	Subset				Result	Limit	
NTNV	GPRS	1 TX Slot	824.2	31.97	-2.90	26.92	<=38.45	Pass
		2 TX Slots	824.2	30.89	-2.90	25.84	<=38.45	Pass
		3 TX Slots	824.2	29.06	-2.90	24.01	<=38.45	Pass
		4 TX Slots	824.2	28.14	-2.90	23.09	<=38.45	Pass
		1 TX Slot	836.6	32.07	-2.90	27.02	<=38.45	Pass
		2 TX Slots	836.6	31.03	-2.90	25.98	<=38.45	Pass
		3 TX Slots	836.6	29.17	-2.90	24.12	<=38.45	Pass
		4 TX Slots	836.6	28.23	-2.90	23.18	<=38.45	Pass
		1 TX Slot	848.8	32.36	-2.90	27.31	<=38.45	Pass
		2 TX Slots	848.8	31.31	-2.90	26.26	<=38.45	Pass
		3 TX Slots	848.8	29.45	-2.90	24.40	<=38.45	Pass
		4 TX Slots	848.8	28.51	-2.90	23.46	<=38.45	Pass
	EGPRS	1 TX Slot	824.2	26.73	-2.90	21.68	<=38.45	Pass
		2 TX Slots	824.2	27.53	-2.90	22.48	<=38.45	Pass
		3 TX Slots	824.2	24.26	-2.90	19.21	<=38.45	Pass
		4 TX Slots	824.2	23.27	-2.90	18.22	<=38.45	Pass
		1 TX Slot	836.6	26.30	-2.90	21.25	<=38.45	Pass
		2 TX Slots	836.6	26.31	-2.90	21.26	<=38.45	Pass
		3 TX Slots	836.6	23.98	-2.90	18.93	<=38.45	Pass
		4 TX Slots	836.6	23.08	-2.90	18.03	<=38.45	Pass
		1 TX Slot	848.8	26.78	-2.90	21.73	<=38.45	Pass
		2 TX Slots	848.8	26.22	-2.90	21.17	<=38.45	Pass
		3 TX Slots	848.8	24.63	-2.90	19.58	<=38.45	Pass
		4 TX Slots	848.8	23.63	-2.90	18.58	<=38.45	Pass

Band: PCS1900								
ENV	Mode		Frequency (MHz)	Conducted Power (dBm)	Gain (dbi)	EIRP (dBm)		Verdict
	Network	Subset				Result	Limit	
NTNV	GPRS	1 TX Slot	1850.2	27.64	-0.40	27.24	<=33.01	Pass
		2 TX Slots	1850.2	26.69	-0.40	26.29	<=33.01	Pass
		3 TX Slots	1850.2	24.76	-0.40	24.36	<=33.01	Pass
		4 TX Slots	1850.2	23.84	-0.40	23.44	<=33.01	Pass
		1 TX Slot	1880	27.92	-0.40	27.52	<=33.01	Pass
		2 TX Slots	1880	26.88	-0.40	26.48	<=33.01	Pass
		3 TX Slots	1880	24.86	-0.40	24.46	<=33.01	Pass
		4 TX Slots	1880	23.95	-0.40	23.55	<=33.01	Pass
		1 TX Slot	1909.8	27.89	-0.40	27.49	<=33.01	Pass
		2 TX Slots	1909.8	26.80	-0.40	26.40	<=33.01	Pass
		3 TX Slots	1909.8	24.70	-0.40	24.30	<=33.01	Pass
		4 TX Slots	1909.8	23.79	-0.40	23.39	<=33.01	Pass
	EGPRS	1 TX Slot	1850.2	26.53	-0.40	26.13	<=33.01	Pass
		2 TX Slots	1850.2	25.90	-0.40	25.50	<=33.01	Pass
		3 TX Slots	1850.2	23.86	-0.40	23.46	<=33.01	Pass
		4 TX Slots	1850.2	22.67	-0.40	22.27	<=33.01	Pass
		1 TX Slot	1880	26.87	-0.40	26.47	<=33.01	Pass
		2 TX Slots	1880	26.01	-0.40	25.61	<=33.01	Pass
		3 TX Slots	1880	23.99	-0.40	23.59	<=33.01	Pass
		4 TX Slots	1880	22.69	-0.40	22.29	<=33.01	Pass
1 TX Slot		1909.8	26.19	-0.40	25.79	<=33.01	Pass	
2 TX Slots		1909.8	25.64	-0.40	25.24	<=33.01	Pass	
3 TX Slots		1909.8	23.68	-0.40	23.28	<=33.01	Pass	
4 TX Slots		1909.8	22.05	-0.40	21.65	<=33.01	Pass	
Note1: EIRP=Conducted Power+Antenna Gain								