

MEASUREMENT/TECHNICAL REPORT

Company: Interflex N.A., Inc.

FRN: 0006-6303-47

Models

IF P600

IF P603

FCC ID: P8KPXFB

Description: This is a report to support a Class II permissive change.

Equipment Type: Low Power Communications Device Transmitter (DXX)

Report prepared for:

Interflex, Inc.
20 Dolphin Road
P.O. Box 9338
Forestville, CT 06011-9338
Phone: 860-582-8300
Fax: 860-582-8304

Report prepared by:

Evan D. Gould
Curtis-Straus LLC
527 Great Road
Littleton, MA 01460 USA
Phone: 978-486-8880
FAX: 978-486-8828

Introduction

This report is designed to demonstrate the continued compliance of the IF P600 and IF P603 in light of alternative mounting configurations.

Test Methodology

Radiated emission testing was performed according to the procedures in ANSI C63.4 (1992). The testing was performed at an antenna to EUT distance of 3 meters. The device's performance was investigated to 1GHz. The EUT was powered by a 24V DC power supply. Since the device is installed in one orientation, the emissions were maximized around the vertical axis and the maximum reading was recorded. The integrated antenna cannot be maximized separately.

Test Facility

Curtis-Straus LLC

All testing for the range 9kHz–1000MHz was performed at Curtis-Straus (A2LA Certificate Number 1627-01). The open area test site used to collect the radiated data is located at 527 Great Road, Littleton, MA 01460. Site "F" was used.

Test Equipment

SPECTRUM ANALYZERS					
x	Analyzer	Model No.	Company	Serial No.	Calibration Due
X	YELLOW 9kHz-2.9GHz	8594E	HP	3523A01958	03-JUL-2003

OPEN AREA TEST SITES (OATS)					
x	Site	FCC Code	IC Code	VCCI Code	Calibration Due
X	"F" Florida	93448	IC 2762-F	R-468/ C-480	04-FEB-2004

ANTENNAS					
x	Antenna	Model No.	Company	Serial No.	Calibration Due
X	GREEN-WHITE Bilog: 30MHz-2GHz	CBL6112B	Chase	2574	28-JUL-2002
X	LARGE LOOP Passive Loop: 20Hz-5MHz	6511	EMCO	9704-1154	05-NOV-2003

PREAMPLIFIERS / ATTENUATORS					
x	Preamplifier	Model No.	Company	Serial No.	Calibration Due
X	RED 0.10-2000MHz	ZFL-1000-LN	MiniCircuits/ C-S	n/a	22-MAR-2003

Unless otherwise noted the calibration interval is one year. All equipment is calibrated using standards traceable to NIST or other nationally recognized calibration standard.

Measurement Results

Operating Frequency

These devices operate at 125kHz.

Electric Field Strength Radiation Measurements

Radiated Emissions Table							Curtis-Straus LLC		
Date: 09-Jul-02			Company: Interflex				Table 1		
Engineer: Evan Gould			EUT Desc: IF P600				Work Order: C0541		
Frequency Range: 10kHz-5MHz					Measurement Distance: 3 m				
Notes: communicating with the IF 1070; new mounting box					EUT Min Freq: 16MHz				
					Analyzer: Yellow				
Antenna Polarization (0° - 90°)	Frequency (MHz)	Reading (dBμV)	Preamp Factor (dB)	Antenna Factor (dB/m)	Cable Factor (dB)	Adjusted Reading (dBμV/m)	47 CFR 15.209		
							Limit (dBμV/m)	Margin (dB)	Result (Pass/Fail)
0	0.1254	64.4	21.7	51.9	0.0	94.6	105.6	-11.0	Pass
0	0.25	14.3	22.0	51.2	0.0	43.5	99.6	-56.1	Pass
0	0.3756	34.9	22.0	50.8	0.0	63.7	96.1	-32.4	Pass
0	0.5	8.4	22.1	50.6	0.0	36.9	73.6	-36.7	Pass
0	0.626	29.5	22.1	50.4	0.0	57.8	71.6	-13.8	Pass
0	0.75	12.2	22.1	50.3	0.0	40.4	70.1	-29.7	Pass
0	0.8757	21.7	22.0	50.1	0.0	49.8	68.7	-18.9	Pass
0	1.0	26.6	22.0	50.0	0.0	54.6	67.6	-13.0	Pass
0	1.125	28.6	22.0	49.8	0.0	56.4	66.5	-10.1	Pass
0	1.252	21.6	22.0	49.6	0.0	49.2	65.6	-16.4	Pass
Table Result: Pass by -10.1 dB Worst Freq: 1.125 MHz									
Test Site: "F"		Pre-Amp: Red		Cable: 65 ft RG8A/U			Antenna: Lg Loop		

Radiated Emissions Table							Curtis-Straus LLC		
Date: 09-Jul-02			Company: Interflex				Table 2		
Engineer: Evan Gould			EUT Desc: IF P603				Work Order: C0541		
Frequency Range: 10kHz-5MHz				Measurement Distance: 3 m					
Notes: communicating with the IF 1070; new mounting box				EUT Min Freq: 16MHz					
							Analyzer: Yellow		
Antenna Polarization (0° - 90°)	Frequency (MHz)	Reading (dBμV)	Preamp Factor (dB)	Antenna Factor (dB/m)	Cable Factor (dB)	Adjusted Reading (dBμV/m)	47 CFR 15.209		
							Limit (dBμV/m)	Margin (dB)	Result (Pass/Fail)
0	0.1254	64.0	21.7	51.9	0.0	94.2	105.6	-11.4	Pass
0	0.25	16.0	22.0	51.2	0.0	45.2	99.6	-54.4	Pass
0	0.3756	35.5	22.0	50.8	0.0	64.3	96.1	-31.8	Pass
0	0.5	9.5	22.1	50.6	0.0	38.0	73.6	-35.6	Pass
0	0.626	31.5	22.1	50.4	0.0	59.8	71.6	-11.8	Pass
0	0.75	13.0	22.1	50.3	0.0	41.2	70.1	-28.9	Pass
0	0.8757	22.1	22.0	50.1	0.0	50.2	68.7	-18.5	Pass
0	1.0	25.8	22.0	50.0	0.0	53.8	67.6	-13.8	Pass
0	1.125	29.3	22.0	49.8	0.0	57.1	66.5	-9.4	Pass
0	1.252	22.1	22.0	49.6	0.0	49.7	65.6	-15.9	Pass
Table Result: Pass by -9.4 dB Worst Freq: 1.125 MHz									
Test Site: "F"		Pre-Amp: Red		Cable: 65 ft RG8A/U			Antenna: Lg Loop		

Radiated Emissions Table							Curtis-Straus LLC		
Date: 09-Jul-02			Company: Interflex				Table 3		
Engineer: Evan Gould			EUT Desc: IF P600 & IF P603				Work Order: C0541		
Frequency Range: 30-1000MHz				Measurement Distance: 3 m					
Notes: communicating with the IF 1070; new mounting box				EUT Max Freq: 16MHz					
							Analyzer: Yellow		
Antenna Polarization (H / V)	Frequency (MHz)	Reading (dBμV)	Preamp Factor (dB)	Antenna Factor (dB/m)	Cable Factor (dB)	Adjusted Reading (dBμV/m)	47 CFR 15.209		
							Limit (dBμV/m)	Margin (dB)	Result (Pass/Fail)
V	30.8	40.7	22.0	17.5	0.4	36.6	40.0	-3.4	Pass
V	31.0	38.8	22.0	17.4	0.4	34.6	40.0	-5.4	Pass
V	32.0	41.9	22.0	16.9	0.4	37.2	40.0	-2.8	Pass
V	49.3	49.0	22.1	8.0	0.5	35.4	40.0	-4.6	Pass
V	60.5	47.5	22.0	5.1	0.6	31.2	40.0	-8.8	Pass
V	75.5	45.2	22.0	6.0	0.7	29.9	40.0	-10.1	Pass
V	91.9	54.0	22.1	9.1	0.8	41.8	43.5	-1.7	Pass
V	110.6	40.2	22.2	11.1	1.0	30.1	43.5	-13.4	Pass
V	121.0	43.0	22.2	11.7	1.0	33.5	43.5	-10.0	Pass
Only IF P600 powered			---	---	---	---	---	---	---
V	68.5	47.9	22.0	5.0	0.7	31.6	40.0	-8.4	Pass
V	68.2	49.4	22.0	5.0	0.7	33.1	40.0	-6.9	Pass
V 30kHzBWpk	92.3	48.5	22.1	9.2	0.8	36.4	43.5	-7.1	Pass
Only IF P603 powered			---	---	---	---	---	---	---
V	68.6	47.2	22.0	5.0	0.7	30.9	40.0	-9.1	Pass
V 30kHzBWpk	92.3	47.3	22.1	9.2	0.8	35.2	43.5	-8.3	Pass
Table Result: Pass by -1.7 dB Worst Freq: 91.9 MHz									
Test Site: "F"		Pre-Amp: Red		Cable: 65 ft RG8A/U			Antenna: Grn-Wht		

Note: When using the installation configuration for which this report was written, it is no longer necessary to install a ferrite (Fair-Rite #0431164951; Interflex p/n: FRP0003) on the ribbon cable between the MPU board and the connector board.

Setup Photos



IF P600



IF P630