



FCC MPE Report

RF Solutions LAMDA Module FCC ID P9OLAMDA9

Document No: TCFs385

Document Control			
Iss 1	10 th September 2018	First release	NDB
Iss 2	30 th October 2018	Remove Appendix	NDB

All the information contained within this document is "commercial in confidence" and may not be viewed, copied or distributed unless authorised to do so by TCFs

ALL Rights Reserved

FCC MPE Report: **Lamda9**



Table of Contents

1.	General information	3
2.	Typical brief product specification	3
3.	FCC Radiofrequency radiation limits	3
4.	Filed Antenna	3
5.	Test Results	3
6.	EMF Exposure Levels Calculated	4
7.	Additional information	4

FCC MPE Report:

Lamda9



Equipment : Lora Type Module
Model No. : Lamda9
FCC ID : P90LAMDA9
Manufacturer: RF Solutions Limited
William Alexander House
William Way
Burgess Hill
RH15 9AG
UK
Tel: +44 (0)1444 227910
Website: www.rfsolutions.co.uk

1. General information

The RF Solutions Lamda9 is a Lora based module, operating in the 902 – 928MHz frequency band. The module is a single frequency centred on 915MHz.

2. Typical brief product specification

Frequency: 915MHz
Transmit power: +13 dBm
Power supply: 3.3 volt
Operating temperature range: Commercial 0°C to +55°C
Storage temperature range: Commercial -25°C to +65°C
Dimensions: 19.95 x 26.95mm (not including antenna)

3. FCC Radiofrequency radiation limits

Frequency	Power density (mW/cm ²)	Averaging time (minutes)
300MHz – 1.5GHz	f/1500	30
1.5GHz – 100GHz	1.0	30

4. Filed Antenna

Maximum gain of the supplied antenna is unity (1dBi). Any antenna used that has a gain of more than 1dBi is not approved for use with this module, as explained in the user manual. See Annex A.

5. Test Results

The maximum output power as 16.7dBm as stated in the FCC Part 15C test report Number: 18R084 FR.

6. EMF Exposure Levels Calculated

The field calculation does not take into account the antenna size, which is assumed to be a point source. An ideal isotropic antenna is used as a reference to compare the performance of practical antennas: P watts is radiated, from a point, uniformly over the surface of sphere of radius r. The POINTING VECTOR gives the power density: Assumed use distance from EUT to Human, 0.2m separation distance warning is required. In this section, the power density at 0.2m location is calculated to examine if it is lower than the limit.

$$E \text{ (V/m)} = \sqrt{30 \times P \times G}$$

$$\text{Power Density: } Pd \text{ (W/m}^2\text{)} = E^2 / 377$$

E = Electric field (V/m)

P = Peak RF output power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (0.2m) *

The formula can be changed to

$$Pd = 30 \times P \times G / 377 \times d^2$$

From the peak EUT RF output power, the minimum mobile separation distance, d=0.2m, as well as the gain of the used antenna, the RF power density can be obtained.

Operating Frequency (MHz)	Max EIRP Average Output Power (dBm)	Max EIRP Average Output Power (W)	Power Density (mW/cm ²)	Limit of Power Density (mW/cm ²)	
915	16.7	0.047	0.0122	0.61	Pass

* Operating distance must be greater than 20cm for any person.

7. Additional information

Disclaimer

TCFs do not accept any legal responsibility for the content of this report and it is assumed that the use of any of the information supplied is taken as such. The content of this report does not form any legally binding contract between TCFs and the client. Using the information supplied in this report, in part or in full, may not guarantee a specific product will be legally entitled to be marketed in any specific country. This disclaimer shall be governed by and construed in accordance with the laws of England and Wales under the exclusive jurisdiction of the courts of England and Wales.

Statement

The test result in this report refers exclusively to the presented test model / sample test results provided. Without written approval of TCFs, the test report shall not be reproduced except in full.

END