

MPE Exposure Formula:

$$S = (P \times G) / (4 \times \pi \times d^2)$$

where:

S = power density

P = transmitter conducted power in (mW)

G = antenna numeric gain

d = distance to radiation center (m) or $(.02^2) = .020$ m

2412 MHz (802.11b)

Enter Data in Linear Units					
Gain =	1.3	Numeric	EUT ant.:	1	dBi
Power =	100	mW	EUT power:	20	dBm
Frequency =	2412	MHz	MPE limit:	1	mW/cm ²
Cable Loss =	0	dB			
EIRP =	125.89	mW		125.89	mW
R (cm) =	3.1651556		S (20cm) =	0.025	

2437 MHz (802.11b)

Enter Data in Linear Units					
Gain =	1.3	Numeric	EUT ant.:	1	dBi
Power =	398	mW	EUT power:	26	dBm
Frequency =	915	MHz	MPE limit:	1	mW/cm ²
Cable Loss =	0	dB			
EIRP =	501.19	mW		501.19	mW
R (cm) =	6.3153157		S (20cm) =	0.100	

2462 MHz (802.11b)

Enter Data in Linear Units					
Gain =	1.3	Numeric	EUT ant.:	1	dBi
Power =	100	mW	EUT power:	20	dBm
Frequency =	927	MHz	MPE limit:	1	mW/cm ²
Cable Loss =	0	dB			
EIRP =	125.89	mW		125.89	mW
R (cm) =	3.1651556		S (20cm) =	0.025	

2412 MHz (802.11g)

Enter Data in Linear Units					
Gain =	1.3	Numeric	EUT ant.:	1	dBi
Power =	200	mW	EUT power:	23	dBm
Frequency =	902	MHz	MPE limit:	1	mW/cm ²
Cable Loss =	0	dB			
EIRP =	251.19	mW		251.19	mW
R (cm) =	4.4709012		S (20cm) =	0.050	

2437 MHz (802.11g)

Enter Data in Linear Units					
Gain =	1.3	Numeric	EUT ant.:	1	dBi
Power =	398	mW	EUT power:	26	dBm
Frequency =	915	MHz	MPE limit:	1	mW/cm ²
Cable Loss =	0	dB			
EIRP =	501.19	mW		501.19	mW
R (cm) =	6.3153157		S (20cm) =	0.100	

2462 MHz (802.11g)

Enter Data in Linear Units					
Gain =	1.3	Numeric	EUT ant.:	1	dBi
Power =	200	mW	EUT power:	23	dBm
Frequency =	927	MHz	MPE limit:	1	mW/cm ²
Cable Loss =	0	dB			
EIRP =	251.19	mW		251.19	mW
R (cm) =	4.4709012		S (20cm) =	0.050	