



FCC RADIO TEST REPORT

FCC ID : PKRISGM3000A
Equipment : M3000A
Brand Name : Inseego
Model Name : M3000A
Marketing Name : M3000
Applicant : Inseego Corp.
9710 Scranton Road Suite 200, San
Diego,, CA 92121
Manufacturer : Inseego Corp.
9710 Scranton Road Suite 200, San
Diego,, CA 92121
Standard : FCC 47 CFR Part 2, 22(H), 24(E), 27

The product was received on Mar. 17, 2022 and testing was performed from Apr. 11, 2022 to Jun. 16, 2022. We, Sporton International Inc. EMC & Wireless Communications Laboratory, would like to declare that the tested sample has been evaluated in accordance with the test procedures given in ANSI / TIA-603-E and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. EMC & Wireless Communications Laboratory, the test report shall not be reproduced except in full.

Approved by: Louis Wu

Sporton International Inc. EMC & Wireless Communications Laboratory

No. 52, Huaya 1st Rd., Guishan Dist., Taoyuan City 333, Taiwan (R.O.C.)



Table of Contents

History of this test report.....	3
Summary of Test Result.....	4
1 General Description	6
1.1 Product Feature of Equipment Under Test.....	6
1.2 Modification of EUT	6
1.3 Testing Location	7
1.4 Applicable Standards.....	7
2 Test Configuration of Equipment Under Test	8
2.1 Test Mode.....	8
2.2 Connection Diagram of Test System.....	13
2.3 Support Unit used in test configuration and system	13
2.4 Measurement Results Explanation Example.....	13
2.5 Frequency List of Low/Middle/High Channels	14
3 Conducted Test Items.....	19
3.1 Measuring Instruments	19
3.2 Conducted Output Power and ERP/EIRP	20
3.3 Peak-to-Average Ratio	21
3.4 Occupied Bandwidth.....	22
3.5 Conducted Band Edge	23
3.6 Conducted Spurious Emission	25
3.7 Frequency Stability	26
4 Radiated Test Items	27
4.1 Measuring Instruments	27
4.2 Radiated Spurious Emission Measurement	29
5 List of Measuring Equipment.....	30
6 Uncertainty of Evaluation.....	32
Appendix A. Test Results of Conducted Test	
Appendix B. Test Results of Radiated Test	
Appendix C. Setup Photographs	



History of this test report

Report No.	Version	Description	Issued Date
FG1D2414C	01	Initial issue of report	Jun. 21, 2022
FG1D2414C	02	Revise antenna gain	Jul. 08, 2022

Summary of Test Result

Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
3.2	§2.1046	Conducted Output Power	Reporting only	-
	§22.913 (a)(2)	Effective Radiated Power (n5) (n26)	Pass	
	§27.50 (c)(10)	Effective Radiated Power (n12) (n13) (n71)		
	§24.232 (c) §27.50 (h)(2)	Equivalent Isotropic Radiated Power (n2) (n25) (n7) (n38) (n41)		
	§27.50 (d)(4)	Equivalent Isotropic Radiated Power (n66) (n70)		
3.3	§24.232 (d) §27.50 (d)(5)	Peak-to-Average Ratio	Pass	-
3.4	§2.1049	Occupied Bandwidth	Reporting only	-
3.5	§2.1051 §22.917 (a) §24.238 (a) §27.53 (c)(2) §27.53 (g) §27.53 (h)	Conducted Band Edge Measurement (n2) (n5) (n12) (n13) (n25) (n26) (n66) (n70) (n71)	Pass	-
	§2.1051 §27.53 (m)(4)	Conducted Band Edge Measurement (n7) (n38) (n41)		
3.6	§2.1051 §22.917 (a) §24.238 (a) §27.53 (c)(2) §27.53 (g) §27.53 (h)	Conducted Spurious Emission (n2) (n5) (n12) (n13) (n25) (n26) (n66) (n70) (n71)	Pass	-
	§2.1051 §27.53 (m)(4)	Conducted Spurious Emission (n7) (n38) (n41)		
3.7	§2.1055 §22.355 §24.235 §27.54	Frequency Stability Temperature & Voltage	Pass	-



Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
4.2	§2.1053 §22.917 (a) §24.238 (a) §27.53 (c)(2) §27.53 (f) §27.53 (g) §27.53 (h)	Radiated Spurious Emission (n2) (n5) (n12) (n13) (n25) (n26) (n66) (n70) (n71)	Pass	Under limit 13.24 dB at 7494.000 MHz
	§2.1051 §27.53 (m)(4)	Radiated Spurious Emission (n7) (n38) (n41)		

Declaration of Conformity:

1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented in accordance with the regulation limits or requirements declared by manufacturers.
It's means measurement values may risk exceeding the limit of regulation standards, if measurement uncertainty is include in test results.
2. The measurement uncertainty please refer to this report "Uncertainty of Evaluation".

Comments and Explanations:

The product specifications of the EUT presented in the report are declared by the manufacturer who shall take full responsibility for the authenticity.

Reviewed by: William Chen**Report Producer: Cindy Liu**



1 General Description

1.1 Product Feature of Equipment Under Test

3G-WCDMA, 4G-LTE, 5G-FR1 & FR2, Wi-Fi 2.4GHz 802.11b/g/n/ax, Wi-Fi 5GHz 802.11a/n/ac/ax and GNSS.

Product Feature	
Antenna Type	WWAN: Fixed Internal Antenna
Antenna Gain	<Ant. 0>: 5G NR n2: 1.6 dBi 5G NR n5: 0.8 dBi 5G NR n7: 0.6 dBi 5G NR n12: -0.1 dBi 5G NR n13: -0.1 dBi 5G NR n25: 1.6 dBi 5G NR n26: 0.8 dBi 5G NR n41: 1.5 dBi 5G NR n66: 1.8 dBi 5G NR n71: 1.0 dBi <Ant. 8>: 5G NR n2: 1.8 dBi 5G NR n38: 1.5 dBi 5G NR n41: 1.5 dBi 5G NR n70 1.1 dBi 5G NR n66 1.1 dBi

Remark: The EUT's information above is declared by manufacturer. Please refer to Comments and Explanations in report summary.

1.2 Modification of EUT

No modifications are made to the EUT during all test items.

1.3 Testing Location

Test Site	Sporton International Inc. EMC & Wireless Communications Laboratory	
Test Site Location	No.52, Huaya 1st Rd., Guishan Dist., Taoyuan City 333, Taiwan (R.O.C.) TEL: +886-3-327-3456 FAX: +886-3-328-4978	
Test Site No.	Sporton Site No.	
	TH03-HY	03CH07-HY
Test Engineer	Ivy Yeh	Jesse Wang, Stan Hsieh and Ken Wu
Temperature (°C)	20~24	22.9~26.6
Relative Humidity (%)	50~58	56.3~61.5

Note: The test site complies with ANSI C63.4 2014 requirement.

FCC Designation No.: TW1190

1.4 Applicable Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ ANSI C63.26-2015
- ♦ ANSI / TIA-603-E
- ♦ FCC 47 CFR Part 2, 22(H), 24(E), 27
- ♦ FCC KDB 971168 D01 Power Meas. License Digital Systems v03r01
- ♦ FCC KDB 412172 D01 Determining ERP and EIRP v01r01
- ♦ FCC KDB 414788 D01 Radiated Test Site v01r01.
- ♦ FCC KDB 662911 D01 Multiple Transmitter Output v02r01.

Remark:

1. All test items were verified and recorded according to the standards and without any deviation during the test.
2. This EUT has also been tested and complied with the requirements of FCC Part 15, Subpart B, recorded in a separate test report.
3. The TAF code is not including all the FCC KDB listed without accreditation.



2 Test Configuration of Equipment Under Test

2.1 Test Mode

Antenna port conducted and radiated test items listed below are performed according to KDB 971168 D01 Power Meas. License Digital Systems v03r01 with maximum output power.

For radiated measurement, the measured emission level of the EUT was maximized by rotating the EUT on a turntable, adjusting the orientation of the EUT and EUT antenna in three orthogonal axis (X: flat, Y: portrait, Z: landscape), and adjusting the measurement antenna orientation, following C63.26 exploratory test procedures and find X Plane for 5G NR n7, n12, n38, n70, n71, EN-DC 2A-n71A, 7A-n71A, 66A-n71A, 2A-n66A, 7A-n66A, 12A-n66A, 13A-n66A, 5A-n2A; Y Plane for 5G NR n13, n66, EN-DC 2A-n5A, 66A-n5A, 48A-n5A; Z Plane for 5G NR n25, n26, n41, n41 (MIMO), EN-DC 5A-n66A, 48A-n66A, 13A-n2A, 66A-n2A as worst plane.

Test Items	NR Band	Bandwidth (MHz)								Modulation					RB #			Test Channel		
		5	10	15	20	25	30	40	50	PI/2 BPSK	QPSK	16QAM	64QAM	256QAM	1	Half	Full	L	M	H
Max. Output Power	n2	v	v	v	v	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
	n5	v	v	v	v	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
	n7	v	v	v	v	v	v	v		v	v	v	v	v	v	v	v	v	v	v
	n12	v	v		-	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
	n13	v	v	-	-	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
	n25	v	v	v	v	v	v	v	-	v	v	v	v	v	v	v	v	v	v	v
	n26	v	v	v	v	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
	n38	-	v	v	v		v	v	-	v	v	v	v	v	v	v	v	v	v	v
	n66	v	v	v	v		v	v	-	v	v	v	v	v	v	v	v	v	v	v
	n70	v	v	v	-	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
	n71	v	v	v	v	-	-	-	-	v	v	v	v	v	v	v	v	v	v	v
Peak-to-Average Ratio	n2	Covered by n25																		
	n5	Covered by n26																		
	n7				v					v	v	v	v	v			v		v	
	n12		v		-	-	-	-	-	v	v	v	v	v			v		v	
	n13		v	-	-	-	-	-	-	v	v	v	v	v			v		v	
	n25				v				-	v	v	v	v	v			v		v	
	n26				v	-	-	-	-	v	v	v	v	v			v		v	
	n38	Covered by n41																		
	n66				v				-	v	v	v	v	v			v		v	
	n70			v	-	-	-	-	-	v	v	v	v	v			v		v	
	n71				v	-	-	-	-	v	v	v	v	v			v		v	



Test Items	NR Band	Bandwidth (MHz)								Modulation					RB #			Test Channel		
		5	10	15	20	25	30	40	50	PI/2 BPSK	QPSK	16QAM	64QAM	256QAM	1	Half	Full	L	M	H
26dB and 99% Bandwidth	n2	Covered by n25																		
	n5	Covered by n26																		
	n7	v	v	v	v	v	v	v		v	v	v	v	v			v		v	
	n12	v	v		-	-	-	-	-	v	v	v	v	v			v		v	
	n13	v	v	-	-	-	-	-	-	v	v	v	v	v			v		v	
	n25	v	v	v	v		v	v	-	v	v	v	v	v			v		v	
	n26	v	v	v	v	-	-	-	-	v	v	v	v	v			v		v	
	n38	Covered by n41																		
	n66	v	v	v	v		v	v	-	v	v	v	v	v			v		v	
	n70	v	v	v	-	-	-	-	-	v	v	v	v	v			v		v	
	n71	v	v	v	v	-	-	-	-	v	v	v	v	v			v		v	
Conducted Band Edge	n2	Covered by n25																		
	n5	Covered by n26																		
	n7	v	v	v	v	v	v	v		v	v	v	v	v	v		v	v		v
	n12	v	v		-	-	-	-	-	v	v	v	v	v	v		v	v		v
	n13	v	v	-	-	-	-	-	-	v	v	v	v	v	v		v	v		v
	n25	v	v	v	v		v	v	-	v	v	v	v	v	v		v	v		v
	n26	v	v	v	v	-	-	-	-	v	v	v	v	v	v		v	v		v
	n38	Covered by n41																		
	n66	v	v	v	v		v	v	-	v	v	v	v	v	v		v	v		v
	n70	v	v	v	-	-	-	-	-	v	v	v	v	v	v		v	v		v
	n71	v	v	v	v	-	-	-	-	v	v	v	v	v	v		v	v		v
Conducted Spurious Emission	n2	Covered by n25																		
	n5	Covered by n26																		
	n7	v									v				v			v	v	v
	n12	v			-	-	-	-	-		v				v			v	v	v
	n13	v		-	-	-	-	-	-		v				v			v	v	v
	n25	v							-		v				v			v	v	v
	n26	v				-	-	-	-		v				v			v	v	v
	n38	Covered by n41																		
	n66	v							-		v				v			v	v	v
	n70	v			-	-	-	-	-		v				v			v	v	v
	n71	v				-	-	-	-		v				v			v	v	v



Test Items	NR Band	Bandwidth (MHz)								Modulation					RB #			Test Channel		
		5	10	15	20	25	30	40	50	PI/2 BPSK	QPSK	16QAM	64QAM	256QAM	1	Half	Full	L	M	H
Frequency Stability	n2	Covered by n25																		
	n5	Covered by n26																		
	n7				v					v							v		v	
	n12		v		-	-	-	-	-	v							v		v	
	n13		v	-	-	-	-	-	-	v							v		v	
	n25				v				-	v							v		v	
	n26				v	-	-	-	-	v							v		v	
	n38	Covered by n41																		
	n66				v	-			-	v							v		v	
	n70			v	-	-	-	-	-	v							v		v	
	n71				v	-	-	-	-	v							v		v	
E.R.P / E.I.R.P	n2	v	v	v	v	-	-	-	-	v	v	v	v	v	Max. Power					
	n5	v	v	v	v	-	-	-	-	v	v	v	v	v						
	n7	v	v	v	v	v	v	v		v	v	v	v	v						
	n12	v	v		-	-	-	-	-	v	v	v	v	v						
	n13	v	v	-	-	-	-	-	-	v	v	v	v	v						
	n25	v	v	v	v	v	v	v	-	v	v	v	v	v						
	n26	v	v	v	v	-	-	-	-	v	v	v	v	v						
	n38	-	v	v	v		v	v	-	v	v	v	v	v						
	n66	v	v	v	v		v	v	-	v	v	v	v	v						
	n70	v	v	v	-	-	-	-	-	v	v	v	v	v						
	n71	v	v	v	v	-	-	-	-	v	v	v	v	v						




Test Items	NR Band	Bandwidth (MHz)								Modulation					RB #			Test Channel		
		5	10	15	20	25	30	40	50	PI/2 BPSK	QPSK	16QAM	64QAM	256QAM	1	Half	Full	L	M	H
Radiated Spurious Emission	n2	Covered by n25																		
	n5	Covered by n26																		
	n7	Worst Case																v	v	v
	n12	Worst Case																v	v	v
	n13	Worst Case																v	v	v
	n25	Worst Case																v	v	v
	n26	Worst Case																v	v	v
	n38	Worst Case																v	v	v
	n66	Worst Case																v	v	v
	n70	Worst Case																v	v	v
	n71	Worst Case																v	v	v
Remark	1. The mark “v ” means that this configuration is chosen for testing 2. The mark “-” means that this bandwidth is not supported. 3. The device is investigated from 30MHz to 10 times of fundamental signal for radiated spurious emission test under different RB size/offset and modulations in exploratory test. Subsequently, only the worst case emissions are reported. 4. Test combination are EN-DC 2A-n5A, EN-DC 66A-n5A, EN-DC 48A-n5A, EN-DC 5A-n2A, EN-DC 13A-n2A, EN-DC 66A-n2A, EN-DC 12A-n66A, EN-DC13A-n66A, EN-DC 2A-n66A, EN-DC 7A-n66A, EN-DC 5A-n66A, EN-DC 48A-n66A, EN-DC 2A-n71A, EN-DC 7A-n71A, EN-DC 66A-n71A. 5. Wider operating range bandwidth covers narrower one when the power is higher or the same. 6. For radiated measurement, pre-scanned in two modes, DFT-s OFDM and CP OFDM. The worst cases (DFT-s OFDM) were recorded in this report, the worst modes of FR1 and LTE for simultaneous transmission were verified and compliant. 7. One representative bandwidth is selected to perform PAR and frequency stability.																			



Test Items	NR Band	Bandwidth (MHz)												Modulation					RB #			Test Channel		
		10	15	20	30	40	50	60	70	80	90	100	PI/2 BPSK	QPSK	16QAM	64QAM	256QAM	1	Half	Full	L	M	H	
Max. Output Power	n41			v	v	v	v	v	v	v	v	v	v	v	v	v	v	v	v	v	v	v	v	
Peak-to-Average Ratio	n41			v									v	v	v	v	v			v		v		
26dB and 99% Bandwidth	n41			v	v	v	v	v	v	v	v	v	v	v	v	v	v			v		v		
Conducted Band Edge	n41			v	v	v	v	v	v	v	v	v	v	v	v	v	v	v		v	v		v	
Conducted Spurious Emission	n41			v										v				v			v	v	v	
Frequency Stability	n41			v									v							v		v		
	n41			v	v	v	v	v	v	v	v	v	v	v	v	v	v	Max Power						
Radiated Spurious Emission	n41	Worst Case																			v	v	v	
Remark	<div>1. The mark “v ” means that this configuration is chosen for testing</div> <div>2. The mark “-” means that this bandwidth is not supported.</div> <div>3. The device is investigated from 30MHz to 10 times of fundamental signal for radiated spurious emission test under different RB size/offset and modulations in exploratory test. Subsequently, only the worst case emissions are reported.</div> <div>4. One representative bandwidth is selected to perform PAR and frequency stability.</div>																							

2.2 Connection Diagram of Test System



2.3 Support Unit used in test configuration and system

Item	Equipment	Brand Name	Model No.	FCC ID	Data Cable	Power Cord
1.	5G Wireless Test Platform	Anritsu	MT8000A	N/A	N/A	Unshielded, 1.8 m
2.	System Simulator	Anritsu	MT8821C	N/A	N/A	Unshielded, 1.8 m

2.4 Measurement Results Explanation Example

For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

Offset = RF cable loss + attenuator factor.

Following shows an offset computation example with cable loss 4.2 dB and 10dB attenuator.

Example :

Offset(dB) = RF cable loss(dB) + attenuator factor(dB).

$$= 4.2 + 10 = 14.2 \text{ (dB)}$$

2.5 Frequency List of Low/Middle/High Channels

5G NR n2 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
20	Channel	372000	376000	380000
	Frequency	1860	1880	1900
15	Channel	371500	376000	380500
	Frequency	1857.5	1880	1902.5
10	Channel	371000	376000	381000
	Frequency	1855	1880	1905
5	Channel	370500	376000	381500
	Frequency	1852.5	1880	1907.5

5G NR n5 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
20	Channel	166800	167300	167800
	Frequency	834	836.5	839
15	Channel	166300	167300	168300
	Frequency	831.5	836.5	841.5
10	Channel	165800	167300	168800
	Frequency	829	836.5	844
5	Channel	165300	167300	169300
	Frequency	826.5	836.5	846.5

5G NR n7 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
40	Channel	504000	507000	510000
	Frequency	2520	2535	2550
30	Channel	503000	507000	511000
	Frequency	2515	2535	2555
25	Channel	502000	507000	511550
	Frequency	2512.5	2535	2557.5
20	Channel	502000	507000	512000
	Frequency	2510	2535	2560
15	Channel	501500	507000	512500
	Frequency	2507.5	2535	2562.5
10	Channel	501000	507000	513000
	Frequency	2505	2535	2565
5	Channel	500500	507000	513500
	Frequency	2502.5	2535	2567.5

5G NR n12 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
10	Channel	140800	141500	142200
	Frequency	704	707.5	711
5	Channel	140300	141500	142700
	Frequency	701.5	707.5	713.5

5G NR n13 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
10	Channel	-	156400	-
	Frequency	-	782	-
5	Channel	155900	156400	156900
	Frequency	779.5	782	784.5

5G NR n25 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
40	Channel	374000	376500	379000
	Frequency	1870	1882.5	1895
30	Channel	373000	376500	380000
	Frequency	1865	1882.5	1990
25	Channel	372500	376500	380500
	Frequency	1862.5	1882.5	1902.5
20	Channel	372000	376500	381000
	Frequency	1860	1882.5	1905
15	Channel	371500	376500	381500
	Frequency	1857.5	1882.5	1907.5
10	Channel	371000	376500	382000
	Frequency	1855	1882.5	1910
5	Channel	370500	376500	382500
	Frequency	1852.5	1882.5	1912.5

5G NR n26 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
20	Channel	166800	167300	167800
	Frequency	834	836.5	839
15	Channel	166300	167300	168300
	Frequency	831.5	836.5	841.5
10	Channel	165800	167300	168800
	Frequency	829	836.5	844
5	Channel	165300	167300	169300
	Frequency	826.5	836.5	846.5



5G NR n38 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
40	Channel	518000	519000	520000
	Frequency	2590	2595	2600
30	Channel	517000	519000	521000
	Frequency	2585	2595	2605
20	Channel	516000	519000	522000
	Frequency	2580	2595	2610
15	Channel	515500	519000	522500
	Frequency	2577.5	2595	2612.5
10	Channel	515000	519000	523000
	Frequency	2575	2595	2615

5G NR n41 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
100	Channel	509202	518598	528000
	Frequency	2546.01	2592.99	2640
90	Channel	508200	518598	528996
	Frequency	2541	2592.99	2644.98
80	Channel	507204	518598	529998
	Frequency	2536.02	2592.99	2649.99
70	Channel	506202	518598	531000
	Frequency	2531.01	2592.99	2655
60	Channel	505200	518598	531996
	Frequency	2526	2592.99	2659.98
50	Channel	504204	518598	532998
	Frequency	2521.02	2592.99	2664.99
40	Channel	503202	518598	534000
	Frequency	2516.01	2592.99	2670
30	Channel	502200	518598	534996
	Frequency	2511	2592.99	2674.98
20	Channel	501204	518598	535998
	Frequency	2506.02	2592.99	2679.99



5G NR Band n66 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
40	Channel	346000	349000	352000
	Frequency	1730	1745	1760
30	Channel	345000	349000	353000
	Frequency	1725	1745	1765
20	Channel	344000	349000	354000
	Frequency	1720	1745	1770
15	Channel	343500	349000	354500
	Frequency	1717.5	1745	1772.5
10	Channel	343000	349000	355000
	Frequency	1715	1745	1775
5	Channel	342500	349000	355500
	Frequency	1712.5	1745	1777.5

5G NR Band n70 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
15	Channel	-	340500	-
	Frequency	-	1702.5	-
10	Channel	340000	340500	341000
	Frequency	1700	1702.5	1705
5	Channel	339500	340500	341500
	Frequency	1697.5	1702.5	1707.5

5G NR Band n71 Channel and Frequency List				
BW [MHz]	Channel/Frequency(MHz)	Lowest	Middle	Highest
20	Channel	134600	136100	137600
	Frequency	673	680.5	688
15	Channel	134100	136100	138100
	Frequency	670.5	680.5	690.5
10	Channel	133600	136100	138600
	Frequency	668	680.5	693
5	Channel	133100	136100	139100
	Frequency	665.5	680.5	695.5


3 Conducted Test Items

3.1 Measuring Instruments


See list of measuring instruments of this test report.

3.1.1 Test Setup


3.1.2 Conducted Output Power



3.1.3 Peak-to-Average Ratio, Occupied Bandwidth ,Conducted Band-Edge and Conducted Spurious Emission



3.1.4 Frequency Stability



3.1.5 Test Result of Conducted Test

Please refer to Appendix A.

3.2 Conducted Output Power and ERP/EIRP

3.2.1 Description of the Conducted Output Power Measurement and ERP/EIRP Measurement

A system simulator was used to establish communication with the EUT. Its parameters were set to force the EUT transmitting at maximum output power. The measured power in the radio frequency on the transmitter output terminals shall be reported.

The ERP of mobile transmitters must not exceed 7 Watts for 5G NR n5 and n26

The ERP of mobile transmitters must not exceed 3 Watts for 5G NR n12 and n13 and n71

The EIRP of mobile transmitters must not exceed 2 Watts for 5G NR n2 and n25 and n7 and n38 and n41.

The EIRP of mobile transmitters must not exceed 1 Watts for 5G NR n66 and n70

According to KDB 412172 D01 Power Approach,

$EIRP = P_T + G_T - L_C$, $ERP = EIRP - 2.15$, where

P_T = transmitter output power in dBm

G_T = gain of the transmitting antenna in dBi

L_C = signal attenuation in the connecting cable between the transmitter and antenna in dB

3.2.2 Test Procedures

1. The transmitter output port was connected to the system simulator.
2. Set EUT at maximum power through the system simulator.
3. Select lowest, middle, and highest channels for each band and different modulation.
4. Measure and record the power level from the system simulator.
5. The MIMO mode is completely uncorrelated, so the directional gain is selected the maximum gain among all antennas.



3.3 Peak-to-Average Ratio

3.3.1 Description of the PAR Measurement

Power Complementary Cumulative Distribution Function (CCDF) curves provide a means for characterizing the power peaks of a digitally modulated signal on a statistical basis. A CCDF curve depicts the probability of the peak signal amplitude exceeding the average power level. Most contemporary measurement instrumentation include the capability to produce CCDF curves for an input signal provided that the instrument's resolution bandwidth can be set wide enough to accommodate the entire input signal bandwidth. In measuring transmissions in this band using an average power technique, the peak-to-average ratio (PAR) of the transmission may not exceed 13 dB.

3.3.2 Test Procedures

The testing follows ANSI C63.26-2015 Section 5.2.6

1. The EUT was connected to spectrum and system simulator via a power divider.
2. Set the CCDF (Complementary Cumulative Distribution Function) option in spectrum analyzer.
3. The highest RF powers were measured and recorded the maximum PAPR level associated with a probability of 0.1 %.
4. Record the deviation as Peak to Average Ratio.

3.4 Occupied Bandwidth

3.4.1 Description of Occupied Bandwidth Measurement

The occupied bandwidth is the width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage 0.5% of the total mean transmitted power.

The 26 dB emission bandwidth is defined as the frequency range between two points, one above and one below the carrier frequency, at which the spectral density of the emission is attenuated 26 dB below the maximum in-band spectral density of the modulated signal. Spectral density (power per unit bandwidth) is to be measured with a detector of resolution bandwidth equal to approximately 1.0% of the emission bandwidth.

3.4.2 Test Procedures

The testing follows ANSI C63.26-2015 Section 5.4.3 (26dB) and Section 5.4.4 (99OB)

1. The EUT was connected to spectrum analyzer and system simulator via a power divider.
2. The spectrum analyzer center frequency is set to the nominal EUT channel center frequency. The span range for the spectrum analyzer shall be between two and five times the anticipated OBW.
3. The nominal resolution bandwidth (RBW) shall be in the range of 1 to 5 % of the anticipated OBW, and the VBW shall be at least 3 times the RBW.
4. Set the detection mode to peak, and the trace mode to max hold.
5. Determine the reference value: Set the EUT to transmit a modulated signal. Allow the trace to stabilize. Set the spectrum analyzer marker to the highest level of the displayed trace.
(this is the reference value)
6. Determine the “-26 dB down amplitude” as equal to (Reference Value – X).
7. Place two markers, one at the lowest and the other at the highest frequency of the envelope of the spectral display such that each marker is at or slightly below the “-X dB down amplitude” determined in step 6. If a marker is below this “-X dB down amplitude” value it shall be placed as close as possible to this value. The OBW is the positive frequency difference between the two markers.
8. Use the 99 % power bandwidth function of the spectrum analyzer and report the measured bandwidth.



3.5 Conducted Band Edge

3.5.1 Description of Conducted Band Edge Measurement

22.917(a)

For operations in the 824 – 849 MHz band, the FCC limit is $43 + 10\log_{10}(P[\text{Watts}])$ dB below the transmitter power $P(\text{Watts})$ in a 100kHz bandwidth. However, in the 1MHz bands immediately outside and adjacent to the licensee's frequency block, a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed.

24.238 (a)

For operations in the 1850-1910 and 1930-1990 MHz band, the FCC limit is $43 + 10\log_{10}(P[\text{Watts}])$ dB below the transmitter power $P(\text{Watts})$ in a 1MHz bandwidth. However, in the 1 MHz bands immediately outside and adjacent to the frequency block a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed.

27.53 (g)

For operations in the 600MHz band and 698-746 MHz band, the FCC limit is $43 + 10\log_{10}(P[\text{Watts}])$ dB below the transmitter power $P(\text{Watts})$ in a 100 kHz bandwidth. However, in the 100 kilohertz bands immediately outside and adjacent to a licensee's frequency block, a resolution bandwidth of at least 30 kHz may be employed.

27.53 (h)

For operations in the 1710 – 1755 MHz band, 1755-1780 MHz, the FCC limit is $43 + 10\log_{10}(P[\text{Watts}])$ dB below the transmitter power $P(\text{Watts})$ in a 1 MHz bandwidth. However, in the 1MHz bands immediately outside and adjacent to the licensee's frequency block, a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed.

27.53(m)(4)

For mobile digital stations, the attenuation factor shall be not less than $40 + 10 \log (P)$ dB on all frequencies between the channel edge and 5 megahertz from the channel edge, $43 + 10 \log (P)$ dB on all frequencies between 5 megahertz and X megahertz from the channel edge, and $55 + 10 \log (P)$ dB on all frequencies more than X megahertz from the channel edge, where X is the greater of 6 megahertz or the actual emission bandwidth as defined in paragraph (m)(6) of this section. In addition, the attenuation factor shall not be less than $43 + 10 \log (P)$ dB on all frequencies between 2490.5 MHz and 2496 MHz and $55 + 10 \log (P)$ dB at or below 2490.5 MHz. Mobile Satellite Service licensees operating on frequencies below 2495 MHz may also submit a documented interference complaint against BRS licensees operating on channel BRS Channel 1 on the same terms and conditions as adjacent channel BRS or EBS licensees.

3.5.2 Test Procedures

The testing follows FCC KDB 971168 D01 v03r01 Section 6.1.

1. The EUT was connected to spectrum analyzer and system simulator via a power divider.
2. The band edges of low and high channels for the highest RF powers were measured.
3. Set RBW $\geq 1\%$ EBW in the 1MHz band immediately outside and adjacent to the band edge.
4. Beyond the 1 MHz band from the band edge, RBW=1MHz was used.
5. Set spectrum analyzer with RMS detector.
6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.
7. Checked that all the results comply with the emission limit line.

The limit line is derived from $43 + 10\log(P)$ dB below the transmitter power P(Watts)

For 5G NR n7, n41

The other 40 dB, and 55 dB have additionally applied same calculation above.

8. For MIMO mode, add additional MIMO factor $10\log(NTX=2) = 3.01$ dB into the spectrum analyzer offset.

3.6 Conducted Spurious Emission

3.6.1 Description of Conducted Spurious Emission Measurement

The power of any emission outside of the authorized operating frequency ranges must be lower than the transmitter power (P) by a factor of at least $43 + 10 \log (P)$ dB.

For 5G NR n7, n41

The power of any emission outside of the authorized operating frequency ranges must be lower than the transmitter power (P) by a factor of at least $55 + 10 \log (P)$ dB.

It is measured by means of a calibrated spectrum analyzer and scanned from 30 MHz up to a frequency including its 10th harmonic.

3.6.2 Test Procedures

The testing follows FCC KDB 971168 D01 v03r01 Section 6.1.

1. The EUT was connected to spectrum analyzer and system simulator via a power divider.
2. The RF output of EUT was connected to the spectrum analyzer by RF cable and attenuator.
The path loss was compensated to the results for each measurement.
3. The middle channel for the highest RF power within the transmitting frequency was measured.
4. The conducted spurious emission for the whole frequency range was taken.
5. Make the measurement with the spectrum analyzer's RBW = 1MHz, VBW = 3MHz.
6. Set spectrum analyzer with RMS detector.
7. Taking the record of maximum spurious emission.
8. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.
9. The limit line is derived from $43 + 10\log(P)$ dB below the transmitter power P(Watts)
For 5G NR n7, n41
The limit line is derived from $55 + 10\log(P)$ dB below the transmitter power P(Watts)
10. For MIMO mode, add additional MIMO factor $10\log(NTX=2) = 3.01$ dB into the spectrum analyzer offset.

3.7 Frequency Stability

3.7.1 Description of Frequency Stability Measurement

22.355

The frequency stability shall be measured by variation of ambient temperature and variation of primary supply voltage to ensure that the fundamental emission stays within the authorized frequency block. The frequency stability of the transmitter shall be maintained within $\pm 0.00025\%$ ($\pm 2.5\text{ppm}$) of the center frequency.

24.235 & 27.54

The frequency stability shall be sufficient to ensure that the fundamental emission stays within the authorized frequency block.

3.7.2 Test Procedures for Temperature Variation

The testing follows FCC KDB 971168 D01 v03r01 Section 9.0.

1. The EUT was set up in the thermal chamber and connected with the system simulator.
2. With power OFF, the temperature was decreased to -30°C and the EUT was stabilized before testing. Power was applied and the maximum change in frequency was recorded within one minute.
3. With power OFF, the temperature was raised in 10°C step up to 50°C . The EUT was stabilized at each step for at least half an hour. Power was applied and the maximum frequency change was recorded within one minute.

3.7.3 Test Procedures for Voltage Variation

The testing follows FCC KDB 971168 D01 v03r01 Section 9.0.

1. The EUT was placed in a temperature chamber at $20\pm 5^{\circ}\text{C}$ and connected with the system simulator.
2. The power supply voltage to the EUT was varied from 85% to 115% of the nominal value measured at the input to the EUT.
3. The variation in frequency was measured for the worst case.


4 Radiated Test Items

4.1 Measuring Instruments


See list of measuring instruments of this test report.

4.1.1 Test Setup


For radiated emissions below 30MHz




For radiated test from 30MHz to 1GHz



For radiated test from 1GHz to 18GHz



For radiated test above 18GHz



4.1.2 Test Result of Radiated Test

Please refer to Appendix B.

Note:

The low frequency, which started from 9 kHz to 30MHz, was pre-scanned and the result which was 20dB lower than the limit line was not reported.

There is adequate comparison measurement of both open-field test site and alternative test site - semi-Anechoic chamber according to 414788 D01 Radiated Test Site v01r01, and the result came out very similar.

4.2 Radiated Spurious Emission Measurement

4.2.1 Description of Radiated Spurious Emission Measurement

The radiated spurious emission was measured by substitution method according to ANSI / TIA-603-E. The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitter power (P) by a factor of at least $43 + 10 \log (P)$ dB.

For 5G NR n7, n38, n41

The power of any emission outside of the authorized operating frequency ranges must be attenuated below the transmitter power (P) by a factor of at least $55 + 10 \log (P)$ dB.

The spectrum is scanned from 30 MHz up to a frequency including its 10th harmonic.

4.2.2 Test Procedures

The testing follows FCC KDB 971168 D01 v03r01 Section 7 and ANSI / TIA-603-E Section 2.2.12.

1. The EUT was placed on a turntable with 0.8 meter for frequency below 1GHz and 1.5 meter for frequency above 1GHz respectively above ground.
2. The EUT was set 3 meters from the receiving antenna, which was mounted on the antenna tower.
3. The table was rotated 360 degrees to determine the position of the highest spurious emission.
4. The height of the receiving antenna is varied between one meter and four meters to search the maximum spurious emission for both horizontal and vertical polarizations.
5. Make the measurement with the spectrum analyzer's RBW = 1MHz, VBW = 3MHz, taking the record of maximum spurious emission.
6. Measure the burst average result by setting trace = max hold or trace = average with duty cycle factor when margin is not enough.
7. A horn antenna was substituted in place of the EUT and was driven by a signal generator.
8. Tune the output power of signal generator to the same emission level with EUT maximum spurious emission.
9. Taking the record of output power at antenna port.
10. Repeat step 7 to step 8 for another polarization.
11. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.

The limit line is derived from $43 + 10\log(P)$ dB below the transmitter power P(Watts)

For 5G NR n7, n38, n41

The limit line is derived from $55 + 10\log(P)$ dB below the transmitter power P(Watts)

$EIRP \text{ (dBm)} = S.G. \text{ Power} - Tx \text{ Cable Loss} + Tx \text{ Antenna Gain}$

$ERP \text{ (dBm)} = EIRP - 2.15$



5 List of Measuring Equipment

Instrument	Brand Name	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Bilog Antenna	TESEQ	CBL 6111D & 00800N1D01N-06	35419 & 03	30MHz~1GHz	Apr. 24, 2022	May 06, 2022~ May 30, 2022	Apr. 23, 2023	Radiation (03CH07-HY)
Double Ridge Horn Antenna	ESCO	3117	00075962	1GHz ~ 18GHz	Dec. 03, 2021	May 06, 2022~ May 30, 2022	Dec. 02, 2022	Radiation (03CH07-HY)
Preamplifier	MITEQ	AMF-7D-00101 800-30-10P	1590075	1GHz~18GHz	Apr. 21, 2022	May 06, 2022~ May 30, 2022	Apr. 20, 2023	Radiation (03CH07-HY)
Preamplifier	COM-POWER	PA-103A	161241	10MHz~1GHz	Oct. 04, 2021	May 06, 2022~ May 30, 2022	Oct. 03, 2022	Radiation (03CH07-HY)
Preamplifier	Agilent	8449B	3008A02362	1GHz~26.5GHz	Oct. 04, 2021	May 06, 2022~ May 30, 2022	Oct. 03, 2022	Radiation (03CH07-HY)
Preamplifier	EMEC	EM18G40G	0600789	18-40GHz	Jul. 23, 2021	May 06, 2022~ May 30, 2022	Jul. 22, 2022	Radiation (03CH07-HY)
Spectrum Analyzer	Agilent	N9030A	MY52350276	3Hz~44GHz	Jul. 22, 2021	May 06, 2022~ May 30, 2022	Jul. 21, 2022	Radiation (03CH07-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 104	MY15682/4	30MHz to 18GHz	Feb. 23, 2022	May 06, 2022~ May 30, 2022	Feb. 22, 2023	Radiation (03CH07-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 104	MY24971/4	9kHz to 18GHz	Feb. 23, 2022	May 06, 2022~ May 30, 2022	Feb. 22, 2023	Radiation (03CH07-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 104	MY28655/4	9kHz to 18GHz	Feb. 23, 2022	May 06, 2022~ May 30, 2022	Feb. 22, 2023	Radiation (03CH07-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 126	532078/126E	30MHz~18GHz	Sep. 17, 2021	May 06, 2022~ May 30, 2022	Sep. 16, 2022	Radiation (03CH07-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 102	MY2858/2	18GHz~40GHz	Feb. 23, 2022	May 06, 2022~ May 30, 2022	Feb. 22, 2023	Radiation (03CH07-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 102	801606/2	9KHz ~ 40GHz	Apr. 14, 2022	May 06, 2022~ May 30, 2022	Apr. 13, 2023	Radiation (03CH07-HY)
Controller	EMEC	EM1000	N/A	Control Ant Mast	N/A	May 06, 2022~ May 30, 2022	N/A	Radiation (03CH07-HY)
Controller	MF	MF-7802	N/A	Control Turn table	N/A	May 06, 2022~ May 30, 2022	N/A	Radiation (03CH07-HY)
Antenna Mast	EMEC	AM-BS-4500E	N/A	Boresight mast 1M~4M	N/A	May 06, 2022~ May 30, 2022	N/A	Radiation (03CH07-HY)
Turn Table	ChainTek	Chaintek 3000	N/A	0~360 Degree	N/A	May 06, 2022~ May 30, 2022	N/A	Radiation (03CH07-HY)
Software	Audix	E3	N/A	N/A	N/A	May 06, 2022~ May 30, 2022	N/A	Radiation (03CH07-HY)
USB Data Logger	TECPEL	TR-32	HE17XB2495	N/A	Mar. 07, 2022	May 06, 2022~ May 30, 2022	Mar. 06, 2023	Radiation (03CH07-HY)
Horn Antenna	EMCO	3117	00143261	1GHz~18GHz	Feb. 11, 2022	May 06, 2022~ May 30, 2022	Feb. 10, 2023	Radiation (03CH07-HY)
SHF-EHF Horn Antenna	SCHWARZBECK	BBHA 9170	BBHA9170251	18GHz~40GHz	Nov. 30, 2021	May 06, 2022~ May 30, 2022	Nov. 29, 2022	Radiation (03CH07-HY)
Signal Generator	Rohde & Schwarz	SMF100A	101107	100kHz~40GHz	Dec. 08, 2021	May 06, 2022~ May 30, 2022	Dec. 07, 2022	Radiation (03CH07-HY)



Instrument	Brand Name	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Programmable Power Supply	GW Instek	PSS-2005	EL890001	50Hz~60Hz	Oct. 06, 2021	Apr. 11, 2022~ Jun. 16, 2022	Oct. 05, 2022	Conducted (TH03-HY)
Signal Analyzer	Rohde & Schwarz	FSV3044	101049	10Hz~44GHz	Aug. 31, 2021	Apr. 11, 2022~ Jun. 16, 2022	Aug. 30, 2022	Conducted (TH03-HY)
Temperature Chamber	ESPEC	SH-641	92013720	-40℃ ~90℃	Sep. 09, 2021	Apr. 11, 2022~ Jun. 16, 2022	Sep. 08, 2022	Conducted (TH03-HY)
Hygrometer	TECPEL	DTM-303B	TP200886	NA	Mar. 21, 2022	Apr. 11, 2022~ Jun. 16, 2022	Mar. 20, 2023	Conducted (TH03-HY)
Base Station (Measure)	Anritsu	MT8821C	6261849015	LTE	Ocr. 06, 2021	Apr. 11, 2022~ Jun. 16, 2022	Oct. 05, 2022	Conducted (TH03-HY)
Base Station (Measure)	Anritsu	MT8000A	6261940327	FR1	Oct. 29, 2021	Apr. 11, 2022~ Jun. 16, 2022	Oct. 28, 2022	Conducted (TH03-HY)



6 Uncertainty of Evaluation

Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	3.16 dB
---	---------

Uncertainty of Radiated Emission Measurement (1 GHz ~ 18 GHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	3.71 dB
---	---------

Uncertainty of Radiated Emission Measurement (18 GHz ~ 40 GHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2Uc(y)$)	4.16 dB
---	---------



Appendix A. Test Results of Conducted Test

Conducted Output Power(Average power) and ERP/EIRP

<SISO Mode>

NR n2 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
5	1	1	PI/2 BPSK	24.00	24.15	24.06	25.84	0.3837		
5	1	23		23.84	24.16	24.01				
5	12	6		23.89	24.22	24.02				
5	1	0		23.43	23.68	23.55				
5	1	24		23.35	23.70	23.46				
5	25	0		23.45	23.75	23.52				
5	1	1	QPSK	23.88	24.21	24.06				
5	1	23		23.78	24.12	24.00				
5	12	6		23.90	24.24	24.04				
5	1	0		22.86	23.18	23.07				
5	1	24		22.81	23.16	23.02				
5	25	0		22.91	23.24	23.04				
5	1	1	16-QAM	22.82	23.18	23.00	24.78	0.3006		
5	1	1	64-QAM	21.70	21.93	21.74				
5	1	1	256-QAM	18.95	19.18	19.01				
Limit	EIRP < 2W			Result			Pass			

NR n2 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
10	1	1	PI/2 BPSK	24.10	24.23	24.07	25.84	0.3837		
10	1	50		23.96	24.15	24.00				
10	25	12		24.04	24.24	24.05				
10	1	0		23.56	23.71	23.60				
10	1	51		23.38	23.67	23.55				
10	50	0		23.49	23.77	23.57				
10	1	1	QPSK	24.04	24.16	24.10				
10	1	50		23.94	24.13	24.02				
10	25	12		24.03	24.24	24.04				
10	1	0		23.12	23.20	23.15				
10	1	51		22.96	23.15	23.05				
10	50	0		23.01	23.22	23.07				
10	1	1	16-QAM	23.04	23.17	23.12	24.77	0.2999		
10	1	1	64-QAM	21.84	21.92	21.79				
10	1	1	256-QAM	19.04	19.15	19.07				
Limit	EIRP < 2W			Result			Pass			



NR n2 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
15	1	1	PI/2 BPSK	24.06	24.28	24.20	26.00	0.3981		
15	1	77		24.15	24.26	24.18				
15	36	18		24.09	24.36	24.20				
15	1	0		23.54	23.78	23.69				
15	1	78		23.58	23.77	23.68				
15	75	0		23.53	23.87	23.70				
15	1	1	QPSK	24.09	24.30	24.21				
15	1	77		24.14	24.32	24.19				
15	36	18		24.03	24.40	24.18				
15	1	0		23.10	23.32	23.24				
15	1	78		23.14	23.35	23.07				
15	75	0		23.03	23.36	23.22				
15	1	1	16-QAM	22.99	23.26	23.18	24.86	0.3062		
15	1	1	64-QAM	21.80	22.01	21.93				
15	1	1	256-QAM	19.05	19.27	19.20				
Limit	EIRP < 2W			Result			Pass			

NR n2 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
20	1	1	PI/2 BPSK	24.01	24.00	24.41	26.01	0.3990		
20	1	104		24.13	24.12	24.13				
20	50	25		23.98	24.21	24.13				
20	1	0		23.53	23.50	23.68				
20	1	105		23.67	23.63	23.63				
20	100	0		23.46	23.74	23.67				
20	1	1	QPSK	23.95	24.05	24.22				
20	1	104		24.14	24.09	24.16				
20	50	25		23.95	24.28	24.18				
20	1	0		22.97	23.07	23.18				
20	1	105		23.10	23.10	23.17				
20	100	0		22.98	23.25	23.16				
20	1	1	16-QAM	23.04	23.06	23.19	24.79	0.3013		
20	1	1	64-QAM	21.52	21.60	21.97				
20	1	1	256-QAM	19.44	19.47	19.21				
Limit	EIRP < 2W			Result			Pass			



NR n5 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
5	1	1	PI/2 BPSK	23.41	23.50	23.41	22.16	0.1644		
5	1	23		23.50	23.42	23.46				
5	12	6		23.40	23.40	23.45				
5	1	0		22.96	23.02	22.87				
5	1	24		22.98	22.90	22.93				
5	25	0		23.00	22.93	22.95				
5	1	1	QPSK	23.47	23.50	23.41				
5	1	23		23.51	23.39	23.47				
5	12	6		23.40	23.40	23.45				
5	1	0		22.48	22.46	22.40				
5	1	24		22.48	22.40	22.48				
5	25	0		22.51	22.42	22.45				
5	1	1	16-QAM	22.50	22.36	22.39	21.15	0.1303		
5	1	1	64-QAM	21.16	21.15	21.09				
5	1	1	256-QAM	18.46	18.61	18.43				
Limit	ERP < 7W			Result			Pass			

NR n5 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
10	1	1	PI/2 BPSK	23.40	23.40	23.29	22.11	0.1626		
10	1	50		23.35	23.39	23.30				
10	25	12		23.45	23.43	23.36				
10	1	0		22.88	22.80	22.76				
10	1	51		22.83	22.85	22.89				
10	50	0		22.92	22.94	22.83				
10	1	1	QPSK	23.38	23.37	23.29				
10	1	50		23.29	23.44	23.33				
10	25	12		23.46	23.45	23.31				
10	1	0		22.40	22.41	22.25				
10	1	51		22.31	22.38	22.34				
10	50	0		22.38	22.40	22.30				
10	1	1	16-QAM	22.35	22.34	22.27	21.00	0.1259		
10	1	1	64-QAM	21.02	21.05	20.91				
10	1	1	256-QAM	18.39	18.40	18.25				
Limit	ERP < 7W			Result			Pass			



NR n5 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
15	1	1	PI/2 BPSK	23.51	23.58	23.47	22.23	0.1671		
15	1	77		23.42	23.40	23.44				
15	36	18		23.54	23.56	23.40				
15	1	0		23.06	23.05	22.98				
15	1	78		22.87	22.93	22.93				
15	75	0		23.04	23.03	23.04				
15	1	1	QPSK	23.56	23.54	23.50				
15	1	77		23.42	23.38	23.46				
15	36	18		23.58	23.54	23.39				
15	1	0		22.59	22.57	22.51				
15	1	78		22.40	22.35	22.40				
15	75	0		22.58	22.53	22.49				
15	1	1	16-QAM	22.54	22.50	22.43	21.19	0.1315		
15	1	1	64-QAM	21.18	21.08	21.18				
15	1	1	256-QAM	18.64	18.81	18.51				
Limit	ERP < 7W			Result			Pass			

NR n5 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
20	1	1	PI/2 BPSK	23.53	23.55	23.73	22.38	0.1730		
20	1	104		23.33	23.50	23.44				
20	50	25		23.54	23.56	23.54				
20	1	0		22.97	23.07	23.04				
20	1	105		22.89	22.99	22.92				
20	100	0		23.03	23.04	23.01				
20	1	1	QPSK	23.54	23.72	23.42				
20	1	104		23.42	23.54	23.24				
20	50	25		23.53	23.56	23.47				
20	1	0		22.52	22.56	22.47				
20	1	105		22.37	22.53	22.31				
20	100	0		22.50	22.57	22.49				
20	1	1	16-QAM	22.46	22.40	22.43	21.11	0.1291		
20	1	1	64-QAM	21.12	21.20	21.22				
20	1	1	256-QAM	18.66	18.62	18.64				
Limit	ERP < 7W			Result			Pass			



NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
5	1	1	PI/2 BPSK	23.68	23.46	23.63	24.35	0.2723		
5	1	23		23.72	23.48	23.71				
5	12	6		23.70	23.44	23.69				
5	1	0		23.19	22.96	23.16				
5	1	24		23.22	22.99	23.22				
5	25	0		23.21	22.99	23.21				
5	1	1	QPSK	23.70	23.42	23.61				
5	1	23		23.75	23.45	23.71				
5	12	6		23.67	23.43	23.60				
5	1	0		22.68	22.49	22.68				
5	1	24		22.77	22.50	22.74				
5	25	0		22.75	22.49	22.72				
5	1	1	16-QAM	22.59	22.32	22.51	23.19	0.2084		
5	1	1	64-QAM	21.42	21.18	21.43				
5	1	1	256-QAM	18.68	18.40	18.68				
Limit	EIRP < 2W			Result			Pass			

NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
10	1	1	PI/2 BPSK	23.49	23.48	23.56	24.33	0.2710		
10	1	50		23.63	23.44	23.73				
10	25	12		23.60	23.54	23.68				
10	1	0		23.05	22.97	23.13				
10	1	51		23.13	22.97	23.22				
10	50	0		23.07	23.02	23.17				
10	1	1	QPSK	23.40	23.52	23.61				
10	1	50		23.51	23.52	23.69				
10	25	12		23.58	23.50	23.66				
10	1	0		22.35	22.48	22.60				
10	1	51		22.44	22.51	22.70				
10	50	0		22.58	22.51	22.66				
10	1	1	16-QAM	22.34	22.34	22.39	22.99	0.1991		
10	1	1	64-QAM	20.84	21.21	21.34				
10	1	1	256-QAM	18.78	18.47	18.60				
Limit	EIRP < 2W			Result			Pass			



NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
15	1	1	PI/2 BPSK	23.72	23.68	23.77	24.55	0.2851		
15	1	77		23.83	23.61	23.94				
15	36	18		23.81	23.62	23.87				
15	1	0		23.22	23.14	23.24				
15	1	78		23.30	23.08	23.41				
15	75	0		23.25	23.15	23.33				
15	1	1	QPSK	23.74	23.73	23.81				
15	1	77		23.85	23.61	23.95				
15	36	18		23.83	23.69	23.88				
15	1	0		22.79	22.71	22.94				
15	1	78		22.80	22.60	22.96				
15	75	0		22.83	22.67	22.87				
15	1	1	16-QAM	22.62	22.52	22.65	23.25	0.2113		
15	1	1	64-QAM	21.46	21.37	21.52				
15	1	1	256-QAM	18.74	18.66	18.80				
Limit	EIRP < 2W			Result			Pass			

NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
20	1	1	PI/2 BPSK	23.75	23.67	23.70	24.52	0.2831		
20	1	104		23.85	23.53	23.88				
20	50	25		23.87	23.67	23.81				
20	1	0		23.23	23.17	23.16				
20	1	105		23.31	23.03	23.38				
20	100	0		23.32	23.13	23.24				
20	1	1	QPSK	23.76	23.70	23.71				
20	1	104		23.83	23.57	23.92				
20	50	25		23.87	23.65	23.80				
20	1	0		22.78	22.72	22.70				
20	1	105		22.64	22.59	22.95				
20	100	0		22.82	22.70	22.82				
20	1	1	16-QAM	22.65	22.53	22.58	23.25	0.2113		
20	1	1	64-QAM	21.55	21.42	21.37				
20	1	1	256-QAM	18.78	18.70	18.60				
Limit	EIRP < 2W			Result			Pass			



NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
25	1	1	PI/2 BPSK	23.92	23.81	23.68	24.80	0.3020		
25	1	131		23.96	23.74	23.99				
25	64	32		23.99	23.77	23.84				
25	1	0		23.40	23.34	23.21				
25	1	132		23.48	23.24	23.48				
25	128	0		23.46	23.21	23.30				
25	1	1	QPSK	23.97	23.86	23.77				
25	1	131		23.98	23.75	23.99				
25	64	32		24.20	23.73	23.80				
25	1	0		22.98	22.92	22.78				
25	1	132		23.02	22.74	23.03				
25	128	0		23.00	22.75	22.84				
25	1	1	16-QAM	22.84	22.66	22.65	23.44	0.2208		
25	1	1	64-QAM	21.63	21.55	21.44				
25	1	1	256-QAM	18.91	18.77	18.72				
Limit	EIRP < 2W			Result			Pass			

NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
30	1	1	PI/2 BPSK	23.67	23.83	23.68	24.53	0.2838		
30	1	158		23.68	23.67	23.91				
30	80	40		23.72	23.71	23.70				
30	1	0		23.18	23.34	23.18				
30	1	159		23.26	23.21	23.41				
30	160	0		23.28	23.23	23.28				
30	1	1	QPSK	23.67	23.77	23.72				
30	1	158		23.75	23.74	23.93				
30	80	40		23.79	23.64	23.71				
30	1	0		22.74	22.77	22.64				
30	1	159		22.81	22.78	23.00				
30	160	0		22.84	22.84	22.78				
30	1	1	16-QAM	22.53	22.56	22.51	23.16	0.2070		
30	1	1	64-QAM	21.40	21.49	21.36				
30	1	1	256-QAM	18.66	18.85	18.67				
Limit	EIRP < 2W			Result			Pass			



NR n7 Maximum Average Power [dBm] (GT - LC = 0.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
40	1	1	PI/2 BPSK	23.77	23.73	24.21	24.81	0.3027		
40	1	214		23.79	23.78	23.97				
40	108	54		23.82	23.65	23.84				
40	1	0		23.21	23.26	23.32				
40	1	215		23.25	23.23	23.47				
40	216	0		23.36	23.24	23.34				
40	1	1	QPSK	23.79	23.74	23.89				
40	1	214		23.79	23.75	23.99				
40	108	54		23.90	23.76	23.81				
40	1	0		22.81	22.75	22.89				
40	1	215		22.79	22.80	23.02				
40	216	0		22.80	22.78	22.87				
40	1	1	16-QAM	22.68	22.60	22.67	23.28	0.2128		
40	1	1	64-QAM	21.47	21.43	21.52				
40	1	1	256-QAM	18.81	18.83	18.87				
Limit	EIRP < 2W			Result			Pass			



NR n12 Maximum Average Power [dBm] (GT - LC = -0.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
5	1	1	PI/2 BPSK	23.78	23.84	23.84	21.71	0.1483		
5	1	23		23.85	23.89	23.93				
5	12	6		23.80	23.95	23.86				
5	1	0		23.26	23.35	23.35				
5	1	24		23.33	23.41	23.39				
5	25	0		23.27	23.49	23.34				
5	1	1	QPSK	23.77	23.89	23.89				
5	1	23		23.90	23.94	23.95				
5	12	6		23.82	23.96	23.85				
5	1	0		22.79	22.87	22.87				
5	1	24		22.86	22.94	22.91				
5	25	0		22.81	22.96	22.85				
5	1	1	16-QAM	22.83	22.84	22.85	20.60	0.1148		
5	1	1	64-QAM	21.47	21.55	21.49				
5	1	1	256-QAM	18.75	18.84	18.85				
Limit	ERP < 3W			Result			Pass			

NR n12 Maximum Average Power [dBm] (GT - LC = -0.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
10	1	1	PI/2 BPSK	23.83	23.91	23.99	21.74	0.1493		
10	1	50		23.84	23.88	23.90				
10	25	12		23.81	23.96	23.89				
10	1	0		23.28	23.43	23.45				
10	1	51		23.38	23.42	23.42				
10	50	0		23.33	23.41	23.39				
10	1	1	QPSK	23.83	23.91	23.98				
10	1	50		23.91	23.92	23.90				
10	25	12		23.84	23.95	23.88				
10	1	0		23.83	22.90	22.94				
10	1	51		22.82	22.88	22.96				
10	50	0		22.90	23.87	22.90				
10	1	1	16-QAM	22.80	22.90	23.02	20.77	0.1194		
10	1	1	64-QAM	21.50	21.62	21.60				
10	1	1	256-QAM	18.68	18.80	18.87				
Limit	ERP < 3W			Result			Pass			



NR n13 Maximum Average Power [dBm] (GT - LC = -0.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
5	1	1	PI/2 BPSK	23.90	23.81	23.78	21.65	0.1462		
5	1	23		23.87	23.85	23.77				
5	12	6		23.90	23.86	23.74				
5	1	0		20.91	23.30	23.28				
5	1	24		22.24	23.31	23.27				
5	25	0		23.33	23.37	23.28				
5	1	1	QPSK	23.87	23.83	23.86				
5	1	23		23.85	23.86	23.77				
5	12	6		23.82	23.84	23.75				
5	1	0		22.92	22.88	22.83				
5	1	24		22.90	22.84	22.75				
5	25	0		22.84	22.83	22.76				
5	1	1	16-QAM	22.89	22.95	22.85	20.70	0.1175		
5	1	1	64-QAM	21.61	21.55	21.51				
5	1	1	256-QAM	19.00	18.71	18.77				
Limit	ERP < 3W			Result			Pass			

NR n13 Maximum Average Power [dBm] (GT - LC = -0.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
10	1	1	PI/2 BPSK	-	23.91	-	21.66	0.1466		
10	1	50		-	23.76	-				
10	25	12		-	23.85	-				
10	1	0		-	23.37	-				
10	1	51		-	23.31	-				
10	50	0		-	23.38	-				
10	1	1	QPSK	-	23.85	-				
10	1	50		-	23.77	-				
10	25	12		-	23.83	-				
10	1	0		-	22.85	-				
10	1	51		-	22.75	-				
10	50	0		-	22.87	-				
10	1	1	16-QAM	-	22.97	-	20.72	0.1180		
10	1	1	64-QAM	-	21.65	-				
10	1	1	256-QAM	-	18.85	-				
Limit	ERP < 3W			Result			Pass			



NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
5	1	1	PI/2 BPSK	23.83	24.23	24.02	25.90	0.3890		
5	1	23		23.82	24.30	24.05				
5	12	6		23.80	24.25	24.03				
5	1	0		23.32	23.70	23.50				
5	1	24		23.30	23.75	23.52				
5	25	0		23.35	23.81	23.58				
5	1	1	QPSK	23.79	24.20	24.01				
5	1	23		23.78	24.26	24.03				
5	12	6		23.75	24.20	24.02				
5	1	0		22.82	23.23	23.07				
5	1	24		22.81	23.30	23.03				
5	25	0		22.80	23.32	23.06				
5	1	1	16-QAM	22.70	23.03	22.88	24.63	0.2904		
5	1	1	64-QAM	21.63	21.95	21.77				
5	1	1	256-QAM	18.86	19.20	19.08				
Limit	EIRP < 2W			Result			Pass			

NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
10	1	1	PI/2 BPSK	23.86	24.16	24.04	25.93	0.3917		
10	1	50		23.93	24.21	24.03				
10	25	12		24.03	24.33	24.12				
10	1	0		23.38	23.65	23.55				
10	1	51		23.92	23.68	23.54				
10	50	0		23.54	23.79	23.63				
10	1	1	QPSK	23.82	24.15	24.05				
10	1	50		23.93	24.16	24.07				
10	25	12		24.00	24.32	24.11				
10	1	0		22.84	23.21	23.10				
10	1	51		22.88	23.20	23.07				
10	50	0		23.04	23.32	23.10				
10	1	1	16-QAM	22.71	23.00	22.90	24.60	0.2884		
10	1	1	64-QAM	21.66	21.93	21.80				
10	1	1	256-QAM	18.84	19.16	19.05				
Limit	EIRP < 2W			Result			Pass			



NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
15	1	1	PI/2 BPSK	24.05	24.37	24.38	26.09	0.4064		
15	1	77		24.18	24.36	24.23				
15	36	18		24.13	24.48	24.43				
15	1	0		23.56	23.95	23.85				
15	1	78		23.68	23.92	23.74				
15	75	0		23.63	24.01	23.92				
15	1	1	QPSK	24.09	24.42	24.41				
15	1	77		24.17	24.39	24.30				
15	36	18		24.13	24.49	24.44				
15	1	0		23.10	23.49	23.44				
15	1	78		23.20	23.41	23.32				
15	75	0		23.16	23.53	23.44				
15	1	1	16-QAM	23.17	23.29	23.42	25.02	0.3177		
15	1	1	64-QAM	21.76	22.18	22.09				
15	1	1	256-QAM	19.06	19.44	19.45				
Limit	EIRP < 2W			Result			Pass			

NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
20	1	1	PI/2 BPSK	23.95	24.31	24.47	26.08	0.4055		
20	1	104		24.35	24.34	24.25				
20	50	25		24.13	24.48	24.45				
20	1	0		23.46	23.77	23.92				
20	1	105		23.84	23.85	23.78				
20	100	0		23.63	24.00	24.00				
20	1	1	QPSK	24.02	24.14	24.48				
20	1	104		24.39	24.22	24.30				
20	50	25		24.13	24.48	24.45				
20	1	0		23.01	23.30	23.18				
20	1	105		23.37	23.38	23.30				
20	100	0		23.15	23.56	23.51				
20	1	1	16-QAM	22.84	23.14	23.34	24.94	0.3119		
20	1	1	64-QAM	21.72	21.73	22.18				
20	1	1	256-QAM	19.10	19.39	19.44				
Limit	EIRP < 2W			Result			Pass			



NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
25	1	1	PI/2 BPSK	23.96	24.31	24.41	26.08	0.4055		
25	1	131		24.30	24.37	24.18				
25	64	32		24.17	24.48	24.36				
25	1	0		23.50	23.79	23.91				
25	1	132		23.95	23.87	23.74				
25	128	0		23.62	23.94	23.84				
25	1	1	QPSK	24.00	24.38	24.40				
25	1	131		24.33	24.43	24.26				
25	64	32		24.18	24.47	24.36				
25	1	0		23.02	23.35	23.44				
25	1	132		23.47	23.40	23.30				
25	128	0		23.19	23.48	23.37				
25	1	1	16-QAM	22.76	23.19	23.23	24.83	0.3041		
25	1	1	64-QAM	21.71	22.10	22.11				
25	1	1	256-QAM	19.01	19.35	19.47				
Limit	EIRP < 2W			Result			Pass			

NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
30	1	1	PI/2 BPSK	24.00	24.21	24.34	26.08	0.4055		
30	1	158		24.44	24.32	24.13				
30	80	40		24.20	24.48	24.29				
30	1	0		23.45	23.69	23.87				
30	1	159		23.92	24.32	23.67				
30	160	0		23.73	23.86	23.89				
30	1	1	QPSK	24.02	24.22	24.41				
30	1	158		24.48	24.35	24.19				
30	80	40		24.24	24.48	24.36				
30	1	0		23.07	23.32	23.44				
30	1	159		23.54	23.38	23.24				
30	160	0		23.31	23.40	23.42				
30	1	1	16-QAM	22.85	23.09	23.19	24.79	0.3013		
30	1	1	64-QAM	21.75	21.91	22.12				
30	1	1	256-QAM	18.99	19.26	19.45				
Limit	EIRP < 2W			Result			Pass			



NR n25 Maximum Average Power [dBm] (GT - LC = 1.6 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
40	1	1	PI/2 BPSK	23.89	24.03	24.49	26.09	0.4064		
40	1	214		24.27	24.20	24.29				
40	108	54		24.31	24.38	24.39				
40	1	0		23.41	23.58	23.87				
40	1	215		23.76	23.72	23.77				
40	216	0		23.82	23.77	23.90				
40	1	1	QPSK	23.86	24.07	24.40				
40	1	214		24.29	24.31	24.30				
40	108	54		24.32	24.48	24.45				
40	1	0		22.92	23.11	23.46				
40	1	215		23.31	23.30	23.33				
40	216	0		23.28	23.31	23.41				
40	1	1	16-QAM	22.87	22.98	23.31	24.91	0.3097		
40	1	1	64-QAM	21.32	21.82	22.14				
40	1	1	256-QAM	18.94	19.17	19.51				
Limit	EIRP < 2W			Result			Pass			



NR n26 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
5	1	1	PI/2 BPSK	23.66	23.60	23.58	22.35	0.1718		
5	1	23		23.62	23.64	23.62				
5	12	6		23.64	23.65	23.67				
5	1	0		23.17	23.05	23.11				
5	1	24		23.04	23.11	23.15				
5	25	0		23.14	23.15	23.18				
5	1	1	QPSK	23.67	23.62	23.64				
5	1	23		23.56	23.66	23.63				
5	12	6		23.65	23.65	23.70				
5	1	0		22.68	22.62	22.62				
5	1	24		22.60	22.60	22.68				
5	25	0		22.63	22.68	22.72				
5	1	1	16-QAM	22.72	22.54	22.63	21.37	0.1371		
5	1	1	64-QAM	21.38	21.24	21.28				
5	1	1	256-QAM	18.66	18.61	18.58				
Limit	ERP < 7W			Result			Pass			

NR n26 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
10	1	1	PI/2 BPSK	23.58	23.59	23.55	22.35	0.1718		
10	1	50		23.56	23.70	23.62				
10	25	12		23.62	23.66	23.57				
10	1	0		23.13	23.10	23.01				
10	1	51		23.09	23.17	23.15				
10	50	0		23.17	23.21	23.08				
10	1	1	QPSK	23.65	23.64	23.58				
10	1	50		23.56	23.69	23.63				
10	25	12		23.67	23.66	23.55				
10	1	0		22.64	22.62	22.51				
10	1	51		22.53	22.70	22.59				
10	50	0		22.65	22.65	22.57				
10	1	1	16-QAM	22.63	22.67	22.56	21.32	0.1355		
10	1	1	64-QAM	21.26	21.31	21.19				
10	1	1	256-QAM	18.66	18.65	18.53				
Limit	ERP < 7W			Result			Pass			



NR n26 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
15	1	1	PI/2 BPSK	23.78	23.75	23.64	22.47	0.1766		
15	1	77		23.66	23.68	23.65				
15	36	18		23.65	23.76	23.71				
15	1	0		23.24	23.17	23.08				
15	1	78		23.10	23.18	23.14				
15	75	0		23.17	23.25	23.20				
15	1	1	QPSK	23.82	23.76	23.59				
15	1	77		23.69	23.71	23.66				
15	36	18		23.69	23.73	23.60				
15	1	0		22.77	22.75	22.65				
15	1	78		22.64	22.67	22.70				
15	75	0		22.71	22.74	22.69				
15	1	1	16-QAM	22.81	22.64	22.55	21.46	0.1400		
15	1	1	64-QAM	21.45	21.37	21.24				
15	1	1	256-QAM	18.78	18.72	18.55				
Limit	ERP < 7W			Result			Pass			

NR n26 Maximum Average Power [dBm] (GT - LC = 0.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
20	1	1	PI/2 BPSK	23.71	23.83	23.69	22.48	0.1770		
20	1	104		23.58	23.71	23.62				
20	50	25		23.64	23.72	23.71				
20	1	0		23.20	23.20	23.17				
20	1	105		23.06	23.22	23.20				
20	100	0		23.14	23.24	23.18				
20	1	1	QPSK	23.74	23.68	23.60				
20	1	104		23.66	23.65	23.62				
20	50	25		23.61	23.76	23.70				
20	1	0		22.72	22.72	22.63				
20	1	105		22.61	22.66	22.64				
20	100	0		22.66	22.74	22.71				
20	1	1	16-QAM	22.73	22.78	22.62	21.43	0.1390		
20	1	1	64-QAM	21.41	21.20	21.13				
20	1	1	256-QAM	18.76	19.24	19.26				
Limit	ERP < 7W			Result			Pass			



NR n38 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
10	1	1	PI/2 BPSK	24.15	24.16	24.18	25.72	0.3733		
10	1	22		24.12	24.15	24.08				
10	12	6		24.15	24.22	24.21				
10	1	0		23.59	23.58	23.62				
10	1	23		23.53	23.62	23.55				
10	24	0		23.66	23.73	23.67				
10	1	1	QPSK	24.13	24.13	24.18				
10	1	22		24.08	24.11	24.08				
10	12	6		24.17	24.19	24.19				
10	1	0		23.05	23.10	23.10				
10	1	23		23.08	23.16	23.08				
10	24	0		23.17	23.20	23.20				
10	1	1	16-QAM	23.32	23.18	23.12	24.82	0.3034		
10	1	1	64-QAM	21.57	21.77	21.63				
10	1	1	256-QAM	19.38	19.35	19.55				
Limit	EIRP < 2W			Result			Pass			

NR n38 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
15	1	1	PI/2 BPSK	24.28	24.26	24.38	25.98	0.3963		
15	1	36		24.31	24.30	24.39				
15	18	9		24.43	24.29	24.48				
15	1	0		23.76	23.74	23.94				
15	1	37		23.79	23.78	23.88				
15	36	0		23.96	23.84	23.97				
15	1	1	QPSK	24.20	24.19	24.42				
15	1	36		24.30	24.26	24.37				
15	18	9		24.40	24.32	24.46				
15	1	0		23.27	23.20	23.45				
15	1	37		23.36	23.19	23.34				
15	36	0		23.45	23.32	23.48				
15	1	1	16-QAM	23.28	23.20	23.51	25.01	0.3170		
15	1	1	64-QAM	21.75	21.69	21.97				
15	1	1	256-QAM	19.51	19.59	19.73				
Limit	EIRP < 2W			Result			Pass			



NR n38 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
20	1	1	PI/2 BPSK	24.41	24.20	24.33	25.97	0.3954		
20	1	49		24.34	24.20	24.30				
20	25	12		24.45	24.25	24.43				
20	1	0		23.80	23.71	23.80				
20	1	50		23.87	23.75	23.81				
20	50	0		23.95	23.76	23.87				
20	1	1	QPSK	24.33	24.18	24.29				
20	1	49		24.30	24.10	24.27				
20	25	12		24.38	24.28	24.47				
20	1	0		23.31	23.21	23.27				
20	1	50		23.35	23.20	23.28				
20	50	0		23.43	23.28	23.43				
20	1	1	16-QAM	23.51	23.20	23.28	25.01	0.3170		
20	1	1	64-QAM	21.86	21.64	21.72				
20	1	1	256-QAM	19.56	19.53	19.55				
Limit	EIRP < 2W			Result			Pass			

NR n38 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
30	1	1	PI/2 BPSK	24.31	24.30	24.33	25.98	0.3963		
30	1	76		24.47	24.48	24.40				
30	36	18		24.32	24.25	24.35				
30	1	0		23.74	23.79	23.81				
30	1	77		23.93	23.97	23.88				
30	75	0		23.89	23.84	23.92				
30	1	1	QPSK	24.19	24.26	24.20				
30	1	76		24.32	24.47	24.37				
30	36	18		24.33	24.26	24.39				
30	1	0		23.22	23.27	23.29				
30	1	77		23.42	23.47	23.37				
30	75	0		23.36	23.32	23.40				
30	1	1	16-QAM	23.37	23.35	23.33	24.87	0.3069		
30	1	1	64-QAM	21.81	21.71	21.80				
30	1	1	256-QAM	19.60	19.59	19.69				
Limit	EIRP < 2W			Result			Pass			



NR n38 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
40	1	1	PI/2 BPSK	24.45	24.37	24.50	26.00	0.3981		
40	1	104		24.49	24.46	24.48				
40	50	25		24.40	24.28	24.47				
40	1	0		23.88	23.87	23.93				
40	1	105		24.06	23.96	23.96				
40	100	0		23.96	23.86	23.99				
40	1	1	QPSK	24.39	24.33	24.47				
40	1	104		24.50	24.43	24.46				
40	50	25		24.42	24.30	24.44				
40	1	0		23.44	23.36	23.44				
40	1	105		23.57	23.41	23.45				
40	100	0		23.46	23.44	23.51				
40	1	1	16-QAM	23.45	23.35	23.76	25.26	0.3357		
40	1	1	64-QAM	21.74	21.77	21.94				
40	1	1	256-QAM	19.62	19.70	19.73				
Limit	EIRP < 2W			Result			Pass			



NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
20	1	1	PI/2 BPSK	24.41	27.10	26.76	28.62	0.7278		
20	1	49		24.57	27.12	26.66				
20	25	12		24.49	27.12	26.71				
20	1	0		20.88	23.49	23.29				
20	1	50		21.02	23.64	23.15				
20	50	0		23.96	26.61	23.21				
20	1	1	QPSK	23.39	27.05	26.72				
20	1	49		24.52	27.10	26.65				
20	25	12		24.51	27.08	26.71				
20	1	0		20.83	23.46	23.33				
20	1	50		21.02	23.54	23.16				
20	50	0		23.51	26.10	25.74				
20	1	1	16-QAM	23.35	25.99	25.84	27.49	0.5610		
20	1	1	64-QAM	21.71	24.56	24.32				
20	1	1	256-QAM	19.63	22.41	22.08				
Limit	EIRP < 2W			Result			Pass			

NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
30	1	1	PI/2 BPSK	24.42	27.02	27.01	28.66	0.7345		
30	1	76		24.74	27.16	26.88				
30	36	18		24.64	27.01	26.94				
30	1	0		20.96	23.57	23.52				
30	1	77		21.20	23.67	23.42				
30	75	0		24.13	26.61	26.51				
30	1	1	QPSK	24.43	26.97	26.97				
30	1	76		24.70	27.12	26.85				
30	36	18		24.64	27.05	26.94				
30	1	0		20.95	23.55	23.51				
30	1	77		21.24	23.63	23.43				
30	75	0		23.66	26.10	25.87				
30	1	1	16-QAM	23.57	26.22	26.15	27.72	0.5916		
30	1	1	64-QAM	22.06	24.71	24.51				
30	1	1	256-QAM	19.75	22.45	22.25				
Limit	EIRP < 2W			Result			Pass			



NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
40	1	1	PI/2 BPSK	24.46	27.22	27.15	28.78	0.7551		
40	1	104		24.61	27.28	26.92				
40	50	25		24.59	27.22	26.95				
40	1	0		20.98	23.84	23.62				
40	1	105		21.25	23.83	23.49				
40	100	0		24.09	26.72	26.44				
40	1	1	QPSK	24.41	27.23	27.09				
40	1	104		24.57	27.22	26.89				
40	50	25		24.57	27.24	26.88				
40	1	0		20.91	23.75	23.64				
40	1	105		21.24	23.76	23.45				
40	100	0		23.56	26.23	25.96				
40	1	1	16-QAM	23.51	26.28	26.25	27.78	0.5998		
40	1	1	64-QAM	21.97	24.84	24.59				
40	1	1	256-QAM	19.81	22.56	22.34				
Limit	EIRP < 2W			Result			Pass			

NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
50	1	1	PI/2 BPSK	24.28	27.05	27.00	28.58	0.7211		
50	1	131		24.45	27.05	26.72				
50	64	32		24.48	27.08	26.92				
50	1	0		20.77	23.62	23.54				
50	1	132		21.01	23.57	23.18				
50	128	0		23.91	26.58	26.39				
50	1	1	QPSK	24.32	27.01	27.02				
50	1	131		24.46	27.00	26.61				
50	64	32		24.48	27.06	26.90				
50	1	0		20.81	23.58	23.53				
50	1	132		21.04	23.54	23.18				
50	128	0		23.52	26.07	25.94				
50	1	1	16-QAM	23.39	26.12	26.12	27.62	0.5781		
50	1	1	64-QAM	21.87	24.57	24.65				
50	1	1	256-QAM	19.56	22.29	22.23				
Limit	EIRP < 2W			Result			Pass			



NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
60	1	1	PI/2 BPSK	24.37	26.95	26.92	28.64	0.7311		
60	1	160		24.44	26.98	26.66				
60	81	40		24.45	27.05	26.91				
60	1	0		20.89	23.54	23.47				
60	1	161		21.11	23.45	23.47				
60	162	0		24.06	26.60	26.35				
60	1	1	QPSK	24.28	26.87	26.89				
60	1	160		24.46	26.88	26.57				
60	81	40		24.43	27.14	26.98				
60	1	0		20.84	23.42	23.54				
60	1	161		21.09	23.35	23.15				
60	162	0		23.58	26.09	25.88				
60	1	1	16-QAM	23.42	26.11	25.95	27.61	0.5768		
60	1	1	64-QAM	21.91	24.58	24.40				
60	1	1	256-QAM	19.65	22.35	22.18				
Limit	EIRP < 2W			Result			Pass			

NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
70	1	1	PI/2 BPSK	24.34	26.84	26.81	28.41	0.6934		
70	1	187		24.46	26.77	26.58				
70	90	45		24.49	26.89	26.65				
70	1	0		20.80	23.32	23.36				
70	1	188		20.92	23.26	23.09				
70	180	0		24.02	26.43	26.16				
70	1	1	QPSK	24.29	26.81	26.74				
70	1	187		24.37	26.72	26.57				
70	90	45		24.45	26.91	26.64				
70	1	0		20.78	23.31	23.31				
70	1	188		20.90	23.18	23.01				
70	180	0		23.49	25.91	25.75				
70	1	1	16-QAM	23.39	25.89	25.85	27.39	0.5483		
70	1	1	64-QAM	21.83	24.42	24.31				
70	1	1	256-QAM	19.66	22.07	22.05				
Limit	EIRP < 2W			Result			Pass			



NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
80	1	1	PI/2 BPSK	24.22	26.78	26.81	28.45	0.6998		
80	1	215		24.47	26.74	26.68				
80	108	54		24.43	26.88	26.79				
80	1	0		20.71	23.35	23.35				
80	1	216		20.93	23.32	23.16				
80	216	0		23.97	26.42	26.27				
80	1	1	QPSK	24.19	26.84	26.78				
80	1	215		24.40	26.68	26.59				
80	108	54		24.47	26.95	26.69				
80	1	0		20.73	23.27	23.38				
80	1	216		20.90	23.26	23.07				
80	216	0		23.44	25.84	25.74				
80	1	1	16-QAM	23.43	25.84	25.83	27.34	0.5420		
80	1	1	64-QAM	21.74	24.03	24.44				
80	1	1	256-QAM	19.54	21.98	22.05				
Limit	EIRP < 2W			Result			Pass			

NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
90	1	1	PI/2 BPSK	24.24	26.82	26.89	28.44	0.6982		
90	1	243		24.47	26.79	26.61				
90	120	60		24.43	26.94	26.87				
90	1	0		20.71	23.23	23.44				
90	1	244		20.94	23.32	23.13				
90	243	0		23.84	26.36	26.35				
90	1	1	QPSK	24.19	26.78	26.86				
90	1	243		24.41	26.82	26.43				
90	120	60		24.44	26.91	26.87				
90	1	0		20.68	23.15	23.35				
90	1	244		20.92	23.32	23.01				
90	243	0		23.40	25.88	25.83				
90	1	1	16-QAM	23.18	25.84	25.85	27.35	0.5433		
90	1	1	64-QAM	21.81	24.39	24.49				
90	1	1	256-QAM	19.41	22.02	22.15				
Limit	EIRP < 2W			Result			Pass			



NR n41 Maximum Average Power [dBm] (GT - LC = 1.5 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
100	1	1	PI/2 BPSK	24.24	26.76	26.91	28.48	0.7047		
100	1	271		24.57	26.78	26.68				
100	135	67		24.41	26.94	26.91				
100	1	0		20.77	23.38	23.33				
100	1	272		21.09	23.35	23.19				
100	270	0		23.43	26.44	26.37				
100	1	1	QPSK	24.21	26.76	26.84				
100	1	271		24.48	26.80	26.54				
100	135	67		24.40	26.98	26.84				
100	1	0		20.69	23.35	23.36				
100	1	272		21.03	23.37	23.15				
100	270	0		23.42	25.96	25.86				
100	1	1	16-QAM	23.26	25.90	26.02	27.52	0.5649		
100	1	1	64-QAM	21.80	24.38	24.53				
100	1	1	256-QAM	19.43	21.98	23.92				
Limit	EIRP < 2W			Result			Pass			



NR n66 Maximum Average Power [dBm] (GT - LC = 1.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
5	1	1	PI/2 BPSK	23.80	23.96	24.30	26.14	0.4111		
5	1	23		23.81	24.13	24.31				
5	12	6		23.79	24.10	24.34				
5	1	0		23.28	23.46	23.80				
5	1	24		23.25	23.59	23.78				
5	25	0		23.31	23.66	23.83				
5	1	1	QPSK	23.73	23.90	24.26				
5	1	23		23.71	24.00	24.30				
5	12	6		23.81	24.17	24.34				
5	1	0		22.73	22.96	23.31				
5	1	24		22.73	23.02	23.29				
5	25	0		22.82	23.12	23.33				
5	1	1	16-QAM	22.82	23.12	23.28	25.08	0.3221		
5	1	1	64-QAM	21.31	21.69	22.03				
5	1	1	256-QAM	19.38	19.57	19.29				
Limit	EIRP < 1W			Result			Pass			

NR n66 Maximum Average Power [dBm] (GT - LC = 1.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
10	1	1	PI/2 BPSK	23.85	24.01	24.31	26.17	0.4140		
10	1	50		23.91	24.07	24.37				
10	25	12		23.98	24.18	24.27				
10	1	0		23.41	23.53	23.77				
10	1	51		23.36	23.56	23.80				
10	50	0		23.42	23.55	23.90				
10	1	1	QPSK	23.98	24.03	24.26				
10	1	50		23.86	24.12	24.36				
10	25	12		23.90	24.05	24.37				
10	1	0		22.95	23.04	23.30				
10	1	51		22.93	23.12	23.33				
10	50	0		22.90	23.00	23.37				
10	1	1	16-QAM	22.83	22.97	23.23	25.03	0.3184		
10	1	1	64-QAM	21.64	21.75	22.05				
10	1	1	256-QAM	18.90	19.01	19.26				
Limit	EIRP < 1W			Result			Pass			



NR n66 Maximum Average Power [dBm] (GT - LC = 1.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
15	1	1	PI/2 BPSK	23.90	24.10	24.14	26.19	0.4159		
15	1	77		24.04	24.22	24.33				
15	36	18		23.98	24.21	24.24				
15	1	0		23.37	23.62	23.67				
15	1	78		23.55	23.73	23.87				
15	75	0		23.48	23.74	23.83				
15	1	1	QPSK	23.89	24.12	24.21				
15	1	77		24.08	24.22	24.39				
15	36	18		24.00	24.25	24.28				
15	1	0		22.89	23.18	23.19				
15	1	78		23.12	23.30	23.32				
15	75	0		23.03	23.23	23.33				
15	1	1	16-QAM	22.82	23.04	23.19	24.99	0.3155		
15	1	1	64-QAM	21.31	21.86	21.90				
15	1	1	256-QAM	18.87	19.14	19.14				
Limit	EIRP < 1W			Result			Pass			

NR n66 Maximum Average Power [dBm] (GT - LC = 1.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
20	1	1	PI/2 BPSK	23.85	24.12	24.16	26.17	0.4140		
20	1	104		24.07	24.18	24.37				
20	50	25		23.96	24.21	24.34				
20	1	0		23.38	23.62	23.64				
20	1	105		23.50	23.66	23.87				
20	100	0		23.47	23.73	23.91				
20	1	1	QPSK	23.90	24.17	23.97				
20	1	104		24.03	24.24	24.17				
20	50	25		23.91	24.25	24.30				
20	1	0		22.79	23.16	23.10				
20	1	105		23.01	23.20	23.29				
20	100	0		22.96	23.24	23.36				
20	1	1	16-QAM	22.78	23.12	22.98	24.92	0.3105		
20	1	1	64-QAM	21.55	21.89	21.97				
20	1	1	256-QAM	18.79	19.12	19.35				
Limit	EIRP < 1W			Result			Pass			



NR n66 Maximum Average Power [dBm] (GT - LC = 1.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
30	1	1	PI/2 BPSK	23.95	24.09	24.29	26.28	0.4246		
30	1	158		24.13	24.29	24.46				
30	80	40		24.11	24.30	24.45				
30	1	0		23.45	23.57	23.80				
30	1	159		23.65	23.86	23.98				
30	160	0		23.68	23.81	23.97				
30	1	1	QPSK	23.99	24.11	24.48				
30	1	158		24.20	24.34	24.47				
30	80	40		24.12	24.32	24.43				
30	1	0		23.03	23.14	23.34				
30	1	159		23.21	23.35	23.52				
30	160	0		23.18	23.31	23.47				
30	1	1	16-QAM	22.94	23.06	23.36	25.16	0.3281		
30	1	1	64-QAM	21.73	21.80	22.27				
30	1	1	256-QAM	18.99	19.16	19.59				
Limit	EIRP < 1W			Result			Pass			

NR n66 Maximum Average Power [dBm] (GT - LC = 1.8 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	EIRP (dBm)	EIRP(W)		
40	1	1	PI/2 BPSK	23.90	24.07	24.49	26.29	0.4256		
40	1	214		24.12	24.28	24.44				
40	108	54		24.10	24.29	24.35				
40	1	0		23.35	23.55	23.69				
40	1	215		23.64	23.77	23.94				
40	216	0		23.60	23.75	23.82				
40	1	1	QPSK	23.92	24.14	24.19				
40	1	214		24.28	24.32	24.46				
40	108	54		24.10	24.35	24.35				
40	1	0		22.93	23.13	23.23				
40	1	215		23.20	23.33	23.53				
40	216	0		24.09	23.30	23.36				
40	1	1	16-QAM	22.82	23.07	23.10	24.90	0.3090		
40	1	1	64-QAM	21.59	21.81	21.90				
40	1	1	256-QAM	18.92	19.06	19.25				
Limit	EIRP < 1W			Result			Pass			



NR n70 Maximum Average Power [dBm] (GT - LC = 1.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
5	1	1	PI/2 BPSK	24.00	23.88	23.75	22.95	0.1972		
5	1	23		23.92	23.89	23.90				
5	12	6		23.72	23.82	23.88				
5	1	0		23.46	23.06	23.41				
5	1	24		23.22	23.35	23.08				
5	25	0		23.52	23.08	23.31				
5	1	1	QPSK	23.73	23.76	23.68				
5	1	23		23.64	23.86	23.60				
5	12	6		23.65	23.85	23.85				
5	1	0		22.92	22.88	22.50				
5	1	24		22.78	22.67	22.63				
5	25	0		22.89	22.50	22.86				
5	1	1	16-QAM	22.92	22.77	22.92	21.87	0.1538		
5	1	1	64-QAM	21.64	21.67	21.64				
5	1	1	256-QAM	18.98	18.97	18.93				
Limit	EIRP < 1W			Result			Pass			

NR n70 Maximum Average Power [dBm] (GT - LC = 1.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
10	1	1	PI/2 BPSK	23.81	23.65	23.77	22.9	0.1950		
10	1	50		23.83	23.77	23.84				
10	25	12		23.70	23.44	23.63				
10	1	0		23.24	23.39	23.16				
10	1	51		23.09	23.06	23.34				
10	50	0		23.32	23.08	23.17				
10	1	1	QPSK	23.95	23.51	23.70				
10	1	50		23.84	23.63	23.83				
10	25	12		23.87	23.80	23.68				
10	1	0		22.96	22.63	22.95				
10	1	51		22.83	22.79	22.80				
10	50	0		22.93	22.91	22.98				
10	1	1	16-QAM	22.73	22.76	22.63	21.71	0.1483		
10	1	1	64-QAM	21.45	21.24	21.68				
10	1	1	256-QAM	18.67	18.81	19.03				
Limit	EIRP < 1W			Result			Pass			



NR n70 Maximum Average Power [dBm] (GT - LC = 1.1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
15	1	1	PI/2 BPSK	-	24.00	-	22.95	0.1972		
15	1	77		-	23.95	-				
15	36	18		-	23.87	-				
15	1	0		-	23.51	-				
15	1	78		-	23.06	-				
15	75	0		-	23.55	-				
15	1	1	QPSK	-	23.99	-			22.95	0.1972
15	1	77		-	23.99	-				
15	36	18		-	23.83	-				
15	1	0		-	23.07	-				
15	1	78		-	22.71	-				
15	75	0		-	22.88	-				
15	1	1	16-QAM	-	22.87	-	21.82	0.1521		
15	1	1	64-QAM	-	21.66	-				
15	1	1	256-QAM	-	18.73	-				
Limit	EIRP < 1W			Result			Pass			



NR n71 Maximum Average Power [dBm] (GT - LC = 1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
5	1	1	PI/2 BPSK	23.66	23.64	23.70	22.67	0.1849		
5	1	23		23.67	23.65	23.69				
5	12	6		23.73	23.68	23.72				
5	1	0		23.18	23.07	23.22				
5	1	24		23.27	23.17	23.19				
5	25	0		23.19	23.20	23.19				
5	1	1	QPSK	23.65	23.68	23.66				
5	1	23		23.68	23.65	23.68				
5	12	6		23.76	23.71	23.69				
5	1	0		22.63	22.66	22.62				
5	1	24		23.82	22.71	22.59				
5	25	0		22.68	22.70	22.66				
5	1	1	16-QAM	22.63	22.69	22.62	21.54	0.1426		
5	1	1	64-QAM	21.28	21.26	21.49				
5	1	1	256-QAM	18.62	18.54	18.67				
Limit	ERP < 3W			Result			Pass			

NR n71 Maximum Average Power [dBm] (GT - LC = 1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
10	1	1	PI/2 BPSK	23.66	23.67	23.66	22.63	0.1832		
10	1	50		23.67	23.71	23.65				
10	25	12		23.72	23.70	23.64				
10	1	0		23.17	23.14	23.15				
10	1	51		23.16	23.24	23.10				
10	50	0		23.25	23.21	23.10				
10	1	1	QPSK	23.67	23.71	23.68				
10	1	50		23.73	23.73	23.62				
10	25	12		23.78	23.71	23.60				
10	1	0		22.69	22.64	22.67				
10	1	51		22.67	22.72	22.62				
10	50	0		22.76	22.68	22.56				
10	1	1	16-QAM	22.69	22.66	22.70	21.55	0.1429		
10	1	1	64-QAM	21.30	21.32	21.28				
10	1	1	256-QAM	18.56	18.72	18.62				
Limit	ERP < 3W			Result			Pass			



NR n71 Maximum Average Power [dBm] (GT - LC = 1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
15	1	1	PI/2 BPSK	23.69	23.75	23.64	22.68	0.1854		
15	1	77		23.76	23.62	23.67				
15	36	18		23.77	23.82	23.70				
15	1	0		23.18	23.32	23.16				
15	1	78		23.27	23.09	23.14				
15	75	0		23.24	23.31	23.15				
15	1	1	QPSK	23.71	23.76	23.82				
15	1	77		23.80	23.66	23.68				
15	36	18		23.76	23.83	23.70				
15	1	0		22.73	22.76	22.71				
15	1	78		22.81	22.69	22.68				
15	75	0		22.78	22.80	22.65				
15	1	1	16-QAM	22.68	22.78	22.71	21.63	0.1455		
15	1	1	64-QAM	21.30	21.42	21.42				
15	1	1	256-QAM	18.63	18.77	18.70				
Limit	ERP < 3W			Result			Pass			

NR n71 Maximum Average Power [dBm] (GT - LC = 1 dB)										
BW [MHz]	RB Size	RB Offset	Mod	Lowest	Middle	Highest	ERP (dBm)	ERP(W)		
20	1	1	PI/2 BPSK	23.60	23.70	23.94	22.79	0.1901		
20	1	104		23.69	23.64	23.65				
20	50	25		23.74	23.87	23.67				
20	1	0		23.12	23.21	23.36				
20	1	105		23.13	23.12	23.20				
20	100	0		23.26	23.33	23.31				
20	1	1	QPSK	23.67	23.79	23.93				
20	1	104		23.70	23.70	23.73				
20	50	25		23.77	23.81	23.71				
20	1	0		22.67	22.73	22.80				
20	1	105		22.70	22.72	22.70				
20	100	0		22.76	22.80	22.73				
20	1	1	16-QAM	22.64	22.75	22.90	21.75	0.1496		
20	1	1	64-QAM	21.23	21.47	21.52				
20	1	1	256-QAM	18.61	18.81	18.83				
Limit	ERP < 3W			Result			Pass			



<MIMO Mode>

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
20	1	1	QPSK	18.42	21.15	20.83	18.31	21.16	21.04	21.38	24.17	23.95	28.80	0.7586
20	1	49		18.51	21.26	20.81	18.21	20.19	20.96	21.37	23.77	23.90		
20	25	12		18.72	21.33	20.93	18.44	21.22	21.12	21.59	24.29	24.04		
20	1	0		16.55	19.17	18.68	16.32	19.07	18.99	19.45	22.13	21.85		
20	1	50		16.75	19.24	18.79	16.35	19.15	18.95	19.56	22.21	21.88		
20	51	0		17.12	19.74	19.41	16.87	19.55	19.54	20.01	22.66	22.49		
20	1	1	16-QAM	18.03	20.58	20.28	18.01	20.85	20.88	21.03	23.73	23.60	28.24	0.6668
20	1	1	64-QAM	16.61	19.17	18.88	16.21	19.10	18.87	19.42	22.15	21.89		
20	1	1	256-QAM	13.32	16.32	16.08	13.35	16.23	16.21	16.35	19.29	19.16		
Limit	EIRP < 2W			Result									Pass	

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
30	1	1	QPSK	18.49	21.07	20.82	18.36	21.06	20.79	21.44	24.08	23.82	28.85	0.7674
30	1	76		18.87	21.43	20.98	18.57	21.23	21.08	21.73	24.34	24.04		
30	39	19		18.77	21.22	20.87	18.54	21.09	21.04	21.67	24.17	23.97		
30	1	0		16.65	19.13	18.83	16.54	19.21	18.92	19.61	22.18	21.89		
30	1	77		16.95	19.32	18.78	16.58	19.35	19.17	19.78	22.35	21.99		
30	78	0		17.27	19.81	19.45	17.05	19.59	19.55	20.17	22.71	22.51		
30	1	1	16-QAM	17.94	20.73	20.28	18.08	20.77	20.57	21.02	23.76	23.44	28.27	0.6714
30	1	1	64-QAM	16.54	19.11	18.79	16.31	18.98	18.77	19.44	22.06	21.79		
30	1	1	256-QAM	13.67	16.42	16.05	13.69	16.32	16.22	16.69	19.38	19.15		
Limit	EIRP < 2W			Result									Pass	

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
40	1	1	QPSK	18.58	21.31	21.19	18.22	20.92	21.19	21.41	24.13	24.20	28.90	0.7762
40	1	104		18.83	21.45	21.06	18.39	21.31	21.14	21.63	24.39	24.11		
40	53	26		18.64	21.32	21.03	18.34	21.13	21.10	21.50	24.24	24.08		
40	1	0		16.67	19.45	19.15	16.43	19.23	19.10	19.56	22.35	22.14		
40	1	105		16.84	19.45	19.01	16.41	19.31	19.23	19.64	22.39	22.13		
40	106	0		17.17	19.86	19.65	16.98	19.72	19.79	20.09	22.80	22.73		
40	1	1	16-QAM	17.93	20.81	20.62	18.01	20.84	20.71	20.98	23.84	23.68	28.35	0.6839
40	1	1	64-QAM	16.54	19.31	19.22	16.24	19.01	19.02	19.40	22.17	22.13		
40	1	1	256-QAM	13.73	16.40	16.37	13.65	16.37	16.29	16.70	19.40	19.34		
Limit	EIRP < 2W			Result									Pass	



NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
50	1	1	QPSK	18.50	21.15	21.11	18.21	21.21	21.26	21.37	24.19	24.20	28.71	0.7430
50	1	131		18.74	21.09	20.75	18.44	21.08	21.15	21.60	24.10	23.96		
50	67	33		18.78	21.29	21.04	18.46	21.04	21.17	21.63	24.18	24.12		
50	1	0		16.77	19.11	19.09	16.35	19.04	19.07	19.58	22.09	22.09		
50	1	132		16.92	19.22	18.86	16.45	19.15	19.18	19.70	22.20	22.03		
50	133	0		17.26	19.78	19.56	17.01	19.68	19.72	20.15	22.74	22.65		
50	1	1	16-QAM	17.93	20.64	20.55	17.95	20.72	20.83	20.95	23.69	23.70	28.21	0.6622
50	1	1	64-QAM	16.68	19.10	19.08	16.16	18.92	18.96	19.44	22.02	22.03		
50	1	1	256-QAM	13.68	16.32	16.19	13.51	16.27	16.34	16.61	19.31	19.28		
Limit	EIRP < 2W			Result									Pass	

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
60	1	1	QPSK	18.27	21.06	21.05	18.07	20.95	21.05	21.18	24.02	24.06	28.72	0.7447
60	1	160		18.64	21.05	20.76	18.29	21.12	21.03	21.48	24.10	23.91		
60	81	40		18.66	21.24	21.07	18.38	21.15	20.98	21.53	24.21	24.04		
60	1	0		16.59	19.15	19.04	16.13	18.91	19.07	19.38	22.04	22.07		
60	1	161		16.81	19.19	18.89	16.35	19.20	19.06	19.60	22.21	21.99		
60	162	0		17.14	19.71	19.54	16.82	19.66	19.54	19.99	22.70	22.55		
60	1	1	16-QAM	17.92	20.76	20.53	17.88	20.49	20.79	20.91	23.64	23.67	28.18	0.6577
60	1	1	64-QAM	16.45	19.18	19.14	16.07	18.75	18.93	19.27	21.98	22.05		
60	1	1	256-QAM	13.75	16.18	16.06	13.30	16.26	16.33	16.54	19.23	19.21		
Limit	EIRP < 2W			Result									Pass	

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
70	1	1	QPSK	18.36	20.96	18.73	18.08	20.65	18.84	21.23	23.82	21.80	28.56	0.7178
70	1	187		18.73	20.89	20.60	18.36	21.04	20.84	21.56	23.98	23.73		
70	95	47		18.56	21.15	20.98	18.30	20.92	20.91	21.44	24.05	23.96		
70	1	0		16.44	18.83	18.89	16.04	18.78	18.94	19.25	21.82	21.93		
70	1	188		16.52	18.78	18.66	16.28	19.03	19.92	19.41	21.92	22.35		
70	189	0		16.99	19.55	19.36	16.75	19.53	19.47	19.88	22.55	22.43		
70	1	1	16-QAM	17.87	20.35	20.26	17.78	20.32	20.55	20.84	23.35	23.42	27.93	0.6209
70	1	1	64-QAM	16.48	18.82	18.82	15.92	18.66	18.83	19.22	21.75	21.84		
70	1	1	256-QAM	13.58	16.04	16.02	13.45	16.02	16.13	16.53	19.04	19.09		
Limit	EIRP < 2W			Result									Pass	



NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
80	1	1	QPSK	18.30	20.92	20.86	17.95	20.93	20.74	21.14	23.94	23.81	28.53	0.7129
80	1	215		18.55	20.78	20.59	18.40	21.15	20.95	21.49	23.98	23.78		
80	109	54		18.51	21.06	20.92	18.14	20.95	21.03	21.34	24.02	23.99		
80	1	0		16.39	18.85	18.92	15.92	18.66	18.83	19.17	21.77	21.89		
80	1	216		16.69	18.87	18.65	16.39	19.13	19.07	19.55	22.01	21.88		
80	217	0		17.01	19.61	19.45	16.62	19.53	19.62	19.83	22.58	22.55		
80	1	1	16-QAM	17.85	20.39	20.35	17.71	20.38	20.55	20.79	23.39	23.46	27.97	0.6266
80	1	1	64-QAM	16.44	18.86	18.85	16.58	18.65	18.73	19.52	21.77	21.80		
80	1	1	256-QAM	13.46	16.07	16.05	13.21	15.89	15.99	16.35	18.99	19.03		
Limit	EIRP < 2W			Result									Pass	

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
90	1	1	QPSK	18.23	20.82	20.95	18.00	20.60	20.80	21.13	23.72	23.89	28.57	0.7194
90	1	243		18.57	20.84	20.94	18.40	21.25	21.12	21.50	24.06	24.04		
90	123	61		18.21	21.02	20.82	18.53	21.01	20.85	21.38	24.03	23.85		
90	1	0		16.33	18.85	18.98	15.98	18.71	18.75	19.17	21.79	21.88		
90	1	244		16.71	18.92	19.03	16.41	19.01	19.22	19.57	21.98	22.14		
90	245	0		16.92	19.53	19.35	16.69	19.54	19.38	19.82	22.55	22.38		
90	1	1	16-QAM	17.80	20.35	20.54	17.39	20.19	20.28	20.61	23.28	23.42	27.93	0.6209
90	1	1	64-QAM	16.64	18.88	18.98	16.01	18.54	18.81	19.35	21.72	21.91		
90	1	1	256-QAM	13.51	16.09	16.03	13.25	15.78	15.85	16.39	18.95	18.95		
Limit	EIRP < 2W			Result									Pass	

NR n41 Maximum Average Power [dBm], DG = 4.51 dBi														
BW	RB	RB	Mod	Antenna 8			Antenna 0			Combine			EIRP	EIRP
(MHz)	Size	Offset		Lowest	Middle	Highest	Lowest	Middle	Highest	Lowest	Middle	Highest	(dBm)	(W)
100	1	1	QPSK	18.28	20.77	20.82	18.01	20.40	20.69	21.16	23.60	23.77	28.57	0.7194
100	1	271		18.49	20.72	20.62	18.48	20.96	20.92	21.50	23.85	23.78		
100	137	68		18.50	21.09	20.95	18.15	21.01	21.02	21.34	24.06	24.00		
100	1	0		16.35	18.85	18.90	16.01	18.56	18.73	19.19	21.72	21.83		
100	1	272		16.54	18.92	18.81	16.47	19.01	19.04	19.52	21.98	21.94		
100	273	0		16.98	19.52	19.42	16.64	19.48	19.54	19.82	22.51	22.49		
100	1	1	16-QAM	16.39	20.29	20.37	16.13	20.03	20.45	19.27	23.17	23.42	27.93	0.6209
100	1	1	64-QAM	16.34	18.79	18.98	15.89	18.43	18.59	19.13	21.62	21.80		
100	1	1	256-QAM	13.36	16.00	15.65	13.26	15.71	16.01	16.32	18.87	18.84		
Limit	EIRP < 2W			Result									Pass	


**FR1 n7****Peak-to-Average Ratio**

Mode	FR1 n7 / 20MHz / DFT-S OFDM				
Mod.	PI/2 BPSK	QPSK	16QAM	64QAM	Limit: 13dB
RB Size	Full RB	Full RB	Full RB	Full RB	Result
Middle CH	4.00	5.02	5.16	5.46	PASS
Mode	FR1 n7 / 20MHz / DFT-S OFDM				
Mod.	256QAM				Limit: 13dB
RB Size	Full RB				Result
Middle CH	6.96				PASS




FR1 n7 / 20MHz / DFT-S OFDM / Middle Channel / Full RB


PI/2 BPSK




QPSK




16QAM



64QAM



256QAM



**26dB Bandwidth**


Mode	FR1 n7 : 26dB BW(MHz) / DFT-S OFDM							
BW	5MHz		10MHz		15MHz		20MHz	
Mod.	PI/2 BPSK		PI/2 BPSK		PI/2 BPSK		PI/2 BPSK	
Middle CH	5.04		9.51		14.54		18.98	
BW	25MHz		30MHz		40MHz		50MHz	
Mod.	PI/2 BPSK		PI/2 BPSK		PI/2 BPSK		PI/2 BPSK	
Middle CH	23.78		29.55		41.08			

Mode	FR1 n7 : 26dB BW(MHz) / CP OFDM							
BW	5MHz		10MHz		15MHz		20MHz	
Mod.	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM
Middle CH	5.10	5.08	10.15	10.01	15.17	14.93	20.06	20.06
Mod.	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM
Middle CH	4.97	5.06	9.97	10.11	15.11	15.11	19.94	20.06
BW	25MHz		30MHz		40MHz		50MHz	
Mod.	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM
Middle CH	24.83	24.78	29.67	29.61	41.24	41.24		
Mod.	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM
Middle CH	24.83	24.83	29.73	29.55	41.16	41.00		




FR1 n7 / 5MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 5MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM



64QAM




256QAM






FR1 n7 / 10MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 10MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM








64QAM



256QAM




FR1 n7 / 15MHz / DFT-S OFDM / Middle Channel / Full RB
PI/2 BPSK

FR1 n7 / 15MHz / CP OFDM / Middle Channel / Full RB
QPSK

16QAM

64QAM

256QAM





FR1 n7 / 20MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 20MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM








64QAM



256QAM




FR1 n7 / 25MHz / DFT-S OFDM / Middle Channel / Full RB
PI/2 BPSK

FR1 n7 / 25MHz / CP OFDM / Middle Channel / Full RB
QPSK

16QAM

64QAM

256QAM





FR1 n7 / 30MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 30MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM



64QAM




256QAM






FR1 n7 / 40MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 40MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM



64QAM



256QAM



**Occupied Bandwidth**


Mode	FR1 n7 : 99%OBW(MHz) / DFT-S OFDM							
BW	5MHz		10MHz		15MHz		20MHz	
Mod.	PI/2 BPSK		PI/2 BPSK		PI/2 BPSK		PI/2 BPSK	
Middle CH	4.46		8.91		13.49		17.88	
BW	25MHz		30MHz		40MHz		50MHz	
Mod.	PI/2 BPSK		PI/2 BPSK		PI/2 BPSK		PI/2 BPSK	
Middle CH	22.90		28.63		38.80			

Mode	FR1 n7 : 99%OBW (MHz) / CP OFDM							
BW	5MHz		10MHz		15MHz		20MHz	
Mod.	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM
Middle CH	4.50	4.51	9.29	9.29	14.20	14.16	18.99	18.97
Mod.	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM
Middle CH	4.50	4.49	9.27	9.30	14.19	14.13	18.96	19.03
BW	25MHz		30MHz		40MHz		50MHz	
Mod.	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM	QPSK	16QAM
Middle CH	23.84	23.76	28.62	28.61	38.86	38.91		
Mod.	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM	64QAM	256QAM
Middle CH	23.78	23.76	28.59	28.55	38.90	38.75		




FR1 n7 / 5MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 5MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM







64QAM



256QAM




FR1 n7 / 10MHz / DFT-S OFDM / Middle Channel / Full RB
PI/2 BPSK

FR1 n7 / 10MHz / CP OFDM / Middle Channel / Full RB
QPSK

16QAM

64QAM

256QAM



FR1 n7 / 15MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 15MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM



64QAM




256QAM




FR1 n7 / 20MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 20MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM








64QAM



256QAM




FR1 n7 / 25MHz / DFT-S OFDM / Middle Channel / Full RB
PI/2 BPSK

FR1 n7 / 25MHz / CP OFDM / Middle Channel / Full RB
QPSK

16QAM

64QAM

256QAM





FR1 n7 / 30MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 30MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM



64QAM




256QAM






FR1 n7 / 40MHz / DFT-S OFDM / Middle Channel / Full RB

PI/2 BPSK




FR1 n7 / 40MHz / CP OFDM / Middle Channel / Full RB


QPSK




16QAM



64QAM



256QAM







Conducted Band Edge

FR1 n7 / 5MHz / DFT-S OFDM / PI/2 BPSK

Lowest Band Edge / 1RB0

Highest Band Edge / 1RBmax



Lowest Band Edge / Full RB

Highest Band Edge / Full RB

