



3301 E. Deseret Drive, St. George, UT 84790
www.wilsonelectronics.com • info@wilsonelectronics.com
phone 1-800-204-4104 • fax 1-435-656-2432

November 26, 2014

Subject: RF MPE EXPOSURE
Re: FCC ID: PWO460022

To Whom It May Concern:

The MPE calculations for model 460022 signal booster were done for each frequency band: 1700/2100 MHz, 800 MHz, 700 MHz Band 13, 700 MHz Band 12, and 1900 MHz. For each band two calculations were done; these included the worst case scenario for each of the different types of antennas that may be connected to this signal booster: outside antennas. The order of the attached calculations is as follows:

1700/2100 MHz band:

1. Outside Antenna: 314453-40075

800 MHz band:

2. Outside Antenna: 311129-400100

700 MHz Band 13:

3. Outside Antenna: 314411-40075

700 MHz Band 12:

4. Outside Antenna: 314411-40075

1900 MHz band:

5. Outside Antenna: 314473-0640

A booster's uplink power must not exceed 1 watt equivalent isotropic radiated power (EIRP) for each band of operation. Composite downlink power must not exceed 0.05 watt EIRP for each band of operation (20.21(e)(8)(i)(D)). The following formula was used to calculate the equivalent isotropic radiated power:

$$\text{EIRP} = \text{Power Out (Watts)} * \text{Duty Cycle Percent} * \text{Antenna Gain (non-log)} * \text{Coax loss (non-log)}$$

The power density (mW/cm^2) is calculated using the following formula:

$$\text{Calculated Power Density} = 1000 * \text{EIRP (Watts)} / (4 * \pi * (\text{Distance from Antenna (cm)})^2)$$

Sincerely,

A handwritten signature in black ink, appearing to read 'Patrick L. Cook'.

Patrick L. Cook
Chief Technology Officer



Minimum Safe Distance From Antennas

Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

Frequency MHz	1710
Pout Watts	0.32659
Duty Cycle Percent	100.0%
Ant. Gain dBi	8.20
Coax Loss dB	4.49
Distance From Antenna In cm	20.0

RESULTS OF CALCULATIONS

Ant. Gain less Coax Loss dBi	3.71
Distance From Antenna In Inches	7.87
EIRP (Watts)	0.7674
FCC Power Density Limit (mw/cm ²)	1.00
Calculated Power Density (mw/cm ²)	0.1527

REFERENCE DATA

Pout dBm	25.14
Antenna Gain (non-log)	6.61
Coax loss (non-log)	0.36
General FCC Limit (mw/cm ²)	1.00

Antenna # 314453-40075



Minimum Safe Distance From Antennas

Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

Frequency MHz	824
Pout Watts	0.27797
Duty Cycle Percent	100.0%
Ant. Gain dBi	9.60
Coax Loss dB	4.70
Distance From Antenna In cm	20.0

RESULTS OF CALCULATIONS

Ant. Gain less Coax Loss dBi	4.90
Distance From Antenna In Inches	7.87
EIRP (Watts)	0.8590
FCC Power Density Limit (mw/cm ²)	0.55
Calculated Power Density (mw/cm ²)	0.1709

REFERENCE DATA

Pout dBm	24.44
Antenna Gain (non-log)	9.12
Coax loss (non-log)	0.34
General FCC Limit (mw/cm ²)	f/1500

Antenna # 311129-400100



Minimum Safe Distance From Antennas

Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

Frequency MHz	776
Pout Watts	0.27227
Duty Cycle Percent	100.0%
Ant. Gain dBi	7.20
Coax Loss dB	3.00
Distance From Antenna In cm	20.0

RESULTS OF CALCULATIONS

Ant. Gain less Coax Loss dBi	4.20
Distance From Antenna In Inches	7.87
EIRP (Watts)	0.7161
FCC Power Density Limit (mw/cm ²)	0.52
Calculated Power Density (mw/cm ²)	0.1425

REFERENCE DATA

Pout dBm	24.35
Antenna Gain (non-log)	5.25
Coax loss (non-log)	0.50
General FCC Limit (mw/cm ²)	f/1500

Antenna # 314411-40075



Minimum Safe Distance From Antennas

Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

Frequency MHz	698
Pout Watts	0.26792
Duty Cycle Percent	100.0%
Ant. Gain dBi	9.60
Coax Loss dB	5.10
Distance From Antenna In cm	20.0

RESULTS OF CALCULATIONS

Ant. Gain less Coax Loss dBi	4.50
Distance From Antenna In Inches	7.87
EIRP (Watts)	0.7551
FCC Power Density Limit (mw/cm ²)	0.47
Calculated Power Density (mw/cm ²)	0.1502

REFERENCE DATA

Pout dBm	24.28
Antenna Gain (non-log)	9.12
Coax loss (non-log)	0.31
General FCC Limit (mw/cm ²)	f/1500

Antenna # 314411-40075



Minimum Safe Distance From Antennas

Based upon FCC OET Bulletin 65 and other FCC Sources

INPUT DATA

Frequency MHz	1850
Pout Watts	0.26607
Duty Cycle Percent	100.0%
Ant. Gain dBi	10.00
Coax Loss dB	5.26
Distance From Antenna In cm	20.0

RESULTS OF CALCULATIONS

Ant. Gain less Coax Loss dBi	4.74
Distance From Antenna In Inches	7.87
EIRP (Watts)	0.7925
FCC Power Density Limit (mw/cm ²)	1.00
Calculated Power Density (mw/cm ²)	0.1577

REFERENCE DATA

Pout dBm	24.25
Antenna Gain (non-log)	10.00
Coax loss (non-log)	0.30
General FCC Limit (mw/cm ²)	1.00

Antenna # 314473-0640