



Antenna Kitting Information

Model 460062 Signal Booster

Component	Type	Product Number	Gain (dBi) / Loss (dB)					
			B12 700 MHz	B13 700 MHz	B5 800 MHz	B4 1700 MHz	B2 1900 MHz	B4 2200 MHz
Outdoor Antenna	Directional	314475	7.5	7.5	7.3	8.8	8.8	8.8
		314411	7.5	7.5	7.3	8.8	8.8	8.8
	Omni	304422	2	2	2	5	5	5
		304423	2	2	2	5	5	5
		304421	2	2	2	4	4	4
		304424	2	2	2	4	4	4
Outdoor Cable	Wilson 400 (75 ft)	952375	2.6	2.6	2.8	4.3	4.6	5
	RG-11 (75 ft)	951175	3.1	3.1	3.4	5.5	6.0	6.6
Indoor Cable	Wilson 400 (60 ft)	952360	2.3	2.3	2.5	3.7	3.9	4.3
	RG-11 (50 ft)	951150	2.1	2.1	2.2	3.7	4.0	4.4
Indoor Antenna	Dome	304412	2	2	2	4	4	4
		304419	2	2	2	4	4	4
	Panel	311135	5.2	5.2	4.4	10.1	10.6	8.2
		311155	5.2	5.2	4.4	10.1	10.6	8.2

*All equivalent or lesser antennas and cables are suitable for use with 460062 signal boosters



WILSON ELECTRONICS, LLC
 3301 E. Deseret Dr, St. George, UT 84790
 T. 1 800 204 4104 F. 1 435 673 0899 E. info@weboost.com
 www.weboost.com www.wilsonpro.com

Accessory Kit Options

Component	Type	Product Number	Gain/Loss					
			B12 700 MHz	B13 700 MHz	B5 800 MHz	B4 1700 MHz	B2 1900 MHz	B4 2200 MHz
Outdoor Antenna	Panel	314473	5.2	5.2	4.4	10.1	10.6	8.2
	Directional	301111	10	10	10.8	-6.8	-13.8	-13.8
		311228	12	12	12	12.9	13.1	11.2
		314475	7.5	7.5	7.3	8.8	8.8	8.8
		314445	7.2	7.2	6.9	8.9	8.4	9.2
	Omni	304423	2	2	2	5	5	5
		304421	2	2	2	4	4	4
Outdoor Cable	RG-6 (Qty: 2 50ft)	290650	8.5	9	9.3	14.1	14.8	16
Indoor Cable	RG-6 (50ft)	290650	4.3	4.5	4.7	7.1	7.4	8
Indoor Antenna	Dome	304419	2	2	2	4	4	4
	Panel	301211	-0.8	-0.8	1.5	2.4	3.4	1.2
		311155	5.2	5.2	4.4	10.1	10.6	8.2
		314440	5.75	5.75	6	7.3	7.3	7.6
		314444	5.75	5.75	6	7.3	7.3	7.6
*All equivalent or lesser antennas and cables are suitable for use with 460062 signal boosters								

END OF REPORT