

RF Exposure Report

Report No.: SA150410E09C

FCC ID: PY315100300

Test Model: R6400

Received Date: Apr. 10, 2015

Test Date: Apr. 17, 2015 and Sep. 23, 2015

Issued Date: Oct. 01, 2015

Applicant: NETGEAR, Inc.

Address: 350 East Plumeria Drive San Jose, CA 95134

Issued By: Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch
Hsin Chu Laboratory

Lab Address: No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.

Test Location (1): No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.

Test Location (2): No. 49, Ln. 206, Wende Rd., Shangshan Tsuen, Chiung Lin Hsiang, Hsin
Chu Hsien 307, Taiwan R.O.C.



This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification. The report must not be used by the client to claim product certification, approval, or endorsement by any government agencies.



Table of Contents

Release Control Record	3
1 Certificate of Conformity	4
2 RF Exposure	5
2.1 Limits for Maximum Permissible Exposure (MPE).....	5
2.2 MPE Calculation Formula	5
2.3 Classification	5
2.4 Antenna Gain	5
3 Calculation Result of Maximum Conducted Power	6



A D T

Release Control Record

Issue No.	Description	Date Issued
SA150410E09C	Original release.	Oct. 01, 2015

1 Certificate of Conformity

Product: AC1750 Smart WiFi Router

Brand: NETGEAR

Test Model: R6400

Sample Status: ENGINEERING SAMPLE

Applicant: NETGEAR, Inc.

Test Date: Apr. 17, 2015 and Sep. 23, 2015

Standards: FCC Part 2 (Section 2.1091)

KDB 447498 D03

IEEE C95.1

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared by :  , **Date:** Oct. 01, 2015
Claire Kuan / Specialist

Approved by :  , **Date:** Oct. 01, 2015
May Chen / Manager

2 RF Exposure

2.1 Limits for Maximum Permissible Exposure (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)	Average Time (minutes)
Limits For General Population / Uncontrolled Exposure				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

2.2 MPE Calculation Formula

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

2.3 Classification

The antenna of this product, under normal use condition, is at least 33cm away from the body of the user.

So, this device is classified as **Mobile Device**.

2.4 Antenna Gain

The antennas provided to the EUT, please refer to the following table:

Antenna No.	Transmitter Circuit	Ant. Gain(dBi) <Including cable loss>	Frequency range (GHz to GHz)	Ant. Type	Connector Type
98612PIPF003	Chain (0)	3.4	2.4~2.4835	Dipole	i-pex(MHF)
		3.94	5.15~5.25		
		3.73	5.725~5.85		
98612PIPF004	Chain (1)	3.23	2.4~2.4835	Dipole	i-pex(MHF)
		3.66	5.15~5.25		
		3.77	5.725~5.85		
98612PIPF005	Chain (2)	3.36	2.4~2.4835	Dipole	i-pex(MHF)
		3.32	5.15~5.25		
		3.74	5.725~5.85		

3 Calculation Result of Maximum Conducted Power

The data (Except U-NII-3 band data) was copied from the original test report (Report No.: SA150410E09)

CDD MODE

For 15.247:

802.11b

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2412-2462	537.365	8.1	33	0.25353	1

NOTE:

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.1\text{dBi}$$

802.11g

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2412-2462	536.684	8.1	33	0.25321	1

NOTE:

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.1\text{dBi}$$

802.11n (HT20)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2412-2462	435.03	8.1	33	0.20525	1

NOTE:

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.1\text{dBi}$$

802.11n (HT40)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
2422-2452	112.913	8.1	33	0.05327	1

NOTE:

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.1\text{dBi}$$

For 15.407:

802.11a

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5180-5240	274.765	8.41	33	0.13923	1
5745-5825	251.978	8.52	33	0.13096	1

NOTE:

$$\text{For 5180-5240 MHz: Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.41\text{dBi}$$

$$\text{For 5745-5825 MHz: Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.52\text{dBi}$$

Beamforming MODE

For 15.407:

802.11ac (VHT20)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5180-5240	331.812	8.41	33	0.16813	1
5745-5825	342.088	8.52	33	0.17779	1

NOTE:

For 5180-5240 MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.41\text{dBi}$

For 5745-5825 MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.52\text{dBi}$

802.11ac (VHT40)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5190-5230	278.695	8.41	33	0.14122	1
5755-5795	557.193	8.52	33	0.28958	1

NOTE:

For 5180-5240 MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.41\text{dBi}$

For 5745-5825 MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.52\text{dBi}$

802.11ac (VHT80)

Frequency Band (MHz)	Max Power (mW)	Antenna Gain (dBi)	Distance (cm)	Power Density (mW/cm ²)	Limit (mW/cm ²)
5210	103.865	8.41	33	0.05263	1
5775	178.17	8.52	33	0.09260	1

NOTE:

For 5180-5240 MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.41\text{dBi}$

For 5745-5825 MHz: Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.52\text{dBi}$

CONCLUSION:

Both of the 2.4GHz and 5GHz can transmit simultaneously, the formula of calculated the MPE is:

$$CPD_1 / LPD_1 + CPD_2 / LPD_2 + \dots \text{etc.} < 1$$

CPD = Calculation power density

LPD = Limit of power density

Therefore, the worst-case situation is $0.25353 / 1 + 0.28958 / 1 = 0.54311$, which is less than "1".

--- END ---