

# TEST REPORT

## CERTIFICATE OF CONFORMITY

**Standard:** 47 CFR FCC Part 15, Subpart E (Section 15.407)

**Report No.:** RFBBQZ-WTW-P26040594-6

**FCC ID:** PY326200664

**Product:** Nighthawk 5G M8 Pro

**Brand:** NETGEAR

**Model No.:** MR8400

**Received Date:** 2026/5/6

**Test Date:** 2026/5/26 ~ 2026/7/17

**Issued Date:** 2026/8/6

**Applicant and Manufacturer:** NETGEAR, INC.

**Address:** 3553 N. First St., San Jose, California 95134, United States

**Issued By:** Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch  
Lin Kou Laboratories

**Lab Address:** No. 47-2, 14th Ling, Chia Pau Vil., Lin Kou Dist., New Taipei City 244, Taiwan

**Test Location:** No. 19, Hwa Ya 2nd Rd., Wen Hwa Vil., Kwei Shan Dist., Taoyuan City 333, Taiwan

**FCC Registration /** 788550 / TW0003

**Designation Number:**

**Approved by:**

Jeremy Lin

**Date:**

2026/8/6

Jeremy Lin / Project Engineer

This test report consists of 206 pages in total. It may be duplicated completely for legal use with the approval of the applicant. It should not be reproduced except in full, without the written approval of our laboratory. The test results in the report only apply to the tested sample. The test results in this report are traceable to the national or international standards.



Prepared by : Vera Huang / Specialist

This report is governed by, and incorporates by reference, the Conditions of Testing as posted at the date of issuance of this report at <http://www.bureauveritas.com/home/about-us/our-business/cps/about-us/terms-conditions/> and is intended for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. Measurement uncertainty is only provided upon request for accredited tests. Statements of conformity are based on simple acceptance criteria without taking measurement uncertainty into account, unless otherwise requested in writing. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence or if you require measurement uncertainty; provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents.

## Table of Contents

|                                                                     |           |
|---------------------------------------------------------------------|-----------|
| <b>Release Control Record .....</b>                                 | <b>4</b>  |
| <b>1 Certificate.....</b>                                           | <b>5</b>  |
| <b>2 Summary of Test Results .....</b>                              | <b>6</b>  |
| 2.1 Measurement Uncertainty .....                                   | 6         |
| 2.2 Supplementary Information .....                                 | 6         |
| <b>3 General Information .....</b>                                  | <b>7</b>  |
| 3.1 General Description of EUT .....                                | 7         |
| 3.2 Antenna Description of EUT .....                                | 9         |
| 3.3 Channel List.....                                               | 10        |
| 3.4 Test Mode Applicability and Tested Channel Detail.....          | 14        |
| 3.5 Duty Cycle of Test Signal.....                                  | 16        |
| 3.6 Test Program Used and Operation Descriptions .....              | 17        |
| 3.7 Connection Diagram of EUT and Peripheral Devices .....          | 17        |
| 3.8 Configuration of Peripheral Devices and Cable Connections ..... | 17        |
| <b>4 Test Instruments .....</b>                                     | <b>18</b> |
| 4.1 Maximum RF Output Power .....                                   | 18        |
| 4.2 Maximum Power Spectral Density .....                            | 18        |
| 4.3 Emission Bandwidth .....                                        | 18        |
| 4.4 In-Band Emission Mask.....                                      | 18        |
| 4.5 Occupied Bandwidth.....                                         | 18        |
| 4.6 Contention-based Protocol.....                                  | 19        |
| 4.7 AC Power Conducted Emissions .....                              | 19        |
| 4.8 Unwanted Emissions below 1 GHz .....                            | 20        |
| 4.9 Unwanted Emissions above 1 GHz.....                             | 21        |
| <b>5 Limits of Test Items.....</b>                                  | <b>22</b> |
| 5.1 Maximum RF Output Power .....                                   | 22        |
| 5.2 Maximum Power Spectral Density .....                            | 22        |
| 5.3 Emission Bandwidth .....                                        | 22        |
| 5.4 In-Band Emission Mask.....                                      | 23        |
| 5.5 Occupied Bandwidth.....                                         | 23        |
| 5.6 Contention-based Protocol.....                                  | 23        |
| 5.7 AC Power Conducted Emissions .....                              | 23        |
| 5.8 Unwanted Emissions below 1 GHz .....                            | 24        |
| 5.9 Unwanted Emissions above 1 GHz.....                             | 24        |
| <b>6 Test Arrangements.....</b>                                     | <b>25</b> |
| 6.1 Maximum RF Output Power .....                                   | 25        |
| 6.1.1 Test Setup .....                                              | 25        |
| 6.1.2 Test Procedure .....                                          | 25        |
| 6.2 Maximum Power Spectral Density .....                            | 25        |
| 6.2.1 Test Setup .....                                              | 25        |
| 6.2.2 Test Procedure .....                                          | 25        |
| 6.3 Emission Bandwidth .....                                        | 26        |
| 6.3.1 Test Setup .....                                              | 26        |
| 6.3.2 Test Procedure .....                                          | 26        |
| 6.4 In-Band Emission Mask.....                                      | 27        |
| 6.4.1 Test Setup .....                                              | 27        |
| 6.4.2 Test Procedure .....                                          | 27        |
| 6.5 Occupied Bandwidth.....                                         | 28        |
| 6.5.1 Test Setup .....                                              | 28        |
| 6.5.2 Test Procedure .....                                          | 28        |
| 6.6 Contention-based Protocol.....                                  | 29        |
| 6.6.1 Test Setup .....                                              | 29        |
| 6.6.2 Test Procedure .....                                          | 29        |
| 6.7 AC Power Conducted Emissions .....                              | 30        |

|          |                                                      |            |
|----------|------------------------------------------------------|------------|
| 6.7.1    | Test Setup .....                                     | 30         |
| 6.7.2    | Test Procedure .....                                 | 30         |
| 6.8      | Unwanted Emissions below 1 GHz .....                 | 31         |
| 6.8.1    | Test Setup .....                                     | 31         |
| 6.8.2    | Test Procedure .....                                 | 32         |
| 6.9      | Unwanted Emissions above 1 GHz .....                 | 33         |
| 6.9.1    | Test Setup .....                                     | 33         |
| 6.9.2    | Test Procedure .....                                 | 33         |
| <b>7</b> | <b>Test Results of Test Item .....</b>               | <b>34</b>  |
| 7.1      | Maximum RF Output Power .....                        | 34         |
| 7.2      | Maximum Power Spectral Density .....                 | 42         |
| 7.3      | Emission Bandwidth .....                             | 54         |
| 7.4      | In-Band Emission Mask .....                          | 62         |
| 7.5      | Occupied Bandwidth .....                             | 102        |
| 7.6      | Contention-based Protocol .....                      | 110        |
| 7.7      | AC Power Conducted Emissions .....                   | 123        |
| 7.8      | Unwanted Emissions below 1 GHz .....                 | 125        |
| 7.9      | Unwanted Emissions above 1 GHz .....                 | 129        |
| <b>8</b> | <b>Pictures of Test Arrangements .....</b>           | <b>205</b> |
| <b>9</b> | <b>Information of the Testing Laboratories .....</b> | <b>206</b> |

## Release Control Record

| Issue No.              | Description      | Date Issued |
|------------------------|------------------|-------------|
| RFBBQZ-WTW-P26040594-6 | Original Release | 2026/8/6    |

## 1 Certificate

**Product:** Nighthawk 5G M8 Pro

**Brand:** NETGEAR

**Test Model:** MR8400

**Sample Status:** Engineering sample

**Applicant and Manufacturer:** NETGEAR, INC.

**Test Date:** 2026/5/26 ~ 2026/7/17

**Standard:** 47 CFR FCC Part 15, Subpart E (Section 15.407)

**Measurement procedure:** ANSI C63.10-2020+Cor.1-2023+C63.10a-2024+Errata to C63.10a-2024

KDB 987594 D02 U-NII 6 GHz EMC Measurement v03

KDB 789033 D02 General UNII Test Procedure New Rules v02r01

KDB 662911 D01 Multiple Transmitter Output v02r01

The above equipment has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's RF characteristics under the conditions specified in this report.

## 2 Summary of Test Results

| 47 CFR FCC Part 15, Subpart E (Section 15.407) |                                |        |                                                                 |
|------------------------------------------------|--------------------------------|--------|-----------------------------------------------------------------|
| Clause                                         | Test Item                      | Result | Remark                                                          |
| 15.407(a)(5)                                   | Maximum RF Output Power        | Pass   | Meet the requirement of limit.                                  |
| 15.407(a)(5)                                   | Maximum Power Spectral Density | Pass   | Meet the requirement of limit.                                  |
| 15.407(a)(11)                                  | Emission Bandwidth             | Pass   | Meet the requirement of limit.                                  |
| ---                                            | Occupied Bandwidth             | -      | Reference only.                                                 |
| 15.407(b)(9)                                   | AC Power Conducted Emissions   | Pass   | Minimum passing margin is -15.50 dB at 0.67003 MHz              |
| 15.407(b)(9)                                   | Unwanted Emissions below 1 GHz | Pass   | Minimum passing margin is -12.3 dB at 858.01 MHz and 869.26 MHz |
| 15.407(b)(6)<br>15.407(b)(10)                  | Unwanted Emissions above 1 GHz | Pass   | Minimum passing margin is -0.5 dB at 7125.00 MHz                |
| 15.407(b)(7)                                   | In-Band Emission Mask          | Pass   | Meet the requirement of limit.                                  |
| 15.407(d)(6)                                   | Contention-based Protocol      | Pass   | Meet the requirement of limit.                                  |
| 15.203                                         | Antenna Requirement            | Pass   | Antenna connector is ipex(MHF) not a standard connector.        |

Notes:

1. Determining compliance based on the results of the compliance measurement, not taking into account measurement instrumentation uncertainty.
2. Per TCBC notice, FCC allows 99% BW measurements for Wi-Fi 320MHz BW mode instead of Emission Bandwidth.

### 2.1 Measurement Uncertainty

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the EUT as specified in CISPR 16-4-2:

| Measurement                    | Specification   | Expanded Uncertainty (k=2)<br>(±) |
|--------------------------------|-----------------|-----------------------------------|
| Occupied Bandwidth             | -               | 72 Hz                             |
| AC Power Conducted Emissions   | 9 kHz ~ 30 MHz  | 3.23 dB                           |
| Unwanted Emissions below 1 GHz | 9 kHz ~ 30 MHz  | 3.59 dB                           |
|                                | 30 MHz ~ 1 GHz  | 3.64 dB                           |
| Unwanted Emissions above 1 GHz | 1 GHz ~ 18 GHz  | 2.29 dB                           |
|                                | 18 GHz ~ 40 GHz | 2.29 dB                           |

The other instruments specified are routine verified to remain within the calibrated levels, no measurement uncertainty is required to be calculated.

### 2.2 Supplementary Information

There is not any deviation from the test standards for the test method, and no modifications required for compliance.

### 3 General Information

#### 3.1 General Description of EUT

|                       |                                                                                                                                                                                                                        |
|-----------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Product               | Nighthawk 5G M8 Pro                                                                                                                                                                                                    |
| Brand                 | NETGEAR                                                                                                                                                                                                                |
| Test Model            | MR8400                                                                                                                                                                                                                 |
| Status of EUT         | Engineering sample                                                                                                                                                                                                     |
| Power Supply Rating   | 3.85 Vdc from Battery<br>5 Vdc / 9 Vdc from Adapter                                                                                                                                                                    |
| Modulation Type       | 64QAM, 16QAM, QPSK, BPSK for OFDM<br>1024QAM for OFDMA in 11ax mode<br>4096QAM for OFDMA in 11be mode                                                                                                                  |
| Modulation Technology | OFDM, OFDMA                                                                                                                                                                                                            |
| Transfer Rate         | Up to 5764.7 Mbps                                                                                                                                                                                                      |
| Operating Frequency   | 5.955 GHz ~ 6.415 GHz<br>6.425 GHz ~ 6.525 GHz<br>6.535 GHz ~ 6.865 GHz<br>6.875 GHz ~ 7.115 GHz                                                                                                                       |
| Number of Channel     | 802.11a, 802.11ax (HE20), 802.11be (EHT20): 59<br>802.11ax (HE40), 802.11be (EHT40): 29<br>802.11ax (HE80), 802.11be (EHT80): 14<br>802.11ax (HE160), 802.11be (EHT160): 7<br>802.11be (EHT320): 6                     |
| Partial RU Mode       | Not support                                                                                                                                                                                                            |
| Channel Puncturing    | Not support                                                                                                                                                                                                            |
| Output Power          | 5.955 GHz ~ 6.415 GHz: EIRP: 114.016 mW (20.57 dBm)<br>6.425 GHz ~ 6.525 GHz: EIRP: 113.433 mW (20.55 dBm)<br>6.535 GHz ~ 6.865 GHz: EIRP: 94.545 mW (19.76 dBm)<br>6.875 GHz ~ 7.115 GHz: EIRP: 92.216 mW (19.65 dBm) |
| Equipment Class       | 6XD: 15E 6 GHz Low-power Indoor client<br>6ID: 15E 6 GHz Low-power indoor access point                                                                                                                                 |

Note:

1. The EUT uses following accessories.

|              |              |                                          |
|--------------|--------------|------------------------------------------|
| Battery      | Brand        | NETGEAR                                  |
|              | Model        | W-20b                                    |
|              | Power Rating | 3.85V, 19.96Wh                           |
| AC Adapter 1 | Brand        | NETGEAR                                  |
|              | Model        | 2AGD02131                                |
|              | Part Number  | 332-11838-01                             |
|              | AC Input     | 100-120Vac, 50/60 Hz                     |
|              | DC Output    | 5V/9V, 3A/2.34A                          |
|              | Manufacturer | CHANNEL WELL TECHNOLOGY                  |
| AC Adapter 2 | Brand        | NETGEAR                                  |
|              | Model        | ADT-21NPD-09-EPCU                        |
|              | Part Number  | 332-11830-01                             |
|              | AC Input     | 100-120Vac, 50/60 Hz                     |
|              | DC Output    | 5V/9V, 3A/2.34A                          |
|              | Manufacturer | Honor: Vietnam Honor High Tech Co., Ltd. |
| Type C Cable | Brand        | JI-HAW ELECTRONICS CO., LTD              |
|              | Model        | 310-10092-01                             |
|              | Signal Line  | 0.95M                                    |

2. There are WLAN (2.4 GHz & 5 GHz & 6 GHz) and WWAN technology used for the EUT.

3. Simultaneously transmission combination.

| Combination | Technology |                |              |              |
|-------------|------------|----------------|--------------|--------------|
| 1           | WWAN       | WLAN (2.4 GHz) | WLAN (5 GHz) | WLAN (6 GHz) |

Note: The emission of the simultaneous operation has been evaluated and no non-compliance was found.

4. The above EUT information is declared by manufacturer and for more detailed features description, please refer to the manufacturer's specifications or user's manual.

### 3.2 Antenna Description of EUT

1. The antenna information is listed as below.

| Antenna No. | RF Chain No. | Antenna Net Max. Gain (dBi) | Antenna Net Min. Gain (dBi) | Frequency range   | Antenna Type | Connector Type |
|-------------|--------------|-----------------------------|-----------------------------|-------------------|--------------|----------------|
| WLAN 0      | 0            | 0.54                        | -0.03                       | 2.4~2.4835GHz     | Monopole     | ipex(MHF)      |
|             |              | 3.04                        | 2.91                        | 5.15~5.25GHz      |              |                |
|             |              | 3.06                        | 3.04                        | 5.25~5.35GHz      |              |                |
|             |              | 3.71                        | 3.11                        | 5.47~5.725GHz     |              |                |
|             |              | 3.65                        | 3.52                        | 5.725~5.85GHz     |              |                |
|             |              | 3.52                        | 3.31                        | 5.850GHz~5.895GHz |              |                |
|             |              | 3.25                        | 2.45                        | 5.925GHz~6.425GHz |              |                |
|             |              | 2.45                        | 2.27                        | 6.425GHz~6.525GHz |              |                |
|             |              | 2.27                        | 1.93                        | 6.525GHz~6.875GHz |              |                |
|             |              | 1.93                        | 1.79                        | 6.875Hz~7.125GHz  |              |                |
| WLAN 1      | 1            | 0.69                        | 0.16                        | 2.4~2.4835GHz     | PIFA         | ipex(MHF)      |
|             |              | -0.08                       | -0.3                        | 5.15~5.25GHz      |              |                |
|             |              | -0.25                       | -0.3                        | 5.25~5.35GHz      |              |                |
|             |              | 1.44                        | 0.35                        | 5.47~5.725GHz     |              |                |
|             |              | 1.41                        | 1.36                        | 5.725~5.85GHz     |              |                |
|             |              | 1.36                        | 1.35                        | 5.850GHz~5.895GHz |              |                |
|             |              | 1.67                        | 1.19                        | 5.925GHz~6.425GHz |              |                |
|             |              | 1.95                        | 1.67                        | 6.425GHz~6.525GHz |              |                |
|             |              | 2.31                        | 1.95                        | 6.525GHz~6.875GHz |              |                |
|             |              | 2.01                        | 1.26                        | 6.875Hz~7.125GHz  |              |                |

\* Detail antenna specification please refer to antenna datasheet and/or antenna measurement report.

2. The EUT incorporates a MIMO function:

| 6 GHz Band        |                       |     |
|-------------------|-----------------------|-----|
| Modulation Mode   | TX & RX Configuration |     |
| 802.11a           | 2TX                   | 2RX |
| 802.11ax (HE20)   | 2TX                   | 2RX |
| 802.11ax (HE40)   | 2TX                   | 2RX |
| 802.11ax (HE80)   | 2TX                   | 2RX |
| 802.11ax (HE160)  | 2TX                   | 2RX |
| 802.11be (EHT20)  | 2TX                   | 2RX |
| 802.11be (EHT40)  | 2TX                   | 2RX |
| 802.11be (EHT80)  | 2TX                   | 2RX |
| 802.11be (EHT160) | 2TX                   | 2RX |
| 802.11be (EHT320) | 2TX                   | 2RX |

Note: The modulation and bandwidth of 802.11ax and 802.11be modes are similar at 20 MHz (40 MHz, 80 MHz, 160 MHz). Therefore the investigated worst case is the representative mode in test report.

### 3.3 Channel List

#### U-NII-5:

24 channels are provided for 802.11a, 802.11ax (HE20), 802.11be (EHT20):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| 1       | 5955 MHz  | 5       | 5975 MHz  | 9       | 5995 MHz  | 13      | 6015 MHz  |
| 17      | 6035 MHz  | 21      | 6055 MHz  | 25      | 6075 MHz  | 29      | 6095 MHz  |
| 33      | 6115 MHz  | 37      | 6135 MHz  | 41      | 6155 MHz  | 45      | 6175 MHz  |
| 49      | 6195 MHz  | 53      | 6215 MHz  | 57      | 6235 MHz  | 61      | 6255 MHz  |
| 65      | 6275 MHz  | 69      | 6295 MHz  | 73      | 6315 MHz  | 77      | 6335 MHz  |
| 81      | 6355 MHz  | 85      | 6375 MHz  | 89      | 6395 MHz  | 93      | 6415 MHz  |

12 channels are provided for 802.11ax (HE40), 802.11be (EHT40):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| 3       | 5965 MHz  | 11      | 6005 MHz  | 19      | 6045 MHz  | 27      | 6085 MHz  |
| 35      | 6125 MHz  | 43      | 6165 MHz  | 51      | 6205 MHz  | 59      | 6245 MHz  |
| 67      | 6285 MHz  | 75      | 6325 MHz  | 83      | 6365 MHz  | 91      | 6405 MHz  |

6 channels are provided for 802.11ax (HE80), 802.11be (EHT80):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| 7       | 5985 MHz  | 23      | 6065 MHz  | 39      | 6145 MHz  | 55      | 6225 MHz  |
| 71      | 6305 MHz  | 87      | 6385 MHz  |         |           |         |           |

3 channels are provided for 802.11ax (HE160), 802.11be (EHT160):

| Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|
| 15      | 6025 MHz  | 47      | 6185 MHz  | 79      | 6345 MHz  |

2 channels are provided for 802.11be (EHT320):

| Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|
| 31      | 6105 MHz  | 63      | 6265 MHz  |

#### U-NII-6:

5 channels are provided for 802.11a, 802.11ax (HE20), 802.11be (EHT20):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| 97      | 6435 MHz  | 101     | 6455 MHz  | 105     | 6475 MHz  | 109     | 6495 MHz  |
| 113     | 6515 MHz  |         |           |         |           |         |           |

3 channels are provided for 802.11ax (HE40), 802.11be (EHT40):

| Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|
| 99      | 6445 MHz  | 107     | 6485 MHz  | *115    | 6525 MHz  |

1 channel is provided for 802.11ax (HE80), 802.11be (EHT80):

| Channel | Frequency |
|---------|-----------|
| 103     | 6465 MHz  |

1 channel is provided for 802.11ax (HE160), 802.11be (EHT160):

| Channel | Frequency |
|---------|-----------|
| *111    | 6505 MHz  |

1 channel is provided for 802.11be (EHT320):

| Channel | Frequency |
|---------|-----------|
| *95     | 6425 MHz  |

## U-NII-7:

17 channels are provided for 802.11a, 802.11ax (HE20), 802.11be (EHT20):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| 117     | 6535 MHz  | 121     | 6555 MHz  | 125     | 6575 MHz  | 129     | 6595 MHz  |
| 133     | 6615 MHz  | 137     | 6635 MHz  | 141     | 6655 MHz  | 145     | 6675 MHz  |
| 149     | 6695 MHz  | 153     | 6715 MHz  | 157     | 6735 MHz  | 161     | 6755 MHz  |
| 165     | 6775 MHz  | 169     | 6795 MHz  | 173     | 6815 MHz  | 177     | 6835 MHz  |
| 181     | 6855 MHz  |         |           |         |           |         |           |

8 channels are provided for 802.11ax (HE40), 802.11be (EHT40):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| 123     | 6565 MHz  | 131     | 6605 MHz  | 139     | 6645 MHz  | 147     | 6685 MHz  |
| 155     | 6725 MHz  | 163     | 6765 MHz  | 171     | 6805 MHz  | 179     | 6845 MHz  |

5 channels are provided for 802.11ax (HE80), 802.11be (EHT80):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| *119    | 6545 MHz  | 135     | 6625 MHz  | 151     | 6705 MHz  | 167     | 6785 MHz  |
| *183    | 6865 MHz  |         |           |         |           |         |           |

2 channels are provided for 802.11ax (HE160), 802.11be (EHT160):

| Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|
| 143     | 6665 MHz  | *175    | 6825 MHz  |

2 channels are provided for 802.11be (EHT320):

| Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|
| *127    | 6585 MHz  | *159    | 6745 MHz  |

#### U-NII-8:

13 channels are provided for 802.11a, 802.11ax (HE20), 802.11be (EHT20):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| *185    | 6875 MHz  | 189     | 6895 MHz  | 193     | 6915 MHz  | 197     | 6935 MHz  |
| 201     | 6955 MHz  | 205     | 6975 MHz  | 209     | 6995 MHz  | 213     | 7015 MHz  |
| 217     | 7035 MHz  | 221     | 7055 MHz  | 225     | 7075 MHz  | 229     | 7095 MHz  |
| 233     | 7115 MHz  |         |           |         |           |         |           |

6 channels are provided for 802.11ax (HE40), 802.11be (EHT40):

| Channel | Frequency | Channel | Frequency | Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|---------|-----------|---------|-----------|
| *187    | 6885 MHz  | 195     | 6925 MHz  | 203     | 6965 MHz  | 211     | 7005 MHz  |
| 219     | 7045 MHz  | 227     | 7085 MHz  |         |           |         |           |

2 channels are provided for 802.11ax (HE80), 802.11be (EHT80):

| Channel | Frequency | Channel | Frequency |
|---------|-----------|---------|-----------|
| 199     | 6945 MHz  | 215     | 7025 MHz  |

1 channel is provided for 802.11ax (HE160), 802.11be (EHT160):

| Channel | Frequency |
|---------|-----------|
| 207     | 6985 MHz  |

1 channel is provided for 802.11be (EHT320):

| Channel | Frequency |
|---------|-----------|
| *191    | 6905 MHz  |

Note: \* mean these are straddle channels.

### 3.4 Test Mode Applicability and Tested Channel Detail

|             |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |
|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Pre-Scan:   | <ol style="list-style-type: none"> <li>1. EUT can be used in the following ways: X-axis / Y-axis / Z-axis. Pre-scan these ways and find the worst case as a representative test condition.</li> <li>2. EUT has the following AC Adapter: AC Adapter 1 / AC Adapter 2. Pre-scan these AC Adapters and find the worst case as a representative test condition.</li> <li>3. EUT has the following output power mode: Adapter Mode and Battery Mode. The adapter mode is available only when the device is powered by AC adapter connected to AC mains, that also illustrated in the user manual. For unwanted emissions above 1 GHz, pre-scan these power modes and find the worst case as a representative test condition.</li> <li>4. The final test modes consider the modulation and the worst data rates as shown in the table below. EUT supports AP mode and client mode. The same output power level is used on the two modes. Due to the limit of the client mode is more restrictive than the AP mode, the client mode test data also shows the compliance of the AP mode. Therefore, this report only shows the test data of client mode.<br/><br/>For AP mode is available only when the device is powered by AC adapter connected to AC mains, also illustrated in the user manual.</li> </ol> |
| Worst Case: | <ol style="list-style-type: none"> <li>1. X-axis / Y-axis / Z-axis Worst Condition: Y-axis</li> <li>2. Adapter Worst Condition: AC Adapter 2</li> <li>3. Power mode Worst Condition for unwanted emissions above 1 GHz: Adapter Mode</li> </ol>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          |


Following channel(s) was (were) selected for the final test as listed below:

| Test Item                      | EUT Configure Mode | Mode              | Signal Mode | Tested Channel                                        | Modulation | Data Rate Parameter |
|--------------------------------|--------------------|-------------------|-------------|-------------------------------------------------------|------------|---------------------|
| Maximum RF Output Power        | A, B               | 802.11a           | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | 6Mb/s               |
|                                |                    | 802.11be (EHT20)  | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT40)  | CDD         | 3, 43, 91, 99, 107, 115, 123, 155, 179, 187, 211, 227 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT80)  | CDD         | 7, 39, 87, 103, 119, 151, 183, 199, 215               | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT160) | CDD         | 15, 47, 79, 111, 143, 175, 207                        | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 63, 95, 127, 159, 191                             | BPSK       | MCS0                |
| Maximum Power Spectral Density | A, B               | 802.11a           | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | 6Mb/s               |
|                                |                    | 802.11be (EHT20)  | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT40)  | CDD         | 3, 43, 91, 99, 107, 115, 123, 155, 179, 187, 211, 227 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT80)  | CDD         | 7, 39, 87, 103, 119, 151, 183, 199, 215               | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT160) | CDD         | 15, 47, 79, 111, 143, 175, 207                        | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 63, 95, 127, 159, 191                             | BPSK       | MCS0                |
| Emission Bandwidth             | A, B               | 802.11a           | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | 6Mb/s               |
|                                |                    | 802.11be (EHT20)  | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT40)  | CDD         | 3, 43, 91, 99, 107, 115, 123, 155, 179, 187, 211, 227 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT80)  | CDD         | 7, 39, 87, 103, 119, 151, 183, 199, 215               | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT160) | CDD         | 15, 47, 79, 111, 143, 175, 207                        | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 63, 95, 127, 159, 191                             | BPSK       | MCS0                |

| Test Item                      | EUT Configure Mode | Mode              | Signal Mode | Tested Channel                                        | Modulation | Data Rate Parameter |
|--------------------------------|--------------------|-------------------|-------------|-------------------------------------------------------|------------|---------------------|
| In-Band Emission Mask          | A, B               | 802.11a           | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | 6Mb/s               |
|                                |                    | 802.11be (EHT20)  | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT40)  | CDD         | 3, 43, 91, 99, 107, 115, 123, 155, 179, 187, 211, 227 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT80)  | CDD         | 7, 39, 87, 103, 119, 151, 183, 199, 215               | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT160) | CDD         | 15, 47, 79, 111, 143, 175, 207                        | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 63, 95, 127, 159, 191                             | BPSK       | MCS0                |
| Occupied Bandwidth             | A, B               | 802.11a           | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | 6Mb/s               |
|                                |                    | 802.11be (EHT20)  | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT40)  | CDD         | 3, 43, 91, 99, 107, 115, 123, 155, 179, 187, 211, 227 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT80)  | CDD         | 7, 39, 87, 103, 119, 151, 183, 199, 215               | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT160) | CDD         | 15, 47, 79, 111, 143, 175, 207                        | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 63, 95, 127, 159, 191                             | BPSK       | MCS0                |
| Contention-based Protocol      | A                  | 802.11be (EHT20)  | CDD         | 33, 97, 161, 193                                      | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 95, 159, 191                                      | BPSK       | MCS0                |
| AC Power Conducted Emissions   | A                  | 802.11be (EHT320) | CDD         | 63                                                    | BPSK       | MCS0                |
| Unwanted Emissions below 1 GHz | A                  | 802.11be (EHT320) | CDD         | 63                                                    | BPSK       | MCS0                |
|                                | B                  | 802.11be (EHT80)  | CDD         | 7                                                     | BPSK       | MCS0                |
| Unwanted Emissions above 1 GHz | A                  | 802.11a           | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | 6Mb/s               |
|                                |                    | 802.11be (EHT20)  | CDD         | 1, 45, 93, 97, 105, 113, 117, 149, 181, 185, 209, 233 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT40)  | CDD         | 3, 43, 91, 99, 107, 115, 123, 155, 179, 187, 211, 227 | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT80)  | CDD         | 7, 39, 87, 103, 119, 151, 183, 199, 215               | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT160) | CDD         | 15, 47, 79, 111, 143, 175, 207                        | BPSK       | MCS0                |
|                                |                    | 802.11be (EHT320) | CDD         | 31, 63, 95, 127, 159, 191                             | BPSK       | MCS0                |
| EUT Configure Mode:            | A                  | Adapter Mode      |             |                                                       |            |                     |
|                                | B                  | Battery Mode      |             |                                                       |            |                     |

### 3.5 Duty Cycle of Test Signal

**802.11a:** Duty cycle = 2.105 ms / 2.115 ms x 100% = 99.5%  
**802.11be (EHT20):** Duty cycle = 100 ms / 100 ms x 100% = 100.0%  
**802.11be (EHT40):** Duty cycle = 100 ms / 100 ms x 100% = 100.0%  
**802.11be (EHT80):** Duty cycle = 100 ms / 100 ms x 100% = 100.0%  
**802.11be (EHT160):** Duty cycle = 100 ms / 100 ms x 100% = 100.0%  
**802.11be (EHT320):** Duty cycle = 100 ms / 100 ms x 100% = 100.0%




### 3.6 Test Program Used and Operation Descriptions


Controlling software QRCT\_Ver 4.0.210.0 has been activated to set the EUT under transmission condition continuously at specific channel frequency.

### 3.7 Connection Diagram of EUT and Peripheral Devices

#### Mode A



#### Mode B



### 3.8 Configuration of Peripheral Devices and Cable Connections

| ID | Cable Descriptions | Qty. | Length (m) | Shielding (Yes/No) | Cores (Qty.) | Remarks                         |
|----|--------------------|------|------------|--------------------|--------------|---------------------------------|
| 1  | Type C Cable       | 1    | 0.95       | No                 | 0            | Accessory of EUT (for RF Setup) |

## 4 Test Instruments

The calibration interval of the all test instruments are 12 months and the calibrations are traceable to NML/ROC and NIST/USA.

### 4.1 Maximum RF Output Power

| Description<br>Manufacturer       | Model No.      | Serial No.        | Calibrated<br>Date | Calibrated<br>Until |
|-----------------------------------|----------------|-------------------|--------------------|---------------------|
| Fixed Attenuator<br>Woken         | 00800A1K01A-10 | 00800A1K01A-10-01 | 2026/5/21          | 2027/5/20           |
| Peak Power Analyzer<br>Keysight   | 8990B          | MY51000485        | 2026/1/23          | 2027/1/22           |
| USB Power Sensor<br>Anritsu       | MA24408A       | 12994             | 2025/12/5          | 2026/12/4           |
| Wideband Power Sensor<br>Keysight | N1923A         | MY58020002        | 2026/1/26          | 2027/1/25           |
|                                   |                | MY58140009        | 2026/1/26          | 2027/1/25           |

Notes:

1. The test was performed in HY - Oven room(Hwaya).
2. Tested Date: 2026/6/26 ~ 2026/7/1

### 4.2 Maximum Power Spectral Density

| Description<br>Manufacturer | Model No.                        | Serial No.        | Calibrated<br>Date | Calibrated<br>Until |
|-----------------------------|----------------------------------|-------------------|--------------------|---------------------|
| Fixed Attenuator<br>Woken   | 00800A1K01A-10                   | 00800A1K01A-10-01 | 2026/5/21          | 2027/5/20           |
| Software<br>BV              | ADT_RF Test Software<br>V7.6.5.4 | N/A               | N/A                | N/A                 |
| Spectrum Analyzer<br>R&S    | FSU43                            | 101261            | 2026/5/4           | 2027/5/3            |

Notes:

1. The test was performed in HY - Oven room(Hwaya).
2. Tested Date: 2026/6/26 ~ 2026/7/1

### 4.3 Emission Bandwidth

Refer to section 4.2 to get the tested date and information of the instruments.

### 4.4 In-Band Emission Mask

Refer to section 4.2 to get the tested date and information of the instruments.

### 4.5 Occupied Bandwidth

Refer to section 4.2 to get the tested date and information of the instruments.

#### 4.6 Contention-based Protocol

| Description<br>Manufacturer             | Model No.          | Serial No. | Calibrated<br>Date | Calibrated<br>Until |
|-----------------------------------------|--------------------|------------|--------------------|---------------------|
| MXG Vector Signal Generator<br>Keysight | N5182B             | MY57301272 | 2026/4/8           | 2027/4/7            |
|                                         | N5182BX07(N5182BU) | MY59360204 | 2026/4/8           | 2027/4/7            |
| Power Divider<br>Woken                  | 0120A02058001M     | DCMD33WIK3 | 2026/4/18          | 2027/4/17           |
|                                         |                    | DCMD33WIK7 | 2026/4/18          | 2027/4/17           |
| Signal & Spectrum Analyzer<br>R&S       | FSW26              | 102023     | 2025/11/14         | 2026/11/13          |

Notes:

1. The test was performed in HY - Adaptivity room(Hwaya).
2. Tested Date: 2026/7/14

#### 4.7 AC Power Conducted Emissions

| Description<br>Manufacturer        | Model No.            | Serial No.     | Calibrated<br>Date | Calibrated<br>Until |
|------------------------------------|----------------------|----------------|--------------------|---------------------|
| 50 ohm terminal resistance         | E1-011279            | 04             | 2025/12/4          | 2026/12/3           |
|                                    | E1-011280            | 05             | 2025/12/4          | 2026/12/3           |
|                                    | E1-011311            | 09             | 2025/12/4          | 2026/12/3           |
| DC LISN<br>Schwarzbeck             | NNBM 8126G           | 8126G-069      | 2025/11/3          | 2026/11/2           |
| Diode Pulse Limiter<br>Schwarzbeck | VTSD 9561 F-N        | 01445          | 2026/4/18          | 2027/4/17           |
| EMI Test Receiver<br>R&S           | ESCI                 | 100613         | 2025/11/27         | 2026/11/26          |
| Extension Power Line<br>EMCI       | EMCI-EXP-EU-US       | 023            | 2026/3/6           | 2027/3/5            |
| LISN<br>R&S                        | ENV216               | 101826         | 2026/3/6           | 2027/3/5            |
|                                    | ESH3-Z5              | 100311         | 2025/8/28          | 2026/8/27           |
| RF Coaxial Cable<br>Woken          | 5D-FB                | Cable-cond1-01 | 2026/1/3           | 2027/1/2            |
| Software<br>BVADT                  | BVADT_Conc_ V7.4.1.0 | N/A            | N/A                | N/A                 |
| V-LISN<br>Schwarzbeck              | NNBL 8226-2          | 8226-142       | 2025/8/27          | 2026/8/26           |

Notes:

1. The test was performed in HY - Conduction 1.
2. Tested Date: 2026/7/14

#### 4.8 Unwanted Emissions below 1 GHz

| Description<br>Manufacturer       | Model No.                   | Serial No.   | Calibrated Date | Calibrated Until |
|-----------------------------------|-----------------------------|--------------|-----------------|------------------|
| Antenna Tower<br>inn-co GmbH      | MA 4000                     | 010303       | N/A             | N/A              |
| Bi_Log Antenna<br>Schwarzbeck     | VULB 9168                   | 9168-155     | 2025/9/16       | 2026/9/15        |
| EMI Test Receiver<br>R&S          | ESR3                        | 102782       | 2025/12/8       | 2026/12/7        |
| Loop Antenna<br>TESEQ             | HLA 6121                    | 45745        | 2025/9/1        | 2026/8/31        |
| Preamplifier<br>Agilent           | 8447D                       | 2944A10631   | 2026/4/18       | 2027/4/17        |
| RF Coaxial Cable<br>Woken         | 8D-FB                       | Cable-CH4-01 | 2026/6/26       | 2027/6/25        |
| Signal & Spectrum Analyzer<br>R&S | FSW43                       | 101582       | 2026/5/2        | 2027/5/1         |
| Software<br>BV ADT                | ADT_Radiated_<br>V7.7.1.1.1 | N/A          | N/A             | N/A              |
| Turn Table<br>BV ADT              | TT100                       | TT93021705   | N/A             | N/A              |
| Turn Table Controller<br>BV ADT   | SC100                       | SC93021705   | N/A             | N/A              |

Notes:

1. The test was performed in HY - 966 chamber 3(Hwaya).
2. Tested Date: 2026/7/17

#### 4.9 Unwanted Emissions above 1 GHz

| Description<br>Manufacturer              | Model No.                   | Serial No.                                          | Calibrated<br>Date     | Calibrated<br>Until    |
|------------------------------------------|-----------------------------|-----------------------------------------------------|------------------------|------------------------|
| Antenna Tower<br>inn-co GmbH             | MA 4000                     | 010303                                              | N/A                    | N/A                    |
| Boresight antenna tower<br>fixture<br>BV | BAF-02                      | 5                                                   | N/A                    | N/A                    |
| EMI Test Receiver<br>R&S                 | ESR3                        | 102782                                              | 2025/12/8              | 2026/12/7              |
| Horn Antenna<br>Schwarzbeck              | BBHA 9120D                  | 9120D-408                                           | 2025/11/9              | 2026/11/8              |
|                                          | BBHA 9170                   | 9170-480                                            | 2025/11/9              | 2026/11/8              |
|                                          |                             | BBHA9170241                                         | 2025/10/28             | 2026/10/27             |
|                                          |                             | BBHA9170243                                         | 2025/11/9              | 2026/11/8              |
| Preamplifier<br>EMCI                     | EMC 184045                  | 980116                                              | 2025/9/21              | 2026/9/20              |
| Preamplifier<br>Keysight                 | 83017A                      | MY53270295                                          | 2026/4/18              | 2027/4/17              |
| RF Coaxial Cable<br>EMCI                 | EMC102-KM-KM-600            | 150928                                              | 2025/6/30<br>2026/6/26 | 2026/6/29<br>2027/6/25 |
|                                          | EMC102-KM-KM-3000           | 150929                                              | 2025/6/30<br>2026/6/26 | 2026/6/29<br>2027/6/25 |
| RF Coaxial Cable<br>HUBER+SUHNER         | EMC104-SM-SM-10000          | Cable-CH1-01(RFC-SMS-100-SMS-120+RFC-SMS-100-SMS-4) | 2026/4/18              | 2027/4/17              |
|                                          | SUCOFLEX 104                | Cable-CH4-03(250724)                                | 2026/4/18              | 2027/4/17              |
| Signal & Spectrum<br>Analyzer<br>R&S     | FSW43                       | 101582                                              | 2026/5/2               | 2027/5/1               |
| Software<br>BV ADT                       | ADT_Radiated_<br>V7.7.1.1.1 | N/A                                                 | N/A                    | N/A                    |
| Turn Table<br>BV ADT                     | TT100                       | TT93021705                                          | N/A                    | N/A                    |
| Turn Table Controller<br>BV ADT          | SC100                       | SC93021705                                          | N/A                    | N/A                    |

Notes:

1. The test was performed in HY - 966 chamber 3(Hwaya).
2. Tested Date: 2026/5/26 ~ 2026/7/16

## 5 Limits of Test Items

### 5.1 Maximum RF Output Power

| Operation Band     | Equipment Class                              | Limit                 |
|--------------------|----------------------------------------------|-----------------------|
|                    |                                              | Maximum Average Power |
| U-NII-5<br>U-NII-6 | 6XD: 15E 6 GHz Low-power Indoor client       | EIRP 24 dBm           |
| U-NII-7<br>U-NII-8 | 6ID: 15E 6 GHz Low-power indoor access point | EIRP 30 dBm           |

Per KDB 662911 Method of conducted output power measurement on IEEE 802.11 devices,

Array Gain = 0 dB (i.e., no array gain) for  $N_{ANT} \leq 4$ ;

Array Gain = 0 dB (i.e., no array gain) for channel widths  $\geq 40$  MHz for any  $N_{ANT}$ ;

Array Gain =  $5 \log(N_{ANT}/N_{SS})$  dB or 3 dB, whichever is less for 20-MHz channel widths with  $N_{ANT} \geq 5$ .

For power measurements on all other devices: Array Gain =  $10 \log(N_{ANT}/N_{SS})$  dB.

### 5.2 Maximum Power Spectral Density

| Operation Band     | Equipment Class                              | Limit                 |
|--------------------|----------------------------------------------|-----------------------|
|                    |                                              | Maximum Power Density |
| U-NII-5<br>U-NII-6 | 6XD: 15E 6 GHz Low-power Indoor client       | EIRP -1 dBm/MHz       |
| U-NII-7<br>U-NII-8 | 6ID: 15E 6 GHz Low-power indoor access point | EIRP 5 dBm/MHz        |

### 5.3 Emission Bandwidth

The maximum transmitter channel bandwidth for U-NII devices in the 5.925-7.125 GHz band is 320 MHz.

#### 5.4 In-Band Emission Mask

| Test Item     | Frequencies (MHz)                                                                       | (X) dBc <sup>*1</sup> |
|---------------|-----------------------------------------------------------------------------------------|-----------------------|
| Emission Mask | At 1 MHz outside of channel edge                                                        | 20                    |
|               | At one channel bandwidth from the channel center <sup>*2</sup>                          | 28                    |
|               | At one- and one-half times the channel bandwidth away from channel center <sup>*3</sup> | 40                    |
|               | More than one- and one-half times the channel bandwidth                                 | 40                    |

<sup>\*1</sup> : The power spectral density must be suppressed by "x" dB

<sup>\*2</sup> : At frequencies between one megahertz outside an unlicensed device's channel edge and one channel bandwidth from the center of the channel, the limits must be linearly interpolated between 20 dB and 28 dB suppression,

<sup>\*3</sup> : At frequencies between one and one- and one-half times an unlicensed device's channel bandwidth, the limits must be linearly interpolated between 28 dB and 40 dB suppression.

#### 5.5 Occupied Bandwidth

The results are for reference only.

#### 5.6 Contention-based Protocol

Unlicensed indoor low-power devices must detect co-channel radio frequency power that is at least -62 dBm (The threshold is referenced to a 0 dBi antenna gain.) or lower. Additionally, indoor low-power devices must detect co-channel energy with 90% or greater certainty.

#### 5.7 AC Power Conducted Emissions

| Frequency (MHz) | Conducted Limit (dBuV) |         |
|-----------------|------------------------|---------|
|                 | Quasi-peak             | Average |
| 0.15 - 0.5      | 66 - 56                | 56 - 46 |
| 0.50 - 5.0      | 56                     | 46      |
| 5.0 - 30.0      | 60                     | 50      |

Notes:

1. The lower limit shall apply at the transition frequencies.
2. The limit decreases in line with the logarithm of the frequency in the range of 0.15 to 0.50 MHz.

## 5.8 Unwanted Emissions below 1 GHz

Radiated emissions which fall in the restricted bands must comply with the radiated emission limits specified as below table.

| Frequencies (MHz) | Field Strength (microvolts/meter) | Measurement Distance (meters) |
|-------------------|-----------------------------------|-------------------------------|
| 0.009 ~ 0.490     | 2400/F(kHz)                       | 300                           |
| 0.490 ~ 1.705     | 24000/F(kHz)                      | 30                            |
| 1.705 ~ 30.0      | 30                                | 30                            |
| 30 ~ 88           | 100                               | 3                             |
| 88 ~ 216          | 150                               | 3                             |
| 216 ~ 960         | 200                               | 3                             |
| Above 960         | 500                               | 3                             |

Notes:

1. The lower limit shall apply at the transition frequencies.
2. Emission level (dBuV/m) = 20 log Emission level (uV/m).

## 5.9 Unwanted Emissions above 1 GHz

Radiated emissions which fall in the restricted bands must comply with the radiated emission limits specified as below table.

| Frequencies (MHz) | Field Strength (microvolts/meter) | Measurement Distance (meters) |
|-------------------|-----------------------------------|-------------------------------|
| Above 960         | 500                               | 3                             |

Notes:

1. The lower limit shall apply at the transition frequencies.
2. Emission level (dBuV/m) = 20 log Emission level (uV/m).
3. For frequencies above 1000 MHz, the field strength limits are based on average detector, however, the peak field strength of any emission shall not exceed the maximum permitted average limits, specified above by more than 20 dB under any condition of modulation.

Limits of unwanted emission out of the restricted bands

| Frequencies (MHz)       | EIRP Limit             | Equivalent Field Strength at 3 m |
|-------------------------|------------------------|----------------------------------|
| 5925 MHz > F > 7125 MHz | Peak: -7 (dBm/MHz)     | 88.2 (dBuV/m)                    |
|                         | Average: -27 (dBm/MHz) | 68.2 (dBuV/m)                    |


Note: The following formula is used to convert the equipment isotropic radiated power (eirp) to field strength:

$$E = \frac{1000000 \sqrt{30P}}{3} \mu\text{V/m, where P is the eirp (Watts).}$$

## 6 Test Arrangements

### 6.1 Maximum RF Output Power

#### 6.1.1 Test Setup




Note: The correction factor has already been compensated by the instrument.

#### 6.1.2 Test Procedure

Method PM is used to perform output power measurement, trigger and gating function of wide band power meter is enabled to measure max output power of TX on burst and set the detector to average. Duty factor is not added to measured value.

### 6.2 Maximum Power Spectral Density

#### 6.2.1 Test Setup



Note: The correction factor has already been compensated by the instrument.

#### 6.2.2 Test Procedure


##### For specified measurement bandwidth 1 MHz:

##### Method SA-1

- Set span to encompass the entire 99% OBW of the signal.
- Set RBW = 1 MHz, Set VBW  $\geq$  3 MHz, Detector = RMS.
- Sweep points  $\geq [2 \times \text{span} / \text{RBW}]$ . (This gives bin-to-bin spacing  $\leq \text{RBW} / 2$ , so that narrowband signals are not lost between frequency bins.)
- Sweep time = auto, trigger set to "free run".
- Trace average at least 100 traces in power averaging mode.
- Record the max value

## 6.3 Emission Bandwidth

### 6.3.1 Test Setup




Note: The correction factor has already been compensated by the instrument.

### 6.3.2 Test Procedure

- a. Set RBW = shall be in the range of 1% to 5% of the emission bandwidth.
- b. Set the VBW > RBW.
- c. Detector = peak.
- d. Trace mode = max-hold.
- e. Measure the maximum width of the emission that is 26 dB down from the peak of the emission. Compare this with the RBW setting of the instrument. Readjust RBW and repeat measurement as needed until the RBW/EBW ratio is in the range of 1% to 5%.

## 6.4 In-Band Emission Mask

### 6.4.1 Test Setup




Note: The correction factor has already been compensated by the instrument.

### 6.4.2 Test Procedure

- a. Connect output of the antenna port to a spectrum analyzer and adjust appropriate attenuation.
- b. Measure the 26 dB EBW using the test procedure 12.5.2 of ANSI C63.10-2020. (This will be used to determine the channel edge.)
- c. Measure the power spectral density ( for emissions mask reference) using the following procedure:
  - a) Set the span to encompass the entire 26 dB EBW of the signal.
  - b) Set RBW = same RBW used for 26 dB EBW measurement.
  - c) Set VBW  $\geq 3 \times$  RBW
  - d) Number of points in sweep  $\geq [2 \times \text{span} / \text{RBW}]$ .
  - e) Sweep time = auto.
  - f) Detector = RMS (i.e., power averaging)
  - g) Trace average at least 100 traces in power averaging (rms) mode.
  - h) Use the peak search function on the instrument to find the peak of the spectrum.
- d. Using the measuring equipment limit line function, develop the emissions mask based on the following requirements. The emissions power spectral density must be reduced below the peak power spectral density (in dB) as follows:
  - a) Suppressed by 20 dB at 1 MHz outside of the channel edge. (The channel edge is defined as the 26-dB point on either side of the carrier center frequency.)
  - b) Suppressed by 28 dB at one channel bandwidth from the channel center.
  - c) Suppressed by 40 dB at one- and one-half times the channel bandwidth from the channel center.
- e. Adjust the span to encompass the entire mask as necessary and clear trace.
- f. Trace average at least 100 traces in power averaging (rms) mode.
- g. Adjust the reference level as necessary so that the crest of the channel touches the top of the emission mask.

## 6.5 Occupied Bandwidth

### 6.5.1 Test Setup



Note: The correction factor has already been compensated by the instrument.


### 6.5.2 Test Procedure

The occupied bandwidth is the frequency bandwidth such that, below its lower and above its upper frequency limits, the mean powers are each equal to 0.5% of the total mean power of the given emission. The following procedure shall be used for measuring 99% power bandwidth:

- a. The instrument center frequency is set to the nominal EUT channel center frequency. The frequency span for the spectrum analyzer shall be between 1.5 times and 5.0 times the OBW.
- b. The nominal IF filter bandwidth (3 dB RBW) shall be in the range of 1% to 5% of the OBW, and VBW shall be at least three times the RBW, unless otherwise specified by the applicable requirement.
- c. Set the reference level of the instrument as required, keeping the signal from exceeding the maximum input mixer level for linear operation. In general, the peak of the spectral envelope shall be more than  $[10 \log (OBW/RBW)]$  below the reference level.
- d. Step a) through step c) might require iteration to adjust within the specified range.
- e. Video averaging is not permitted. Where practical, a sample detection and single sweep mode shall be used. Otherwise, peak detection and max-hold mode (until the trace stabilizes) shall be used.
- f. Use the 99% power bandwidth function of the instrument and report the measured bandwidth.

## 6.6 Contention-based Protocol

### 6.6.1 Test Setup



### 6.6.2 Test Procedure


- Set the signal analyzer center frequency to the nominal EUT channel center frequency. The span range of the signal analyzer shall be between two times and five times the OBW of the EUT. Connect the output port of the EUT to the signal analyzer 2. Ensure that the attenuator 2 provides enough attenuation to not overload the signal analyzer 2 receiver.
- Monitoring the signal analyzer 2, verify the EUT is operating and transmitting with the parameters (set as following section 4.7.5 EUT operating condition).
- Determine number of times detection threshold test as following table,

| If                                                    | Number of Tests                                                    | Placement of Incumbent Transmission                                        |
|-------------------------------------------------------|--------------------------------------------------------------------|----------------------------------------------------------------------------|
| $BW_{EUT} \leq BW_{Inc}$                              | Once                                                               | Same as EUT transmission                                                   |
| $BW_{Inc} < BW_{EUT} \leq 2 \times BW_{Inc}$          | Once                                                               | Contained within $BW_{EUT}$                                                |
| $2 \times BW_{Inc} < BW_{EUT} \leq 4 \times BW_{Inc}$ | Twice.<br>(Incumbent transmission is contained within $BW_{EUT}$ ) | Closely to the lower edge and upper edge of the EUT Channel                |
| $BW_{EUT} > 4 \times BW_{Inc}$                        | Three times                                                        | Closely to the lower edge, in the middle and upper edge of the EUT Channel |

- The power measurement of AWGN signal refers to method SA-1 in section 12.4.2.2 of ANSI C63.10-2020.
- Using an AWGN signal source, generate (but do not transmit, i.e., RF OFF) a 10 MHz-wide AWGN signal. Use step c table to determine the center frequency of the 10 MHz AWGN signal relative to the EUT's channel bandwidth and center frequency.
- Set the AWGN signal power to an extremely low level (more than 20 dB below the -62 dBm threshold). Connect the AWGN signal source, via a 3-dB splitter, to the signal analyzer 1 and the EUT.
- Transmit the AWGN signal (RF ON) and verify its characteristics on the signal analyzer 1.
- Monitor the signal analyzer 2 to verify if the AWGN signal has been detected and the EUT has ceased transmission. If the EUT continues to transmit, then incrementally increase the AWGN signal power level until the EUT stops transmitting.
- (Including all losses in the RF paths) Determine and record the AWGN signal power level (at the EUT's antenna port) at which the EUT ceased transmission. Repeat the procedure at least 10 times to verify the EUT can detect an AWGN signal with 90% (or better) level of certainty.
- Refer to step c table to determine number of times the detection threshold testing needs to be repeated. If testing is required more than once, then go back to step d, choose a different center frequency for the AWGN signal and repeat the process.

## 6.7 AC Power Conducted Emissions

### 6.7.1 Test Setup



**Note: 1.Support units were connected to second LISN.**

For the actual test configuration, please refer to the attached file (Test Setup Photo).

### 6.7.2 Test Procedure


- Exploratory ac power-line conducted emission measurements: The EUT shall be operated on the mid channel and in the mode with highest output power unless the fundamental operates in the AC power-line emission test range then the EUT shall be operated in the range of typical modes of operation.
- The EUT was placed on a 0.8 meter to the top of table and placed 0.4 meters from the conducting wall of the shielded room with EUT being connected to the power mains through a line impedance stabilization network (LISN). Other support units were connected to the power mains through another LISN. The two LISNs provide 50 ohm/ 50 uH of coupling impedance for the measuring instrument.
- Both lines of the power mains connected to the EUT were checked for maximum conducted interference.
- The frequency range from 150 kHz to 30 MHz was searched. Emission levels under (Limit – 20 dB) was not recorded.

**Note:** The resolution bandwidth and video bandwidth of test receiver is 9 kHz for quasi-peak detection (QP) and average detection (AV) at frequency 0.15 MHz-30 MHz.


## 6.8 Unwanted Emissions below 1 GHz

### 6.8.1 Test Setup

#### For Radiated emission below 30 MHz



#### For Radiated emission above 30 MHz



For the actual test configuration, please refer to the attached file (Test Setup Photo).

## 6.8.2 Test Procedure

### For Radiated emission below 30 MHz

- a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at 3 meter chamber room for test. The table was rotated 360 degrees to determine the position of the highest radiation.
- b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- c. Parallel, perpendicular, and ground-parallel orientations of the antenna are set to make the measurement.
- d. For each suspected emission, the EUT was arranged to its worst case and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
- e. The test-receiver system was set to Quasi-Peak Detect Function and Specified Bandwidth with Maximum Hold Mode (however, peak detector measurements may be used to determine compliance with QP requirements), except for the frequency band (9 kHz to 90 kHz and 110 kHz to 490 kHz) set to average detect function and peak detect function.

#### Notes:

1. The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 200 Hz at frequency below 150 kHz.
2. The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 9 kHz or 10 kHz at frequency (150 kHz to 30 MHz).
3. All modes of operation were investigated and the worst-case emissions are reported.

### For Radiated emission above 30 MHz


- a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at 3 meter chamber room for test. The table was rotated 360 degrees to determine the position of the highest radiation.
- b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- c. The height of antenna is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
- e. The test-receiver system was set to Quasi-peak(QP) detect function, Average(AV) detect function, Peak(PK) detect function and specified bandwidth with maximum hold mode when the test frequencies less than or equal to 1 GHz.

#### Notes:

1. The resolution bandwidth and video bandwidth of test receiver/spectrum analyzer is 120 kHz for Quasi-peak detection (QP) at frequency below 1 GHz (however, peak detector measurements may be used to determine compliance with QP requirements).
2. All modes of operation were investigated and the worst-case emissions are reported.

## 6.9 Unwanted Emissions above 1 GHz

### 6.9.1 Test Setup



For the actual test configuration, please refer to the attached file (Test Setup Photo).

### 6.9.2 Test Procedure

- The EUT was placed on the top of a rotating table 1.5 meters above the ground at 3 meter chamber room for test. The table was rotated 360 degrees to determine the position of the highest radiation.
- The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.
- The height of antenna is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.
- The test-receiver system was set to peak and average detects function and specified bandwidth with maximum hold mode when the test frequency is above 1 GHz. If the peak reading value also meets average limit, measurement with the average detector is unnecessary.

#### Notes:

- The resolution bandwidth of test receiver/spectrum analyzer is 1 MHz and the video bandwidth is 3 MHz for Peak detection (PK) and Average detection (AV) at frequency above 1 GHz.
- For fundamental and harmonic signal measurement, the resolution bandwidth of test receiver/spectrum analyzer is 1 MHz and the video bandwidth is  $\geq 1/T$  (Duty cycle  $< 98\%$ ) or 10 Hz (Duty cycle  $\geq 98\%$ ) for Average detection (AV) at frequency above 1 GHz.
- All modes of operation were investigated and the worst-case emissions are reported.

## 7 Test Results of Test Item

### 7.1 Maximum RF Output Power

|                           |              |            |            |
|---------------------------|--------------|------------|------------|
| Environmental Conditions: | 25°C, 60% RH | Tested By: | Match Tsui |
|---------------------------|--------------|------------|------------|

#### Mode A

#### 802.11a

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 1     | 5955              | 7.24                | 7.07    | 10.39            | 10.17             | 3.25               | 21.959    | 13.42      | 24               | Pass        |
| 45    | 6175              | 7.26                | 6.90    | 10.219           | 10.09             | 3.25               | 21.598    | 13.34      | 24               | Pass        |
| 93    | 6415              | 7.84                | 7.16    | 11.281           | 10.52             | 3.25               | 23.842    | 13.77      | 24               | Pass        |
| 97    | 6435              | 7.50                | 6.65    | 10.247           | 10.11             | 2.45               | 18.013    | 12.56      | 24               | Pass        |
| 105   | 6475              | 7.47                | 6.79    | 10.36            | 10.15             | 2.45               | 18.212    | 12.6       | 24               | Pass        |
| 113   | 6515              | 7.37                | 6.80    | 10.244           | 10.10             | 2.45               | 18.008    | 12.55      | 24               | Pass        |
| 117   | 6535              | 7.18                | 6.84    | 10.055           | 10.02             | 2.31               | 17.115    | 12.33      | 24               | Pass        |
| 149   | 6695              | 7.07                | 6.97    | 10.071           | 10.03             | 2.31               | 17.142    | 12.34      | 24               | Pass        |
| 181   | 6855              | 7.28                | 6.71    | 10.034           | 10.01             | 2.31               | 17.079    | 12.32      | 24               | Pass        |
| 185   | 6875              | 7.30                | 6.90    | 10.268           | 10.11             | 2.31               | 17.478    | 12.42      | 24               | Pass        |
| 209   | 6995              | 8.69                | 8.20    | 14.003           | 11.46             | 2.01               | 22.244    | 13.47      | 24               | Pass        |
| 233   | 7115              | 8.62                | 8.27    | 13.992           | 11.46             | 2.01               | 22.227    | 13.47      | 24               | Pass        |

#### Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

## 802.11be (EHT20)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 1     | 5955              | 7.95                | 7.77    | 12.221           | 10.87             | 3.25               | 25.829    | 14.12      | 24               | Pass        |
| 45    | 6175              | 7.41                | 7.23    | 10.793           | 10.33             | 3.25               | 22.811    | 13.58      | 24               | Pass        |
| 93    | 6415              | 8.47                | 7.74    | 12.974           | 11.13             | 3.25               | 27.42     | 14.38      | 24               | Pass        |
| 97    | 6435              | 8.26                | 7.80    | 12.724           | 11.05             | 2.45               | 22.368    | 13.5       | 24               | Pass        |
| 105   | 6475              | 8.18                | 7.85    | 12.672           | 11.03             | 2.45               | 22.276    | 13.48      | 24               | Pass        |
| 113   | 6515              | 8.25                | 7.75    | 12.64            | 11.02             | 2.45               | 22.22     | 13.47      | 24               | Pass        |
| 117   | 6535              | 7.73                | 7.31    | 11.312           | 10.54             | 2.31               | 19.255    | 12.85      | 24               | Pass        |
| 149   | 6695              | 7.61                | 7.41    | 11.276           | 10.52             | 2.31               | 19.194    | 12.83      | 24               | Pass        |
| 181   | 6855              | 7.90                | 7.57    | 11.881           | 10.75             | 2.31               | 20.223    | 13.06      | 24               | Pass        |
| 185   | 6875              | 8.03                | 7.72    | 12.269           | 10.89             | 2.31               | 20.884    | 13.2       | 24               | Pass        |
| 209   | 6995              | 8.86                | 8.65    | 15.02            | 11.77             | 2.01               | 23.86     | 13.78      | 24               | Pass        |
| 233   | 7115              | 0.62                | 0.52    | 2.281            | 3.58              | 2.01               | 3.623     | 5.59       | 24               | Pass        |

### Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT40)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 3     | 5965              | 9.71                | 9.72    | 18.73            | 12.73             | 3.25               | 39.586    | 15.98      | 24               | Pass        |
| 43    | 6165              | 9.32                | 9.10    | 16.679           | 12.22             | 3.25               | 35.251    | 15.47      | 24               | Pass        |
| 91    | 6405              | 9.75                | 9.45    | 18.251           | 12.61             | 3.25               | 38.573    | 15.86      | 24               | Pass        |
| 99    | 6445              | 9.78                | 9.42    | 18.256           | 12.61             | 2.45               | 32.093    | 15.06      | 24               | Pass        |
| 107   | 6485              | 9.82                | 9.47    | 18.445           | 12.66             | 2.45               | 32.425    | 15.11      | 24               | Pass        |
| 115   | 6525              | 9.77                | 9.42    | 18.234           | 12.61             | 2.45               | 32.054    | 15.06      | 24               | Pass        |
| 123   | 6565              | 9.71                | 9.48    | 18.226           | 12.61             | 2.31               | 31.024    | 14.92      | 24               | Pass        |
| 155   | 6725              | 9.42                | 8.91    | 16.53            | 12.18             | 2.31               | 28.137    | 14.49      | 24               | Pass        |
| 179   | 6845              | 9.85                | 9.44    | 18.451           | 12.66             | 2.31               | 31.407    | 14.97      | 24               | Pass        |
| 187   | 6885              | 9.88                | 9.61    | 18.869           | 12.76             | 2.31               | 32.118    | 15.07      | 24               | Pass        |
| 211   | 7005              | 9.79                | 9.57    | 18.585           | 12.69             | 2.01               | 29.523    | 14.7       | 24               | Pass        |
| 227   | 7085              | 9.52                | 9.68    | 18.243           | 12.61             | 2.01               | 28.98     | 14.62      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT80)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 7     | 5985              | 13.42               | 13.34   | 43.556           | 16.39             | 3.25               | 92.055    | 19.64      | 24               | Pass        |
| 39    | 6145              | 13.43               | 13.23   | 43.067           | 16.34             | 3.25               | 91.022    | 19.59      | 24               | Pass        |
| 87    | 6385              | 13.84               | 13.44   | 46.29            | 16.65             | 3.25               | 97.833    | 19.9       | 24               | Pass        |
| 103   | 6465              | 13.86               | 13.50   | 46.709           | 16.69             | 2.45               | 82.111    | 19.14      | 24               | Pass        |
| 119   | 6545              | 13.34               | 12.94   | 41.256           | 16.15             | 2.45               | 72.525    | 18.6       | 24               | Pass        |
| 151   | 6705              | 13.22               | 13.06   | 41.22            | 16.15             | 2.31               | 70.163    | 18.46      | 24               | Pass        |
| 183   | 6865              | 13.44               | 13.32   | 43.558           | 16.39             | 2.31               | 74.143    | 18.7       | 24               | Pass        |
| 199   | 6945              | 14.67               | 14.15   | 55.311           | 17.43             | 2.01               | 87.864    | 19.44      | 24               | Pass        |
| 215   | 7025              | 14.54               | 14.31   | 55.422           | 17.44             | 2.01               | 88.04     | 19.45      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT160)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 15    | 6025              | 14.58               | 13.92   | 53.368           | 17.27             | 3.25               | 112.793   | 20.52      | 24               | Pass        |
| 47    | 6185              | 14.57               | 14.00   | 53.761           | 17.30             | 3.25               | 113.623   | 20.55      | 24               | Pass        |
| 79    | 6345              | 14.52               | 14.02   | 53.549           | 17.29             | 3.25               | 113.175   | 20.54      | 24               | Pass        |
| 111   | 6505              | 14.33               | 14.16   | 53.163           | 17.26             | 2.45               | 93.456    | 19.71      | 24               | Pass        |
| 143   | 6665              | 14.36               | 14.18   | 53.472           | 17.28             | 2.31               | 91.018    | 19.59      | 24               | Pass        |
| 175   | 6825              | 14.38               | 14.18   | 53.598           | 17.29             | 2.31               | 91.232    | 19.6       | 24               | Pass        |
| 207   | 6985              | 14.36               | 14.29   | 54.143           | 17.34             | 2.01               | 86.009    | 19.35      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT320)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 31    | 6105              | 14.44               | 14.09   | 53.442           | 17.28             | 3.25               | 112.949   | 20.53      | 24               | Pass        |
| 63    | 6265              | 14.50               | 14.11   | 53.947           | 17.32             | 3.25               | 114.016   | 20.57      | 24               | Pass        |
| 95    | 6425              | 14.42               | 14.15   | 53.671           | 17.30             | 3.25               | 113.433   | 20.55      | 24               | Pass        |
| 127   | 6585              | 14.39               | 14.20   | 53.782           | 17.31             | 2.45               | 94.545    | 19.76      | 24               | Pass        |
| 159   | 6745              | 14.44               | 14.15   | 53.799           | 17.31             | 2.31               | 91.574    | 19.62      | 24               | Pass        |
| 191   | 6905              | 14.58               | 14.06   | 54.176           | 17.34             | 2.31               | 92.216    | 19.65      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

## Mode B

### 802.11a

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 1     | 5955              | 7.24                | 7.07    | 10.39            | 10.17             | 3.25               | 21.959    | 13.42      | 24               | Pass        |
| 45    | 6175              | 7.26                | 6.90    | 10.219           | 10.09             | 3.25               | 21.598    | 13.34      | 24               | Pass        |
| 93    | 6415              | 7.84                | 7.16    | 11.281           | 10.52             | 3.25               | 23.842    | 13.77      | 24               | Pass        |
| 97    | 6435              | 7.50                | 6.65    | 10.247           | 10.11             | 2.45               | 18.013    | 12.56      | 24               | Pass        |
| 105   | 6475              | 7.47                | 6.79    | 10.36            | 10.15             | 2.45               | 18.212    | 12.6       | 24               | Pass        |
| 113   | 6515              | 7.37                | 6.80    | 10.244           | 10.10             | 2.45               | 18.008    | 12.55      | 24               | Pass        |
| 117   | 6535              | 7.18                | 6.84    | 10.055           | 10.02             | 2.31               | 17.115    | 12.33      | 24               | Pass        |
| 149   | 6695              | 7.07                | 6.97    | 10.071           | 10.03             | 2.31               | 17.142    | 12.34      | 24               | Pass        |
| 181   | 6855              | 7.28                | 6.71    | 10.034           | 10.01             | 2.31               | 17.079    | 12.32      | 24               | Pass        |
| 185   | 6875              | 7.30                | 6.90    | 10.268           | 10.11             | 2.31               | 17.478    | 12.42      | 24               | Pass        |
| 209   | 6995              | 8.69                | 8.20    | 14.003           | 11.46             | 2.01               | 22.244    | 13.47      | 24               | Pass        |
| 233   | 7115              | 8.62                | 8.27    | 13.992           | 11.46             | 2.01               | 22.227    | 13.47      | 24               | Pass        |

#### Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

## 802.11be (EHT20)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 1     | 5955              | 7.95                | 7.77    | 12.221           | 10.87             | 3.25               | 25.829    | 14.12      | 24               | Pass        |
| 45    | 6175              | 7.41                | 7.23    | 10.793           | 10.33             | 3.25               | 22.811    | 13.58      | 24               | Pass        |
| 93    | 6415              | 8.47                | 7.74    | 12.974           | 11.13             | 3.25               | 27.42     | 14.38      | 24               | Pass        |
| 97    | 6435              | 8.26                | 7.80    | 12.724           | 11.05             | 2.45               | 22.368    | 13.5       | 24               | Pass        |
| 105   | 6475              | 8.18                | 7.85    | 12.672           | 11.03             | 2.45               | 22.276    | 13.48      | 24               | Pass        |
| 113   | 6515              | 8.25                | 7.75    | 12.64            | 11.02             | 2.45               | 22.22     | 13.47      | 24               | Pass        |
| 117   | 6535              | 7.73                | 7.31    | 11.312           | 10.54             | 2.31               | 19.255    | 12.85      | 24               | Pass        |
| 149   | 6695              | 7.61                | 7.41    | 11.276           | 10.52             | 2.31               | 19.194    | 12.83      | 24               | Pass        |
| 181   | 6855              | 7.90                | 7.57    | 11.881           | 10.75             | 2.31               | 20.223    | 13.06      | 24               | Pass        |
| 185   | 6875              | 8.03                | 7.72    | 12.269           | 10.89             | 2.31               | 20.884    | 13.2       | 24               | Pass        |
| 209   | 6995              | 8.86                | 8.65    | 15.02            | 11.77             | 2.01               | 23.86     | 13.78      | 24               | Pass        |
| 233   | 7115              | 0.62                | 0.52    | 2.281            | 3.58              | 2.01               | 3.623     | 5.59       | 24               | Pass        |

### Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT40)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 3     | 5965              | 9.71                | 9.72    | 18.73            | 12.73             | 3.25               | 39.586    | 15.98      | 24               | Pass        |
| 43    | 6165              | 9.32                | 9.10    | 16.679           | 12.22             | 3.25               | 35.251    | 15.47      | 24               | Pass        |
| 91    | 6405              | 9.75                | 9.45    | 18.251           | 12.61             | 3.25               | 38.573    | 15.86      | 24               | Pass        |
| 99    | 6445              | 9.78                | 9.42    | 18.256           | 12.61             | 2.45               | 32.093    | 15.06      | 24               | Pass        |
| 107   | 6485              | 9.82                | 9.47    | 18.445           | 12.66             | 2.45               | 32.425    | 15.11      | 24               | Pass        |
| 115   | 6525              | 9.77                | 9.42    | 18.234           | 12.61             | 2.45               | 32.054    | 15.06      | 24               | Pass        |
| 123   | 6565              | 9.71                | 9.48    | 18.226           | 12.61             | 2.31               | 31.024    | 14.92      | 24               | Pass        |
| 155   | 6725              | 9.42                | 8.91    | 16.53            | 12.18             | 2.31               | 28.137    | 14.49      | 24               | Pass        |
| 179   | 6845              | 9.85                | 9.44    | 18.451           | 12.66             | 2.31               | 31.407    | 14.97      | 24               | Pass        |
| 187   | 6885              | 9.88                | 9.61    | 18.869           | 12.76             | 2.31               | 32.118    | 15.07      | 24               | Pass        |
| 211   | 7005              | 9.79                | 9.57    | 18.585           | 12.69             | 2.01               | 29.523    | 14.7       | 24               | Pass        |
| 227   | 7085              | 9.52                | 9.68    | 18.243           | 12.61             | 2.01               | 28.98     | 14.62      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT80)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 7     | 5985              | 9.97                | 9.89    | 19.681           | 12.94             | 3.25               | 41.596    | 16.19      | 24               | Pass        |
| 39    | 6145              | 9.98                | 9.78    | 19.46            | 12.89             | 3.25               | 41.128    | 16.14      | 24               | Pass        |
| 87    | 6385              | 9.95                | 9.55    | 18.901           | 12.76             | 3.25               | 39.947    | 16.01      | 24               | Pass        |
| 103   | 6465              | 9.97                | 9.61    | 19.072           | 12.80             | 2.45               | 33.527    | 15.25      | 24               | Pass        |
| 119   | 6545              | 9.93                | 9.53    | 18.814           | 12.74             | 2.45               | 33.074    | 15.19      | 24               | Pass        |
| 151   | 6705              | 9.98                | 9.82    | 19.548           | 12.91             | 2.31               | 33.274    | 15.22      | 24               | Pass        |
| 183   | 6865              | 9.97                | 9.85    | 19.592           | 12.92             | 2.31               | 33.349    | 15.23      | 24               | Pass        |
| 199   | 6945              | 9.88                | 9.36    | 18.357           | 12.64             | 2.01               | 29.161    | 14.65      | 24               | Pass        |
| 215   | 7025              | 9.87                | 9.64    | 18.91            | 12.77             | 2.01               | 30.039    | 14.78      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT160)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 15    | 6025              | 9.97                | 9.31    | 18.462           | 12.66             | 3.25               | 39.019    | 15.91      | 24               | Pass        |
| 47    | 6185              | 9.95                | 9.38    | 18.555           | 12.68             | 3.25               | 39.216    | 15.93      | 24               | Pass        |
| 79    | 6345              | 9.95                | 9.45    | 18.696           | 12.72             | 3.25               | 39.514    | 15.97      | 24               | Pass        |
| 111   | 6505              | 9.92                | 9.75    | 19.258           | 12.85             | 2.45               | 33.854    | 15.3       | 24               | Pass        |
| 143   | 6665              | 9.85                | 9.67    | 18.929           | 12.77             | 2.31               | 32.22     | 15.08      | 24               | Pass        |
| 175   | 6825              | 9.72                | 9.52    | 18.329           | 12.63             | 2.31               | 31.199    | 14.94      | 24               | Pass        |
| 207   | 6985              | 9.95                | 9.88    | 19.613           | 12.93             | 2.01               | 31.156    | 14.94      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

### 802.11be (EHT320)

| Chan. | Chan. Freq. (MHz) | Average Power (dBm) |         | Total Power (mW) | Total Power (dBm) | Maximum Gain (dBi) | EIRP (mW) | EIRP (dBm) | EIRP Limit (dBm) | Test Result |
|-------|-------------------|---------------------|---------|------------------|-------------------|--------------------|-----------|------------|------------------|-------------|
|       |                   | Chain 0             | Chain 1 |                  |                   |                    |           |            |                  |             |
| 31    | 6105              | 9.88                | 9.53    | 18.702           | 12.72             | 3.25               | 39.526    | 15.97      | 24               | Pass        |
| 63    | 6265              | 9.87                | 9.38    | 18.375           | 12.64             | 3.25               | 38.835    | 15.89      | 24               | Pass        |
| 95    | 6425              | 9.95                | 9.68    | 19.175           | 12.83             | 3.25               | 40.526    | 16.08      | 24               | Pass        |
| 127   | 6585              | 9.95                | 9.76    | 19.348           | 12.87             | 2.45               | 34.012    | 15.32      | 24               | Pass        |
| 159   | 6745              | 9.79                | 9.42    | 18.278           | 12.62             | 2.31               | 31.112    | 14.93      | 24               | Pass        |
| 191   | 6905              | 9.95                | 9.27    | 18.338           | 12.63             | 2.31               | 31.214    | 14.94      | 24               | Pass        |

Notes:

1. Directional gain is the maximum gain of antennas.
2. For U-NII-5, The maximum gain is 3.25 dBi.
3. For U-NII-6, The maximum gain is 2.45 dBi.
4. For U-NII-7, The maximum gain is 2.31 dBi.
5. For U-NII-8, The maximum gain is 2.01 dBi.

## 7.2 Maximum Power Spectral Density

|                           |              |            |            |
|---------------------------|--------------|------------|------------|
| Environmental Conditions: | 25°C, 60% RH | Tested By: | Match Tsui |
|---------------------------|--------------|------------|------------|

### Mode A

#### 802.11a

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 1     | 5955              | -9.78         | -9.92   | -6.84               | 5.51                   | -1.33              | -1                       | Pass        |
| 45    | 6175              | -9.41         | -9.72   | -6.55               | 5.51                   | -1.04              | -1                       | Pass        |
| 93    | 6415              | -9.59         | -10.07  | -6.81               | 5.51                   | -1.3               | -1                       | Pass        |
| 97    | 6435              | -9.85         | -9.43   | -6.62               | 5.21                   | -1.41              | -1                       | Pass        |
| 105   | 6475              | -9.23         | -9.58   | -6.39               | 5.21                   | -1.18              | -1                       | Pass        |
| 113   | 6515              | -9.34         | -9.55   | -6.43               | 5.21                   | -1.22              | -1                       | Pass        |
| 117   | 6535              | -9.51         | -9.98   | -6.73               | 5.30                   | -1.43              | -1                       | Pass        |
| 149   | 6695              | -9.79         | -9.42   | -6.59               | 5.30                   | -1.29              | -1                       | Pass        |
| 181   | 6855              | -9.58         | -9.91   | -6.73               | 5.30                   | -1.43              | -1                       | Pass        |
| 185   | 6875              | -9.79         | -9.60   | -6.68               | 5.30                   | -1.38              | -1                       | Pass        |
| 209   | 6995              | -8.82         | -9.56   | -6.16               | 4.98                   | -1.18              | -1                       | Pass        |
| 233   | 7115              | -8.80         | -9.44   | -6.10               | 4.98                   | -1.12              | -1                       | Pass        |

#### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

## 802.11be (EHT20)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 1     | 5955              | -9.78         | -9.93   | -6.84               | 5.51                   | -1.33              | -1                       | Pass        |
| 45    | 6175              | -9.63         | -10.08  | -6.84               | 5.51                   | -1.33              | -1                       | Pass        |
| 93    | 6415              | -9.20         | -10.26  | -6.69               | 5.51                   | -1.18              | -1                       | Pass        |
| 97    | 6435              | -9.23         | -9.96   | -6.57               | 5.21                   | -1.36              | -1                       | Pass        |
| 105   | 6475              | -9.28         | -9.52   | -6.39               | 5.21                   | -1.18              | -1                       | Pass        |
| 113   | 6515              | -9.32         | -9.59   | -6.44               | 5.21                   | -1.23              | -1                       | Pass        |
| 117   | 6535              | -9.23         | -10.17  | -6.66               | 5.30                   | -1.36              | -1                       | Pass        |
| 149   | 6695              | -9.33         | -9.42   | -6.36               | 5.30                   | -1.06              | -1                       | Pass        |
| 181   | 6855              | -9.45         | -9.70   | -6.56               | 5.30                   | -1.26              | -1                       | Pass        |
| 185   | 6875              | -9.36         | -9.80   | -6.56               | 5.30                   | -1.26              | -1                       | Pass        |
| 209   | 6995              | -8.96         | -9.69   | -6.30               | 4.98                   | -1.32              | -1                       | Pass        |
| 233   | 7115              | -16.21        | -16.21  | -13.20              | 4.98                   | -8.22              | -1                       | Pass        |

### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

## 802.11be (EHT40)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 3     | 5965              | -9.30         | -10.33  | -6.77               | 5.51                   | -1.26              | -1                       | Pass        |
| 43    | 6165              | -9.46         | -10.34  | -6.87               | 5.51                   | -1.36              | -1                       | Pass        |
| 91    | 6405              | -10.50        | -11.08  | -7.77               | 5.51                   | -2.26              | -1                       | Pass        |
| 99    | 6445              | -9.17         | -11.15  | -7.04               | 5.21                   | -1.83              | -1                       | Pass        |
| 107   | 6485              | -9.18         | -10.30  | -6.69               | 5.21                   | -1.48              | -1                       | Pass        |
| 115   | 6525              | -9.33         | -9.92   | -6.60               | 5.30                   | -1.3               | -1                       | Pass        |
| 123   | 6565              | -9.33         | -9.84   | -6.57               | 5.30                   | -1.27              | -1                       | Pass        |
| 155   | 6725              | -9.06         | -9.69   | -6.35               | 5.30                   | -1.05              | -1                       | Pass        |
| 179   | 6845              | -9.28         | -9.86   | -6.55               | 5.30                   | -1.25              | -1                       | Pass        |
| 187   | 6885              | -10.27        | -10.38  | -7.31               | 5.30                   | -2.01              | -1                       | Pass        |
| 211   | 7005              | -10.29        | -10.51  | -7.39               | 4.98                   | -2.41              | -1                       | Pass        |
| 227   | 7085              | -10.23        | -10.29  | -7.25               | 4.98                   | -2.27              | -1                       | Pass        |

### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

### 802.11be (EHT80)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 7     | 5985              | -9.51         | -10.11  | -6.79               | 5.51                   | -1.28              | -1                       | Pass        |
| 39    | 6145              | -9.53         | -10.22  | -6.85               | 5.51                   | -1.34              | -1                       | Pass        |
| 87    | 6385              | -9.54         | -10.00  | -6.75               | 5.51                   | -1.24              | -1                       | Pass        |
| 103   | 6465              | -9.15         | -9.84   | -6.47               | 5.21                   | -1.26              | -1                       | Pass        |
| 119   | 6545              | -9.49         | -9.83   | -6.65               | 5.30                   | -1.35              | -1                       | Pass        |
| 151   | 6705              | -9.51         | -9.98   | -6.73               | 5.30                   | -1.43              | -1                       | Pass        |
| 183   | 6865              | -9.52         | -9.78   | -6.64               | 5.30                   | -1.34              | -1                       | Pass        |
| 199   | 6945              | -8.74         | -9.30   | -6.00               | 4.98                   | -1.02              | -1                       | Pass        |
| 215   | 7025              | -9.09         | -9.78   | -6.41               | 4.98                   | -1.43              | -1                       | Pass        |

Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

### 802.11be (EHT160)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 15    | 6025              | -9.83         | -10.95  | -7.34               | 5.51                   | -1.83              | -1                       | Pass        |
| 47    | 6185              | -10.28        | -10.86  | -7.55               | 5.51                   | -2.04              | -1                       | Pass        |
| 79    | 6345              | -10.43        | -10.82  | -7.61               | 5.51                   | -2.1               | -1                       | Pass        |
| 111   | 6505              | -9.84         | -10.40  | -7.10               | 5.30                   | -1.8               | -1                       | Pass        |
| 143   | 6665              | -10.58        | -10.72  | -7.64               | 5.30                   | -2.34              | -1                       | Pass        |
| 175   | 6825              | -10.55        | -10.39  | -7.46               | 5.30                   | -2.16              | -1                       | Pass        |
| 207   | 6985              | -10.56        | -10.69  | -7.61               | 4.98                   | -2.63              | -1                       | Pass        |

Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.


## 802.11be (EHT320)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 31    | 6105              | -12.53        | -12.78  | -9.64               | 5.51                   | -4.13              | -1                       | Pass        |
| 63    | 6265              | -12.99        | -13.43  | -10.19              | 5.51                   | -4.68              | -1                       | Pass        |
| 95    | 6425              | -13.45        | -13.04  | -10.23              | 5.51                   | -4.72              | -1                       | Pass        |
| 127   | 6585              | -13.33        | -12.88  | -10.09              | 5.30                   | -4.79              | -1                       | Pass        |
| 159   | 6745              | -13.28        | -12.97  | -10.11              | 5.30                   | -4.81              | -1                       | Pass        |
| 191   | 6905              | -13.27        | -13.78  | -10.51              | 5.30                   | -5.21              | -1                       | Pass        |


### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.


## Spectrum Plot of Maximum Value




802.11a / Chain 0: CH 233




802.11be (EHT20) / Chain 0: CH 209




802.11be (EHT40) / Chain 0: CH 155



802.11be (EHT80) / Chain 0: CH 199



802.11be (EHT160) / Chain 0: CH 15



802.11be (EHT320) / Chain 0: CH 31

## Mode B

### 802.11a

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 1     | 5955              | -9.78         | -9.92   | -6.84               | 5.51                   | -1.33              | -1                       | Pass        |
| 45    | 6175              | -9.41         | -9.72   | -6.55               | 5.51                   | -1.04              | -1                       | Pass        |
| 93    | 6415              | -9.59         | -10.07  | -6.81               | 5.51                   | -1.3               | -1                       | Pass        |
| 97    | 6435              | -9.85         | -9.43   | -6.62               | 5.21                   | -1.41              | -1                       | Pass        |
| 105   | 6475              | -9.23         | -9.58   | -6.39               | 5.21                   | -1.18              | -1                       | Pass        |
| 113   | 6515              | -9.34         | -9.55   | -6.43               | 5.21                   | -1.22              | -1                       | Pass        |
| 117   | 6535              | -9.51         | -9.98   | -6.73               | 5.30                   | -1.43              | -1                       | Pass        |
| 149   | 6695              | -9.79         | -9.42   | -6.59               | 5.30                   | -1.29              | -1                       | Pass        |
| 181   | 6855              | -9.58         | -9.91   | -6.73               | 5.30                   | -1.43              | -1                       | Pass        |
| 185   | 6875              | -9.79         | -9.60   | -6.68               | 5.30                   | -1.38              | -1                       | Pass        |
| 209   | 6995              | -8.82         | -9.56   | -6.16               | 4.98                   | -1.18              | -1                       | Pass        |
| 233   | 7115              | -8.80         | -9.44   | -6.10               | 4.98                   | -1.12              | -1                       | Pass        |

#### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

## 802.11be (EHT20)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 1     | 5955              | -9.78         | -9.93   | -6.84               | 5.51                   | -1.33              | -1                       | Pass        |
| 45    | 6175              | -9.63         | -10.08  | -6.84               | 5.51                   | -1.33              | -1                       | Pass        |
| 93    | 6415              | -9.20         | -10.26  | -6.69               | 5.51                   | -1.18              | -1                       | Pass        |
| 97    | 6435              | -9.23         | -9.96   | -6.57               | 5.21                   | -1.36              | -1                       | Pass        |
| 105   | 6475              | -9.28         | -9.52   | -6.39               | 5.21                   | -1.18              | -1                       | Pass        |
| 113   | 6515              | -9.32         | -9.59   | -6.44               | 5.21                   | -1.23              | -1                       | Pass        |
| 117   | 6535              | -9.23         | -10.17  | -6.66               | 5.30                   | -1.36              | -1                       | Pass        |
| 149   | 6695              | -9.33         | -9.42   | -6.36               | 5.30                   | -1.06              | -1                       | Pass        |
| 181   | 6855              | -9.45         | -9.70   | -6.56               | 5.30                   | -1.26              | -1                       | Pass        |
| 185   | 6875              | -9.36         | -9.80   | -6.56               | 5.30                   | -1.26              | -1                       | Pass        |
| 209   | 6995              | -8.96         | -9.69   | -6.30               | 4.98                   | -1.32              | -1                       | Pass        |
| 233   | 7115              | -16.21        | -16.21  | -13.20              | 4.98                   | -8.22              | -1                       | Pass        |

### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

## 802.11be (EHT40)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 3     | 5965              | -9.30         | -10.33  | -6.77               | 5.51                   | -1.26              | -1                       | Pass        |
| 43    | 6165              | -9.46         | -10.34  | -6.87               | 5.51                   | -1.36              | -1                       | Pass        |
| 91    | 6405              | -10.50        | -11.08  | -7.77               | 5.51                   | -2.26              | -1                       | Pass        |
| 99    | 6445              | -9.17         | -11.15  | -7.04               | 5.21                   | -1.83              | -1                       | Pass        |
| 107   | 6485              | -9.18         | -10.30  | -6.69               | 5.21                   | -1.48              | -1                       | Pass        |
| 115   | 6525              | -9.33         | -9.92   | -6.60               | 5.30                   | -1.3               | -1                       | Pass        |
| 123   | 6565              | -9.33         | -9.84   | -6.57               | 5.30                   | -1.27              | -1                       | Pass        |
| 155   | 6725              | -9.06         | -9.69   | -6.35               | 5.30                   | -1.05              | -1                       | Pass        |
| 179   | 6845              | -9.28         | -9.86   | -6.55               | 5.30                   | -1.25              | -1                       | Pass        |
| 187   | 6885              | -10.27        | -10.38  | -7.31               | 5.30                   | -2.01              | -1                       | Pass        |
| 211   | 7005              | -10.29        | -10.51  | -7.39               | 4.98                   | -2.41              | -1                       | Pass        |
| 227   | 7085              | -10.23        | -10.29  | -7.25               | 4.98                   | -2.27              | -1                       | Pass        |

### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

### 802.11be (EHT80)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 7     | 5985              | -9.51         | -10.11  | -6.79               | 5.51                   | -1.28              | -1                       | Pass        |
| 39    | 6145              | -9.53         | -10.22  | -6.85               | 5.51                   | -1.34              | -1                       | Pass        |
| 87    | 6385              | -9.54         | -10.00  | -6.75               | 5.51                   | -1.24              | -1                       | Pass        |
| 103   | 6465              | -9.15         | -9.84   | -6.47               | 5.21                   | -1.26              | -1                       | Pass        |
| 119   | 6545              | -9.49         | -9.83   | -6.65               | 5.30                   | -1.35              | -1                       | Pass        |
| 151   | 6705              | -9.51         | -9.98   | -6.73               | 5.30                   | -1.43              | -1                       | Pass        |
| 183   | 6865              | -9.52         | -9.78   | -6.64               | 5.30                   | -1.34              | -1                       | Pass        |
| 199   | 6945              | -8.74         | -9.30   | -6.00               | 4.98                   | -1.02              | -1                       | Pass        |
| 215   | 7025              | -9.09         | -9.78   | -6.41               | 4.98                   | -1.43              | -1                       | Pass        |

Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.

### 802.11be (EHT160)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 15    | 6025              | -14.95        | -15.34  | -12.13              | 5.51                   | -6.62              | -1                       | Pass        |
| 47    | 6185              | -14.72        | -15.48  | -12.07              | 5.51                   | -6.56              | -1                       | Pass        |
| 79    | 6345              | -14.94        | -15.31  | -12.11              | 5.51                   | -6.6               | -1                       | Pass        |
| 111   | 6505              | -14.93        | -14.97  | -11.94              | 5.30                   | -6.64              | -1                       | Pass        |
| 143   | 6665              | -14.79        | -15.18  | -11.97              | 5.30                   | -6.67              | -1                       | Pass        |
| 175   | 6825              | -15.04        | -15.36  | -12.19              | 5.30                   | -6.89              | -1                       | Pass        |
| 207   | 6985              | -14.95        | -14.98  | -11.95              | 4.98                   | -6.97              | -1                       | Pass        |

Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.


## 802.11be (EHT320)

| Chan. | Chan. Freq. (MHz) | PSD (dBm/MHz) |         | Total PSD (dBm/MHz) | Directional Gain (dBi) | EIRP PSD (dBm/MHz) | EIRP PSD Limit (dBm/MHz) | Test Result |
|-------|-------------------|---------------|---------|---------------------|------------------------|--------------------|--------------------------|-------------|
|       |                   | Chain 0       | Chain 1 |                     |                        |                    |                          |             |
| 31    | 6105              | -17.52        | -17.52  | -14.51              | 5.51                   | -9                 | -1                       | Pass        |
| 63    | 6265              | -18.09        | -17.63  | -14.84              | 5.51                   | -9.33              | -1                       | Pass        |
| 95    | 6425              | -17.88        | -17.43  | -14.64              | 5.51                   | -9.13              | -1                       | Pass        |
| 127   | 6585              | -18.17        | -17.31  | -14.71              | 5.30                   | -9.41              | -1                       | Pass        |
| 159   | 6745              | -18.07        | -17.71  | -14.88              | 5.30                   | -9.58              | -1                       | Pass        |
| 191   | 6905              | -17.75        | -18.09  | -14.91              | 5.30                   | -9.61              | -1                       | Pass        |


### Notes:

1. Method E) 2) a) of power density measurement of KDB 662911 is using for calculating total power density. Total power density is summing entire spectra across corresponding frequency bins on the various outputs by computer.
2. Directional gain =  $10 \log[(10^{\text{Chain0}/20} + 10^{\text{Chain1}/20})^2 / 2]$
3. For U-NII-5, The directional gain is 5.51 dBi.
4. For U-NII-6, The directional gain is 5.21 dBi.
5. For U-NII-7, The directional gain is 5.3 dBi.
6. For U-NII-8, The directional gain is 4.98 dBi.


## Spectrum Plot of Maximum Value




802.11a / Chain 0: CH 233




802.11be (EHT20) / Chain 0: CH 209




802.11be (EHT40) / Chain 0: CH 155



802.11be (EHT80) / Chain 0: CH 199



802.11be (EHT160) / Chain 0: CH 47



802.11be (EHT320) / Chain 1: CH 127

### 7.3 Emission Bandwidth

|                           |              |            |            |
|---------------------------|--------------|------------|------------|
| Environmental Conditions: | 25°C, 60% RH | Tested By: | Match Tsui |
|---------------------------|--------------|------------|------------|

#### Mode A

##### 802.11a

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 1       | 5955            | 23.77                | 23.43   | 320                 | Pass        |
| 45      | 6175            | 23.84                | 23.92   | 320                 | Pass        |
| 93      | 6415            | 23.75                | 23.46   | 320                 | Pass        |
| 97      | 6435            | 23.92                | 23.92   | 320                 | Pass        |
| 105     | 6475            | 23.78                | 23.32   | 320                 | Pass        |
| 113     | 6515            | 23.78                | 23.57   | 320                 | Pass        |
| 117     | 6535            | 23.68                | 23.49   | 320                 | Pass        |
| 149     | 6695            | 23.98                | 23.61   | 320                 | Pass        |
| 181     | 6855            | 23.61                | 23.87   | 320                 | Pass        |
| 185     | 6875            | 23.76                | 23.87   | 320                 | Pass        |
| 209     | 6995            | 23.89                | 23.50   | 320                 | Pass        |
| 233     | 7115            | 23.91                | 23.85   | 320                 | Pass        |

##### 802.11be (EHT20)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 1       | 5955            | 23.79                | 23.64   | 320                 | Pass        |
| 45      | 6175            | 23.43                | 23.80   | 320                 | Pass        |
| 93      | 6415            | 23.23                | 23.97   | 320                 | Pass        |
| 97      | 6435            | 23.97                | 23.84   | 320                 | Pass        |
| 105     | 6475            | 23.49                | 24.04   | 320                 | Pass        |
| 113     | 6515            | 23.39                | 24.14   | 320                 | Pass        |
| 117     | 6535            | 23.66                | 23.71   | 320                 | Pass        |
| 149     | 6695            | 23.35                | 23.55   | 320                 | Pass        |
| 181     | 6855            | 23.71                | 23.63   | 320                 | Pass        |
| 185     | 6875            | 23.41                | 23.67   | 320                 | Pass        |
| 209     | 6995            | 23.62                | 23.96   | 320                 | Pass        |
| 233     | 7115            | 23.31                | 23.93   | 320                 | Pass        |

### 802.11be (EHT40)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 3       | 5965            | 44.64                | 45.11   | 320                 | Pass        |
| 43      | 6165            | 44.00                | 44.55   | 320                 | Pass        |
| 91      | 6405            | 45.00                | 44.52   | 320                 | Pass        |
| 99      | 6445            | 44.79                | 44.63   | 320                 | Pass        |
| 107     | 6485            | 45.04                | 44.91   | 320                 | Pass        |
| 115     | 6525            | 44.90                | 44.79   | 320                 | Pass        |
| 123     | 6565            | 44.80                | 44.23   | 320                 | Pass        |
| 155     | 6725            | 44.73                | 44.44   | 320                 | Pass        |
| 179     | 6845            | 45.13                | 44.81   | 320                 | Pass        |
| 187     | 6885            | 44.78                | 45.00   | 320                 | Pass        |
| 211     | 7005            | 44.37                | 45.05   | 320                 | Pass        |
| 227     | 7085            | 45.23                | 44.82   | 320                 | Pass        |

### 802.11be (EHT80)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 7       | 5985            | 89.46                | 89.17   | 320                 | Pass        |
| 39      | 6145            | 89.91                | 89.65   | 320                 | Pass        |
| 87      | 6385            | 90.62                | 89.61   | 320                 | Pass        |
| 103     | 6465            | 88.99                | 88.35   | 320                 | Pass        |
| 119     | 6545            | 88.95                | 91.22   | 320                 | Pass        |
| 151     | 6705            | 89.70                | 89.51   | 320                 | Pass        |
| 183     | 6865            | 87.72                | 90.00   | 320                 | Pass        |
| 199     | 6945            | 90.66                | 88.64   | 320                 | Pass        |
| 215     | 7025            | 89.62                | 90.47   | 320                 | Pass        |

### 802.11be (EHT160)


| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 15      | 6025            | 174.35               | 173.12  | 320                 | Pass        |
| 47      | 6185            | 174.28               | 174.95  | 320                 | Pass        |
| 79      | 6345            | 176.67               | 174.61  | 320                 | Pass        |
| 111     | 6505            | 174.98               | 172.28  | 320                 | Pass        |
| 143     | 6665            | 172.65               | 173.10  | 320                 | Pass        |
| 175     | 6825            | 177.37               | 175.73  | 320                 | Pass        |
| 207     | 6985            | 175.89               | 177.93  | 320                 | Pass        |

### 802.11be (EHT320)


| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 31      | 6105            | 333.42               | 335.67  | 320                 | Note        |
| 63      | 6265            | 336.96               | 334.31  | 320                 | Note        |
| 95      | 6425            | 336.10               | 336.87  | 320                 | Note        |
| 127     | 6585            | 334.53               | 334.87  | 320                 | Note        |
| 159     | 6745            | 334.86               | 335.07  | 320                 | Note        |
| 191     | 6905            | 336.33               | 336.87  | 320                 | Note        |

Note: For channels with a nominal bandwidth of 320 MHz, compliance is demonstrated by way of the 99% BW.


## Spectrum Plot of Maximum Value




802.11a / Chain 0: CH 149




802.11be (EHT20) / Chain 1: CH 113




802.11be (EHT40) / Chain 0: CH 227



802.11be (EHT80) / Chain 1: CH 119



802.11be (EHT160) / Chain 1: CH 207



802.11be (EHT320) / Chain 0: CH 63

## Mode B

### 802.11a

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 1       | 5955            | 23.77                | 23.43   | 320                 | Pass        |
| 45      | 6175            | 23.84                | 23.92   | 320                 | Pass        |
| 93      | 6415            | 23.75                | 23.46   | 320                 | Pass        |
| 97      | 6435            | 23.92                | 23.92   | 320                 | Pass        |
| 105     | 6475            | 23.78                | 23.32   | 320                 | Pass        |
| 113     | 6515            | 23.78                | 23.57   | 320                 | Pass        |
| 117     | 6535            | 23.68                | 23.49   | 320                 | Pass        |
| 149     | 6695            | 23.98                | 23.61   | 320                 | Pass        |
| 181     | 6855            | 23.61                | 23.87   | 320                 | Pass        |
| 185     | 6875            | 23.76                | 23.87   | 320                 | Pass        |
| 209     | 6995            | 23.89                | 23.50   | 320                 | Pass        |
| 233     | 7115            | 23.91                | 23.85   | 320                 | Pass        |

### 802.11be (EHT20)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 1       | 5955            | 23.79                | 23.64   | 320                 | Pass        |
| 45      | 6175            | 23.43                | 23.80   | 320                 | Pass        |
| 93      | 6415            | 23.23                | 23.97   | 320                 | Pass        |
| 97      | 6435            | 23.97                | 23.84   | 320                 | Pass        |
| 105     | 6475            | 23.49                | 24.04   | 320                 | Pass        |
| 113     | 6515            | 23.39                | 24.14   | 320                 | Pass        |
| 117     | 6535            | 23.66                | 23.71   | 320                 | Pass        |
| 149     | 6695            | 23.35                | 23.55   | 320                 | Pass        |
| 181     | 6855            | 23.71                | 23.63   | 320                 | Pass        |
| 185     | 6875            | 23.41                | 23.67   | 320                 | Pass        |
| 209     | 6995            | 23.62                | 23.96   | 320                 | Pass        |
| 233     | 7115            | 23.31                | 23.93   | 320                 | Pass        |

### 802.11be (EHT40)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 3       | 5965            | 44.64                | 45.11   | 320                 | Pass        |
| 43      | 6165            | 44.00                | 44.55   | 320                 | Pass        |
| 91      | 6405            | 45.00                | 44.52   | 320                 | Pass        |
| 99      | 6445            | 44.79                | 44.63   | 320                 | Pass        |
| 107     | 6485            | 45.04                | 44.91   | 320                 | Pass        |
| 115     | 6525            | 44.90                | 44.79   | 320                 | Pass        |
| 123     | 6565            | 44.80                | 44.23   | 320                 | Pass        |
| 155     | 6725            | 44.73                | 44.44   | 320                 | Pass        |
| 179     | 6845            | 45.13                | 44.81   | 320                 | Pass        |
| 187     | 6885            | 44.78                | 45.00   | 320                 | Pass        |
| 211     | 7005            | 44.37                | 45.05   | 320                 | Pass        |
| 227     | 7085            | 45.23                | 44.82   | 320                 | Pass        |

### 802.11be (EHT80)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 7       | 5985            | 88.44                | 87.78   | 320                 | Pass        |
| 39      | 6145            | 89.43                | 88.09   | 320                 | Pass        |
| 87      | 6385            | 91.00                | 88.13   | 320                 | Pass        |
| 103     | 6465            | 88.04                | 89.49   | 320                 | Pass        |
| 119     | 6545            | 87.56                | 89.58   | 320                 | Pass        |
| 151     | 6705            | 88.53                | 88.43   | 320                 | Pass        |
| 183     | 6865            | 88.29                | 87.72   | 320                 | Pass        |
| 199     | 6945            | 90.69                | 88.77   | 320                 | Pass        |
| 215     | 7025            | 88.50                | 88.80   | 320                 | Pass        |

### 802.11be (EHT160)







| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 15      | 6025            | 174.98               | 174.55  | 320                 | Pass        |
| 47      | 6185            | 175.16               | 175.98  | 320                 | Pass        |
| 79      | 6345            | 178.27               | 175.40  | 320                 | Pass        |
| 111     | 6505            | 172.09               | 173.30  | 320                 | Pass        |
| 143     | 6665            | 176.90               | 170.87  | 320                 | Pass        |
| 175     | 6825            | 176.21               | 171.69  | 320                 | Pass        |
| 207     | 6985            | 173.86               | 173.10  | 320                 | Pass        |

### 802.11be (EHT320)

| Channel | Frequency (MHz) | 26dB Bandwidth (MHz) |         | Maximum Limit (MHz) | Test Result |
|---------|-----------------|----------------------|---------|---------------------|-------------|
|         |                 | Chain 0              | Chain 1 |                     |             |
| 31      | 6105            | 332.57               | 336.39  | 320                 | Note        |
| 63      | 6265            | 336.09               | 336.01  | 320                 | Note        |
| 95      | 6425            | 334.29               | 334.03  | 320                 | Note        |
| 127     | 6585            | 333.96               | 334.38  | 320                 | Note        |
| 159     | 6745            | 337.84               | 334.00  | 320                 | Note        |
| 191     | 6905            | 335.44               | 335.02  | 320                 | Note        |

Note: For channels with a nominal bandwidth of 320 MHz, compliance is demonstrated by way of the 99% BW.

## Spectrum Plot of Maximum Value




## 7.4 In-Band Emission Mask


|                           |              |            |            |
|---------------------------|--------------|------------|------------|
| Environmental Conditions: | 25°C, 60% RH | Tested By: | Match Tsui |
|---------------------------|--------------|------------|------------|

### Mode A


#### 802.11a




## Spectrum Plot




802.11a / Chain 0: CH 117




802.11a / Chain 0: CH 149




802.11a / Chain 0: CH 181



802.11a / Chain 0: CH 185




802.11a / Chain 0: CH 209




802.11a / Chain 0: CH 233


## Spectrum Plot




802.11a / Chain 1: CH 1




802.11a / Chain 1: CH 45




802.11a / Chain 1: CH 93



802.11a / Chain 1: CH 97




802.11a / Chain 1: CH 105




802.11a / Chain 1: CH 113


## Spectrum Plot




802.11a / Chain 1: CH 117




802.11a / Chain 1: CH 149




802.11a / Chain 1: CH 181



802.11a / Chain 1: CH 185




802.11a / Chain 1: CH 209




802.11a / Chain 1: CH 233


## 802.11be (EHT20)




## Spectrum Plot




802.11be (EHT20) / Chain 0: CH 117




802.11be (EHT20) / Chain 0: CH 149




802.11be (EHT20) / Chain 0: CH 181



802.11be (EHT20) / Chain 0: CH 185




802.11be (EHT20) / Chain 0: CH 209




802.11be (EHT20) / Chain 0: CH 233


## Spectrum Plot




802.11be (EHT20) / Chain 1: CH 1




802.11be (EHT20) / Chain 1: CH 45




802.11be (EHT20) / Chain 1: CH 93



802.11be (EHT20) / Chain 1: CH 97




802.11be (EHT20) / Chain 1: CH 105




802.11be (EHT20) / Chain 1: CH 113


## Spectrum Plot




802.11be (EHT20) / Chain 1: CH 117




802.11be (EHT20) / Chain 1: CH 149




802.11be (EHT20) / Chain 1: CH 181



802.11be (EHT20) / Chain 1: CH 185




802.11be (EHT20) / Chain 1: CH 209




802.11be (EHT20) / Chain 1: CH 233


## 802.11be (EHT40)




## Spectrum Plot




802.11be (EHT40) / Chain 0: CH 123




802.11be (EHT40) / Chain 0: CH 155




802.11be (EHT40) / Chain 0: CH 179



802.11be (EHT40) / Chain 0: CH 187




802.11be (EHT40) / Chain 0: CH 211




802.11be (EHT40) / Chain 0: CH 227


## Spectrum Plot




802.11be (EHT40) / Chain 1: CH 3




802.11be (EHT40) / Chain 1: CH 43




802.11be (EHT40) / Chain 1: CH 91



802.11be (EHT40) / Chain 1: CH 99




802.11be (EHT40) / Chain 1: CH 107




802.11be (EHT40) / Chain 1: CH 115


## Spectrum Plot




802.11be (EHT40) / Chain 1: CH 123




802.11be (EHT40) / Chain 1: CH 155




802.11be (EHT40) / Chain 1: CH 179



802.11be (EHT40) / Chain 1: CH 187



802.11be (EHT40) / Chain 1: CH 211




802.11be (EHT40) / Chain 1: CH 227


## 802.11be (EHT80)




## Spectrum Plot




802.11be (EHT80) / Chain 0: CH 183




802.11be (EHT80) / Chain 0: CH 199




802.11be (EHT80) / Chain 0: CH 215



802.11be (EHT80) / Chain 1: CH 7




802.11be (EHT80) / Chain 1: CH 39




802.11be (EHT80) / Chain 1: CH 87


## Spectrum Plot




802.11be (EHT80) / Chain 1: CH 103




802.11be (EHT80) / Chain 1: CH 119




802.11be (EHT80) / Chain 1: CH 151



802.11be (EHT80) / Chain 1: CH 183



802.11be (EHT80) / Chain 1: CH 199




802.11be (EHT80) / Chain 1: CH 215


## 802.11be (EHT160)




## Spectrum Plot




802.11be (EHT160) / Chain 0: CH 207




802.11be (EHT160) / Chain 1: CH 15




802.11be (EHT160) / Chain 1: CH 47



802.11be (EHT160) / Chain 1: CH 79




802.11be (EHT160) / Chain 1: CH 111




802.11be (EHT160) / Chain 1: CH 143

# Spectrum Plot



802.11be (EHT160) / Chain 1: CH 175




802.11be (EHT160) / Chain 1: CH 207


## 802.11be (EHT320)




## Spectrum Plot




802.11be (EHT320) / Chain 1: CH 31




802.11be (EHT320) / Chain 1: CH 63




802.11be (EHT320) / Chain 1: CH 95



802.11be (EHT320) / Chain 1: CH 127



802.11be (EHT320) / Chain 1: CH 159




802.11be (EHT320) / Chain 1: CH 191


## Mode B

### 802.11a


#### Spectrum Plot




## Spectrum Plot




802.11a / Chain 0: CH 117




802.11a / Chain 0: CH 149




802.11a / Chain 0: CH 181



802.11a / Chain 0: CH 185




802.11a / Chain 0: CH 209




802.11a / Chain 0: CH 233


## Spectrum Plot




802.11a / Chain 1: CH 1




802.11a / Chain 1: CH 45




802.11a / Chain 1: CH 93



802.11a / Chain 1: CH 97




802.11a / Chain 1: CH 105




802.11a / Chain 1: CH 113


## Spectrum Plot




802.11a / Chain 1: CH 117




802.11a / Chain 1: CH 149




802.11a / Chain 1: CH 181



802.11a / Chain 1: CH 185




802.11a / Chain 1: CH 209




802.11a / Chain 1: CH 233


## 802.11be (EHT20)




## Spectrum Plot




802.11be (EHT20) / Chain 0: CH 117




802.11be (EHT20) / Chain 0: CH 149




802.11be (EHT20) / Chain 0: CH 181



802.11be (EHT20) / Chain 0: CH 185




802.11be (EHT20) / Chain 0: CH 209




802.11be (EHT20) / Chain 0: CH 233


## Spectrum Plot




802.11be (EHT20) / Chain 1: CH 1




802.11be (EHT20) / Chain 1: CH 45




802.11be (EHT20) / Chain 1: CH 93



802.11be (EHT20) / Chain 1: CH 97




802.11be (EHT20) / Chain 1: CH 105




802.11be (EHT20) / Chain 1: CH 113


## Spectrum Plot




802.11be (EHT20) / Chain 1: CH 117




802.11be (EHT20) / Chain 1: CH 149




802.11be (EHT20) / Chain 1: CH 181



802.11be (EHT20) / Chain 1: CH 185




802.11be (EHT20) / Chain 1: CH 209




802.11be (EHT20) / Chain 1: CH 233


## 802.11be (EHT40)




## Spectrum Plot




802.11be (EHT40) / Chain 0: CH 123




802.11be (EHT40) / Chain 0: CH 155




802.11be (EHT40) / Chain 0: CH 179



802.11be (EHT40) / Chain 0: CH 187




802.11be (EHT40) / Chain 0: CH 211




802.11be (EHT40) / Chain 0: CH 227


## Spectrum Plot




802.11be (EHT40) / Chain 1: CH 3




802.11be (EHT40) / Chain 1: CH 43




802.11be (EHT40) / Chain 1: CH 91



802.11be (EHT40) / Chain 1: CH 99




802.11be (EHT40) / Chain 1: CH 107




802.11be (EHT40) / Chain 1: CH 115


## Spectrum Plot




802.11be (EHT40) / Chain 1: CH 123




802.11be (EHT40) / Chain 1: CH 155




802.11be (EHT40) / Chain 1: CH 179



802.11be (EHT40) / Chain 1: CH 187



802.11be (EHT40) / Chain 1: CH 211




802.11be (EHT40) / Chain 1: CH 227


## 802.11be (EHT80)




## Spectrum Plot




802.11be (EHT80) / Chain 0: CH 183




802.11be (EHT80) / Chain 0: CH 199




802.11be (EHT80) / Chain 0: CH 215



802.11be (EHT80) / Chain 1: CH 7




802.11be (EHT80) / Chain 1: CH 39




802.11be (EHT80) / Chain 1: CH 87


## Spectrum Plot




802.11be (EHT80) / Chain 1: CH 103




802.11be (EHT80) / Chain 1: CH 119




802.11be (EHT80) / Chain 1: CH 151



802.11be (EHT80) / Chain 1: CH 183




802.11be (EHT80) / Chain 1: CH 199




802.11be (EHT80) / Chain 1: CH 215


## 802.11be (EHT160)




## Spectrum Plot




802.11be (EHT160) / Chain 0: CH 207




802.11be (EHT160) / Chain 1: CH 15




802.11be (EHT160) / Chain 1: CH 47



802.11be (EHT160) / Chain 1: CH 79




802.11be (EHT160) / Chain 1: CH 111




802.11be (EHT160) / Chain 1: CH 143

# Spectrum Plot




802.11be (EHT160) / Chain 1: CH 175




802.11be (EHT160) / Chain 1: CH 207

## 802.11be (EHT320)


### Spectrum Plot




802.11be (EHT320) / Chain 0: CH 31




802.11be (EHT320) / Chain 0: CH 63




802.11be (EHT320) / Chain 0: CH 95



802.11be (EHT320) / Chain 0: CH 127




802.11be (EHT320) / Chain 0: CH 159




802.11be (EHT320) / Chain 0: CH 191


## Spectrum Plot




802.11be (EHT320) / Chain 1: CH 31




802.11be (EHT320) / Chain 1: CH 63




802.11be (EHT320) / Chain 1: CH 95



802.11be (EHT320) / Chain 1: CH 127



802.11be (EHT320) / Chain 1: CH 159



802.11be (EHT320) / Chain 1: CH 191

## 7.5 Occupied Bandwidth

|                           |              |            |            |
|---------------------------|--------------|------------|------------|
| Environmental Conditions: | 25°C, 60% RH | Tested By: | Match Tsui |
|---------------------------|--------------|------------|------------|

### Mode A

#### 802.11a

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 1       | 5955            | 17.28                    | 17.04   |
| 45      | 6175            | 17.40                    | 17.28   |
| 93      | 6415            | 17.28                    | 17.16   |
| 97      | 6435            | 17.28                    | 17.28   |
| 105     | 6475            | 17.16                    | 17.04   |
| 113     | 6515            | 17.28                    | 17.40   |
| 117     | 6535            | 17.40                    | 17.04   |
| 149     | 6695            | 17.40                    | 17.16   |
| 181     | 6855            | 17.28                    | 17.16   |
| 185     | 6875            | 17.28                    | 17.16   |
| 209     | 6995            | 17.28                    | 17.04   |
| 233     | 7115            | 17.04                    | 17.16   |

#### 802.11be (EHT20)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 1       | 5955            | 19.20                    | 19.20   |
| 45      | 6175            | 19.20                    | 19.20   |
| 93      | 6415            | 19.20                    | 19.20   |
| 97      | 6435            | 19.20                    | 19.08   |
| 105     | 6475            | 19.20                    | 19.20   |
| 113     | 6515            | 19.08                    | 19.20   |
| 117     | 6535            | 19.20                    | 19.08   |
| 149     | 6695            | 19.20                    | 19.08   |
| 181     | 6855            | 19.20                    | 19.20   |
| 185     | 6875            | 19.20                    | 19.08   |
| 209     | 6995            | 19.20                    | 19.20   |
| 233     | 7115            | 19.20                    | 19.20   |

### 802.11be (EHT40)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 3       | 5965            | 38.16                    | 38.64   |
| 43      | 6165            | 38.64                    | 38.40   |
| 91      | 6405            | 38.64                    | 38.64   |
| 99      | 6445            | 38.40                    | 38.64   |
| 107     | 6485            | 38.40                    | 38.64   |
| 115     | 6525            | 38.40                    | 38.40   |
| 123     | 6565            | 38.64                    | 38.64   |
| 155     | 6725            | 38.64                    | 38.64   |
| 179     | 6845            | 38.64                    | 38.64   |
| 187     | 6885            | 38.40                    | 38.16   |
| 211     | 7005            | 38.40                    | 38.16   |
| 227     | 7085            | 38.40                    | 38.40   |

### 802.11be (EHT80)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 7       | 5985            | 78.24                    | 78.24   |
| 39      | 6145            | 77.28                    | 77.76   |
| 87      | 6385            | 77.76                    | 77.76   |
| 103     | 6465            | 77.76                    | 77.76   |
| 119     | 6545            | 77.76                    | 77.76   |
| 151     | 6705            | 77.76                    | 77.28   |
| 183     | 6865            | 78.24                    | 77.76   |
| 199     | 6945            | 77.76                    | 77.76   |
| 215     | 7025            | 77.76                    | 77.76   |


### 802.11be (EHT160)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 15      | 6025            | 159.36                   | 156.48  |
| 47      | 6185            | 157.44                   | 157.44  |
| 79      | 6345            | 157.44                   | 158.40  |
| 111     | 6505            | 157.44                   | 156.48  |
| 143     | 6665            | 157.44                   | 157.44  |
| 175     | 6825            | 157.44                   | 157.44  |
| 207     | 6985            | 158.40                   | 157.44  |

### 802.11be (EHT320)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 31      | 6105            | 316.80                   | 314.88  |
| 63      | 6265            | 316.80                   | 316.80  |
| 95      | 6425            | 316.80                   | 318.72  |
| 127     | 6585            | 314.88                   | 314.88  |
| 159     | 6745            | 316.80                   | 316.80  |
| 191     | 6905            | 318.72                   | 314.88  |

## Spectrum Plot of Maximum Value



## Mode B

### 802.11a

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 1       | 5955            | 17.28                    | 17.04   |
| 45      | 6175            | 17.40                    | 17.28   |
| 93      | 6415            | 17.28                    | 17.16   |
| 97      | 6435            | 17.28                    | 17.28   |
| 105     | 6475            | 17.16                    | 17.04   |
| 113     | 6515            | 17.28                    | 17.40   |
| 117     | 6535            | 17.40                    | 17.04   |
| 149     | 6695            | 17.40                    | 17.16   |
| 181     | 6855            | 17.28                    | 17.16   |
| 185     | 6875            | 17.28                    | 17.16   |
| 209     | 6995            | 17.28                    | 17.04   |
| 233     | 7115            | 17.04                    | 17.16   |

### 802.11be (EHT20)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 1       | 5955            | 19.20                    | 19.20   |
| 45      | 6175            | 19.20                    | 19.20   |
| 93      | 6415            | 19.20                    | 19.20   |
| 97      | 6435            | 19.20                    | 19.08   |
| 105     | 6475            | 19.20                    | 19.20   |
| 113     | 6515            | 19.08                    | 19.20   |
| 117     | 6535            | 19.20                    | 19.08   |
| 149     | 6695            | 19.20                    | 19.08   |
| 181     | 6855            | 19.20                    | 19.20   |
| 185     | 6875            | 19.20                    | 19.08   |
| 209     | 6995            | 19.20                    | 19.20   |
| 233     | 7115            | 19.20                    | 19.20   |

### 802.11be (EHT40)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 3       | 5965            | 38.16                    | 38.64   |
| 43      | 6165            | 38.64                    | 38.40   |
| 91      | 6405            | 38.64                    | 38.64   |
| 99      | 6445            | 38.40                    | 38.64   |
| 107     | 6485            | 38.40                    | 38.64   |
| 115     | 6525            | 38.40                    | 38.40   |
| 123     | 6565            | 38.64                    | 38.64   |
| 155     | 6725            | 38.64                    | 38.64   |
| 179     | 6845            | 38.64                    | 38.64   |
| 187     | 6885            | 38.40                    | 38.16   |
| 211     | 7005            | 38.40                    | 38.16   |
| 227     | 7085            | 38.40                    | 38.40   |

### 802.11be (EHT80)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 7       | 5985            | 77.28                    | 77.76   |
| 39      | 6145            | 77.76                    | 77.76   |
| 87      | 6385            | 77.76                    | 77.76   |
| 103     | 6465            | 77.76                    | 78.24   |
| 119     | 6545            | 77.76                    | 77.76   |
| 151     | 6705            | 77.76                    | 77.76   |
| 183     | 6865            | 77.28                    | 77.76   |
| 199     | 6945            | 77.76                    | 77.76   |
| 215     | 7025            | 78.24                    | 77.76   |







### 802.11be (EHT160)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 15      | 6025            | 157.44                   | 158.40  |
| 47      | 6185            | 157.44                   | 157.44  |
| 79      | 6345            | 158.40                   | 158.40  |
| 111     | 6505            | 157.44                   | 156.48  |
| 143     | 6665            | 159.36                   | 157.44  |
| 175     | 6825            | 156.48                   | 157.44  |
| 207     | 6985            | 157.44                   | 158.40  |

### 802.11be (EHT320)

| Channel | Frequency (MHz) | Occupied Bandwidth (MHz) |         |
|---------|-----------------|--------------------------|---------|
|         |                 | Chain 0                  | Chain 1 |
| 31      | 6105            | 318.72                   | 316.80  |
| 63      | 6265            | 314.88                   | 316.80  |
| 95      | 6425            | 316.80                   | 316.80  |
| 127     | 6585            | 316.80                   | 316.80  |
| 159     | 6745            | 314.88                   | 316.80  |
| 191     | 6905            | 314.88                   | 316.80  |

## Spectrum Plot of Maximum Value



## 7.6 Contention-based Protocol

|                           |              |            |               |
|---------------------------|--------------|------------|---------------|
| Environmental Conditions: | 25°C, 60% RH | Tested By: | Frankie Chang |
|---------------------------|--------------|------------|---------------|

| Companion Device Information |         |           |                           |
|------------------------------|---------|-----------|---------------------------|
| Product                      | Brand   | Model No. | Software/Firmware Version |
| Hotspot Router               | NETGEAR | M7        | V3.3(LE10_PostCS10)-perf  |

### For U-NII-5


| Contention Based Protocol Measurement |                         |                |                     |                        |             |                    |                         |                      |                 |               |
|---------------------------------------|-------------------------|----------------|---------------------|------------------------|-------------|--------------------|-------------------------|----------------------|-----------------|---------------|
| Operation Mode                        | Channel Bandwidth (MHz) | Channel Number | Channel Freq. (MHz) | Injected Signal (AWGN) |             | Antenna Gain (dBi) | Path Loss (dB) (Note 3) | Adjusted Power (dBm) | Detection Limit | EUT TX Status |
|                                       |                         |                |                     | Freq. (MHz)            | Power (dBm) |                    |                         |                      |                 |               |
| 802.11be                              | 20                      | 33             | 6115                | 6115                   | -69         | 1.19               | 0                       | -70.19               | -62             | OFF           |
|                                       |                         |                |                     |                        | -73         | 1.19               | 0                       | -74.19               | -62             | Minimal       |
|                                       |                         |                |                     |                        | -81         | 1.19               | 0                       | -82.19               | -62             | ON            |
|                                       | 320                     | 31             | 6105                | 5950                   | -73         | 1.19               | 0                       | -74.19               | -62             | OFF           |
|                                       |                         |                |                     |                        | -77         | 1.19               | 0                       | -78.19               | -62             | Minimal       |
|                                       |                         |                |                     |                        | -81         | 1.19               | 0                       | -82.19               | -62             | ON            |
|                                       |                         |                |                     | 6105                   | -66         | 1.19               | 0                       | -67.19               | -62             | OFF           |
|                                       |                         |                |                     |                        | -69         | 1.19               | 0                       | -70.19               | -62             | Minimal       |
|                                       |                         |                |                     |                        | -81         | 1.19               | 0                       | -82.19               | -62             | ON            |
|                                       |                         |                |                     | 6260                   | -64         | 1.19               | 0                       | -65.19               | -62             | OFF           |
|                                       |                         |                |                     |                        | -74         | 1.19               | 0                       | -75.19               | -62             | Minimal       |
|                                       |                         |                |                     |                        | -81         | 1.19               | 0                       | -82.19               | -62             | ON            |

#### Notes:

1. After investigation (consider antenna gain and path loss), the one representative port (Chain 1) was measured and presented in the report.
2. Adjusted Power (dBm) = Injected Signal (AWGN) Power (dBm) - Antenna Gain (dBi) + Path Loss (dB)
3. Antenna gain values include all the applicable path losses.
4. This device does not use the channel puncturing mechanism for incumbent avoidance, but instead employs the bandwidth reduction mechanism to perform its function.

| Contention Based Protocol Detection Probability |                         |                         |     |     |     |     |     |     |     |     |     |     |                       |                 |             |
|-------------------------------------------------|-------------------------|-------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----------------------|-----------------|-------------|
| Operation Mode                                  | Channel Bandwidth (MHz) | AWGN Signal Freq. (MHz) | #01 | #02 | #03 | #04 | #05 | #06 | #07 | #08 | #09 | #10 | Detection Probability | Detection Limit | Test Result |
|                                                 |                         |                         |     |     |     |     |     |     |     |     |     |     |                       |                 |             |
| 802.11be                                        | 20                      | 6115                    | v   | v   | v   | v   | x   | v   | v   | v   | v   | v   | 90%                   | 90%             | Pass        |
|                                                 | 320                     | 5950                    | v   | v   | v   | v   | v   | v   | x   | v   | v   | v   | 90%                   | 90%             | Pass        |
|                                                 |                         | 6105                    | v   | v   | v   | v   | x   | v   | v   | v   | v   | v   | 90%                   | 90%             | Pass        |
|                                                 |                         | 6260                    | v   | v   | v   | v   | v   | x   | v   | v   | v   | v   | 90%                   | 90%             | Pass        |

### Plots of EUT Tx waveform



### Plots of Injected signal (AWGN) level

