

Prediction of MPE limit at a given distance

Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = \frac{PG}{4\pi R^2}$$

where: S = power density

P = power input to the antenna

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna

RFID

Maximum peak output power at device output terminal:	-43.33 dBm
Cable and Jumper loss:	0.0 dB
Maximum peak output power at antenna input terminal:	-43.33 dBm
	4.64515E-05 mW
Single Antenna gain (typical):	0 dBi
Number of Antennae:	1
Total Antenna gain (typical):	0 dBi
	1 (numeric)
Prediction distance:	20 cm
Prediction frequency:	13.56 MHz
MPE limit for uncontrolled exposure at prediction frequency:	13.27433628 mW/cm ²
Power density at prediction frequency:	0.00000001 mW/cm²
	0.0000001 W/m ²
Tx On time:	100.000000 ms
Tx period time:	100.000000 ms
Average Factor:	100.000000 %
Average Power density at prediction frequency:	0.0000001 W/m ²
Percentage to limit:	6.96173E-08 %

Bluetooth

Maximum peak output power at device output terminal:	-0.06 dBm
Cable and Jumper loss:	0.0 dB
Maximum peak output power at antenna input terminal:	-0.06 dBm
	0.986279486 mW
Single Antenna gain (typical):	1.3 dBi
Number of Antennae:	1
Total Antenna gain (typical):	1.3 dBi
	1.348962883 (numeric)

Prediction distance: 20 cm
Prediction frequency: 2402 MHz
MPE limit for uncontrolled exposure at prediction frequency: 1 mW/cm²

Power density at prediction frequency: **0.000265** mW/cm²
0.002647 W/m²

Tx On time: **100.000000** ms

Tx period time: **100.000000** ms

Average Factor: **100.000000** %

Average Power density at prediction frequency: **0.002647** W/m²

Percentage to limit: 0.02646855 %

Total Percentage to limit: 0.026468619 %

(PSD1/Limit 1) + (PSD 2/limit 2): 0.000264686 <1