

TEST REPORT

No.: 6-0315-13-1-3a

According to:
FCC Regulations
 Part 22, Part 24

IC-Regulations
 RSS-132 Issue 3, RSS-133 Issue 6, RSS-Gen Issue 3

for

Peiker acoustic GmbH & Co. KG

GSM/W-CDMA/LTE Module V1140-101
 + Antenna US34105
 (GSM/E-GPRS Mode)

FCC-ID: QWY-V1140-101
 IC: 6588A-V1140101

Laboratory Accreditation and Listings			
 Deutsche Akkreditierungsstelle D-PL-12047-01-01	 Reg. No.: 736496 MRA US-EU 0003	 Industry Canada Reg. No.: 3462D-1 Reg. No.: 3462D-2 Reg. No.: 3462D-3	 Voluntary Controls for Electromagnetic Emissions Reg. No.: R-2666 C-2914, T-1967, G-301
 AUTHORIZED RF LABORATORY	 LAB CODE 20011130-00		
accredited according to DIN EN ISO/IEC 17025			
CETECOM GmbH Laboratory Radio Communications & Electromagnetic Compatibility Im Teelbruch 116 • 45219 Essen • Germany Registered in Essen, Germany, Reg. No.: HRB Essen 8984 Tel.: + 49 (0) 20 54 / 95 19-954 • Fax: + 49 (0) 20 54 / 95 19-964 E-mail: info@cetecom.com • Internet: www.cetecom.com			

Table of contents

1. SUMMARY OF TEST RESULTS.....	3
1.1. TX mode, tests overview according FCC Standards	3
1.2. Attestation:.....	4
2. ADMINISTRATIVE DATA	5
2.1. Identification of the testing laboratory	5
2.2. Test location	5
2.3. Organizational items	5
2.4. Applicant's details	5
2.5. Manufacturer's details	5
3. EQUIPMENT UNDER TEST (EUT)	6
3.1. TECHNICAL DATA OF MAIN EUT DECLARED BY APPLICANT	6
3.2. EUT: Type, S/N etc. and short descriptions used in this test report	7
3.3. Auxiliary Equipment (AE): Type, S/N etc. and short descriptions	7
3.4. EUT set-ups	7
3.5. EUT operating modes	8
3.6. Parameter Settings on mobile phone and base station CMU200	9
3.7. Configuration of cables used for testing	10
4. DESCRIPTION OF TEST SYSTEM SET-UP'S	11
4.1. Test system set-up for conducted measurements at antenna port	11
4.2. Test system set-up for radiated spurious emission measurements	12
5. MEASUREMENTS	13
5.1. RF-Parameter - RF Peak power output radiated	13
5.2. RF-Parameter - Radiated out of Band RF emissions and Band Edge	15
5.3. RF-Parameter - RF Peak power output conducted.....	18
5.4. RF-Parameter - Occupied bandwidth and emission bandwidth	20
5.5. RF-Parameter - Conducted out of Band RF emissions and Band Edge	21
5.6. RF-Parameter - Frequency stability on temperature and voltage variations	24
5.7. Measurement uncertainties	29
6. ABBREVIATIONS USED IN THIS REPORT	29
7. ACCREDITATION DETAILS OF CETECOM'S LABORATORIES AND TEST SITES	30
8. INSTRUMENTS AND ANCILLARY	31
8.1. Used equipment "CTC"	31

Table of annex

Total pages

Annex 1: External EUT photographs – separate document TR6-0315-13-1-3-A1	7
Annex 2: Internal EUT photographs – to be supplied by applicant	--
Annex 3: Test set-up photographs – separate document TR6-0315-13-1-3-A3	4
Annex 4: Measurement diagrams	56

The listed attachments are an integral part of this report.

1. Summary of test results

The test results apply exclusively to the test samples as presented in this Report. The CETECOM GmbH does not assume responsibility for any conclusions and generalizations taken in conjunction with other specimens or samples of the type of the item presented to tests.

The Equipment Under Test (in this report, hereinafter referred as EUT) supports radiofrequency technologies. **This test report shows results for GPRS and (E)GPRS technologies only.** Other implemented wireless technologies were not considered within this test report.

Following tests have been performed to show compliance with applicable FCC Part 2, Part 22, Subpart H and Part 24, Subpart E (Broadband PCS) of the FCC CFR 47 Rules, Edition 1. October 2012 and Canada RSS-132, RSS-133 and RSS-Gen standards.

1.1. TX mode, tests overview according FCC and Canadian RSS Standards

No. of Diagram group	Test Cases	Port	References & Limits			EUT set-up	EUT op-mode	Result
			FCC Standard	RSS Section	Test limit			
1	Emissions AC-Power lines conducted (0,15 to 30 MHz)	AC-Power lines	§15.207	RSS-Gen Chapter 7.2.4	§15.207 limits IC: Table 4, Chapter 7.2.4	--	--	Remark 1.)
2	General field strength emissions radiated - (9 kHz to 30 MHz)	Cabinet + inter-connecting cables (radiated)	§15.209(a)	RSS-Gen Chapter 4.11 Chapter 7.2.5, Table 5+6	2400/F(kHz) µV/m 24000/F(kHz) µV/m 30 µV/m	--	--	Remark 1.)
7	RF-Power (ERP/EIRP) radiated		§2.1046 §22.913(a)(2)	RSS-132: 5.4 SRSP-503: 5.1.3	< 7 Watt (ERP)	1	1+2+3+4	passed
8	Spurious emissions radiated (30 MHz to... *tenth-times of the fundamental frequency)		§24.232(c)	RSS-133:4.1/6.4 SRSP-510: 5.1.2	< 2 Watt (EIRP)	1+3	1+3	passed
9	Band-Edge compliance		§2.1053(a) §2.1057 §22.917(a)(b) §24.238(a)(b)	RSS-132: 5.5(i)(ii) RSS-133: 6.5.1(i)(ii)	43+10log(P) dBc	1	1+3	passed

30	RF Power	Antenna terminal	§2.1046	--	N/A	2	1+2+3+4	passed
34	26dB Emission bandwidth		§2.202 §2.1049	RSS-Gen:4.6.1	99% Power	2	1+2+3+4	passed
35	99% Occupied bandwidth		§22.917(a) §24.238(a)					
36	Spurious emissions		§2.1051 §2.1057	RSS-132: 5.5(i)(ii)	43+10log(P) dBc	2	1+2+3+4	passed
37	Band-Edge compliance		§22.917(a)(b) §24.238(a)(b)	RSS-133: 6.5.1(i)(ii)				
38	Frequency stability		§22.355, table C-1 §24.235 §2.1055(a)(2)	RSS-132: 5.3 RSS-133: 6.3	< ±2.5ppm	2	1+2+3+4	passed

Remarks: 1.) See separate test report TR6-0315-13-1-3d for measurements according Part 15, Subpart C.

1.2. Attestation:

I declare that all measurements were performed by me or under my supervision and that all measurements have been performed and are correct to my best knowledge and belief to Industry Canada standards. All requirements as shown in above table are met in accordance with enumerated standards.



 D. Franke
 Responsible for test section


 GmbH
 Im Teichbruch 116
 45219 Essen
 Tel: +49 (0) 20 547 95 19-0
 Fax: +49 (0) 20 547 95 19-99



 Dipl.-Ing N. Perez
 Responsible for test report

2. Administrative Data

2.1. Identification of the testing laboratory

Company name:	CETECOM GmbH
Address:	Im Teelbruch 116 45219 Essen - Kettwig Germany
Responsible for testing laboratory:	Dipl.-Ing. Niels Jeß
Deputy:	Dipl.-Ing. Rachid Acharkaoui

2.2. Test location

2.2.1. Test laboratory "CTC"

Company name:	see chapter 2.1. Identification of the testing laboratory
---------------	---

2.3. Organizational items

Project leader	Dipl.-Ing C. Lorenz
Responsible for test report:	Dipl.-Ing N. Perez
Receipt of EUT:	2013-06-10
Date(s) of test:	2013-06-10 to 2013-07-04
Date of report:	2013-07-24

Version of template:	12.11 Lorenz

2.4. Applicant's details

Applicant's name:	Peiker acoustic GmbH & Co. KG
Address:	Max-Planck-Straße 28-32 61381 Friedrichsdorf Germany
Contact person:	Mr. Philippe Seguret

2.5. Manufacturer's details

Manufacturer's name:	please see Applicant's details
Address:	please see Applicant's details

3. Equipment under test (EUT)

3.1. TECHNICAL DATA OF MAIN EUT DECLARED BY APPLICANT

Main function	GPRS/W-CDMA/LTE Module (NA-LTE-NAD)		
Type	V1140-101		
GSM Frequency range (US/Canada -bands)	GSM 850: 824 – 849 MHz (Uplink), 869-894 MHz (Downlink) GSM1900: 1850-1910 MHz (Uplink), 1930-1990 MHz (Downlink)		
Type of modulation	GSM,GPRS, GMSK EGPRS-Mode: 8-PSK		
Number of channels (USA/Canada -bands)	GSM/GPRS/E-GPRS 850: 4/12/E2 GSM/GPRS/E-GPRS 1900: 1/12/E2		
MS Class	GSM/E-GPRS 850 MHz Band: Channel 128/192/251 GSM/E-GPRS 1900 MHz Band: Channel 512/661/810		
Test Channel frequencies	GSM/E-GPRS 850 MHz Band: Channel 128/192/251 GSM/E-GPRS 1900 MHz Band: Channel 512/661/810		
Emission designator(s)	GSM850: 245KGXW EDGE850: 247KG7W GSM1900: 247KGXW EDGE1900: 247KG7W		
Antenna Type	☐ Integrated ☒ External, no RF- connector ☐ External, separate RF-connector		
Antenna Gain (declared by applicant)	☐ conducted: not declared by applicant ☐ radiated: not declared by the applicant		
Measured Output Power [dBm]: Conducted GPRS 850: Conducted EDGE 850: Conducted GPRS1900: Conducted EDGE1900:	32.7 dBm 27.6 dBm 29.0 dBm 25.7 dBm		
Measured Output Power [dBm]: Radiated GPRS 850 Radiated EDGE 850 Radiated GPRS 1900 Radiated EDGE 1900	29.0 dBm 27.2 dBm 29.2 dBm 29.3 dBm		
FCC-ID	QWY-V1140101		
IC	6588A-V1140101		
Installed options	☒ GSM 900 and GSM 1800 Bands (not usable in USA/Canada)		
Power supply	☒ possibility one: over AC/DC adapter: 12 V DC ☒ possibility two: DC powered only by laboratory power supply with 3.8 Volt		
Special EMI components	--		
EUT sample type	☐ Production	☒ Pre-Production	☐ Engineering
FCC label attached	☐ yes ☒ no		

3.2. EUT: Type, S/N etc. and short descriptions used in this test report

Short description*)	EUT	Type	S/N serial number	HW hardware status	SW software status
EUT A	GSM/W-CDMA/LTE Module	V1140-101	US#405V1140-101 HW1613	3.0	M9615A-CETWTAZM-5.0.17006
EUT B	Antenna	US34105	#34105 US	A02	--
EUT C	Antenna	US34105	#34105 US	A03	--

*) EUT short description is used to simplify the identification of the EUT in this test report.

3.3. Auxiliary Equipment (AE): Type, S/N etc. and short descriptions

AE short description *)	Auxiliary Equipment	Type	S/N serial number	HW hardware status	SW software status
AE 1	LTE-NAD Evaluation Board	Test board	--	--	--
AE 2	KL1/B	Microphone	--	--	--
AE 3	Speaker	Loudspeaker	--	--	--
AE 4	USB cable	--	--	--	--
AE 5	AC/DC Adapter	Fairway WN20U-12A	--	Output: 12 V DC 1.25A	--
AE 6	Notebook	Dell D2120	--	--	Windows 7

*) AE short description is used to simplify the identification of the auxiliary equipment in this test report.

3.4. EUT set-ups

EUT set-up no. *)	Combination of EUT and AE	Remarks
Set. 1	EUT A +EUT B + AE 1 +AE 2 +AE 3 +AE 4 +AE5 +AE 6	Setup for radiated tests
Set. 2	EUT A + AE 1 +AE 2 +AE 3 +AE 4 +AE5 +AE 6	Setup for conducted tests
Set. 3	EUT A +EUT C + AE 1 +AE 2 +AE 3 +AE 4 +AE5 +AE 6	Setup for radiated tests with modified NAD Antenna

*) EUT set-up no. is used to simplify the identification of the EUT set-up in this test report.

3.5. EUT operating modes

EUT operating mode no. *)	Description of operating modes	Additional information
op. 1	GPRS 850 Data Traffic channels = 128/192/251	A communication link is established between the mobile station and the test simulator. The transmitter is operated at its maximum rated output power: 33 dBm (power class 4; power control level 5). USF_Duty CYCLE set to 100%, coding scheme CS-1 for GMSK modulation, slot 3 active, uplink gamma: 3 (33 dBm). The input signal to the receiver is modulated with normal test modulation. The wanted RF input signal level to the receiver of the mobile station is set to a level to provide a stable communication link.
op. 2	E-GPRS 850 Data Traffic channels = 128/192/251	A communication link is established between the mobile station and the test simulator. The transmitter is operated at its maximum rated output power: 33 dBm (power class 4; power control level 5). USF_Duty CYCLE set to 100%, coding scheme MCS-5 for 8PSK modulation, slot 3 active, uplink gamma: 6 (27dBm). The input signal to the receiver is modulated with normal test modulation. The wanted RF input signal level to the receiver of the mobile station is set to a level to provide a stable communication link.
op. 3	GPRS 1900 Data Traffic channels = 512/661/810	A communication link is established between the mobile station and the test simulator. The transmitter is operated at its maximum rated output power: 30 dBm (power class 1; power control level 0). USF_Duty CYCLE set to 100%, coding scheme CS-1 for GMSK modulation, slot 3 active, uplink gamma: 3 (30 dBm). The input signal to the receiver is modulated with normal test modulation. The wanted RF input signal level to the receiver of the mobile station is set to a level to provide a stable communication link
op. 4	E-GPRS 1900 Data traffic channels = 512/661/810	A communication link is established between the mobile station and the test simulator. The transmitter is operated at its maximum rated output power: 30 dBm (power class 1; power control level 0). USF_Duty CYCLE set to 100%, coding scheme MCS-5 for 8-PSK modulation, slot 3 active, uplink gamma: 5 (26 dBm). The input signal to the receiver is modulated with normal test modulation. The wanted RF input signal level to the receiver of the mobile station is set to a level to provide a stable communication link.

*) EUT operating mode no. is used to simplify the test report.

3.6. Parameter Settings on mobile phone and base station CMU200

Following settings apply to the MS during the measurements in **GSM/(E)GPRS-Mode** only:

Parameter	Traffic Mode	Idle Mode
Traffic Channels mobile station (EUT)	GSM 850: TCH _{MS} = 128/ 192 /251 GSM 1900: TCH _{MS} = 512 / 661 / 810	--
maximum power level (PCL)	GSM 850: PCL = 5 (2 Watt) GSM 1900: PCL = 0 (1 Watt)	--
Modulation	GSM/GPRS: GMSK-Modulation Scheme EDGE: 8-PSK Modulation Scheme	--
DTX	off	--
Bitstream	PRBS 2E9-1 (pseudo-random-sequence) – CCITT 0.153	
Timeslot(s) in Uplink	3	
Hopping	off	
Timeslot (slot mode)	GPRS-Mode: single	
Maximum data transmission rate, single time slot	GSM: 9,6 kbit/s Slot GPRS: 17,6 kbit/s Slot EDGE: 59,2 kBit/s Slot	
Speech transcoding (Traffic Mode)	Full rate Version 1	
Speed rate	130 Kb/s	
Mode	BCCH and TCH	
BCCH – base station (CMU,CMD)	GSM 850: 182 GSM 1900: 651	
TCH – base station (CMD, CMU)	auto	
Power level TCH – base station (used timeslot level)	- 70 dBm	
Power level BCCH – base station (control channel level)	- 80 dBm	
External attenuation RF/AF-Input/Output	Accord. calibration prior to measurements	
Mobile Country Code	310	310
Domain	PS	
BS_AG_BLKES_RES	Not applicable	0
Paging reorganisation		Off (0)
Signalling channel		SDCCH
Location Update		Auto
Cell access		Disabled (barred)

Settings for CMU (general)

Repetition	Continuous	
Stop condition	None	
Display mode	Max./Min	
Statistic Count	1000 Bursts	
Decoder	Standard	

Additional settings on the base stations CMU200 for frequency stability measurements

3.7. Configuration of cables used for testing

Cable number	Item	Type	S/N serial number	HW hardware status	Cable length
Cable 1	Antenna lines	--	--	--	1.3 m
Cable 2	USB line	--	--	--	1.5 m
Cable 3	Audio line	--	--	--	1.5 m
Cable 4	Microphone line	--	--	--	0.1 m
Cable 5	Power line	DC power line	--	--	1.5m

4. Description of test system set-up's


4.1. Test system set-up for conducted measurements at antenna port

Specification: ANSI 63.10: 2009

General Description: The EUT's RF-signal is coupled out by a suitable antenna coupling connector directly or via test fixture (1). The signal is first attenuated (2) before it is 0° divided by a power divider (3). One of the signal path is connected to the radio communication tester (4), other branch is connected to the spectrum analyzer (5). The specific attenuation losses for all signal paths/branches are determined prior to the measurement within a set-up calibration. These are then taken into account by correcting the measurement readings on the spectrum-analyzer.

Further information if applicable: for measurements in the climatic chamber, the same equipment and cables are used. The EUT and test fixture are arranged in a climate chamber. The cables are routed through special openings. No additional connectors are needed.

Schematic:




4.2. Test system set-up for radiated spurious emission measurements

Specification: ANSI C63.4-2009 chapter 8, ANSI C63.10-2009 chapter 6.5&6.6

General Description: Evaluating the field emissions have to be done first by an exploratory emissions measurement and a final measurement for most critical frequencies. The tests are performed in a CISPR 16-4 compliant fully anechoic room (FAR) recognized by the regulatory commissions. The measurement distance was set to 3 meter for frequencies up to 20 GHz and 1 meter above 20 GHz. Logarithmic periodic antenna is used for frequency range 1 GHz to 20 GHz, above 20 GHz a horn antenna is used. The antennas are set to fixed antenna height of 1.55 m in respect thereof requirement fulfilled according site validation and FCC listed instead of the height of receiving antenna not applicable for fully anechoic room and the EUT aligned within 3 dB cone of radiation pattern.

Schematic:



Testing method:

Exploratory, preliminary measurements

The EUT and its associated accessories are placed on a non-conductive position manipulator (tipping device) of 1.55 m height which is placed on the turntable. By rotating the turntable (range 0° to 360°, step 45°) and the EUT itself either on 3-orthogonal axis (portable equipment) or 2-orthogonal axis (defined operational position of EUT) the emission spectrum and its characteristics was recorded with an EMI-receiver, broadband antenna and software.

The measurements are performed in horizontal and vertical polarization of the measurement antennas. The results are documented in a diagram. Critical frequencies (low margin to limit) are saved within a table for further investigations. If various operating modes are supported, further investigations are made to find the worst-case of them. Also the interconnection cables and equipment position were varied in order to maximize the emissions.

Final measurement on critical frequencies

Based on the exploratory measurements, the most critical frequencies are re-measured by maintaining the EUT's worst-case operation mode, cable position, etc.

First a frequency zoom around the critical frequency is done to locate the frequency more precisely. After this step, for all identified critical frequencies, the maximum peak was determined. Following parameters were varied: the turntable angle continuously in the range 0 to 360 degree, the EUT itself either over 3-orthogonal axis (not defined usage position) or 2-orthogonal axis (defined usage position). The measurement antenna height is fixed to 1.55 m.

On the determined worst-case position, a final measurement with necessary bandwidth and detector according standard has been carried out. The readings on the spectrum analyzer are corrected with conversion value between field strength and E(I)RP, so the readings shown are equivalent to ERP/EIRP values. Critical measurements near the limit are re-measured with a substitution method accord. ANSI/TIA/EIA 603 C/D

Formula:

$$E_C = E_R + AF + C_L + D_F - G_A \quad (1)$$

$$E_{C(E)RP} = E_C - 95.2 \text{ dB}$$

$$M = L_T - E_{C(E)RP}$$

E_C = Electrical field – corrected value

E_R = Receiver reading

M = Margin

L_T = Limit

AF = Antenna factor

C_L = Cable loss

D_F = Distance correction factor (if used)

G_A = Gain of pre-amplifier (if used)

$E_{C(E)RP}$ = Electrical field corrected for E(I)RP

All units are dB-units, positive margin means value is below limit.

5. Measurements

5.1. RF-Parameter - RF Peak power output radiated

5.1.1. Test location and equipment (for reference numbers please see chapter 'List of test equipment')

test location	☒ CETECOM Essen (Chapter, 2.2.1)	☐ Please see Chapter, 2.2.2	☐ Please see Chapter, 2.2.3
test site	☐ 441 EMI SAR ☐ 487 SAR NSA ☒ 443 FAR		
receiver	☐ 377 ESCS30 ☐ 001 ESS ☐ 489 ESU 40 ☐ 620 ESU 26		
spectr. analys.	☐ 584 FSU ☐ 120 FSEM ☒ 264 FSEK		
antenna	☐ 574 BTA-L ☐ 133 EMCO3115 ☐ 302 BBHA9170 ☒ 608 HL 562 ☒ 549 HL025		
signaling	☐ 392 MT8820A ☐ 436 CMU ☒ 546 CMU		
otherwise	☐ 400 FTC40x15E ☐ 401 FTC40x15E ☐ 110 USB LWL ☐ 482 Filter Matrix ☐ 378 RadiSense		
DC power	☐ 456 EA 3013A ☒ 463 HP3245A ☐ 459 EA 2032-50 ☐ 268 EA- 3050 ☐ 494 AG6632A ☐ 498 NGPE 40		
line voltage	☐ 230 V 50 Hz via public mains ☐ 060 120 V/ 60 Hz via PAS 5000		

5.1.2. Requirements and limits

FCC	§2.1046(a)
IC	RSS-132 : 4.4 + SRSP 503 :5.1.3 for GSM 850; RSS-133 4.1/6.4 + SRSP-510 :5.1.2 for GSM 1900
Limit	Maximum E(I)RP of the mobile phone should be determined.
	Limit GSM850: 7 Watt ERP (38.4 dBm)
	Limit GSM1900: 2 Watt EIRP (33.0 dBm)

5.1.3. Test condition and test set-up

link to test system (if used):		☒ air link	☐ cable connection	☐
EUT-grounding		☒ none	☐ with power supply	☐ additional connection
Equipment set up		☒ table top	☐ floor standing	
Climatic conditions		Temperature: (22±3°C)		Rel. humidity: (40±20)%
Test system set-up		Please see chapter "Test system set-up for radiated spurious emission measurements up to 20 GHz"		
Spectrum Analyzer Settings	Parameter: Scan Mode Span RBW VBW Sweep time Sweep mode Detector	Spectrum analyser mode 20 MHz 3 MHz 10 MHz Coupled repetitive Peak		
Measurement method		The measurements were performed by using the substitution method (ANSI/TIA/EIA 603) with a spectrum-analyzer. This method can be described like follows: 1. choosing of suitable spectrum-analyzer settings for performing the measurements. This settings of the spectrum analyzer must be maintained for both stages of the measurements: EUT emission measurements and also for measurements of the substituted level. 2. The maximum level of the peak power was recorded, while the emissions were maximized by rotating the EUT in three orthogonal axes, which was situated on a non-conductive turntable of 1.55 m height ($P_{MEAS,1}$). This was performed for both measuring antenna polarisations (vertical/horizontal), the maximum of both values is used for further measurements and final substitution ($P_{MEAS,1,MAX}$). 3. As the maximum emission is recorded, the EUT is replaced by a frequency dependant suitable antenna, which is connected to a RF-signal generator, which is transmitting on the determined worst-case frequency as determined in step 2. 4. The RF-signal level of the signal generator is adjusted as long the same worst-case level determined first step is measured at the spectrum analyzer ($P_{SMHU}=P_{MEAS,1,MAX}$). 5. Than the RF-signal cable is disconnected from the antenna and connected to a power-level meter. The level is determined ($P_{MEAS,2}$). 6. The final result is calculated by adding the ERP/EIRP gain of the antenna which substitutes the EUT. $P_{EUT,SUBST} = P_{MEAS,2} + G_{ANTENNA}$		
Mobile phone settings		A call was established with settings according chapter "Parameter settings on mobile phone and base station CMU200" UE Power should be set to maximum, continuous transmission. DTX or other power saving techniques have been disabled The measurements were made at the low, middle and high carrier frequencies of each of the supported operating band. Choosing three TX-carrier frequencies of the mobile phone, should be sufficient to demonstrate compliance.		

5.1.4. Measurement results

5.1.4.1. GSM 850 results

Operating Mode	Carrier Channel		Peak Output Power [dBm]			Antenna Polarisation for maximum Power	Result
	Range	No.	PK	AV			
GPRS 850	Low	128	29.0	1.)	ERP-Value	V/H	passed
	Middle	192	28.8				
	High	251	28.1				
E-GPRS 850	Low	128	26.8	1.)	ERP-Value	V/H	passed
	Middle	192	27.2				
	High	251	26.4				

Remark: 1.) see conducted measurements for PAR factor

5.1.4.2. GSM 1900 results

Operating Mode	Carrier Channel		Peak Output Power [dBm]			Antenna Polarisation for maximum Power	Result
	Range	No.	PK	AV			
GPRS 1900	Low	512	29.2	1.)	EIRP-Value	V/H	passed
	Middle	661	28.5				
	High	810	29.1				
E-GPRS 1900	Low	512	26.7	1.)	EIRP-Value	V/H	passed
	Middle	661	29.3				
	High	810	28.6				

Remark: 1.) see conducted measurements for PAR factor

5.2. RF-Parameter - Radiated out of Band RF emissions and Band Edge

5.2.1. Test location and equipments (for reference numbers please see chapter 'List of test equipment')

test location	☒ CETECOM Essen (Chapter. 2.2.1)	☐ Please see Chapter. 2.2.2	☐ Please see Chapter. 2.2.3
test site	☐ 441 EMI SAR	☐ 487 SAR NSA	☒ 443 FAR
receiver	☐ 377 ESCS30	☐ 001 ESS	☐ 489 ESU 40
spectr. analys.	☐ 584 FSU	☐ 120 FSEM	☒ 264 FSEK
antenna	☒ 608 HL 562	☒ 549 HL 025	☐ 302 BBHA9170
signaling	☐ 017 CMD 65	☐ 323 CMD 55	☐ 340 CMD 55
signaling	☐ 392 MT8820A	☒ 546 CMU	☐ 547 CMU
power supply	☒ 463 HP3245A	☐ 457 EA 3013A	☐ 459 EA 2032-50
otherwise	☐ 529 6dB divider	☐ 530 6dB Att.	☐ 110 USB LWL
line voltage	☐ 230 V 50 Hz via public mains	☒ 060 120 V/ 60 Hz	☐ 268 EA- 3050
			☐ 494 AG6632A
			☐ 431 Near field
			☐ 498 NGPE 40

5.2.2. Requirements and limits

FCC	§2.1053(a), §2.1057(a)(1), §22.917(a)(b), §24.238(a)(b)
IC	RSS-132, Issue 2: 4.5.1.1, RSS-133, Issue 5: 6.5.1(a)(b)
Limit	„the power of emissions shall be attenuated below the transmitter output power (p) by at least 43+10Log(P) dB“ -> Resulting limit: -13dBm

5.2.3. Test condition and test set-up

link to test system (if used):	☒ air link	☐ cable connection
EUT-grounding	☒ none	☐ with power supply
Equipment set up	☒ table top	☐ floor standing
Climatic conditions	Temperature: (22±3°C)	Rel. humidity: (40±20)%
Test system set-up	Please see chapter “Test system set-up for radiated spurious emission measurements up to 20 GHz”	
Measurement method	The spectrum was scanned from 9 kHz to the 10th harmonic of the highest frequency generated within the equipment. A PEAK detector was used except measurements near the block-edge where a AVERAGE detector applied. According chapter “Test system set-up for electric field measurement in the range 30-1000MHz and 1 to 40GHz” and additionally: the readings on the spectrum analyzer are corrected with annually performed chamber path calibration values so the readings shown are equivalent to ERP/EIRP values. Critical measurements near the limit are re-measured with a substitution method accord. ANSI/TIA/EIA 603.	
Mobile phone settings	A call was established with settings according chapter “Parameter settings on mobile phone and base station CMU200” The UE and used accessories (if any used) were set to work according their intended use/specification stated as by the applicant The measurements were made at the low, middle and high carrier frequencies of each of the supported operating band. Choosing three TX-carrier frequencies of the mobile phone, should be sufficient to demonstrate compliance.	

Spectrum-Analyzer settings for GSM/GPRS/E-GPRS 850 Mode

	Start freq. MHz	Stop freq. MHz	R-BW MHz	V-BW MHz	Sweep time sec.	Att. [dB]	Detector
Sweep 1 (subrange 1)	30	1000	1	1	10	10	MaxH-PK
Sweep 2 (subrange 2)	1000	2800	1	1	15	10	MaxH-PK
Sweep 3 (subrange 3)	2800	9000	1	1	60	10	MaxH-PK
Sweep 4a (Block-Edge)	823	824	0.003	0.01	30	10	MaxH-PK
Sweep 4b (Block-Edge)	849	850	0.003	0.01	30	10	MaxH-PK

Spectrum-analyzer settings for GSM/GPRS/E-GPRS 1900 Mode

	Start freq. MHz	Stop freq. MHz	R-BW MHz	V-BW MHz	Sweep time sec.	Att.	Detector
Sweep 1 (subrange 1)	30	1000	1	1	10	10	MaxH-PK
Sweep 2 (subrange 2)	1000	2800	1	1	15	10	MaxH-PK
Sweep 3 (subrange 3)	2800	20000	1	1	160	10	MaxH-PK
Sweep 4a (Block-Edge)	1849	1850	0.003	0.01	30	10	MaxH-PK
Sweep 4b (Block-Edge)	1910	1911	0.003	0.01	30	10	MaxH-AV

5.2.4. Measurement results

The results are presented below in summary form only. For more information please see each diagram enclosed in annex 4.

5.2.4.1. GPRS 850: Set-up 1

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
8.04_RSE_R_Ch128_GPRS	Low	128	30 MHz – 9 GHz	2	Carrier on diagram, not relevant for results	☒	☐	☐	passed
9.04_BE_R_Ch128_GPRS	Low		823 – 824 MHz		Band Edge Compliance	☒	☒	☐	passed
8.05_RSE_R_Ch192_GPRS	Middle	192	30 MHz – 9 GHz		Carrier on diagram, not relevant for results	☒	☐	☐	passed
8.06_RSE_R_Ch251_GPRS	High	251	30 MHz – 9 GHz		Carrier on diagram, not relevant for results	☒	☐	☐	passed
9.02_BE_R_Ch251_GPRS	High		849 – 850 MHz		Band-Edge compliance	☒	☒	☐	passed

Remark:--

5.2.4.2. GPRS 850: Set-up 3

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
-	Low	128	30 MHz – 9 GHz	2	Carrier on diagram, not relevant for results	☐	☐	☐	-
-	Low		823 – 824 MHz		Band Edge Compliance	☐	☐	☐	-
8.105_Ch192_GPRS_retest	Middle	192	30 MHz – 9 GHz		Carrier on diagram, not relevant for results	☒	☐	☐	passed
-	High	251	30 MHz – 9 GHz		Carrier on diagram, not relevant for results	☐	☐	☐	-
-	High		849 – 850 MHz		Band-Edge compliance	☐	☐	☐	-

Remark: Retest was performed only on middle channel

5.2.4.3. GPRS 1900: Set-up 1

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
8.13_RSE_R_Ch512_GPRS	Low	512	30 MHz – 20 GHz	5	Carrier on diagram, not relevant for results	☒	☐	☐	passed
9.09_BE_R_Ch512_GPRS	Low		1849 – 1850 MHz		Band Edge Compliance	☒	☒	☐	passed
8.14_RSE_R_Ch661_GPRS	Middle	661	30 MHz – 20 GHz		Carrier on diagram, not relevant for results	☒	☐	☐	passed
8.15p_RSE_R_Ch810_GPRS	High	810	30 MHz – 20 GHz		Carrier on diagram, not relevant for results	☒	☐	☐	passed
9.10_BE_R_Ch810_GPRS	High		1910 – 1911 MHz		Band-Edge compliance	☒	☒	☐	passed

Remark:--

5.2.4.4. GPRS 1900: Set-up 3

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
-	Low	512	30 MHz – 20 GHz	5	Carrier on diagram, not relevant for results	☐	☐	☐	-
-	Low		1849 – 1850 MHz		Band Edge Compliance	☐	☐	☐	-
8.114_RSE_R_Ch661_GPRS_retest	Middle	661	30 MHz – 20 GHz		Carrier on diagram, not relevant for results	☒	☐	☐	passed
-	High	810	30 MHz – 20 GHz		Carrier on diagram, not relevant for results	☐	☐	☐	-
-	High		1910 – 1911 MHz		Band-Edge compliance	☐	☐	☐	-

Remark: Retest was performed only on middle channel

5.3. RF-Parameter - RF Peak power output conducted

5.3.1. Test location and equipments

test location	☒ CETECOM Essen (Chapter. 2.2.1)	☐ Please see Chapter. 2.2.2	
test site	☒ 347 Radio.lab. 1	☐ Radio.lab. 2	
spectr. analys.	☐ 584 FSU	☐ 489 ESU 40	☐ 264 FSEK ☐ 620 ESU 26
signaling	☐ 392 MT8820A	☒ 436 CMU	☐ 547 CMU
otherwise	☐ 110 USB LWL		
DC power	☒ 456 EA 3013A	☐ 463 HP3245A	☐ 459 EA 2032-50 ☐ 268 EA- 3050 ☐ 494 AG6632A ☐ 498 NGPE 40
otherwise	☐ 331 HC 4055	☒ 248 6 dB Att.	☒ 529 Power div. ☐ - cable OTA20
line voltage	☐ 230 V 50 Hz via public mains	☐ 060 120 V/ 60 Hz via PAS 5000	

5.3.2. Requirements and limits

FCC	§2.1046(a)
IC	RSS-132 : 4.4 + SRSP 503 :5.1.3 for GSM 850; RSS-133 4.1/6.4 + SRSP-510 :5.1.2 for GSM 1900
Limit	Maximum conducted output power of the transmitter should be determined while measured on RF output terminal.
	Limit GSM850: 7 Watt (38.4 dBm)
	Limit GSM1900: 2 Watt (33.0 dBm)

5.3.3. Test condition and test set-up

Climatic conditions	Temperature: (22±3°C)	Rel. humidity: (40±20)%
Test system set-up	Please see chapter "Test system set-up for conducted measurements on antenna port"	
Measurement method	The measurements were performed with the integrated power measurement function of the „radio communication tester CMU200 from Rohde&Schwarz company. In this way spectrum-analyzers instrument limitations can be avoided or minimized. Instead, CMU manufacturers declared measurement error can be considered for this measurement. The attenuation (insertion loss) at the RF Inputs/Outputs of CMU were set according the path loss of the test set-up, determined in a step before starting the measurements. A suitable artificial antenna or RF-connector is provided by the applicant in order to perform the conducted measurements. Any data provided with the artificial antenna or connector, have been taken in account in order to correct the measurement data. (typical 0.3dB for attenuation of antenna connector) Peak and Average Values have been recorded for each channel and band.	
Mobile phone settings	A call was established with settings according chapter "Parameter settings on mobile phone and base station CMU200" UE Power should be set to maximum, continuous transmission. DTX or other power saving techniques have been disabled The measurements were made at the low, middle and high carrier frequencies of each of the supported operating band. Choosing three TX-carrier frequencies of the mobile phone, should be sufficient to demonstrate compliance.	

5.3.4. Measurement results

Op. Mode 1, Set-up 2

Op. Mode	Carrier Channel		Peak Output Power [dBm]	Average Output Power [dBm]	Limit [dBm]	Result
	Range	No.				
GPRS 850	Low	128	32.6	32.4	38.4	Passed
	Middle	192	32.6	32.4		
	High	251	32.9	32.7		

Remark: Maximum PAR value of 3 channels 0.2dB

Op. Mode 2, Set-up 2

Op. Mode	Carrier Channel		Peak Output Power [dBm]	Average Output Power [dBm]	Limit [dBm]	Result
	Range	No.				
E-GPRS 850	Low	128	30.3	27.6	38.4	Passed
	Middle	192	30.3	27.6		
	High	251	30.2	27.4		

Remark: Maximum PAR value of 3 channels 2.8dB

Op. Mode 3, Set-up 2

Op. Mode	Carrier Channel		Peak Output Power [dBm]	Average Output Power [dBm]	Limit [dBm]	Result
	Range	No.				
GPRS 1900	Low	512	29.1	28.9	33.0	Passed
	Middle	661	29.1	28.9		
	High	810	29.1	29.0		

Remark: Maximum PAR value of 3 channels 0.2dB

Op. Mode 4, Set-up 2

Op. Mode	Carrier Channel		Peak Output Power [dBm]	Average Output Power [dBm]	Limit [dBm]	Result
	Range	No.				
E-GPRS 1900	Low	512	28.3	25.6	33.0	Passed
	Middle	661	28.2	25.4		
	High	810	28.3	25.7		

Remark: Maximum PAR value of 3 channels 3.7dB

5.4. RF-Parameter - Occupied bandwidth and emission bandwidth

5.4.1. Test location and equipments

(for reference numbers please see chapter 'List of test equipment')					
test site	☒ 347 Radio.lab. 1	☐ Radio.lab. 2			
spectr. analys.	☐ 584 FSU	☒ 489 ESU40	☐ 264 FSEK	☐ 620 ESU26	
signaling	☐ 392 MT8820A	☐ 436 CMU	☒ 547 CMU		
DC Power	☐ 463 HP3245A	☐ 087 EA3013	☒ 354 NGPE 40	☐ 086 LNG50-10	
otherwise	☒ 529 6dB divider	☒ 530 10dB Att.	☐ 431 Near field		
line voltage	☐ 230 V 50 Hz via public mains		☐ 060 120 V/ 60 Hz via PAS 5000		

5.4.2. Requirements and Limits

FCC	§2.202(a), §2.1049, §22.917(b), §24.238(b)	„the occupied bandwidth is the frequency bandwidth, such that, below it lower and above it upper frequency limits, the mean powers radiated are each equal to 0.5 percent of the total mean power radiated”
IC	RSS-Gen, Issue 3: §4.6.1 & §4.6.3	
ANSI	C63.10-2009	

5.4.3. Test condition and test set-up

Climatic conditions		Temperature: (22±3°C)	Rel. humidity: (40±20)%
Test system set-up		Please see chapter “Test system set-up for conducted measurements at antenna port”	
Spectrum Analyzer Settings	Parameter	Occupied bandwidth:	Emission bandwidth
	Scan Mode	Spectrum analyser mode	Spectrum analyser mode
	Span	1 MHz	1 MHz
	RBW	3 kHz	3 kHz
	VBW	30 kHz	30 kHz
Measurement method	Sweep time	Coupled	Coupled
	Sweep mode	Repetitive, max-hold	single
	Detector	PK	RMS
Measurement method		The used spectrum analyzer FSE or ESU from Rohde & Schwarz contains an integrated function to calculate the occupied bandwidth automatically. From left and right display margin, the upper and lower frequency points where the accumulated power becomes 0.5% of the total power, are calculated. Subtracting the previous determined two frequency points, yields the occupied bandwidth.	Bandwidth defined between 2 markers with are 26dBc compared to highest In-Band Peak Emission.
Mobile phone settings		Provisions with the requirements is based on the fact, that GSM modulation scheme is GMSK Modulation for GSM equipment with a maximum data transmission rate of 17,6 kBit/s per Slot. Provisions with the requirements is based on the fact, that EDGE modulation scheme is 8-PSK Modulation for EDGE equipment with a maximum data transmission rate of 59,2 kBit/s per Slot. A call was established with settings according chapter “Parameter settings on mobile phone and base station CMU200”	

5.4.4. Measurement results

3.7.4. Measurement Results

Operating mode/band Set-up	Carrier Channel		Occupied 99% bandwidth [kHz]	26 dBc Emission bandwidth [kHz]
	Range	No.		
Set-up 2, Op-Mode 1				
GPRS 850	Low	128	241.99	320.51
	Middle	192	243.58	312.50
	High	251	245.19	315.71
Set-up 2, Op-Mode 2				
E-GPRS 850	Low	128	243.59	306.08
	Middle	192	246.79	310.89
	High	251	246.79	309.29
Set-up 2, Op-Mode 3				
GPRS 1900	Low	512	246.79	309.29
	Middle	661	243.58	320.51
	High	810	245.19	301.28
Set-up 2, Op-Mode 4				
E-GPRS 1900	Low	512	246.79	310.90
	Middle	661	241.98	312.50
	High	810	241.99	312.50

Remarks: see annex diagrams

5.5. RF-Parameter - Conducted out of Band RF emissions and Band Edge

5.5.1. Test location and equipments (for reference numbers please see chapter 'List of test equipment')

test location	☒ CETECOM Essen (Chapter. 2.2.1)	☐ Please see Chapter. 2.2.2	☐ Please see Chapter. 2.2.3
test site	☒ 347 Radio.lab. 1	☒ Radio.lab. 2	
spectr. analys.	☐ 584 FSU	☐ 120 FSEM	☐ 264 FSEK ☒ 489 ESU
signaling	☐ 017 CMD 65	☐ 323 CMD 55	☐ 340 CMD 55
signaling	☐ 392 MT8820A	☐ 436 CMU	☒ 547 CMU
power supply	☒ 463 HP3245A	☐ 457 EA 3013A	☐ 459 EA 2032-50 ☐ 268 EA- 3050 ☐ 494 AG6632A ☐ 498 NGPE 40
otherwise	☒ 529 6dB divider	☒ 530 10dB Att.	☐ 431 Near field
line voltage	☐ 230 V 50 Hz via public mains	☐ 060 120 V/ 60 Hz via PAS 5000	

5.5.2. Requirements and limits

FCC	§2.1051, §2.1057(a)(1), §22.917(a)(b), §24.238(a)(b)
IC	RSS-132, Issue 2: 4.5.1.1, RSS-133, Issue 5: 6.5.1(a)(b)
Limit	„the power of emissions shall be attenuated below the transmitter output power (p) by at least 43+10Log(P) dB“ -> Resulting limit: -13dBm

5.5.3. Test condition and test set-up

Climatic conditions	Temperature: (22±3°C)	Rel. humidity: (40±20)%
Test system set-up	Please see chapter “Test system set-up for conducted measurements on antenna port”	
Measurement method	The spectrum was scanned from 9 kHz to the 10th harmonic of the highest frequency generated within the equipment. A PEAK detector was used except measurements near the block-edge where a AVERAGE detector applied. A suitable artificial antenna or RF-connector is provided by the applicant in order to perform the conducted measurements. Any data provided with the artificial antenna or connector, have been taken in account in order to correct the measurement data. (typical 0.3dB for attenuation of antenna connector)	
Spectrum-Analyzer settings	See below tables	
Mobile phone settings	A call was established with settings according chapter “Parameter settings on mobile phone and base station CMU200” UE Power should be set to maximum, continuous transmission. DTX or other power saving techniques have been disabled The measurements were made at the low, middle and high carrier frequencies of each of the supported operating band. Choosing three TX-carrier frequencies of the mobile phone, should be sufficient to demonstrate compliance.	

Spectrum-Analyzer settings for GSM/GPRS/E-GPRS 850 Mode

	Start freq. MHz	Stop freq. MHz	R-BW MHz	V-BW MHz	Sweep time sec.	Att. [dB]	Detector
Sweep 1 (subrange 1)	0.009	1	0.001	0.01	10	25	MaxH-PK
Sweep 1 (subrange 2)	1	30	0.1	1	5	25	MaxH-PK
Sweep 2 (subrange 1)	30	820	1	10	10	35	MaxH-PK
Sweep 2 (subrange 2)	820	1000	1	10	2	45	MaxH-PK
Sweep 2 (subrange 3)	1000	9000	1	10	100	35	MaxH-PK
Sweep 3a (Block-Edge)	823	824	0.003	0.01	70	35	MaxH-PK
Sweep 3b (Block-Edge)	823	824	0.003	0.01	70	35	MaxH-AV
Sweep 4a (Block-Edge)	849	850	0.003	0.01	70	35	MaxH-PK
Sweep 4b (Block-Edge)	849	850	0.003	0.01	70	35	MaxH-AV

Spectrum-Analyzer Settings GSM/GPRS/E-GPRS 1900 Mode

	Start freq. MHz	Stop freq. MHz	R-BW MHz	V-BW MHz	Sweep time sec.	Att.	Detector
Sweep 1 (subrange 1)	0.009	1	0.001	0.01	10	25	MaxH-PK
Sweep 1 (subrange 2)	1	30	0.1	1	5	25	MaxH-PK
Sweep 2 (subrange 1)	30	1000	1	10	100	35	MaxH-PK
Sweep 2 (subrange 2)	1000	2500	1	10	15	35	MaxH-PK
Sweep 2 (subrange 3)	2500	19500	1	10	150	35	MaxH-PK
Sweep 3a (Block-Edge)	1849	1850	0.003	0.01	70	35	MaxH-PK
Sweep 3b (Block-Edge)	1849	1850	0.003	0.01	70	35	MaxH-AV
Sweep 4a (Block-Edge)	1910	1911	0.003	0.01	70	35	MaxH-PK
Sweep 4b (Block-Edge)	1910	1911	0.003	0.01	70	35	MaxH-AV

5.5.4. Measurement results

The results are presented below in summary form only. For more information please see each diagram enclosed in annex diagrams.

5.5.4.1. GPRS 850: Set-up 2

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
36.01_RSE_CH128_GPRS_Sweep1	Low	128	9 kHz – 30 MHz	1	--	☒	☐	☐	passed
36.02_RSE_CH128_GPRS_Sweep2	Low		30MHz – 9 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.01_BE_CH128_GPRS_AV	Low		823-824 MHz		Band Edge Compliance	☐	☒	☐	passed
36.03_RSE_CH192_GPRS_Sweep1	Middle	192	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.04_RSE_CH192_GPRS_Sweep2	Middle		30MHz – 9 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
36.05_RSE_CH251_GPRS_Sweep1	High	251	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.06_RSE_CH251_GPRS_Sweep2	High		30MHz – 9 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.02_BE_CH251_GPRS_AV	High		849 – 850 MHz		Band-Edge compliance	☐	☒	☐	passed

Remark:--

5.5.4.2. E-GPRS 850: Set-up 2

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
36.07_RSE_CH128_EGPRS_Sweep1	Low	128	9 kHz – 30 MHz	2	--	☒	☐	☐	passed
36.08_RSE_CH128_EGPRS_Sweep2	Low		30MHz – 9 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.03_BE_CH128_EGPRS_PK	Low		823 - 824 MHz		Band Edge Compliance	☒	☐	☐	passed
36.09_RSE_Ch192_EGPRS_Sweep1	Middle	192	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.10_RSE_Ch192_EGPRS_Sweep2	Middle		30MHz – 9 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed

36.11_RSE_Ch251_EGPRS_Sweep1	High	251	9 kHz – 30 MHz	2	--	☒	☐	☐	passed
36.12_RSE_Ch251_EGPRS_Sweep2	High		30MHz – 9 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.04_BE_CH251_EGPRS_PK	High		849 – 850 MHz		Band-Edge compliance	☒	☐	☐	passed

Remark:--

5.5.4.3. GPRS 1900: Set-up 2

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	AV	QP	
36.20_RSE_Ch512_GPRS_Sweep1	Low	512	9 kHz – 30 MHz	3	--	☒	☐	☐	passed
36.21_RSE_Ch512_GPRS_Sweep2	Low		30MHz – 20 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.10_BE_Ch512_GPRS_PK	Low		1849 – 1850 MHz		Band Edge Compliance	☒	☐	☐	passed
36.22_RSE_Ch661_GPRS_Sweep1	Middle	661	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.23_RSE_Ch661_GPRS_Sweep2	Middle		30MHz – 20 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
36.24_RSE_Ch810_GPRS_Sweep1	High	810	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.25_RSE_Ch810_GPRS_Sweep2	High		30MHz – 20 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.11_BE_Ch810_GPRS_PK	High		1910 – 1911 MHz		Band-Edge compliance	☒	☐	☐	passed

Remark: --

5.5.4.4. E-GPRS 1900: Set-up 2

Diagram no.	Carrier Channel		Frequency range	OP-mode no.	Remark	Used detector			Result
	Range	No.				PK	A	QP	
36.26_RSE_Ch512_EGPRS_Sweep1	Low	512	9 kHz – 30 MHz	4	--	☒	☐	☐	passed
36.27_RSE_Ch512_EGPRS_Sweep2	Low		30MHz – 20 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.12_BE_Ch512_EGPRS_PK	Low		1849 – 1850 MHz		Band Edge Compliance	☒	☐	☐	passed
36.28_RSE_Ch661_EGPRS_Sweep1	Middle	661	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.29_RSE_Ch661_EGPRS_Sweep2	Middle		30MHz – 20 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
36.30_RSE_Ch810_EGPRS_Sweep1	High	810	9 kHz – 30 MHz		--	☒	☐	☐	passed
36.31_RSE_Ch810_EGPRS_Sweep2	High		30MHz – 20 GHz		Carrier visible on diagram, not relevant for result	☒	☐	☐	passed
37.13_BE_Ch810_EGPRS_PK	High		1910 – 1911 MHz		Band-Edge compliance	☒	☐	☐	passed

Remark: --

5.6. RF-Parameter - Frequency stability on temperature and voltage variations

5.6.1. Test location and equipments (for reference numbers please see chapter 'List of test equipment')

test location	☒ CETECOM Essen (Chapter. 2.2.1)	☐ Please see Chapter. 2.2.2	☐ Please see Chapter. 2.2.3
test site	☒ 347 Radio.lab.1	☒ Radio.lab.2	☐
spectr. analys.	☐ 584 FSU	☐ 489 ESU 40	☐ 264 FSEK
signaling	☐ 392 MT8820A	☐ 436 CMU	☒ 547 CMU
DC power	☐ 456 EA 3013A	☐ 457 EA 3013A	☐ 459 EA 2032-50
otherwise	☒ 529 6dB divider	☒ 530 10dB Att.	☐ 268 EA- 3050
Climatic test chamber	☒ 331 HC 4055		☐ 494 AG6632A
line voltage	☐ 230 V 50 Hz via public mains	☒ 060 120 V/ 60 Hz via PAS 5000	☐ 498 NGPE 40

5.6.2. Requirements and limits

FCC	§2.1055(a)(1), §22.355, §24.235
IC	RSS-132: 4.3, RSS-133: 6.3
Limit	<i>"The frequency stability shall be sufficient to ensure that the fundamental emission stays within the authorized frequency block"</i>

5.6.3. Test condition and test set-up

Test system set-up	Please see chapter "Test system set-up for conducted measurements on antenna port" In order to maintain the voltage constant over the time period of the tests, a dummy battery was connected to a laboratory power supply. The power supply voltage was controlled on the input of the power supply terminals of the EUT.
Measurement method	The GSM RF Channel spacing is 200 kHz according GSM-Spec, with a guard band of 200 kHz of each band of the sub-bands. The purpose of the EUT is to function under all extreme conditions within authorized sub-bands in regard to temperature and voltage variations. The frequency deviation was recorded with base station's build in capability. (CMU) As the standard requires that the fundamental emissions stays within the authorized band, a limit of 0.1ppm is considered low enough to ensure this.
Mobile phone settings	A call was established with settings according chapter "Parameter settings on mobile phone and base station CMU200" The measurements were made at the low, middle and high carrier frequencies of each of the supported operating band. Choosing three TX-carrier frequencies of the mobile phone, should be sufficient to demonstrate compliance.

5.6.4. Measurement results

5.6.4.1. Frequency shift of carrier against a voltage range at constant nominal temperature of 20° Celsius

- 1.) determine the carrier frequency for the lowest and highest channel at room temperature and nominal voltage [20°C]
- 2.) The voltage was reduced in 0.1 Volt steps to the lower end point, where the mobile phone stops working. (this shall be specified by the manufacturer) Record the carrier frequency shift within 2 minutes after powering on the mobile phone, to prevent for self heating effects.
- 3.) The voltage was increased in 0.1 Volt steps to the upper declared voltage of the battery. Record the carrier frequency shift within 2 minutes after powering on the mobile phone, to prevent for self heating effects.

No tests performed across extreme voltage range: limited approval.


OEM integrators should consult grant and applicants recommendations on power supply design rules.

5.6.4.2. Frequency shift of carrier against temperature at constant power supply voltage

- 1.) determine the carrier frequency for the lowest, middle and highest channel at room temperature and nominal voltage [20°C]
- 2.) expose the mobile station to -30°C, wait sufficient time to have constant temperature.
- 3.) Perform the carrier frequencies measurements in 10°C increments from -30°C to +60°C. For about half hour at the specified temperature the mobile was powered-off. After powering-on, the measurements were made within 2 minute for the channel lower channel, in order to prevent self-warming of the mobile.


5.6.4.2.1. GPRS 850 Mode: Op. Mode 2, set-up 1

	Maximum frequency error						
	Channel 128	Channel 192	Channel 251	Channel 128	Channel 192	Channel 251	Verdict
Temperature	[Hz]			[ppm]			Limit=±0.1ppm
-30	13	13	8	0,016	0,016	0,009	Passed
-20	14	12	12	0,017	0,014	0,014	
-10	13	9	11	0,016	0,011	0,013	
0	5	5	4	0,006	0,006	0,005	
10	6	4	6	0,007	0,005	0,007	
20	5	5	6	0,006	0,006	0,007	
30	6	7	7	0,007	0,008	0,008	
40	7	5	6	0,008	0,006	0,007	
50	5	6	6	0,006	0,007	0,007	




5.6.4.2.2. EGPRS 850 Mode: Op. Mode 3, set-up 1

Temperature	Maximum frequency error						Verdict Limit=±0.1ppm
	Channel 128	Channel 192	Channel 251	Channel 128	Channel 192	Channel 251	
	[Hz]	[Hz]	[Hz]	[ppm]	[ppm]	[ppm]	
-30	-17	-14	-16	-0,021	-0,017	-0,019	Passed
-20	-9	-18	-20	-0,011	-0,022	-0,024	
-10	13	15	11	0,016	0,018	0,013	
0	-10	-8	-9	-0,012	-0,010	-0,011	
10	-9	-10	-11	-0,011	-0,012	-0,013	
20	-11	-12	-14	-0,013	-0,014	-0,016	
30	-11	-14	-15	-0,013	-0,017	-0,018	
40	-10	-14	-16	-0,012	-0,017	-0,019	
50	-11	-15	-16	-0,013	-0,018	-0,019	




5.6.4.2.3. GPRS 1900 Mode: Op. Mode 5, set-up 1

	Maximum frequency error						
	Channel 512	Channel 661	Channel 810	Channel 512	Channel 661	Channel 810	Verdict
Temperature	[Hz]			[ppm]			Limit=±0.1ppm
-30	25	17	21	0,014	0,009	0,011	Passed
-20	11	-17	-16	0,006	-0,009	-0,008	
-10	-22	-17	-20	-0,012	-0,009	-0,010	
0	-13	14	-14	-0,007	0,007	-0,007	
10	-13	-14	-15	-0,007	-0,007	-0,008	
20	15	-16	-14	0,008	-0,009	-0,007	
30	-18	-17	-18	-0,010	-0,009	-0,009	
40	-17	-13	-16	-0,009	-0,007	-0,008	
50	16	-14	-17	0,009	-0,007	-0,009	



5.6.4.2.4. EGPRS 1900 Mode: Op. Mode 6, set-up 1

	Maximum frequency error						
	Channel 512	Channel 661	Channel 810	Channel 512	Channel 661	Channel 810	Verdict
Temperature	[Hz]			[ppm]			Limit=±0.1ppm
-30	-17	-21	-23	-0,009	-0,011	-0,012	Passed
-20	-22	-26	-27	-0,012	-0,014	-0,014	
-10	-30	-32	-32	-0,016	-0,017	-0,017	
0	-13	-14	-14	-0,007	-0,007	-0,007	
10	17	-14	-16	0,009	-0,007	-0,008	
20	-16	-12	-15	-0,009	-0,006	-0,008	
30	-18	-8	-18	-0,010	-0,004	-0,009	
40	-17	-14	-19	-0,009	-0,007	-0,010	
50	18	-15	-17	0,010	-0,008	-0,009	



5.7. Measurement uncertainties

The reported uncertainties are calculated based on the standard uncertainty multiplied with the appropriate coverage factor **k**, such that a confidence level of approximately 95% is achieved.

For uncertainty determination, each component used in the concrete measurement set-up was taken in account and it's contribution to the overall uncertainty according it's statistical distribution calculated.

Following table shows expectable uncertainties for each measurement type performed.

RF-Measurement	Frequency range	Calculated uncertainty based on a confidence level of 95%	Remarks:
Power Output conducted	9 kHz .. 20 GHz	1.0 dB	--
Power Output radiated	30 MHz .. 4 GHz	3.17 dB	Substitution method
Conducted emissions on antenna ports	9 kHz .. 20 GHz	1.0 dB	--
Radiated emissions enclosure	150 kHz .. 30 MHz	5.0 dB	Magnetic field
	30 MHz .. 1 GHz	4.2 dB	E-Field
	1 GHz .. 20 GHz	3.17 dB	Substitution method
Occupied bandwidth	9 kHz .. 4 GHz	0.1272 ppm (Delta Marker)	Frequency error
		1.0 dB	Power
Emission bandwidth	9 kHz .. 4 GHz	0.1272 ppm (Delta Marker)	Frequency error
		1.0 dB	Power
Frequency stability	9 kHz .. 20 GHz	0.0636 ppm	--
Conducted emissions on AC-mains port (U _{CISPR})	9 kHz .. 150 kHz	4.0 dB	--
	150 kHz .. 30 MHz	3.6 dB	--

Table: measurement uncertainties, valid for conducted/radiated measurements

6. Abbreviations used in this report

The abbreviations	
ANSI	American National Standards Institute
AV , AVG, CAV	Average detector
EIRP	Equivalent isotropically radiated power, determined within a separate measurement
EGPRS	Enhanced General Packet Radio Service
EUT	Equipment Under Test
FCC	Federal Communications Commission, USA
IC	Industry Canada
n.a.	not applicable
Op-Mode	Operating mode of the equipment
PK	Peak
RBW	resolution bandwidth
RF	Radio frequency
RSS	Radio Standards Specification, Dokuments from Industry Canada
Rx	Receiver
TCH	Traffic channel
Tx	Transmitter
QP	Quasi peak detector
VBW	Video bandwidth
ERP	Effective radiated power

7. Accreditation details of CETECOM's laboratories and test sites

Ref.-No.	Accreditation Certificate	Valid for laboratory area or test site	Accreditation Body
-	D-PL-12047-01-01	All laboratories and test sites of CETECOM GmbH, Essen	DAkkS, Deutsche Akkreditierungsstelle GmbH
337 487 558 348 348	736496	Radiated Measurements 30 MHz to 1 GHz, 3 m / 10 m (OATS) Radiated Measurements 30 MHz to 1 GHz, 3 m (SAR) Radiated Measurements above 1 GHz, 3 m (FAR) Mains Ports Conducted Interference Measurements Telecommunication Ports Conducted Interference Measurem.	FCC, Federal Communications Commission Laboratory Division, USA (MRA US-EU 0003)
337 487 550 558	3462D-1 3462D-2 3462D-2 3462D-3	Radiated Measurements 30 MHz to 1 GHz, 3 m / 10 m (OATS) Radiated Measurements 30 MHz to 1 GHz, 3 m (SAR) Radiated Measurements 1 GHz to 6 GHz, 3 m (SAR) Radiated Measurements above 1 GHz, 3 m (FAR)	IC, Industry Canada Certification and Engineering Bureau
487 550 348 348	R-2666 G-301 C-2914 T-1967	Radiated Measurements 30 MHz to 1 GHz, 3 m (SAR) Radiated Measurements 1 GHz to 6 GHz, 3 m (SAR) Mains Ports Conducted Interference Measurements Telecommunication Ports Conducted Interference Measurem.	VCCI, Voluntary Control Council for Interference by Information Technology Equipment, Japan
OATS = Open Area Test Site, SAR = Semi Anechoic Room, FAR = Fully Anechoic Room			

8. Instruments and Ancillary

8.1. Used equipment “CTC”

The “Ref.-No” in the left column of the following tables allows the clear identification of the laboratory equipment.

8.1.1. Test software and firmware of equipment

Ref.-No.	Equipment	Type	Serial-No.	Version of Firmware or Software during the test
001	EMI Test Receiver	ESS	825132/017	Firm.= 1.21 , OTP=2.0, GRA=2.0
012	Signal Generator (EMS-cond.)	SMY 01	839069/027	Firm.= V 2.02
013	Power Meter (EMS cond.)	NRVD	839111/003	Firm.= V 1.51
017	Digital Radiocommunication Tester	CMD 60 M	844365/014	Firmware = V 3.52 .22.01.99, DECT = D2.87 13.01.99
053	Audio Analyzer	UPA3	860612/022	Firm. V 4.3
119	RT Harmonics Analyzer dig. Flickermeter	B10	G60547	Firm.= V 3.1DHG
140	Signal Generator	SMHU	831314/006	Firm.= 3.21
261	Thermal Power Sensor	NRV-Z55	825083/0008	EPROM-Datum 02.12.04, SE EE 1 B
262	Power Meter	NRV-S	825770/0010	Firm.= 2.6
263	Signal Generator	SMP 04	826190/0007	Firm.=3.21
264	Spectrum Analyzer	FSEK 30	826939/005	Bios=2.1, Analyzer= 3.20
295	Racal Digital Radio Test Set	6103	1572	UNIT Firmware= 4.04, SW-Main=4.04, SW-BBP=1.04, SW-DSP=1.02, Hardboot=1.02, Softboot=2.02
298	Univ. Radio Communication Tester	CMU 200	832221/091	R&S Test Firmware =3.53 /3.54 (current Testsoftw. f. all band used
323	Digital Radiocommunication Tester	CMD 55	825878/0034	Firm.= 3.52 .22.01.99
331	Climatic Test Chamber -40/+80 Grad	HC 4055	43146	TSI 1.53
335	CTC-EMS-Conducted	System EMS Conducted	-	EMC 32 V 8.52
340	Digital Radiocommunication Tester	CMD 55	849709/037	Firm.= 3.52 .22.01.99
355	Power Meter	URV 5	891310/027	Firm.= 1.31
365	10V Insertion Unit 50 Ohm	URV5-Z2	100880	Eprom Data = 31.03.08
366	Ultra Compact Simulator	UCS 500 M4	V0531100594	Firm. UCS 500=001925/3.06a02, rc=ISMIEC 4.10
371	Bluetooth Tester	CBT32	100153	CBT V5.30+ SW-Option K55, K57
377	EMI Test Receiver	ESCS 30	100160	Firm.= 2.30, OTP= 02.01, GRA= 02.36
378	Broadband RF Field Monitor	RadiSense III	03D00013SNO-08	Firm.= V.03D13
383	Signal Generator	SME 03	842 828 /034	Firm.= 4.61
389	Digital Multimeter	Keithley 2000	0583926	Firm. = A13 (Mainboard) A02 (Display)
392	Radio Communication Tester	MT8820A	6K00000788	Firm.= 4.50 #005, IPL=4.01#001,OS=4.02#001, GSM=4.41#013, W-CDMA= 4.54#004, scenario= 4.52#002
436	Univ. Radio Communication Tester	CMU 200	103083	R&S Test Firmware Base=5.14, Mess-Software= GSM:5.14 WCDMA:5.14 (current Testsoftw. F. all band
441	CTC-SAR-EMI Cable Loss	System EMI field (SAR)	-	EMC 32 Version 8.52
442	CTC-SAR-EMS	System EMS field (SAR)	-	EMC 32 Version 8.40
443	CTC-FAR-EMI-RSE	System CTC-FAR-EMI-RSE	-	Spuri 7.2.5 or EMC 32 Ver. 8.53
444	CTC-FAR-EMS field	System-EMS-Field (FAR)	-	EMC 32 Version 8.40
460	Univ. Radio Communication Tester	CMU 200	108901	R&S Test Firmware Base=5.14, GSM=5.14 WCDMA=5.14 (current Testsoftw.,f. all band to be used,
489	EMI Test Receiver	ESU40	1000-30	Firmware=4.43 SP3, Bios=V5.1-16-3, Spec. =01.00
491	ESD Simulator dito	ESD dito	dito307022	V 2.30
524	Voltage Drop Simulator	VDS 200	0196-16	Software Nr: 000037 Version V4.20a01
526	Burst Generator	EFT 200 A	0496-06	Software Nr. 000034 Version V2.32
527	Micro Pulse Generator	MPG 200 B	0496-05	Software-Nr. 000030 Version V2.43
528	Load Dump Simulator	LD 200B	0496-06	Software-Nr. 000031 Version V2.35a01
546	Univ. Radio Communication Tester	CMU 200	106436	R&S Test Firmware Base=5.14, GSM=5.14 WCDMA=5.14 (current Testsoftw.,f. all band to be used
547	Univ. Radio Communication Tester	CMU 200	835390/014	R&S Test Firmware Base=V5.1403 (current Testsoftw., f. all band used, GSM = 5.14 WCDMA: = 5.14
584	Spectrum Analyzer	FSU 8	100248	2.82_SP3
594	Wideband Radio Communication Tester	CMW 500	101757	Firmware Base=2.0.20.9, LTE=2.0.20.8, CDMA= 2.0.10
597	Univ. Radio Communication Tester	CMU 200	100347	R&S Test Firmware Base=5.01, GSM=5.02 WCDMA= not installed, Mainboard= µP1=V.850
598	Spectrum Analyzer	FSEM 30 (Reserve)	831259/013	Firmware Bios 3.40 , Analyzer 3.40 Sp 2
620	EMI Test Receiver	ESU 26	100362	4.43_SP3
642	Wideband Radio Communication Tester	CMW 500	126089	Setup V03.26, Test programm component V02.12.01

8.1.2. Single instruments and test systems

Ref.-No.	Equipment	Type	Serial-No.	Manufacturer	Interval of calibration	Remark	Cal due
001	EMI Test Receiver	ESS	825132/017	Rohde & Schwarz	12 M	-	31.03.2014
005	AC - LISN (50 Ohm/50µH, test site 1)	ESH2-Z5	861741/005	Rohde & Schwarz	24/12 M	-	31.03.2014
007	Single-Line V-Network (50 Ohm/5µH)	ESH3-Z6	892563/002	Rohde & Schwarz	24/12 M	-	31.03.2014
009	Power Meter (EMS-radiated)	NRV	863056/017	Rohde & Schwarz	24 M	-	31.03.2015
016	Line Impedance Simulating Network	Op. 24-D	B6366	Spitzenberger+Spies	36 M	-	31.03.2016
020	Horn Antenna 18 GHz (Subst 1)	3115	9107-3699	EMCO	36/12 M	-	31.03.2014
021	Loop Antenna (H-Field)	6502	9206-2770	EMCO	36 M	-	31.03.2015
030	Loop Antenna (H-field)	HFH-Z2	879604/026	Rohde & Schwarz	36 M	-	31.03.2015
033	RF-current probe (100kHz-30MHz)	ESH2-Z1	879581/18	Rohde & Schwarz	24 M	-	31.03.2015
057	relay-switch-unit (EMS system)	RSU	494440/002	Rohde & Schwarz	pre-m	1a	
060	power amplifier (DC-2kHz)	PAS 5000	B6363	Spitzenberger+Spies	-	3	
066	notch filter (WCDMA; FDD1)	WRCT 1900/2200-5/40-10EEK	5	Wainwright GmbH	12 M	1g	30.06.2014
086	DC - power supply, 0 -10 A	LNG 50-10	-	Heinzinger Electronic	pre-m	2	
087	DC - power supply, 0 -5 A	EA-3013 S	-	Elektro Automatik	pre-m	2	
090	Helmholtz coil: 2x10 coils in series	-	-	RWTÜV	-	4	
091	USB-LWL-Converter	OLS-1	007/2006	Ing. Büro Scheiba	-	4	
099	passive voltage probe	ESH2-Z3	299.7810.52	Rohde & Schwarz	36 M	-	31.03.2015
100	passive voltage probe	Probe TK 9416	without	Schwarzbeck	36 M	-	31.03.2015
110	USB-LWL-Converter	OLS-1	-	Ing. Büro Scheiba	-	4	
119	RT Harmonics Analyzer dig. Flickermeter	B10	G60547	BOCONSULT	36 M	-	31.03.2016
134	horn antenna 18 GHz (Subst 2)	3115	9005-3414	EMCO	pre-m	-	31.03.2014
136	adjustable dipole antenna (Dipole 1)	3121C-DB4	9105-0697	EMCO	36 M	-	31.03.2015
140	Signal Generator	SMHU	831314/006	Rohde & Schwarz	24 M	-	31.03.2014
248	attenuator	SMA 6dB 2W	-	Radiall	pre-m	2	
249	attenuator	SMA 10dB 10W	-	Radiall	pre-m	2	
252	attenuator	N 6dB 12W	-	Radiall	pre-m	2	
256	attenuator	SMA 3dB 2W	-	Radiall	pre-m	2	
257	hybrid	4031C	04491	Narda	pre-m	2	
260	hybrid coupler	4032C	11342	Narda	pre-m	2	
261	Thermal Power Sensor	NRV-Z55	825083/0008	Rohde & Schwarz	24 M	-	31.03.2014
262	Power Meter	NRV-S	825770/0010	Rohde & Schwarz	24 M	-	31.03.2014
263	Signal Generator	SMP 04	826190/0007	Rohde & Schwarz	36 M	-	31.03.2016
264	Spectrum Analyzer	FSEK 30	826939/005	Rohde & Schwarz	12 M	-	31.03.2014
265	peak power sensor	NRV-Z33, Model 04	840414/009	Rohde & Schwarz	24 M	-	31.03.2014
266	peak power sensor	NRV-Z31, Model 04	843383/016	Rohde & Schwarz	24 M	-	31.03.2014
267	notch filter GSM 850	WRCA 800/960-6EEK	9	Wainwright GmbH	pre-m	2	
270	termination	1418 N	BB6935	Weinschel	pre-m	2	
271	termination	1418 N	BE6384	Weinschel	pre-m	2	
272	attenuator (20 dB) 50 W	Model 47	BF6239	Weinschel	pre-m	2	
273	attenuator (10 dB) 100 W	Model 48	BF9229	Weinschel	pre-m	2	
274	attenuator (10 dB) 50 W	Model 47 (10 dB) 50 W	BG0321	Weinschel	pre-m	2	
275	DC-Block	Model 7003 (N)	C5129	Weinschel	pre-m	2	
276	DC-Block	Model 7006 (SMA)	C7061	Weinschel	pre-m	2	
279	power divider	1515 (SMA)	LH855	Weinschel	pre-m	2	
287	pre-amplifier 25MHz - 4GHz	AMF-2D-100M4G-35-10P	379418	Miteq	12 M	1c	30.06.2014
291	high pass filter GSM 850/900	WHJ 2200-4EE	14	Wainwright GmbH	12 M	1c	30.06.2014
298	Univ. Radio Communication Tester	CMU 200	832221/091	Rohde & Schwarz	pre-m	3	
300	AC LISN (50 Ohm/50µH, 1-phase)	ESH3-Z5	892 239/020	Rohde & Schwarz	24/12 M	-	31.03.2014
301	attenuator (20 dB) 50W, 18GHz	47-20-33	AW0272	Lucas Weinschel	pre-m	2	
302	horn antenna 40 GHz (Meas 1)	BBHA9170	155	Schwarzbeck	36 M	-	31.03.2014
303	horn antenna 40 GHz (Subst 1)	BBHA9170	156	Schwarzbeck	36 M	-	31.03.2014
331	Climatic Test Chamber -40/+80 Grad	HC 4055	43146	Heraeus Vötsch	24 M	-	30.11.2014
341	Digital Multimeter	Fluke 112	81650455	Fluke	24 M	-	31.03.2014
342	Digital Multimeter	Voltcraft M-4660A	IB 255466	Voltcraft	24 M	-	31.03.2015
347	laboratory site	radio lab.	-	-	-	5	
348	laboratory site	EMI conducted	-	-	-	5	
354	DC - Power Supply 40A	NGPE 40/40	448	Rohde & Schwarz	pre-m	2	
355	Power Meter	URV 5	891310/027	Rohde & Schwarz	24 M	-	31.03.2014
356	power sensor	NRV-Z1	882322/014	Rohde & Schwarz	24 M	-	31.03.2015
357	power sensor	NRV-Z1	861761/002	Rohde & Schwarz	24 M	-	31.03.2015
371	Bluetooth Tester	CBT32	100153	R&S	24 M	-	31.03.2014
373	Single-Line V-Network (50 Ohm/5µH)	ESH3-Z6	100535	Rohde & Schwarz	24/12 M	-	31.03.2014
376	Horn Antenna 6 GHz	BBHA9120 E	BBHA 9120 E 179	Schwarzbeck	12 M	-	31.03.2014
377	EMI Test Receiver	ESCS 30	100160	Rohde & Schwarz	12 M	-	31.03.2014
389	Digital Multimeter	Keithley 2000	0583926	Keithley	24 M	-	31.03.2015
392	Radio Communication Tester	MT8820A	6K00000788	Anritsu	12 M	-	31.03.2014
431	Model 7405	Near-Field Probe Set	9305-2457	EMCO	-	4	
436	Univ. Radio Communication Tester	CMU 200	103083	Rohde & Schwarz	12 M	-	31.03.2014
441	CTC-SAR-EMI Cable Loss	System EMI field (SAR) Cable	-	CETECOM	12 M	5	31.10.2013

Ref.-No.	Equipment	Type	Serial-No.	Manufacturer	Interval of calibration	Remark	Cal due
443	CTC-FAR-EMI-RSE	System CTC-FAR-EMI-RSE	-	ETS-Lindgren / CETECOM	12 M	5	15.07.2014
448	notch filter WCDMA_FDD II	WRCT 1850.0/2170.0-5/40-	5	Wainwright Instruments GmbH	12 M	1c	30.06.2014
449	notch filter WCDMA FDD V	WRCT 824.0/894.0-5/40-8SSK	1	Wainwright	12 M	1c	30.06.2014
454	Oscilloscope	HM 205-3	9210 P 29661	Hameg	-	4	
456	DC-Power supply 0-5 A	EA 3013 S	207810	Elektro Automatik	pre-m	2	
459	DC -Power supply 0-5 A , 0-32 V	EA-PS 2032-50	910722	Elektro Automatik	pre-m	2	
460	Univ. Radio Communication Tester	CMU 200	108901	Rohde & Schwarz	12 M	-	31.03.2014
463	Universal source	HP3245A	2831A03472	Agilent	-	4	
466	Digital Multimeter	Fluke 112	89210157	Fluke USA	24 M	-	31.03.2014
467	Digital Multimeter	Fluke 112	89680306	Fluke USA	24 M	-	31.03.2014
468	Digital Multimeter	Fluke 112	90090455	Fluke USA	24 M	-	31.03.2014
477	ReRadiating GPS-System	AS-47	-	Automotive Cons. Fink	-	3	
480	power meter (Fula)	NRVS	838392/031	Rohde & Schwarz	24 M	-	31.03.2015
482	filter matrix	Filter matrix SAR 1	-	CETECOM (Brl)	-	1d	
484	pre-amplifier 2,5 - 18 GHz	AMF-5D-02501800-25-10P	1244554	Miteq	12 M	-	30.06.2014
487	System CTC NSA-Verification SAR-EMI	System EMI field (SAR) NSA	-	ETS Lindgren / CETECOM	24 M	-	30.06.2015
489	EMI Test Receiver	ESU40	1000-30	Rohde & Schwarz	12 M	-	31.03.2014
502	band reject filter	WRCG 1709/1786-1699/1796-	SN 9	Wainwright	pre-m	2	
503	band reject filter	WRCG 824/849-814/859-	SN 5	Wainwright	pre-m	2	
512	notch filter GSM 850	WRCA 800/960-02/40-6EEK	SN 24	Wainwright	12 M	1c	30.06.2014
517	relais switch matrix	HF Relais Box Keithley	SE 04	Keithley	pre-m	2	
523	Digital Multimeter	L4411A	MY46000154	Agilent	24 M	-	31.03.2015
529	6 dB Broadband resistive power divider	Model 1515	LH 855	Weinschel	pre-m	2	
530	10 dB Broadband resistive power divider	R 416110000	LOT 9828	-	pre-m	2	
546	Univ. Radio Communication Tester	CMU 200	106436	R&S	12 M	-	31.03.2014
547	Univ. Radio Communication Tester	CMU 200	835390/014	Rohde & Schwarz	12 M	-	31.03.2014
548	Digital-Barometer	GBP 2300	without	Greisinger GmbH	36 M	-	30.06.2015
549	Log.Per-Antenna	HL025	1000060	Rohde & Schwarz	36/12 M	-	31.03.2015
552	high pass filter 2,8-18GHz	WHKX 2.8/18G-10SS	4	Wainwright	12 M	1c	30.06.2014
558	System CTC FAR S-VSWR	System CTC FAR S-VSWR	-	CTC	24 M	-	31.07.2015
574	Biconilog Hybrid Antenna	BTA-L	980026L	Frankonia	36/12 M	-	31.03.2016
584	Spectrum Analyzer	FSU 8	100248	Rohde & Schwarz	24 M	-	31.03.2014
594	Wideband Radio Communication Tester	CMW 500	101757	Rohde & Schwarz	24 M	-	31.03.2014
597	Univ. Radio Communication Tester	CMU 200	100347	Rohde & Schwarz	12 M	-	31.03.2014
598	Spectrum Analyzer	FSEM 30 (Reserve)	831259/013	Rohde & Schwarz	24 M	-	13.01.2015
600	power meter	NRVD (Reserve)	834501/018	Rohde & Schwarz	24 M	-	31.03.2015
601	medium-sensitivity diode sensor	NRV-Z5 (Reserve)	8435323/003	Rohde & Schwarz	24 M	-	31.03.2015
602	peak power sensor	NRV-Z32 (Reserve)	835080	Rohde & Schwarz	24 M	-	31.03.2015
608	UltraLog-Antenna	HL 562	830547/009	Rohde & Schwarz	36/12 M	-	31.03.2014
611	DC power supply	E3632A	KR 75305854	Agilent	pre-m	2	
612	DC power supply	E3632A	MY 40001321	Agilent	pre-m	2	
613	Attenuator	R416120000 20dB 10W	Lot. 9828	Radiall	pre-m	2	
616	Digitalmultimeter	Fluke 177	88900339	Fluke	24 M	-	31.03.2014
617	Power Splitter/Combiner	ZFSC-2-2-S+	S F987001108	Mini Circuits	-	2	
618	Power Splitter/Combiner	50PD-634	600994	JFW Industries USA	-	2	
619	Power Splitter/Combiner	50PD-634	600995	JFW Industries, USA	-	3	
620	EMI Test Receiver	ESU 26	100362	Rohde-Schwarz	12 M	-	01.03.2014
621	Step Attenuator 0-139 dB	RSP	100017	Rohde & Schwarz	pre-m	2	
625	Generic Test Load USB	Generic Test Load USB	-	CETECOM	-	2	
627	data logger	OPUS 1	201.0999.9302.6.4.1.4 3	G. Lufft GmbH	24 M	-	30.05.2014
634	Spectrum Analyzer	FSM (HF-Unit)	826188/010	Rohde & Schwarz	pre-m	2	
636	Thermal Imaging camera	Ti32	Ti32-12060213	Fluke Corporation	24 M	-	31.07.2014
637	High Speed HDMI with Ethernet 1m	HDMI cable with Ethernet 1m	-	KogiLink	-	2	
638	HDMI Kabel with Ethernet 1,5 m flach	HDMI cable with Ethernet	-	Reichelt	-	2	
640	HDMI cable 2m rund	HDMI cable 2m rund	-	Reichelt	-	2	
641	HDMI cable with Ethernet	Certified HDMI cable with	-	PureLink	-	2	
642	Wideband Radio Communication Tester	CMW 500	126089	Rohde&Schwarz	24 M	-	31.03.2014
644	Amplifier	ZX60-2534M+	SN865701299	Mini-Circuits	-	-	
670	Univ. Radio Communication Tester	CMU 200	106833	Rohde & Schwarz	12 M	-	31.03.2014
671	DC-power supply 0-5 A	EA-3013S	-	Elektro Automatik	pre-m	2	
678	Power Meter	NRP	101638	Rohde&Schwarz	pre-m	-	
683	Spectrum Analyzer	FSU	200571	Rohde & Schwarz	pre-m	-	
686	Field Analyzer	EHP-200A	160WX30702	Narda Safety Test Solutions	24 M	-	18.07.2015

8.1.3. Legend

Note / remarks		Calibrated during system calibration:
	1a	System CTC-SAR-EMS (Ref.-No. 442)
	1b	System-CTC-EMS-Conducted (Ref.-No. 335)
	1c	System CTC-FAR-EMI-RSE (Ref.-No. 443)
	1d	System CTC-SAR-EMI (Ref.-No. 441)
	1e	System CTC-OATS (EMI radiated) (Ref.-No. 337)
	1 f	System CTC-CTIA-OTA (Ref.-No. 420)
	1 g	System CTC-FAR-EMS (Ref.-No. 444)
	2	Calibration or equipment check immediately before measurement
	3	Regulatory maintained equipment for functional check or support purpose
	4	Ancillary equipment without calibration e.g. mechanical equipment or monitoring equipment
	5	Test System

Interval of calibration	12 M	12 month
	24 M	24 month
	36 M	36 month
	24/12 M	Calibration every 24 months, between this every 12 months internal validation
	36/12 M	Calibration every 36 months, between this every 12 months internal validation
	Pre-m	Check before starting the measurement
	-	Without calibration