



AFC DUT TEST HARNESS REPORT

FCC ID : QXO-AP3020
Equipment : Access Point
Brand Name : Extreme Networks
Model Name : AP3020
Applicant : Extreme Networks, Inc.
2121 RDU Center Drive Morrisville North Carolina United States 27560
Manufacturer : Extreme Networks, Inc.
2121 RDU Center Drive Morrisville North Carolina United States 27560
Standard : 47 CFR FCC Part 15.407

The product was received on Mar. 16, 2026, and testing was started from Jul. 23, 2026 and completed on Jul. 27, 2026. We, Sporton International Inc. Hsinchu Laboratory, would like to declare that the tested sample has been evaluated in accordance with the procedures given in AFC Device (AFC DUT) Compliance Test Plan Version 1.7 and shown compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. Hsinchu Laboratory, the test report shall not be reproduced except in full.

Approved by: Sam Chen

Sporton International Inc. Hsinchu Laboratory

No.8, Ln. 724, Bo'ai St., Zhubei City, Hsinchu County 302010, Taiwan (R.O.C.)



Table of Contents

1	General Description	6
1.1	Product Feature of Equipment Under Test	6
1.2	Antenna Information	7
1.3	Table for Radio Function	9
1.4	Table for EUT Support Function	9
1.5	Table for Source Information	9
1.6	Accessories	10
1.7	Support Equipment	10
1.8	Applicable Standards	10
1.9	Testing Location	10
2	Measurement Environment	11
2.1	AFCD General Capabilities Declaration	11
2.2	Test Configuration	12
3	Protocol Test Results	14
3.1	Successful Registration and Spectrum Access Request	14
3.2	Unsuccessful Spectrum Access Request	16
3.3	Successful Spectrum Access Update	17
3.4	Unsuccessful Spectrum Access Update	19
3.5	Unsuccessful Server Validation	21
4	Test Equipment and Calibration Data	22
5	Measurement Uncertainty	23

Appendix A. Tools Report

Appendix B. DUT Spectrum Inquiry Request/Response Logs

Appendix C. RF Measurement Plots

Photographs of EUT v01



TEL : 886-3-656-9065
FAX : 886-3-656-9085
Report Template No.: CB-A12_7 Ver2.0



Summary of Test Result

Report Clause	Ref Std. Clause	Test Case Name	Result (PASS/FAIL)	Remark
AFC capability - Inquired Frequency				
Test Group: Inquired Frequency - Always				
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Frequency_20MHz_10611_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Frequency_40MHz_10612_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Frequency_80MHz_10613_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Frequency_160MHz_10614_1	N/A	-
-	3.2.4	CT_AFC_SP_AP_AFCDUSA32_Frequency_10615_1	N/A	-
-	3.3.4	CT_AFC_SP_AP_AFCDSAU33_Frequency_10616_1	N/A	-
-	3.4.4	CT_AFC_SP_AP_AFCDUUA34_Frequency_10617_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Frequency_320MHz_10713_1	N/A	-
AFC capability - Inquired Channel				
Test Group: Inquired Channel - Always				
3.1	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Channel_20MHz_10618_1	PASS	-
3.1	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Channel_40MHz_10619_1	PASS	-
3.1	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Channel_80MHz_10620_1	PASS	-
3.1	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Channel_160MHz_10621_1	PASS	-
3.2	3.2.4	CT_AFC_SP_AP_AFCDUSA32_Channel_10622_1	PASS	-
3.3	3.3.4	CT_AFC_SP_AP_AFCDSAU33_Channel_10623_1	PASS	-
3.4	3.4.4	CT_AFC_SP_AP_AFCDUUA34_Channel_10624_1	PASS	-
3.1	3.1.4	CT_AFC_SP_AP_AFCDRSA31_Channel_320MHz_10714_1	PASS	-
AFC capability - Inquired Frequency & Channel				
Test Group: Inquired Frequency and Channel - Always				
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_FrequencyChannel_20MHz_10625_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_FrequencyChannel_40MHz_10626_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_FrequencyChannel_80MHz_10627_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_FrequencyChannel_160MHz_10628_1	N/A	-
-	3.2.4	CT_AFC_SP_AP_AFCDUSA32_FrequencyChannel_10629_1	N/A	-
-	3.3.4	CT_AFC_SP_AP_AFCDSAU33_FrequencyChannel_10630_1	N/A	-
-	3.4.4	CT_AFC_SP_AP_AFCDUUA34_FrequencyChannel_10631_1	N/A	-
-	3.1.4	CT_AFC_SP_AP_AFCDRSA31_FrequencyChannel_320MHz_10715_1	N/A	-
AFC capability - Server Validation - Mandatory				
Test Group: Server Validation - Always				
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_NonMatchSAN_10632_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_DifferentRootCA_10633_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_MatchSuffixSAN_10634_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_ServerCertRevoked_10635_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_OCSPStaplingDisabled_10636_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_StapledOCSPRespExpired_10637_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_TLSCipherSuiteENULL_10638_1	PASS	-
3.5	3.5.4	CT_AFC_ServerValidation_AP_AFCDUSV35_NoRootCA_10639_1	PASS	-

**Conformity Assessment Condition:**

1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacturee who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
2. The measurement uncertainty please refer to each test result in the chapter "Measurement Uncertainty".

Disclaimer:

The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.

Reviewed by: Sam Chen

Report Producer: Sandy Chuang



1 General Description

1.1 Product Feature of Equipment Under Test

Product Feature of Equipment Under Test	
Power Type	From PoE
EUT Type	☒ Standard Power Access Point with Proxy ☐ Standard Power Access Point without Proxy ☐ Fixed Client with Proxy ☐ Fixed Client without Proxy
Standard AP Operating Configuration	☒ The SP AP initially operates in LPI mode upon power-up. It switches to SP mode after obtaining AFC authorization. ☐ The SP AP does not transmit any signal in 6 GHz upon power-up. It only starts operating in SP mode after obtaining AFC authorization.
Fixed Client Operating Configuration	☐ Connect Standard power AP via in-band (UNII-5&7).It also means DUT supports equipment class: 6FX+6FC. ☐ Connect Standard power AP via out-of-band (other than UNII-5&7).It also means DUT supports equipment class: 6FC only.
Bandwidth (MHz)	20 / 40 / 80 / 160 / 320
Condition of EUT	☒ Indoor ☐ Outdoor
Professional Installation	☒ Yes ☐ No
DUT Firmware version	10.20.1.0-003R
DUT Software version	N/A
DUT Hardware version	N/A
Proxy Firmware version	VE6120K Small 10.20.01.003T
Proxy Software version	N/A
Proxy Hardware version	N/A

Note: The above information was declared by manufacturer.



1.2 Antenna Information

Ant.	RF Port				Brand Name	Model Name	Ant. Type	Connector	Modes of Operation	Gain (dBi)
	WLAN 2.4GHz	WLAN 5GHz	WLAN 6GHz	Bluetooth and IEEE 802.15.4						
1	1	1	1	-	WNC	95XPAM15.G93	PIFA	I-PEX	WLAN 2.4GHz, WLAN 5GHz UNII 1~2A, WLAN 6GHz UNII 5~8 (Radio 1)	Note 1
2	2	2	2	-	WNC	95XPAM15.G92	Dipole	I-PEX		
3	1	1	-	-	WNC	95XPAM15.G90	PIFA	I-PEX	WLAN 2.4GHz, WLAN 5GHz UNII 2C~3 or UNII 1~3 (Radio 2)	
4	2	2	-	-	WNC	95XPAM15.G91	Dipole	I-PEX		
5	-	-	-	1	WNC	95XPAM15.GAP	PIFA	I-PEX	Bluetooth, IEEE 802.15.4 (Radio 3)	
6	-	-	-	1	WNC	95XPAM15.GAQ	Dipole	I-PEX		
7	-	-	-	1	WNC	95XPAM15.G94	PIFA	I-PEX		

Note 1:

Ant.	Antenna Gain (dBi)						
	WLAN 2.4GHz (Radio 1)	WLAN 5GHz UNII 1~2A (Radio 1)		WLAN 6GHz UNII 5~8 (Radio 1)			
	2.45GHz	5.2GHz	5.3GHz	6.175GHz	6.475GHz	6.695GHz	6.995GHz
1	1.12	2.93	2.62	3.38	3.03	3.14	3.59
2	5.37	4	4.54	3.97	4.01	2.34	4.43
Ant.	WLAN 2.4GHz (Radio 2)	WLAN 5GHz UNII 2C~3 or UNII 1~3 (Radio 2)					
	2.45GHz	5.2GHz	5.3GHz	5.6GHz		5.785GHz	
3	2.26	1.95	2.21	2.92		2.29	
4	5.9	4.48	4.52	5.21		5.83	
Ant.	Bluetooth, IEEE 802.15.4 (Radio 3)						
5	4.5						
6	4.9						
7	4.5						

Directional Gain (dBi)							
Item	WLAN 2.4GHz (Radio 1)	WLAN 5GHz UNII 1~2A (Radio 1)		WLAN 6GHz UNII 5~8 (Radio 1)			
	2.45GHz	5.2GHz	5.3GHz	6.175GHz	6.475GHz	6.695GHz	6.995GHz
2T1S	5.37	4.37	4.87	4.05	4.01	3.3	4.67
2T2S	5.37	4	4.54	3.97	4.01	3.14	4.43
Item	WLAN 2.4GHz (Radio 2)	WLAN 5GHz UNII 2C~3 or UNII 1~3 (Radio 2)					
		5.2GHz	5.3GHz	5.6GHz	5.785GHz		
2T1S	5.9	4.48	4.52	5.21	5.83		
2T2S	5.9	4.48	4.52	5.21	5.83		

Note 2: The above information (excepting Ant. 1-4 (WLAN) antenna gain and directional gain) was declared by Manufacturer.

Note 3: The above information was declared by manufacturer.

Note 4: States antenna 5GHz and 6GHz transmission will be restricted per country's regulation.

For Radio 1:

2.4GHz IEEE 802.11b/g/n/VHT/ax/be mode (1, 2TX/2RX)

The EUT can support both 1TX and 2TX functions.

For 1TX

Only Port 1 can be use as transmitting antenna.

For 2TX/2RX

Port 1 and Port 2 can be used as transmitting/receiving antenna.

Port 1 and Port 2 could transmit/receive simultaneously.

5GHz IEEE 802.11a/n/ac/ax/be mode (1, 2TX/2RX)

The EUT can support both 1TX and 2TX functions.

For 1TX

Only Port 1 can be use as transmitting antenna.

For 2TX/2RX

Port 1 and Port 2 can be used as transmitting/receiving antenna.

Port 1 and Port 2 could transmit/receive simultaneously.

6GHz IEEE 802.11ax/be mode (1, 2TX/2RX)

The EUT can support both 1TX and 2TX functions.

For 1TX

Only Port 1 can be use as transmitting antenna.

For 2TX/2RX

Port 1 and Port 2 can be used as transmitting/receiving antenna.

Port 1 and Port 2 could transmit/receive simultaneously.

For Radio 2:

2.4GHz IEEE 802.11b/g/n/VHT/ax/be mode (1, 2TX/2RX)

The EUT can support both 1TX and 2TX functions.

For 1TX

Only Port 1 can be use as transmitting antenna.

For 2TX/2RX

Port 1 and Port 2 can be used as transmitting/receiving antenna.

Port 1 and Port 2 could transmit/receive simultaneously.

5GHz IEEE 802.11a/n/ac/ax/be mode (1, 2TX/2RX)

The EUT can support both 1TX and 2TX functions.

For 1TX

Only Port 1 can be use as transmitting antenna.

For 2TX/2RX



Port 1 and Port 2 can be used as transmitting/receiving antenna.
Port 1 and Port 2 could transmit/receive simultaneously.

For Radio 3:**Bluetooth, IEEE 802.15.4 mode (1TX/1RX)**

The EUT supports all antennas with TX/RX diversity functions.

At once time there is only one antenna port can transmitting/receiving RF signal

1.3 Table for Radio Function

Function Radio (R)	WLAN 2.4GHz	WLAN 5GHz	WLAN 6GHz	Bluetooth	IEEE 802.15.4
1	V	V (UNII 1~2A)	V	-	-
2	V	V (UNII 1~3 or UNII 2C~3)	-	-	-
3	-	-	-	V	V

Note 1: For WLAN 2.4GHz, 5GHz: The Radio 1 and Radio 2 can't operate at the same frequency simultaneously.

Note 2: The above information was declared by manufacturer.

1.4 Table for EUT Support Function

Type of Function	WLAN 2.4GHz	WLAN 5GHz		WLAN 6GHz
		Radio 1	Radio 2	
AP	V	V (UNII 1~2A)	V (UNII 1~3)	V
Bridge	V	V (UNII 1)	V (UNII 1/UNII3)	V
Mesh	V	V (UNII 1)	V (UNII 1/UNII3)	V

Note: The above information was declared by manufacturer.

1.5 Table for Source Information

EUT	1	2	3
Source Item	Main source	Second source	Third source
DDR4 (Location: U301)	Brand: Micron Model: MT40A1G16TB-062E:F	Brand: SK HYNIX Model: H5AG46DXNDX117N	Brand: SAMSUNG Model: K4AAG165WA-BCWE

Note 1: From the above, EUT 1 has selected to execute all test items.

Note 2: The above information was declared by manufacturer.



1.6 Accessories

Accessories
Bracket*1
Cap*1

1.7 Support Equipment

Support Equipment				
No.	Equipment	Brand Name	Model Name	FCC ID
A	Notebook	DELL	E4300	N/A
B	Notebook	DELL	E4300	N/A
C	WLAN module	QCA	QCNCM865	N/A
D	PoE	Microsemi	PD-9501-10GC	N/A
E	Proxy	DELL	OptiPlex	N/A

1.8 Applicable Standards

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ 47 CFR FCC Part 15.407
- ♦ FCC KDB 987594 D05 v01r01

The following reference test guidance is not within the scope of accreditation of TAF.

- ♦ AFC Device (AFC DUT) Compliance Test Plan Version 1.7

1.9 Testing Location

Testing Location Information
Test Lab. : Sporton International Inc. Hsinchu Laboratory Hsinchu ADD: No.8, Ln. 724, Bo'ai St., Zhubei City, Hsinchu County 302010, Taiwan (R.O.C.) (TAF: 3787) TEL: 886-3-656-9065 FAX: 886-3-656-9085 Test site Designation No. TW3787 with FCC. Conformity Assessment Body Identifier (CABID) TW3787 with ISCED.

Test Condition	Test Site No.	Test Engineer	Test Environment (°C / %)	Test Date
RF Conducted	TH01-CB	Caster Chang	23.9-24.3 / 55-59	Jul. 23, 2026~ Jul. 27, 2026



2 Measurement Environment


Measurement Environment Information	
AFC DUT Test Harness version	2.0.65.184

2.1 AFCD General Capabilities Declaration


Item	Question	Vendor Response
1	AFC DUT Type	Standalone AP with Proxy
2	Does the AFC DUT supports sending an Available Spectrum Inquiry Request based on the inquired Frequency Range field?	No
3	Does the AFC DUT supports sending an Available Spectrum Inquiry Request based on the inquired Channels fields?	Yes
4	If the Answer to Items 2 and 3 is "Yes", what is AFC DUT's default inquiry type?	-
5	Does the AFC DUT need to be supplied with BSS configuration parameters?	No
6	Does the AFC DUT manufacturer attest to AFC DUT compliance with rules for LPI operation?	Yes
7	Does the AFC DUT need to be supplied with mandatory registration information to formulate an Available Spectrum Inquiry Request	No
8	If the Answer to Item 7 is "Yes". What is the geographic Supported by the AFC DUT?	N/A
9	Does the AFC DUT supports 160 MHz channel width operation?	Yes
10	Which method does AFC DUT acting as a Fixed Client uses for sending an Available Spectrum Inquiry Request?	No
11	Does the AFC DUT supports 320 MHz channel width operation?	Yes

Note: The above information was declared by manufacturer.

2.2 Test Configuration



Fixed Client Device Test Setup





3 Protocol Test Results

3.1 Successful Registration and Spectrum Access Request

3.1.1 Test Procedure

Step	Description
1	If the AFC DUT is Standard Power Access Point, go to Step 2, else go to Step 12
2	AFC DUT set to Initial Pre-test State. If needed (see Table 9 declaration), configure the AFC DUT with BSS parameters per Table 14 and a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request.
3	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*.
4	AFC DUT Test Harness validates the presence of mandatory registration information
5	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields.
6	Throughout Step 1 to Step 4, RF Test Equipment monitors the output of the AFC DUT to confirm that the AFC DUT does not transmit: • In the band if the AFC DUT supports only SP operation Or • Above LPI limits for AFC DUT whose manufacturer attests to its compliance with rules for LPI operation Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the following: • For SP only operation, AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies. • For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, AFC DUT transmit power in the band is less than CEILING [LPI limits, SP limits contained in the Available Spectrum Inquiry Response] and does not exceed emissions limits in adjacent frequencies.
7	Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request.
8	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*.
9	AFC DUT Test Harness validates the presence of mandatory registration information
10	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields which are significantly different from Step 5.
11	Wait for 5 minutes (configurable) RF Test Equipment monitors any transmission by the AFC DUT conforms to the following: • For SP only operation, AFC DUT conforms to the conditions contained in the latest Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies. • For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, AFC DUT transmit power in the band is less than CEILING [LPI limits, SP limits contained in the latest Available Spectrum Inquiry Response] and does not exceed emissions limits in adjacent frequencies.
12	If the AFC DUT is Fixed Client, go to Step 13 else Stop the test
13	The AFC DUT set to Initial Pre-test State.
14	If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request using either In-band or Out-of-band methods.
15	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*
16	AFC DUT Test Harness validates the presence of mandatory registration information
17	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields.



18	If AFC DUT used Out-of-band method, initiate connection procedure between AFC DUT and SP Access Point by following instructions provided by the AFC DUT Vendor
19	Wait for 60 seconds
20	RF Test Equipment monitors any transmission by the AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies
21	Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request using either In-band or Out-of-band methods
22	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*
23	AFC DUT Test Harness validates the presence of mandatory registration information
24	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields which are significantly different from Step 17.
25	If AFC DUT used Out-of-band method, initiate connection procedure between AFC DUT and SP Access Point by following instructions provided by the AFC DUT Vendor
	Wait for 60 seconds (configurable)
	RF Test Equipment monitors any transmission by the AFC DUT conforms to the conditions contained in the latest Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies

3.1.2 Test Result

Refer as Appendix A~C



3.2 Unsuccessful Spectrum Access Request

3.2.1 Test Procedure

Step	Description
1	If the AFC DUT is Standard Power Access Point, go to Step 2, else go to Step 7
2	AFC DUT set to Initial Pre-test State. If needed (see Table 9 declaration), configure the AFC DUT with BSS parameters per Table 14 and a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request.
3	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*.
4	AFC DUT Test Harness validates mandatory registration information.
5	AFC DUT Test Harness sends an Available Spectrum Inquiry Response indicating that no frequency ranges and/or channels are available.
6	Throughout Step 2 to Step 5 and subsequent to Step 5, RF Test Equipment monitors the output of the AFC DUT to confirm the following: • For SP only operation, AFC DUT does not transmit in the band. • For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, the AFC DUT does not transmit above LPI limits.
7	If the AFC DUT is Fixed Client, go to Step 8 else Stop the test
8	The AFC DUT set to Initial Pre-test State.
9	If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID or IC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request.
10	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*.
11	AFC DUT Test Harness validates mandatory registration information.
12	AFC DUT Test Harness sends an Available Spectrum Inquiry Response indicating that no frequency ranges and/or channels are available using either In-band or Out-of-band methods.
13	If AFC DUT used Out-of-band method, initiate connection procedure between Fixed Client and SP Access Point by following instructions provided by the AFC DUT Vendor
13	Wait for 60 seconds RF Test Equipment monitors that the AFC DUT does not transmit above maximum transmit power limits advertised by the Standard Power Access Point for Standard Client Devices in the channel.

3.2.2 Test Result

Refer as Appendix A~C



3.3 Successful Spectrum Access Update

3.3.1 Test Procedure

Step	Description
1	If the AFC DUT is Standard Power Access Point, go to Step 2, else go to Step 12
2	AFC DUT set to Initial Pre-test State. If needed (see Table 9 declaration), configure the DUT with BSS parameters per Table 14 and a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request.
3	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*.
4	AFC DUT Harness validates mandatory registration information.
5	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields.
6	Throughout the preceding steps, RF Test Equipment monitors the output of the AFC DUT to confirm that the AFC DUT does not transmit: • In the band if the AFC DUT supports only SP operation Or • Above LPI limits for AFC DUT whose manufacturer attests to its compliance with rules for LPI operation Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the following: • For SP only operation, AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies. • For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, AFC DUT transmit power in the band is less than CEILING [LPI limits, SP limits contained in the Available Spectrum Inquiry Response] and does not exceed emissions limits in adjacent frequencies.
7	AFC DUT is power cycled. If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID), new geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate.
8	Wait for 60 seconds If the AFC DUT does not send an Available Spectrum Inquiry Request, RF Test Equipment monitors the output of the AFC DUT to verify the following and STOP the test • For SP only operation, AFC DUT does not transmit in the band. • For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, the AFC DUT does not transmit above LPI limits. If the AFC DUT sends an Available Spectrum Inquiry Request, then CONTINUE with Step 9
9	AFC DUT Test Harness evaluates validity of mandatory registration information
10	AFC DUT Test Harness waits for 60 seconds before sending an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields which are significantly different from Step 5. • During the 60 seconds wait time: ▪ For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, RF Test Equipment monitors the output of the AFC DUT to confirm that AFC DUT does not transmit above LPI threshold limits ▪ For SP only operation, RF Test Equipment monitors the output of the AFC DUT to confirm that AFC DUT doesn't transmit in the band
11	Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the following: • For SP only operation, AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies. • For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, AFC DUT transmit power in the band is less than CEILING [LPI limits, SP limits contained in the Available Spectrum Inquiry Response] and does not exceed emissions limits in adjacent frequencies.
12	If the AFC DUT is Fixed Client, go to Step 13 else Stop the test
13	The AFC DUT set to Initial Pre-test State.



14	If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request using either In-band or Out-of- band methods.
15	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*
16	AFC DUT Test Harness validates the presence of mandatory registration information
17	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields.
18	If AFC DUT used Out-of-band method, initiate connection procedure between AFC DUT and SP Access Point by following instructions provided by the AFC DUT Vendor
19	Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies
20	AFC DUT is power cycled. If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID), new geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate
21	Wait for 60 seconds If the AFC DUT does not send an Available Spectrum Inquiry Request, RF Test Equipment monitors the output of the AFC DUT to verify the AFC DUT does not transmit above maximum transmit power limits advertised by the Standard Power Access Point for Standard Client Devices in the channel and STOP the test. If the AFC DUT sends an Available Spectrum Inquiry Request, then CONTINUE with Step 21
22	AFC DUT Test Harness evaluates validity of mandatory registration information
23	AFC DUT Test Harness waits for 60 seconds before sending an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields which are significantly different from step 17. During the 60 seconds wait time, RF Test Equipment monitors the output of the AFC DUT to confirm that the AFC DUT does not transmit above maximum transmit power limits advertised by the Standard Power Access Point for Standard Client Devices in the channel.
24	If AFC DUT used Out-of-band method, initiate connection procedure between AFC DUT and SP Access Point by following instructions provided by the AFC DUT Vendor
25	Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies

3.3.2 Test Result

Refer as Appendix A~C



3.4 Unsuccessful Spectrum Access Update

3.4.1 Test Procedure

Step	Description
1	If the AFC DUT is Standard Power Access Point, go to Step 2, else go to Step 12
2	AFC DUT set to Initial Pre-test State. If needed (see Table 5 declaration), configure the AFC DUT with BSS parameters per Table 9 and a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the DUT with AFC System URL and server root certificate. Trigger the DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request using either In-band or Out-of-band methods.
3	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields.
4	AFC DUT Test Harness validates mandatory registration information
5	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields.
6	Throughout the Step 2 to 5, RF Test Equipment monitors the output of the AFC DUT to confirm that the AFC DUT does not transmit: • In the band if the AFC DUT supports only SP operation Or • Above LPI limits for AFC DUT whose manufacturer attests to its compliance with rules for LPI operation Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the following: • For SP only operation, AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies. For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, AFC DUT transmit power in the band is less than CEILING [LPI limits, SP limits contained in the Available Spectrum Inquiry Response] and does not exceed emissions limits in adjacent frequencies
7	AFC DUT is power cycled. If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID), new geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate.
8	Wait for 60 seconds • If the AFC DUT does not send an Available Spectrum Inquiry Request, RF Test Equipment monitors the output of the DUT to verify the following and STOP the test: ▪ For SP only operation, AFC DUT does not transmit in the band, ▪ For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, the AFC DUT does not transmit above LPI limits. • If the AFC DUT sends an Available Spectrum Inquiry Request, then CONTINUE with Step 8
9	AFC DUT Test Harness evaluates validity of mandatory registration information.
10	AFC DUT Test Harness sends an Available Spectrum Inquiry Response indicating that no frequency ranges and/or channels are available.
11	Throughout Step 7 to 10 and subsequent to Step 10 Test Equipment monitors the output of the AFC DUT to confirm that: For SP only operation, AFC DUT does not transmit in the band. For AFC DUT whose manufacturer attests to its compliance with rules for LPI operation, the AFC DUT does not transmit above LPI limits.
12	If the AFC DUT is Fixed Client, go to Step 13 else Stop the test
13	The AFC DUT set to Initial Pre-test State.
14	If needed (see Table 9 declaration), configure the DUT with a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate. Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request using either In-band or Out-of- band methods.
15	AFC DUT sends a valid Available Spectrum Inquiry Request containing the inquiredFrequencyRange and/or the inquiredChannels fields*
16	AFC DUT Test Harness validates the presence of mandatory registration information
17	AFC DUT Test Harness sends an Available Spectrum Inquiry Response containing a list of available frequency ranges



	and/or channels and the maximum permissible transmit power in the availableFrequencyInfo and/or availableChannelInfo fields.
18	If AFC DUT used Out-of-band method, initiate connection procedure between AFC DUT and SP Access Point by following instructions provided by the AFC DUT Vendor
19	Wait for 60 seconds RF Test Equipment monitors any transmission by the AFC DUT conforms to the conditions contained in the Available Spectrum Inquiry Response and does not exceed emissions limits in adjacent frequencies
20	AFC DUT is power cycled. If needed (see Table 9 declaration), configure the AFC DUT with a temporary test regulatory identifier (e.g., FCC ID or IC ID), new geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT with AFC System URL and server root certificate
21	Wait for 60 seconds If the AFC DUT does not send an Available Spectrum Inquiry Request, RF Test Equipment monitors that the AFC DUT does not transmit above maximum transmit power limits advertised by the Standard Power Access Point for Standard Client Devices in the channel., If the AFC DUT sends an Available Spectrum Inquiry Request, then CONTINUE with Step 22 else STOP the test
22	AFC DUT Test Harness evaluates validity of mandatory registration information.
23	AFC DUT Test Harness sends an Available Spectrum Inquiry Response indicating that no frequency ranges and/or channels are available.
24	If AFC DUT used Out-of-band method, initiate connection procedure between AFC DUT and SP Access Point by following instructions provided by the AFC DUT Vendor
25	Wait for 60 seconds RF Test Equipment monitors that the AFC DUT does not transmit above maximum transmit power limits advertised by the Standard Power Access Point for Standard Client Devices in the channel.

3.4.2 Test Result

Refer as Appendix A~C



3.5 Unsuccessful Server Validation

3.5.1 Test Procedure

Step	Description
1	The AFC DUT set to Initial Pre-test State. If needed (see Table 9 declaration), configure the AFC DUT with BSS parameters per Table 14 and a temporary test regulatory identifier (e.g., FCC ID), geographic coordinates, antenna height, and uncertainty parameters. Configure the AFC DUT Test Harness with TLS configuration that is the same as the default configuration defined in Section 2.3.1 except for the following: - Run 1: A different server certificate (and private key) with SAN domain name entry "badafc.com" (i.e. that does not match AFC system URL's domain name); signed by the same root certificate as per Section 2.3.1 - Run 2: A different server certificate (and private key) where all attributes other than Public Key are the same as the server certificate per Section 2.3.1, but the certificate is signed by a different root certificate - Run 3: A different server certificate (and private key) with SAN domain name entry "wfatestorg.org" only (i.e. SAN domain name only matches suffix of AFC server's hostname); signed by the same root certificate as per Section 2.3.1 - Run 4: A different server certificate (and private key) where all attributes other than Public Key are the same as the server certificate per Section 2.3.1 signed by the same root certificate as per Section 2.3.1, but the server certificate is revoked as indicated in stapled OCSP response - Run 5: Same configuration as per Section 2.3.1, except OCSP stapling is disabled and CRL/OCSP servers are not available - Run 6: Same configuration as per Section 2.3.1, except stapled OCSP response has expired and CRL/OCSP servers are not available - Run 7: Same configuration as per Section 2.3.1, except only the TLS cipher suite "eNULL" (no encryption) is enabled - Run 8: N/A (same configuration as per Section 2.3.1) Configure the AFC DUT with the AFC System URL and the following root certificate: - Runs 1-7: Root certificate as per Section 2.3.1 - Run 8: No root certificate Trigger the AFC DUT to send to the AFC DUT Test Harness an Available Spectrum Inquiry Request using either In-band or Out-of- band methods.
2	AFC DUT Test Harness waits 10 seconds, and verifies no Available Spectrum Inquiry Request is sent to it.
3	Steps 1 and 2 are repeated for each of the remaining Runs

3.5.2 Test Result

Refer as Appendix A



4 Test Equipment and Calibration Data

Instrument	Brand	Model No.	Serial No.	Characteristics	Calibration Date	Calibration Due Date	Remark
Signal Analyzer	R&S	FSV3044	101320	9kHz ~ 44GHz	Aug. 07, 2025	Aug. 06, 2026	Conducted (TH01-CB)
RF Cable-high	Woken	RG402	High Cable-06	1 GHz – 18 GHz	Sep. 30, 2025	Sep. 29, 2026	Conducted (TH01-CB)
RF Cable-high	Woken	RG402	High Cable-07	1 GHz – 18 GHz	Sep. 30, 2025	Sep. 29, 2026	Conducted (TH01-CB)
RF Cable-high	Woken	RG402	High Cable-08	1 GHz – 18 GHz	Sep. 30, 2025	Sep. 29, 2026	Conducted (TH01-CB)
RF Cable-high	Woken	RG402	High Cable-09	1 GHz – 18 GHz	Sep. 30, 2025	Sep. 29, 2026	Conducted (TH01-CB)
RF Cable-high	Woken	RG402	High Cable-10	1 GHz – 18 GHz	Sep. 30, 2025	Sep. 29, 2026	Conducted (TH01-CB)
RF Power Divider	STI	2 Way	DV-8G -05	1 ~ 8GHz	Sep. 20, 2025	Sep. 19, 2026	Conducted (TH01-CB)
RF Power Divider	STI	2 Way	DV-8G -06	1 ~ 8GHz	Sep. 20, 2025	Sep. 19, 2026	Conducted (TH01-CB)
RF Power Divider	STI	2 Way	DV-8G -07	1 ~ 8GHz	Sep. 20, 2025	Sep. 19, 2026	Conducted (TH01-CB)
RF Power Divider	STI	2 Way	DV-8G -08	1 ~ 8GHz	Sep. 20, 2025	Sep. 19, 2026	Conducted (TH01-CB)

Note: Calibration Interval of instruments listed above is one year.



5 Measurement Uncertainty

Test Items	Uncertainty	Remark
Conducted Emission	3.8 dB	Confidence levels of 95%

AFC DUT Compliance Test Report

DUT Information

AFC DUT System	Standard Power AP with Proxy
DUT Vendor Name	Extreme Networks
DUT Product Model	AP3020

Test Result

POC Requirements	Test Case Name	Test Result
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_NoRootCA_10639_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_TLSCipherSuiteENTL1_10638_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_StapledOCSPRespExpired_10637_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_OCSPStaplingDisabled_10636_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_ServerCertRevoked_10635_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_MatchSuffixSAN_10634_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_DifferentRootCA_10633_1 (Unsuccessful server validation)	PASS
15.407(k)(8)(v)	CT_AFC_ServerValidation_AP_AFCDSV35_NonMatchSAN_10632_1 (Unsuccessful server validation)	PASS
15.407(k)(1), 15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(8)(iii), 15.407(l)(ii), 15.407(k)(8)(iv)	CT_AFC_SP_AP_AFCDSA31_Channel_320MHz_10714_1 (Successful registration and spectrum access request)	PASS
15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(9)(i)	CT_AFC_SP_AP_AFCDSU434_Channel_10624_1 (Unsuccessful spectrum access update)	PASS
15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(9)(i)	CT_AFC_SP_AP_AFCDSU433_Channel_10623_1 (Successful spectrum access update)	PASS
15.407(k)(1), 15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(8)(iii)	CT_AFC_SP_AP_AFCDSU432_Channel_10622_1 (Unsuccessful registration and spectrum access request)	PASS
15.407(k)(1), 15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(8)(iii), 15.407(l)(ii), 15.407(k)(8)(iv)	CT_AFC_SP_AP_AFCDSA31_Channel_160MHz_10621_1 (Successful registration and spectrum access request)	PASS
15.407(k)(1), 15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(8)(iii), 15.407(l)(ii), 15.407(k)(8)(iv)	CT_AFC_SP_AP_AFCDSA31_Channel_80MHz_10620_1 (Successful registration and spectrum access request)	PASS
15.407(k)(1), 15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(8)(iii), 15.407(l)(ii), 15.407(k)(8)(iv)	CT_AFC_SP_AP_AFCDSA31_Channel_40MHz_10619_1 (Successful registration and spectrum access request)	PASS
15.407(k)(1), 15.407(k)(8)(i), 15.407(k)(8)(ii), 15.407(k)(8)(iii), 15.407(l)(ii), 15.407(k)(8)(iv)	CT_AFC_SP_AP_AFCDSA31_Channel_20MHz_10618_1 (Successful registration and spectrum access request)	PASS

Test Measurements

Test Case Name: CT_AFC_ServerValidation_AP_AFCDSV35_NoRootCA_10639_1 (Unsuccessful server validation)

Test Result: PASS

Band: 6GHz

Measurement Name	Description	Value	Validation Result
------------------	-------------	-------	-------------------

AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS
--------------------------------------	---	-------	------

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_TLSCipherSuiteENULL_10638_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_StapledOCSPRespExpired_10637_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_OCSPStaplingDisabled_10636_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_ServerCertRevoked_10635_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_MatchSuffixSAN_10634_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_DifferentRootCA_10633_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_ServerValidation_AP_AFCDUSV35_NonMatchSAN_10632_1 (Unsuccessful server validation)
TestResult:PASS
Band:6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	false	PASS

TestCaseName: CT_AFC_SP_AP_AFCDSA31_Channel_320MHz_10714_1 (Successful registration and spectrum access request)
 TestResult: PASS
 Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_1	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD), SP limits (35.0 dBm EIRP) in Spectrum Response] on channel center frequency index 69 bandwidth 320.	true	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_2	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_2	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_2	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD), SP limits (21.0 dBm EIRP) in Spectrum Response] on channel center frequency index 31 bandwidth 320.	true	PASS

TestCaseName: CT_AFC_SP_AP_AFCDAU34_Channel_10624_1 (Unsuccessful spectrum access update)
 TestResult: PASS
 Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD), SP limits (36.0 dBm EIRP) in Spectrum Response] on channel 85 bandwidth 20.	true	PASS
AFC_DUT_SP_OPERATION_NO_REQ	AFC DUT transmit with standard power in the band in no Spectrum Inquiry Request case	false	PASS

TestCaseName: CT_AFC_SP_AP_AFCDAU33_Channel_10623_1 (Successful spectrum access update)
 TestResult: PASS
 Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION_1	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD), SP limits (29.5 dBm EIRP) in Spectrum Response] on channel 53 bandwidth 20.	true	PASS

AFC_DUT_SP_OPERATION_NO_REQ	AFC DUT transmit with standard power in the band in no Spectrum Inquiry Request case	false	PASS
-----------------------------	--	-------	------

TestCaseName: CT_AFC_SP_AP_AFCDSA32_Channel_10622_1 (Unsuccessful registration and spectrum access request)
TestResult: PASS
Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE	AFC DUT conforms to the conditions in the Spectrum Inquiry Response	true	PASS

TestCaseName: CT_AFC_SP_AP_AFCDSA31_Channel_160MHz_10621_1 (Successful registration and spectrum access request)
TestResult: PASS
Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_1	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING(LPI limits (5 dBm/MHz PSD) , SP limits (35.4 dBm EIRP) in Spectrum Response) on channel center frequency index 143 bandwidth 160.	true	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_2	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_2	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_2	AFC DUT transmit power in the band is less than CEILING(LPI limits (5 dBm/MHz PSD) , SP limits (30.2 dBm EIRP) in Spectrum Response) on channel center frequency index 47 bandwidth 160.	true	PASS

TestCaseName: CT_AFC_SP_AP_AFCDSA31_Channel_80MHz_10620_1 (Successful registration and spectrum access request)
TestResult: PASS
Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_1	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING(LPI limits (5 dBm/MHz PSD) , SP limits (28.5 dBm EIRP) in Spectrum Response) on channel center frequency index 39 bandwidth 80.	true	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_2	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS

AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_2	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_2	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD) , SP limits (30.6 dBm EIRP) in Spectrum Response] on channel center frequency index 87 bandwidth 80.	true	PASS

TestCaseName: CT_AFC_SP_AP_AFCDRSA31_Channel_40MHz_10619_1 (Successful registration and spectrum access request)
TestResult: PASS
Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_1	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD) , SP limits (25.7 dBm EIRP) in Spectrum Response] on channel center frequency index 131 bandwidth 40.	true	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_2	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_2	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_2	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD) , SP limits (24.1 dBm EIRP) in Spectrum Response] on channel center frequency index 51 bandwidth 40.	true	PASS

TestCaseName: CT_AFC_SP_AP_AFCDRSA31_Channel_20MHz_10618_1 (Successful registration and spectrum access request)
TestResult: PASS
Band: 6GHz

Measurement Name	Description	Value	Validation Result
AFC_DUT_SP_OPERATION	AFC DUT transmit with standard power in the band before the Spectrum Inquiry Response	false	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_1	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_1	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_1	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD) , SP limits (34.7 dBm EIRP) in Spectrum Response] on channel 85 bandwidth 20.	true	PASS
AFC_DUT_SEND_SPECTRUM_INQUIRYREQUEST_2	AFC DUT sends an Available Spectrum Inquiry Request	true	PASS
AFC_DUT_SPECTRUM_INQUIRYREQUEST_VALID_2	Valid mandatory registration information	true	PASS
AFC_DUT_CONFORM_SPECTRUM_INQUIRYRESPONSE_2	AFC DUT transmit power in the band is less than CEILING[LPI limits (5 dBm/MHz PSD) , SP limits (23.6 dBm EIRP) in Spectrum Response] on channel 37 bandwidth 20.	true	PASS

AFC capability - Inquired Channel**CT_AFC_SP_AP_AFCRSA31_Channel_20MHz_10618_1**

2026-07-23T06:10:12Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      }
    }
  }
}
```

```
"ellipse": {
  "majorAxis": 30,
  "minorAxis": 19,
  "orientation": 90.0,
  "center": {
    "latitude": 43.83956,
    "longitude": -79.3818
  }
},
"inquiredFrequencyRange": [],
"inquiredChannels": [
  {
    "globalOperatingClass": 131
  },
  {
    "globalOperatingClass": 132
  },
  {
    "globalOperatingClass": 133
  },
  {
    "globalOperatingClass": 134
  },
  {
    "globalOperatingClass": 137
  }
],
"minDesiredPower": 0.0
}
]
```

2026-07-23T06:10:12Z

```
{
  "availableSpectrumInquiryResponses": [
```

```
{
  "response": {
    "responseCode": 0,
    "shortDescription": "SUCCESS"
  },
  "availableChannelInfo": [
    {
      "channelCfi": [
        17,
        21,
        25,
        29,
        65,
        69,
        73,
        77,
        81,
        85,
        89,
        93,
        145,
        149,
        153,
        157
      ],
      "globalOperatingClass": 131,
      "maxEirp": [
        30.1,
        25.0,
        29.6,
        33.6,
        27.3,
        31.5,
        21.9,
        24.6,
        31.9,
        34.7,
```

```
        29.7,  
        30.0,  
        23.4,  
        28.6,  
        29.3,  
        32.4  
    ]  
},  
{  
    "channelCfi": [  
        19,  
        27,  
        67,  
        75,  
        83,  
        91,  
        147,  
        155  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        28.0,  
        32.6,  
        30.3,  
        24.9,  
        34.9,  
        32.7,  
        26.4,  
        32.3  
    ]  
},  
{  
    "channelCfi": [  
        23,  
        71,  
        87,  
        151
```

```
    ],
    "globalOperatingClass": 133,
    "maxEirp": [
        31.0,
        27.9,
        35.7,
        29.4
    ]
},
{
    "channelCfi": [
        79
    ],
    "globalOperatingClass": 134,
    "maxEirp": [
        30.9
    ]
},
{
    "channelCfi": [],
    "globalOperatingClass": 137,
    "maxEirp": []
}
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T06:10:12Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

```
##### 2026-07-23T06:29:49Z #####
{
    "headers": {
        "Host": "testserver.wfatestorg.org",
        "Accept": "application/json",
```

```
"Content-Type": "application/json",
"User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
"Accept-Encoding": "gzip,deflate",
"X-Forwarded-For": "192.168.1.169",
"X-Forwarded-Host": "testserver.wfatestorg.org",
"X-Forwarded-Server": "testserver.wfatestorg.org",
"Content-Length": "659",
"Connection": "Keep-Alive"
},
"body": {
  "version": "1.4",
  "availableSpectrumInquiryRequests": [
    {
      "requestId": "WF122620W-50004",
      "deviceDescriptor": {
        "serialNumber": "WF122620W-50004",
        "certificationId": [
          {
            "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
            "id": "QXO-AP3020"
          }
        ]
      }
    }
  ],
  "location": {
    "indoorDeployment": 1,
    "elevation": {
      "height": 154.9,
      "heightType": "AMSL",
      "verticalUncertainty": 66
    },
    "ellipse": {
      "majorAxis": 30,
      "minorAxis": 19,
      "orientation": 90.0,
      "center": {
        "latitude": 43.83956,
        "longitude": -79.3818
      }
    }
  }
}
```

```
    }
  }
},
"inquiredFrequencyRange": [],
"inquiredChannels": [
  {
    "globalOperatingClass": 131
  },
  {
    "globalOperatingClass": 132
  },
  {
    "globalOperatingClass": 133
  },
  {
    "globalOperatingClass": 134
  },
  {
    "globalOperatingClass": 137
  }
],
"minDesiredPower": 0.0
}
]
}
}
```

2026-07-23T06:29:49Z

```
{
  "availableSpectrumInquiryResponses": [
    {
      "response": {
        "responseCode": 0,
        "shortDescription": "SUCCESS"
      },
      "availableChannelInfo": [
        {
```

```
"channelCfi": [  
    1,  
    5,  
    9,  
    13,  
    33,  
    37,  
    41,  
    45,  
    49,  
    53,  
    57,  
    61,  
    129,  
    133,  
    137,  
    141,  
    161,  
    165,  
    169,  
    173  
],  
"globalOperatingClass": 131,  
"maxEirp": [  
    29.5,  
    23.0,  
    24.7,  
    22.2,  
    33.8,  
    23.6,  
    28.3,  
    34.3,  
    30.5,  
    21.0,  
    26.0,  
    25.9,  
    32.5,
```

```
        34.8,  
        31.8,  
        29.9,  
        24.6,  
        21.1,  
        30.0,  
        22.1  
    ]  
},  
{  
    "channelCfi": [  
        3,  
        11,  
        35,  
        43,  
        51,  
        59,  
        131,  
        139,  
        163,  
        171  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        26.0,  
        25.2,  
        26.6,  
        31.3,  
        24.0,  
        28.9,  
        35.5,  
        32.9,  
        24.1,  
        25.1  
    ]  
},  
{
```

```
"channelCfi": [
    7,
    39,
    55,
    135,
    167
],
"globalOperatingClass": 133,
"maxEirp": [
    28.2,
    29.6,
    27.0,
    35.9,
    27.1
]
},
{
    "channelCfi": [
        47
    ],
    "globalOperatingClass": 134,
    "maxEirp": [
        30.0
    ]
},
{
    "channelCfi": [],
    "globalOperatingClass": 137,
    "maxEirp": []
}
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T06:29:49Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
```



}

CT_AFC_SP_AP_AFCDSA31_Channel_40MHz_10619_1

2026-07-23T06:53:59Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      }
    },
    "ellipse": {
```

```
        "majorAxis": 30,
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}
]
```

```
##### 2026-07-23T06:53:59Z #####
{
    "availableSpectrumInquiryResponses": [
        {
```

```
"response": {
  "responseCode": 0,
  "shortDescription": "SUCCESS"
},
"availableFrequencyInfo": [],
"availableChannelInfo": [],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T06:53:59Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

2026-07-23T07:32:53Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {

```

```
        "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
        "id": "QXO-AP3020"
      }
    ]
  },
  "location": {
    "indoorDeployment": 1
    "elevation": {
      "height": 154.9,
      "heightType": "AMSL",
      "verticalUncertainty": 66
    },
    "ellipse": {
      "majorAxis": 30,
      "minorAxis": 19,
      "orientation": 90.0,
      "center": {
        "latitude": 43.83956,
        "longitude": -79.3818
      }
    }
  },
  "inquiredFrequencyRange": [],
  "inquiredChannels": [
    {
      "globalOperatingClass": 131
    },
    {
      "globalOperatingClass": 132
    },
    {
      "globalOperatingClass": 133
    },
    {
      "globalOperatingClass": 134
    },
    {
```

```
        "globalOperatingClass": 137
      }
    ],
    "minDesiredPower": 0.0
  }
]
}
}
```

2026-07-23T07:32:54Z

```
{
  "availableSpectrumInquiryResponses": [
    {
      "response": {
        "responseCode": 0,
        "shortDescription": "SUCCESS"
      },
      "availableChannelInfo": [
        {
          "channelCfi": [
            1,
            5,
            9,
            13,
            81,
            85,
            89,
            93,
            129,
            133,
            137,
            141,
            145,
            149,
            153,
            157
          ],

```

```
"globalOperatingClass": 131,  
  "maxEirp": [  
    27.1,  
    32.0,  
    22.5,  
    22.7,  
    34.7,  
    25.9,  
    21.7,  
    33.4,  
    22.7,  
    33.3,  
    27.1,  
    26.1,  
    30.0,  
    33.2,  
    31.3,  
    28.8  
  ]  
},  
{  
  "channelCfi": [  
    3,  
    11,  
    83,  
    91,  
    131,  
    139,  
    147,  
    155  
  ],  
  "globalOperatingClass": 132,  
  "maxEirp": [  
    30.1,  
    25.5,  
    28.9,  
    24.7,
```

```
        25.7,
        29.1,
        33.0,
        31.8
    ]
},
{
    "channelCfi": [
        7,
        87,
        135,
        151
    ],
    "globalOperatingClass": 133,
    "maxEirp": [
        28.5,
        27.7,
        28.7,
        34.8
    ]
},
{
    "channelCfi": [
        143
    ],
    "globalOperatingClass": 134,
    "maxEirp": [
        31.7
    ]
},
{
    "channelCfi": [],
    "globalOperatingClass": 137,
    "maxEirp": []
}
],
"requestId": "WF122620W-50004",
```

```
"availabilityExpireTime": "2026-07-24T07:32:54Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

2026-07-23T07:37:54Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1
    }
  }
}
```

```
"elevation": {
  "height": 154.9,
  "heightType": "AMSL",
  "verticalUncertainty": 66
},
"ellipse": {
  "majorAxis": 30,
  "minorAxis": 19,
  "orientation": 90.0,
  "center": {
    "latitude": 43.83956,
    "longitude": -79.3818
  }
},
"inquiredFrequencyRange": [],
"inquiredChannels": [
  {
    "globalOperatingClass": 131
  },
  {
    "globalOperatingClass": 132
  },
  {
    "globalOperatingClass": 133
  },
  {
    "globalOperatingClass": 134
  },
  {
    "globalOperatingClass": 137
  }
],
"minDesiredPower": 0.0
}
]
```



```
}

##### 2026-07-23T07:37:54Z #####

{
  "availableSpectrumInquiryResponses": [
    {
      "response": {
        "responseCode": 0,
        "shortDescription": "SUCCESS"
      },
      "availableChannelInfo": [
        {
          "channelCfi": [
            17,
            21,
            25,
            29,
            33,
            37,
            41,
            45,
            49,
            53,
            57,
            61,
            65,
            69,
            73,
            77,
            161,
            165,
            169,
            173
          ],
          "globalOperatingClass": 131,
          "maxEirp": [
            21.9,
```

```
        31.4,  
        25.1,  
        29.9,  
        31.6,  
        34.5,  
        22.0,  
        32.0,  
        21.1,  
        27.5,  
        28.2,  
        23.4,  
        23.5,  
        33.5,  
        31.7,  
        24.6,  
        25.4,  
        32.0,  
        21.8,  
        32.5  
    ]  
},  
{  
    "channelCfi": [  
        19,  
        27,  
        35,  
        43,  
        51,  
        59,  
        67,  
        75,  
        163,  
        171  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        24.9,
```

```
        28.1,  
        34.6,  
        25.0,  
        24.1,  
        26.4,  
        26.5,  
        27.6,  
        28.4,  
        24.8  
    ]  
},  
{  
    "channelCfi": [  
        23,  
        39,  
        55,  
        71,  
        167  
    ],  
    "globalOperatingClass": 133,  
    "maxEirp": [  
        27.9,  
        28.0,  
        27.1,  
        29.5,  
        27.8  
    ]  
},  
{  
    "channelCfi": [  
        47  
    ],  
    "globalOperatingClass": 134,  
    "maxEirp": [  
        30.1  
    ]  
},
```

```
{
  {
    "channelCfi": [],
    "globalOperatingClass": 137,
    "maxEirp": []
  }
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T07:37:54Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

CT_AFC_SP_AP_AFCDSA31_Channel_80MHz_10620_1

2026-07-23T07:58:28Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      },
      "ellipse": {
```

```
        "majorAxis": 30,
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}

]

}

}

##### 2026-07-23T07:58:28Z #####
{
    "availableSpectrumInquiryResponses": [
        {
```

```
"response": {
  "responseCode": 0,
  "shortDescription": "SUCCESS"
},
"availableChannelInfo": [
  {
    "channelCfi": [
      17,
      21,
      25,
      29,
      33,
      37,
      41,
      45,
      129,
      133,
      137,
      141,
      145,
      149,
      153,
      157
    ],
    "globalOperatingClass": 131,
    "maxEirp": [
      22.8,
      33.9,
      31.7,
      32.9,
      26.4,
      27.8,
      22.6,
      22.5,
      33.3,
      34.5,
      27.7,
```

```
        26.5,  
        31.4,  
        25.3,  
        34.7,  
        27.1  
    ]  
},  
{  
    "channelCfi": [  
        19,  
        27,  
        35,  
        43,  
        131,  
        139,  
        147,  
        155  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        25.8,  
        34.7,  
        29.4,  
        25.5,  
        36.0,  
        29.5,  
        28.3,  
        30.1  
    ]  
},  
{  
    "channelCfi": [  
        23,  
        39,  
        135,  
        151  
    ],  
}
```

```
        "globalOperatingClass": 133,
        "maxEirp": [
            28.8,
            28.5,
            32.5,
            31.3
        ]
    },
    {
        "channelCfi": [
            143
        ],
        "globalOperatingClass": 134,
        "maxEirp": [
            34.3
        ]
    },
    {
        "channelCfi": [],
        "globalOperatingClass": 137,
        "maxEirp": []
    }
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T07:58:28Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

```
##### 2026-07-23T08:02:28Z #####
{
    "headers": {
        "Host": "testserver.wfatestorg.org",
        "Accept": "application/json",
        "Content-Type": "application/json",
```

```
"User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
"Accept-Encoding": "gzip,deflate",
"X-Forwarded-For": "192.168.1.169",
"X-Forwarded-Host": "testserver.wfatestorg.org",
"X-Forwarded-Server": "testserver.wfatestorg.org",
"Content-Length": "659",
"Connection": "Keep-Alive"
},
"body": {
  "version": "1.4",
  "availableSpectrumInquiryRequests": [
    {
      "requestId": "WF122620W-50004",
      "deviceDescriptor": {
        "serialNumber": "WF122620W-50004",
        "certificationId": [
          {
            "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
            "id": "QXO-AP3020"
          }
        ]
      }
    }
  ],
  "location": {
    "indoorDeployment": 1,
    "elevation": {
      "height": 154.9,
      "heightType": "AMSL",
      "verticalUncertainty": 66
    },
    "ellipse": {
      "majorAxis": 30,
      "minorAxis": 19,
      "orientation": 90.0,
      "center": {
        "latitude": 43.83956,
        "longitude": -79.3818
      }
    }
  }
}
```

```
    }
  },
  "inquiredFrequencyRange": [],
  "inquiredChannels": [
    {
      "globalOperatingClass": 131
    },
    {
      "globalOperatingClass": 132
    },
    {
      "globalOperatingClass": 133
    },
    {
      "globalOperatingClass": 134
    },
    {
      "globalOperatingClass": 137
    }
  ],
  "minDesiredPower": 0.0
}
]
```

```
##### 2026-07-23T08:02:29Z #####
{
  "availableSpectrumInquiryResponses": [
    {
      "response": {
        "responseCode": 0,
        "shortDescription": "SUCCESS"
      },
      "availableChannelInfo": [
        {
          "channelCfi": [
```

```
1,  
5,  
9,  
13,  
49,  
53,  
57,  
61,  
65,  
69,  
73,  
77,  
81,  
85,  
89,  
93,  
161,  
165,  
169,  
173  
],  
"globalOperatingClass": 131,  
"maxEirp": [  
28.0,  
33.8,  
21.6,  
31.7,  
27.4,  
24.3,  
32.8,  
34.0,  
32.3,  
24.3,  
29.6,  
24.1,  
31.7,  
24.6,
```

```
        31.9,
        34.9,
        27.5,
        29.1,
        32.7,
        29.4
    ]
},
{
    "channelCfi": [
        3,
        11,
        51,
        59,
        67,
        75,
        83,
        91,
        163,
        171
    ],
    "globalOperatingClass": 132,
    "maxEirp": [
        31.0,
        24.6,
        27.3,
        35.8,
        27.3,
        27.1,
        27.6,
        34.9,
        30.5,
        32.4
    ]
},
{
    "channelCfi": [
```

```
        7,  
        55,  
        71,  
        87,  
        167  
    ],  
    "globalOperatingClass": 133,  
    "maxEirp": [  
        27.6,  
        30.3,  
        30.1,  
        30.6,  
        33.5  
    ]  
},  
{  
    "channelCfi": [  
        79  
    ],  
    "globalOperatingClass": 134,  
    "maxEirp": [  
        33.1  
    ]  
},  
{  
    "channelCfi": [],  
    "globalOperatingClass": 137,  
    "maxEirp": []  
}  
],  
"requestId": "WF122620W-50004",  
"availabilityExpireTime": "2026-07-24T08:02:29Z",  
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"  
}  
],  
"version": "1.4"  
}
```

CT_AFC_SP_AP_AFCRSA31_Channel_160MHz_10621_1

2026-07-23T08:16:29Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      }
    }
  }
}
```

```
"ellipse": {
  "majorAxis": 30,
  "minorAxis": 19,
  "orientation": 90.0,
  "center": {
    "latitude": 43.83956,
    "longitude": -79.3818
  }
},
"inquiredFrequencyRange": [],
"inquiredChannels": [
  {
    "globalOperatingClass": 131
  },
  {
    "globalOperatingClass": 132
  },
  {
    "globalOperatingClass": 133
  },
  {
    "globalOperatingClass": 134
  },
  {
    "globalOperatingClass": 137
  }
],
"minDesiredPower": 0.0
}
]
```

2026-07-23T08:16:29Z

```
{
  "availableSpectrumInquiryResponses": [
```

```
{
  "response": {
    "responseCode": 0,
    "shortDescription": "SUCCESS"
  },
  "availableChannelInfo": [
    {
      "channelCfi": [
        1,
        5,
        9,
        13,
        17,
        21,
        25,
        29,
        129,
        133,
        137,
        141,
        145,
        149,
        153,
        157
      ],
      "globalOperatingClass": 131,
      "maxEirp": [
        24.0,
        25.2,
        23.4,
        27.7,
        21.8,
        27.6,
        27.7,
        26.7,
        29.8,
        32.8,
```

```
        30.6,  
        30.3,  
        34.9,  
        26.4,  
        30.4,  
        29.8  
    ]  
},  
{  
    "channelCfi": [  
        3,  
        11,  
        19,  
        27,  
        131,  
        139,  
        147,  
        155  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        27.0,  
        26.4,  
        24.8,  
        29.7,  
        32.8,  
        33.3,  
        29.4,  
        32.8  
    ]  
},  
{  
    "channelCfi": [  
        7,  
        23,  
        135,  
        151
```

```
    ],
    "globalOperatingClass": 133,
    "maxEirp": [
        29.4,
        27.8,
        35.8,
        32.4
    ]
},
{
    "channelCfi": [
        15,
        143
    ],
    "globalOperatingClass": 134,
    "maxEirp": [
        30.8,
        35.4
    ]
},
{
    "channelCfi": [],
    "globalOperatingClass": 137,
    "maxEirp": []
}
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T08:16:29Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

2026-07-23T08:29:15Z

```
{
    "headers": {
```

```
"Host": "testserver.wfatestorg.org",
"Accept": "application/json",
"Content-Type": "application/json",
"User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
"Accept-Encoding": "gzip,deflate",
"X-Forwarded-For": "192.168.1.169",
"X-Forwarded-Host": "testserver.wfatestorg.org",
"X-Forwarded-Server": "testserver.wfatestorg.org",
"Content-Length": "659",
"Connection": "Keep-Alive"
},
"body": {
  "version": "1.4",
  "availableSpectrumInquiryRequests": [
    {
      "requestId": "WF122620W-50004",
      "deviceDescriptor": {
        "serialNumber": "WF122620W-50004",
        "certificationId": [
          {
            "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
            "id": "QXO-AP3020"
          }
        ]
      }
    }
  ],
  "location": {
    "indoorDeployment": 1,
    "elevation": {
      "height": 154.9,
      "heightType": "AMSL",
      "verticalUncertainty": 66
    }
  },
  "ellipse": {
    "majorAxis": 30,
    "minorAxis": 19,
    "orientation": 90.0,
    "center": {
```

```
        "latitude": 43.83956,
        "longitude": -79.3818
    }
}
},
"inquiredFrequencyRange": [],
"inquiredChannels": [
    {
        "globalOperatingClass": 131
    },
    {
        "globalOperatingClass": 132
    },
    {
        "globalOperatingClass": 133
    },
    {
        "globalOperatingClass": 134
    },
    {
        "globalOperatingClass": 137
    }
],
"minDesiredPower": 0.0
}
]
}
}

##### 2026-07-23T08:29:15Z #####
{
    "availableSpectrumInquiryResponses": [
        {
            "response": {
                "responseCode": 0,
                "shortDescription": "SUCCESS"
            },
        }
    ]
}
```

```
"availableChannelInfo": [  
  {  
    "channelCfi": [  
      33,  
      37,  
      41,  
      45,  
      49,  
      53,  
      57,  
      61,  
      65,  
      69,  
      73,  
      77,  
      81,  
      85,  
      89,  
      93  
    ],  
    "globalOperatingClass": 131,  
    "maxEirp": [  
      26.1,  
      28.8,  
      25.6,  
      21.2,  
      22.3,  
      31.1,  
      27.3,  
      30.0,  
      21.3,  
      29.0,  
      21.9,  
      26.2,  
      24.0,  
      34.7,  
      24.0,  
    ]  
  }  
]
```

```
27.0
]
},
{
  "channelCfi": [
    35,
    43,
    51,
    59,
    67,
    75,
    83,
    91
  ],
  "globalOperatingClass": 132,
  "maxEirp": [
    29.1,
    24.2,
    25.3,
    30.3,
    24.3,
    24.9,
    27.0,
    27.0
  ]
},
{
  "channelCfi": [
    39,
    55,
    71,
    87
  ],
  "globalOperatingClass": 133,
  "maxEirp": [
    27.2,
    28.3,
```

```
        27.3,
        30.0
    ]
},
{
    "channelCfi": [
        47,
        79
    ],
    "globalOperatingClass": 134,
    "maxEirp": [
        30.2,
        30.3
    ]
},
{
    "channelCfi": [
        63
    ],
    "globalOperatingClass": 137,
    "maxEirp": [
        33.3
    ]
}
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T08:29:15Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

CT_AFC_SP_AP_AFCDUSA32_Channel_10622_1

2026-07-27T03:09:24Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      }
    },
    "ellipse": {
```

```
        "majorAxis": 30,
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}

]

}

}

##### 2026-07-27T03:09:24Z #####
{
    "availableSpectrumInquiryResponses": [
        {
```

```
"response": {
  "responseCode": 0,
  "shortDescription": "SUCCESS"
},
"availableChannelInfo": [],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-28T03:09:24Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

CT_AFC_SP_AP_AFCDSAU33_Channel_10623_1

2026-07-27T05:38:44Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      },
      "ellipse": {
```

```
        "majorAxis": 30,
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}

]

}

}

##### 2026-07-27T05:38:44Z #####
{
    "availableSpectrumInquiryResponses": [
        {
```

```
"response": {
  "responseCode": 0,
  "shortDescription": "SUCCESS"
},
"availableChannelInfo": [
  {
    "channelCfi": [
      33,
      37,
      41,
      45,
      49,
      53,
      57,
      61,
      65,
      69,
      73,
      77,
      145,
      149,
      153,
      157
    ],
    "globalOperatingClass": 131,
    "maxEirp": [
      29.4,
      26.7,
      32.5,
      21.5,
      23.9,
      29.5,
      26.0,
      33.5,
      26.2,
      29.7,
      34.5,
```

```
        34.9,
        33.4,
        22.6,
        33.5,
        26.8
    ]
},
{
    "channelCfi": [
        35,
        43,
        51,
        59,
        67,
        75,
        147,
        155
    ],
    "globalOperatingClass": 132,
    "maxEirp": [
        29.7,
        24.5,
        26.9,
        29.0,
        29.2,
        36.0,
        25.6,
        29.8
    ]
},
{
    "channelCfi": [
        39,
        55,
        71,
        151
    ],
    ],
```

```
        "globalOperatingClass": 133,
        "maxEirp": [
            27.5,
            29.9,
            32.2,
            28.6
        ]
    },
    {
        "channelCfi": [
            47
        ],
        "globalOperatingClass": 134,
        "maxEirp": [
            30.5
        ]
    },
    {
        "channelCfi": [],
        "globalOperatingClass": 137,
        "maxEirp": []
    }
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-28T05:38:44Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

CT_AFC_SP_AP_AFCDUUAU34_Channel_10624_1

2026-07-27T05:56:19Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      },
      "ellipse": {
```

```
        "majorAxis": 30,
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}

]

}

}

##### 2026-07-27T05:56:19Z #####
{
    "availableSpectrumInquiryResponses": [
        {
```

```
"response": {  
  "responseCode": 0,  
  "shortDescription": "SUCCESS"  
},  
"availableChannelInfo": [  
  {  
    "channelCfi": [  
      1,  
      5,  
      9,  
      13,  
      17,  
      21,  
      25,  
      29,  
      33,  
      37,  
      41,  
      45,  
      49,  
      53,  
      57,  
      61,  
      65,  
      69,  
      73,  
      77,  
      81,  
      85,  
      89,  
      93,  
      117,  
      121,  
      125,  
      129,  
      133,  
      137,
```

[illegible]

```
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0  
    ]  
},  
{  
    "channelCfi": [  
        3,  
        11,  
        19,  
        27,  
        35,  
        43,  
        51,  
        59,  
        67,  
        75,  
        83,  
        91,  
        123,  
        131,  
        139,
```

```
    147,  
    155,  
    163,  
    171,  
    179  
],  
"globalOperatingClass": 132,  
"maxEirp": [  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0,  
    36.0  
]  
},  
{  
    "channelCfi": [  
        7,  
        23,  
        39,  
        55,  
        71,
```

```
        87,  
        135,  
        151,  
        167  
    ],  
    "globalOperatingClass": 133,  
    "maxEirp": [  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0,  
        36.0  
    ]  
},  
{  
    "channelCfi": [  
        15,  
        47,  
        79,  
        143  
    ],  
    "globalOperatingClass": 134,  
    "maxEirp": [  
        36.0,  
        36.0,  
        36.0,  
        36.0  
    ]  
},  
{  
    "channelCfi": [  
        31  
    ],  
}
```

```
        "globalOperatingClass": 137,  
        "maxEirp": [  
            36.0  
        ]  
    }  
],  
    "requestId": "WF122620W-50004",  
    "availabilityExpireTime": "2026-07-28T05:56:19Z",  
    "rulesetId": "US_47_CFR_PART_15_SUBPART_E"  
}  
],  
    "version": "1.4"  
}
```

CT_AFC_SP_AP_AFCDSA31_Channel_320MHz_10714_1

2026-07-23T08:55:26Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      },
      "ellipse": {
```

```
        "majorAxis": 30,
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}

]

}

}

##### 2026-07-23T08:55:26Z #####
{
    "availableSpectrumInquiryResponses": [
        {
```

```
"response": {
  "responseCode": 0,
  "shortDescription": "SUCCESS"
},
"availableChannelInfo": [
  {
    "channelCfi": [
      33,
      37,
      41,
      45,
      49,
      53,
      57,
      61,
      65,
      69,
      73,
      77,
      81,
      85,
      89,
      93
    ],
    "globalOperatingClass": 131,
    "maxEirp": [
      24.5,
      26.0,
      24.1,
      22.9,
      23.0,
      27.7,
      21.8,
      26.5,
      35.8,
      35.0,
      29.2,
```

```
        30.9,  
        27.3,  
        30.2,  
        29.0,  
        28.7  
    ]  
},  
{  
    "channelCfi": [  
        35,  
        43,  
        51,  
        59,  
        67,  
        75,  
        83,  
        91  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        27.5,  
        25.9,  
        26.0,  
        24.8,  
        36.0,  
        32.2,  
        30.3,  
        31.7  
    ]  
},  
{  
    "channelCfi": [  
        39,  
        55,  
        71,  
        87  
    ],
```

```
"globalOperatingClass": 133,
  "maxEirp": [
    28.9,
    27.8,
    35.2,
    33.3
  ]
},
{
  "channelCfi": [
    47,
    79
  ],
  "globalOperatingClass": 134,
  "maxEirp": [
    30.8,
    36.0
  ]
},
{
  "channelCfi": [
    63
  ],
  "globalOperatingClass": 137,
  "maxEirp": [
    33.9
  ]
}
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T08:55:26Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

2026-07-23T08:57:10Z

```
{
  "headers": {
    "Host": "testserver.wfatestorg.org",
    "Accept": "application/json",
    "Content-Type": "application/json",
    "User-Agent": "Apache-HttpClient/4.5.6 (Java/1.8.0_472-internal)",
    "Accept-Encoding": "gzip,deflate",
    "X-Forwarded-For": "192.168.1.169",
    "X-Forwarded-Host": "testserver.wfatestorg.org",
    "X-Forwarded-Server": "testserver.wfatestorg.org",
    "Content-Length": "659",
    "Connection": "Keep-Alive"
  },
  "body": {
    "version": "1.4",
    "availableSpectrumInquiryRequests": [
      {
        "requestId": "WF122620W-50004",
        "deviceDescriptor": {
          "serialNumber": "WF122620W-50004",
          "certificationId": [
            {
              "rulesetId": "US_47_CFR_PART_15_SUBPART_E",
              "id": "QXO-AP3020"
            }
          ]
        }
      }
    ],
    "location": {
      "indoorDeployment": 1,
      "elevation": {
        "height": 154.9,
        "heightType": "AMSL",
        "verticalUncertainty": 66
      },
      "ellipse": {
        "majorAxis": 30,
```

```
        "minorAxis": 19,
        "orientation": 90.0,
        "center": {
            "latitude": 43.83956,
            "longitude": -79.3818
        }
    },
    "inquiredFrequencyRange": [],
    "inquiredChannels": [
        {
            "globalOperatingClass": 131
        },
        {
            "globalOperatingClass": 132
        },
        {
            "globalOperatingClass": 133
        },
        {
            "globalOperatingClass": 134
        },
        {
            "globalOperatingClass": 137
        }
    ],
    "minDesiredPower": 0.0
}
]
```

```
##### 2026-07-23T08:57:10Z #####
{
    "availableSpectrumInquiryResponses": [
        {
            "response": {
```

```
"responseCode": 0,
"shortDescription": "SUCCESS"
},
"availableChannelInfo": [
  {
    "channelCfi": [
      1,
      5,
      9,
      13,
      17,
      21,
      25,
      29,
      33,
      37,
      41,
      45,
      49,
      53,
      57,
      61
    ],
    "globalOperatingClass": 131,
    "maxEirp": [
      9.4,
      21.3,
      19.8,
      15.5,
      13.3,
      15.7,
      13.5,
      18.6,
      24.3,
      24.5,
      16.8,
      12.7,
```

```
        21.8,  
        13.2,  
        17.1,  
        8.9  
    ]  
},  
{  
    "channelCfi": [  
        3,  
        11,  
        19,  
        27,  
        35,  
        43,  
        51,  
        59  
    ],  
    "globalOperatingClass": 132,  
    "maxEirp": [  
        12.4,  
        18.5,  
        16.3,  
        16.5,  
        27.3,  
        15.7,  
        16.2,  
        11.9  
    ]  
},  
{  
    "channelCfi": [  
        7,  
        23,  
        39,  
        55  
    ],  
    "globalOperatingClass": 133,
```

```
        "maxEirp": [
            15.4,
            19.3,
            18.7,
            14.9
        ]
    },
    {
        "channelCfi": [
            15,
            47
        ],
        "globalOperatingClass": 134,
        "maxEirp": [
            18.4,
            17.9
        ]
    },
    {
        "channelCfi": [
            31
        ],
        "globalOperatingClass": 137,
        "maxEirp": [
            21.0a
        ]
    }
],
"requestId": "WF122620W-50004",
"availabilityExpireTime": "2026-07-24T08:57:10Z",
"rulesetId": "US_47_CFR_PART_15_SUBPART_E"
}
],
"version": "1.4"
}
```

AFC capability - Inquired Channel
AFCD.RSA: Successful registration and spectrum access request

Freq. (MHz)	Mode (LPI or SP)	Bandwidth (MHz)	Antenna Gain (dBi)	Power (dBm)	EIRP (dBm)	AFC Response Limit (dBm)	Result	PSD (dBm/MHz)	EIRP PSD (dBm/MHz)	AFC Response Limit (dBm/MHz)	Result
5975	LPI	20	3.97	13.23	17.20	-	N/A	-0.19	3.78	5.00	Pass
6375	SP	20	3.97	18.32	22.29	34.70	Pass	4.62	8.59	-	N/A
6135	SP	20	3.97	11.32	15.29	23.60	Pass	-2.21	1.76	-	N/A
6605	LPI	40	3.14	14.85	17.99	-	N/A	-1.55	1.59	5.00	Pass
6605	SP	40	3.14	13.68	16.82	25.70	Pass	-2.82	0.32	-	N/A
6205	SP	40	3.97	13.73	17.70	24.10	Pass	-2.78	1.19	-	N/A
5985	LPI	80	3.97	13.90	17.87	-	N/A	-4.89	-0.92	5.00	Pass
6145	SP	80	3.97	15.70	19.67	28.50	Pass	-3.73	0.24	-	N/A
6385	SP	80	3.97	18.36	22.33	30.60	Pass	-0.77	3.20	-	N/A
6345	LPI	160	3.97	16.60	20.57	-	N/A	-5.54	-1.57	5.00	Pass
6665	SP	160	3.14	14.89	18.03	35.40	Pass	-6.87	-3.73	-	N/A
6185	SP	160	3.97	15.39	19.36	30.20	Pass	-6.95	-2.98	-	N/A
6105	LPI	320	3.97	14.95	18.92	-	N/A	-9.75	-5.78	5.00	Pass
6265	OFF*	320	3.97	-	-	35.00	Pass	-	-	-	N/A
6105	SP	320	3.97	10.26	14.23	21.00	Pass	-14.33	-10.36	-	N/A

Note: Operation mode"*" : The product only supports 320MHz Channel 31 (6105MHz). When the AFC response indicates that the Channel is unusable, the radio will be off.

AFCD.USA: Unsuccessful spectrum access request

Freq. (MHz)	Mode (LPI or SP)	Bandwidth (MHz)	Antenna Gain (dBi)	Power (dBm)	EIRP (dBm)	AFC Response Limit (dBm)	Result	PSD (dBm/MHz)	EIRP PSD (dBm/MHz)	AFC Response Limit (dBm/MHz)	Result
5975	LPI	20	3.97	12.84	16.81	-	N/A	-0.08	3.89	5.00	Pass
-	OFF	20	3.97	-	-	-	N/A	-	-	5.00	Pass

AFCD.SAU: Successful spectrum access update

Freq. (MHz)	Mode (LPI or SP)	Bandwidth (MHz)	Antenna Gain (dBi)	Power (dBm)	EIRP (dBm)	AFC Response Limit (dBm)	Result	PSD (dBm/MHz)	EIRP PSD (dBm/MHz)	AFC Response Limit (dBm/MHz)	Result
5975	LPI	20	3.97	12.77	16.74	-	N/A	-0.15	3.82	5.00	Pass
6215	SP	20	3.97	14.37	18.34	29.50	Pass	1.27	5.24	-	N/A
6215	LPI	20	3.97	12.76	16.73	-	N/A	-0.44	3.53	5.00	Pass

AFCD.UAU: Unsuccessful spectrum access update

Freq. (MHz)	Mode (LPI or SP)	Bandwidth (MHz)	Antenna Gain (dBi)	Power (dBm)	EIRP (dBm)	AFC Response Limit (dBm)	Result	PSD (dBm/MHz)	EIRP PSD (dBm/MHz)	AFC Response Limit (dBm/MHz)	Result
6215	LPI	20	3.97	12.81	16.78	-	N/A	-0.42	3.55	5.00	Pass
6375	SP	20	3.97	14.15	18.12	36.00	Pass	1.13	5.10	-	N/A
6375	LPI	20	3.97	12.70	16.67	-	N/A	-0.63	3.34	5.00	Pass

AFC capability - Inquired Channel

CT_AFC_SP_AP_AFCRSA31_Channel_20MHz_10618_1


Frequency (MHz): 5975

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

5975MHz_TX

23/07/2026




5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6375MHz_TX

23/07/2026



Frequency (MHz): 6375

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6375MHz_TX

23/07/2026

CF (Hz)
6.375G

Span (Hz)
30M


RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
20M



Sum=Total Power
PX=Port X

Port 1

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6375MHz

23/07/2026

CF (Hz)
6.375G


Span (Hz)
30M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1


Frequency (MHz): 6135

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6135MHz_TX

23/07/2026




5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6135MHz

23/07/2026



Sum	PD	Port 1
(dBm/Hz)	(dBm/Hz)	(dBm/Hz)
-2.21	-2.21	-2.21

CT_AFC_SP_AP_AFCRSA31_Channel_40MHz_10619_1

Frequency (MHz): 6605

6.525-6.875GHz_802.11be EHT40_Nss1,(MCS0)_1TX


AV Power

6605MHz_TX

23/07/2026

CF (Hz)
6.605G
Span (Hz)
60M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS
CP BW (Hz)
40M

Sum=Total Power
PX=Port X



Port 1

Sum(dBm)	P1(dBm)
14.85	14.85


6.525-6.875GHz_802.11be EHT40_Nss1,(MCS0)_1TX

PSD

6605MHz

23/07/2026

CF (Hz)
6.605G
Span (Hz)
60M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS



Port 1

Sum (dBm/Hz)	PD (dBm/Hz)	Port 1 (dBm/Hz)
-1.55	-1.55	-1.55

Frequency (MHz): 6605

6.525-6.875GHz_802.11be EHT40_Nss1,(MCS0)_1TX

AV Power

6605MHz_TX

23/07/2026

CF (Hz)
6.605G

Span (Hz)
60M


RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
40M



Port 1

Sum=Total Power
PX=Port X

Sum(dBm)	P1(dBm)
13.68	13.68

6.525-6.875GHz_802.11be EHT40_Nss1,(MCS0)_1TX

PSD

6605MHz

23/07/2026

CF (Hz)
6.605G


Span (Hz)
60M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum (dBm/Hz)	PD (dBm/Hz)	Port 1 (dBm/Hz)
-2.82	-2.82	-2.82

Frequency (MHz): 6205

5.925-6.425GHz_802.11be EHT40_Nss1,(MCS0)_1TX


AV Power

6205MHz_TX

23/07/2026

CF (Hz)
6.205G
Span (Hz)
60M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS
CP BW (Hz)
40M

Sum=Total Power
PX=Port X



Sum(dBm)	P1(dBm)
13.73	13.73


5.925-6.425GHz_802.11be EHT40_Nss1,(MCS0)_1TX

PSD

6205MHz

23/07/2026

CF (Hz)
6.205G
Span (Hz)
60M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS



Sum (dBm/Hz)	PD (dBm/Hz)	Port 1 (dBm/Hz)
-2.78	-2.78	-2.78

CT_AFC_SP_AP_AFCRSA31_Channel_80MHz_10620_1

Frequency (MHz): 5985

5.925-6.425GHz_802.11be EHT80_Nss1,(MCS0)_1TX

AV Power

5985MHz_TX

23/07/2026

CF (Hz)
5.985G

Span (Hz)
120M

RBW (Hz)
1M


VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
80M

Sum=Total Power
PX=Port X



Port 1

Sum(dBm)	P1(dBm)
13.90	13.90

5.925-6.425GHz_802.11be EHT80_Nss1,(MCS0)_1TX

PSD

5985MHz

23/07/2026

CF (Hz)
5.985G


Span (Hz)
120M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum	PD	Port 1
(dBm/RBW)	(dBm/RBW)	(dBm/RBW)
-4.89	-4.89	-4.89


Frequency (MHz): 6145

5.925-6.425GHz_802.11be EHT80_Nss1,(MCS0)_1TX

AV Power

6145MHz_TX

23/07/2026




5.925-6.425GHz_802.11be EHT80_Nss1,(MCS0)_1TX

PSD

6145MHz

23/07/2026



Frequency (MHz): 6385

5.925-6.425GHz_802.11be EHT80_Nss1,(MCS0)_1TX


AV Power

6385MHz_TX

23/07/2026

CF (Hz)
6.385G
Span (Hz)
120M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS
CP BW (Hz)
80M

Sum=Total Power
PX=Port X



Port 1

Sum(dBm)	P1(dBm)
18.36	18.36


5.925-6.425GHz_802.11be EHT80_Nss1,(MCS0)_1TX

PSD

6385MHz

23/07/2026

CF (Hz)
6.385G
Span (Hz)
120M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS



Port 1

Sum	PD	Port 1
(dBm/RBW)	(dBm/RBW)	(dBm/RBW)
-0.77	-0.77	-0.77

CT_AFC_SP_AP_AFCDRSA31_Channel_160MHz_10621_1

Frequency (MHz): 6345

5.925-6.425GHz_802.11be EHT160_Nss1,(MCS0)_1TX


AV Power

6345MHz_TX

23/07/2026

CF (Hz)
6.345G
Span (Hz)
240M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS
CP BW (Hz)
160M

Sum=Total Power
PX=Port X



Port 1

Sum(dBm)	P1(dBm)
16.60	16.60


5.925-6.425GHz_802.11be EHT160_Nss1,(MCS0)_1TX

PSD

6345MHz

23/07/2026

CF (Hz)
6.345G
Span (Hz)
240M
RBW (Hz)
1M
VBW (Hz)
3M
Sweep Time (s)
20m
Detector Type
RMS



Port 1

Sum (dBm/RBW)	PD (dBm/RBW)	Port 1 (dBm/RBW)
-5.54	-5.54	-5.54


Frequency (MHz): 6665

6.525-6.875GHz_802.11be EHT160_Nss1,(MCS0)_1TX

AV Power

6665MHz_TX

23/07/2026




6.525-6.875GHz_802.11be EHT160_Nss1,(MCS0)_1TX

PSD

6665MHz

23/07/2026



Sum	PD	Port 1
(dBm/RBW)	(dBm/RBW)	(dBm/RBW)
-6.87	-6.87	-6.87

Frequency (MHz): 6185

5.925-6.425GHz_802.11be EHT160_Nss1,(MCS0)_1TX

AV Power

6185MHz_TX

23/07/2026

CF (Hz)
6.185G

Span (Hz)
240M

RBW (Hz)
1M


VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
160M

Sum=Total Power
PX=Port X



Port 1

Sum(dBm)	P1(dBm)
15.39	15.39

5.925-6.425GHz_802.11be EHT160_Nss1,(MCS0)_1TX

PSD

6185MHz

23/07/2026

CF (Hz)
6.185G


Span (Hz)
240M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum	PD	Port 1
(dBm/RBW)	(dBm/RBW)	(dBm/RBW)
-6.95	-6.95	-6.95

CT_AFC_SP_AP_AFCDRSA31_Channel_320MHz_10714_1

Bandwidth: 320MHz

Frequency (MHz): 6105

5.925-6.425GHz_802.11be EHT320_Nss1,(MCS0)_1TX

AV Power

6105MHz_TX

23/07/2026

CF (Hz)
6.105G

Span (Hz)
480M


RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
320M



Port 1

Sum=Total Power
PX=Port X

Sum(dBm)	P1(dBm)
14.95	14.95

5.925-6.425GHz_802.11be EHT320_Nss1,(MCS0)_1TX

PSD

6105MHz

23/07/2026

CF (Hz)
6.105G


Span (Hz)
480M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum	PD	Port 1
(dBm/RBW)	(dBm/RBW)	(dBm/RBW)
-9.75	-9.75	-9.75



CT_AFC_SP_AP_AFCDUSA32_Channel_10622_1

Bandwidth: 20MHz

Frequency (MHz): 5975

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

5975MHz_TX

27/07/2026

CF (Hz)
5.975G

Span (Hz)
30M

RBW (Hz)
1M


VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
20M

Sum=Total Power
PX=Port X



Port 1

Sum(dBm)	P1(dBm)
12.84	12.84

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

5975MHz

27/07/2026

CF (Hz)
5.975G


Span (Hz)
30M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum	PD	Port 1
(dBm/Hz)	(dBm/Hz)	(dBm/Hz)
-0.08	-0.08	-0.08

CT_AFC_SP_AP_AFCDSAU33_Channel_10623_1

Bandwidth: 20MHz

Frequency (MHz): 5975

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

5975MHz_TX

27/07/2026

CF (Hz)
5.975G

Span (Hz)
30M


RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
20M



Port 1

Sum=Total Power
PX=Port X

Sum(dBm)	P1(dBm)
12.77	12.77

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

5975MHz

27/07/2026

CF (Hz)
5.975G


Span (Hz)
30M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum (dBm/RBW)	PD (dBm/RBW)	Port 1 (dBm/RBW)
-0.15	-0.15	-0.15

Frequency (MHz): 6215

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6215MHz_TX

27/07/2026

CF (Hz)
6.215G

Span (Hz)
30M


RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
20M



Port 1

Sum=Total Power
PX=Port X

Sum(dBm)	P1(dBm)
14.37	14.37

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6215MHz

27/07/2026

CF (Hz)
6.215G


Span (Hz)
30M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum (dBm/RBW)	PD (dBm/RBW)	Port 1 (dBm/RBW)
1.27	1.27	1.27


Frequency (MHz): 6215

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6215MHz_TX

27/07/2026




5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6215MHz

27/07/2026



CT_AFC_SP_AP_AFCDUAU34_Channel_10624_1

Bandwidth: 20MHz


Frequency (MHz): 6215

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6215MHz_TX

27/07/2026




5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6215MHz

27/07/2026



Frequency (MHz): 6375

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6375MHz_TX

27/07/2026

CF (Hz)
6.375G

Span (Hz)
30M


RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS

CP BW (Hz)
20M



Port 1

Sum=Total Power
PX=Port X

Sum(dBm)	P1(dBm)
14.15	14.15

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6375MHz

27/07/2026

CF (Hz)
6.375G


Span (Hz)
30M

RBW (Hz)
1M

VBW (Hz)
3M

Sweep Time (s)
20m

Detector Type
RMS



Port 1

Sum (dBm/RBW)	PD (dBm/RBW)	Port 1 (dBm/RBW)
1.13	1.13	1.13


Frequency (MHz): 6375

5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

AV Power

6375MHz_TX

27/07/2026




5.925-6.425GHz_802.11be EHT20_Nss1,(MCS0)_1TX

PSD

6375MHz


27/07/2026



Duty Cycle

Bandwidth: 20MHz


DC;be20;BWch:20



Ch Freq (Hz)	RBW (Hz)	VBW (Hz)	Sweep Time (s)	Total Sample	Sample Time (s)	TX Time (s)	DC
5.975G	10M	10M	100m	32001	3.125u	91.990625m	0.92

Bandwidth: 40MHz


DC;be40;BWch:40



Ch Freq (Hz)	RBW (Hz)	VBW (Hz)	Sweep Time (s)	Total Sample	Sample Time (s)	TX Time (s)	DC
6.605G	10M	10M	100m	32001	3.125u	92.4m	0.924


Bandwidth: 80MHz

DC;be80;BWch:80




Bandwidth: 160MHz

DC;be160;BWch:160



Bandwidth: 320MHz

DC;be320;BWch:320



Ch Freq (Hz)	RBW (Hz)	VBW (Hz)	Sweep Time (s)	Total Sample	Sample Time (s)	TX Time (s)	DC
6.105G	10M	10M	100m	32001	3.125u	85.8875m	0.859

————THE END————