BTW-301

Operation Manual

Introduction

The BTW-301 is a portable Bluetooth headset solution based on Bluetooth wireless technology which propels you into a new dimension in connectivity. The technology offers fast and reliable transmission of voice and data information between compatible devices.

Bluetooth

The package

1-Bluetooth headset
2-The charger
3-Operation manual

Headset Overview



1-Charging connector
2-Call handling button
3-Indicator light
4-Volume up
5-Volume down
6-Ear hook
7-Speaker
8-Microphone

Getting started

Before use your headset, you must first:
1.Charge the headset battery with our charger.
2.Pair the headset with your mobile phone.

A.Mount The Ear Hook

1.Adjust the ear hook to the position to fit the headset ear hook clip. Mount the ear hook to the phone. See figure 1 and 2.
2.Turn the ear hook clockwise to the degree you prefer. See figure 3 and 4.

(Figure 1)

(Figure 3)

(Figure 2)

(Figure 4)

B.Remove The Ear Hook

3.Turn the ear hook counterclockwise to remove the ear hook. See Figure 5 to 8.

(Figure 5)

(Figure 7)

(Figure 6)

(Figure 8)

C.Adjust The Curve of The Ear Hook

4.Place the ear hook on the table. Lift up the end of the ear hook upward to the angle you prefer. The angle should not be more than 70 degree to avoid the breakage. See Figure 9 and 10.
5.You can lift up the end of ear hook upward &inward to make it smaller for the user who has smaller ear.
6.Do not lift up the ear hook outward. See Figure 11.

(Figure 9)

(Figure 11)

(Figure 10)


(Figure 12)

Charging the battery

The headset comes with a built-in rechargeable battery. When the battery is low, the indicator light flashes red slowly. During the charging, the indicator light shows a steady red light. When the battery is fully charged, the indicator is off.
Please note: The headset is in none-working status while being charged.

To charge the battery

1.Connect the charger to the headset and to the mains.
2.It takes about 3 hours to fully recharge the battery. (It takes at least 8 hours for the first time charging)
3.Disconnect the charger from the headset and the mains when the charging is completed.

Using the headset

Once the headset has been paired with your phone, you can make and receive calls using the headset as long as it is turned on and within the range of the phone – up to 10m (30ft) outdoors or up to 5m (15ft) indoors with no solid objects in between.

Pairing

1.Prepare your phone according to the phone`s user documentation on bluetooth pairing.
2.When the headset is off, press the call handling button for up to 10 seconds until the indicator light on the headset flashes green and red. The headset is now ready for pairing.
3.Continue according to the phone`s user documentation. The passkey for our headset is 1234.

To turn the headset on

Press and hold the call-handling button until you see the indicator light flashes green.

To turn the headset off

When the headset is on, press and hold the call-handling button until the indicator light is off. The indicator light flashes red for 5 time before being off.

Making and answering phone calls

Phone functionality is still available when the headset is connected. You can make and answer the calls using the buttons on the headset. End the call by pressing the call handling button in the middle of a call. If you use the keys on the phone to answer the calls, you will have to take this call from the phone rather than the headset.

Adjust the volume

You can adjust the headset speaker volume during a call.
To increase the volume, press +.
To decrease the volume, press -.

Using voice commands

You will be able to use this function through the headset only if your mobile phone supports voice dialing. Press and hold the call handling button for 2 seconds in standby mode, and your mobile phone will be ready for your voice commands.

PLEASE NOTE:

The warranty will be invalid, if fail to follow the operation manual.

The specification

Standard	Bluetooth 1.1 specification
Range (free space)	10 meters
Frequency Band	2.4GHz~2.4835GHz ISM Band
Connection	Point-to-point
Weight	<25g (including battery)
Speaker	85±3dB
Talk time	Upto 4 hr
Standby time	Upto 120 hr
Output Power	0 dBm (class II)
Power Consumption	30mA(working) ; <1mA(standby)
Battery	Rechargeable Li-ion polymer 150mAh
Charging	6VDC , 100~240VAC adapter
Charging time	2h~3h
Operating Temperature	-10°C ~ 55°C
Storage Temperature	-20°C ~ 60°C
Humidity	10% ~ 90%
Certification Approval	CE , FCC , BQB

Federal Communications Commission (FCC) Statement:

15.21
You are cautioned that changes or modifications not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.

15.105(b)
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.
You are cautioned that changes or modifications not expressly approved by the party responsible for compliance could void your authority to operate the equipment.

FCC RF Radiation Exposure Statement:

This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.