

HiFi | three proofing Bluetooth speakers User's Manual

model you choose or does not match the list of goods and accessories in the box, Please promptly contact Lumsing customer service .



1

① A speaker



2

③ micro-USB charging cable a



3



② 3.5 mm audio line



4

④ User's Manual

Product Features view:



- ① Play / Pause
- ② Volume plus
- ③ volume down
- ④ answer / end
- ⑤ Power indicator
- ⑥ microphone hole
- ⑦ Working lights
- ⑧ USB charging interface
- ⑨ AUX jack
- ⑩ On / Off

Buttons Description

The product is equipped with five buttons:  / switch ;  / volume increase ;  / volume down ;  / play / pause ;  / answer / hang up.

-  Press 2 seconds, it can be achieved on / off function .
-  Short press volume button  plus one, long press volume button  plus volume continuously. (Volume up to the maximum will be prompted to "Maximum Volume")
-  Short press volume button  minus one, a long press volume button  minus volume continuously.
-  In Bluetooth mode, press Play / Pause, press 1-2 seconds off the existing Bluetooth connection and pairing status, long press more than two seconds after clearing the internal Bluetooth connection Bluetooth and accompanied by a list of "beep" tips. In AUX mode this key non-functional operation.
-  Short press to answer an incoming call while long press to hang up.

Parameters

Power : 4W (RMS)	SNR : $\geq 70\text{dB}$	Distortion : $\leq 0.5\%$ @ 1W
Battery capacity : 3.7V/1000mAh	Working hours : $\geq 8\text{h}$ (vary with volume and music)	Frequency Response : 100Hz ~ 20KHz
Speaker : 2-3Ω	Bluetooth Version: 4.0	Bluetooth transmission distance : $\geq 10\text{m}$
Size : W80 × H81 × D83mm	Charging voltage : DC5V, $\geq 500\text{mA}$	

Product Features

- 🔊 1: CS R Bluetooth 4.0
Provides links to distance $\geq 10\text{m}$
- 🎧 2 : stereo amplifier and dual voice coil speakers
Stereo amplifier system and dual voice coil speaker design, sound more realistic \ stable ;
- 🔋 3 : Large capacity battery
Built- in rechargeable lithium battery 3.7V/1000mAh,it can provide ≥ 8 hours playback time (vary with volume and music)
- 🛡️ 4 : Three anti-function
This product protection grade IP64, effectively prevent liquid \ dust from entering the body, and prevent damage caused by fall.
- 🗣️ 5 : Intelligent Voice Prompt
Built-in intelligent voice prompt operation, the operation is convenient

Product description

on / off : Press the key to open the bottom of the speaker , you will be remind boot \ Shutdown

Indicator: red and blue LED lights for working mode indicator, red and green LED lights for power and charging indicator

Bluetooth connectivity: Bluetooth pairing status after boot into the blue LED light has been flashing, the Bluetooth product called "MM526", search for other Bluetooth devices, generally do not need to enter a password to connect , if you need a password please enter "0000 ." There will appear after successful pairing "Bluetooth connection" voice prompts, and blue LED lights lit . After the power turned on within 10 minutes, it doesn't search any device and it will automatically shut down. Reboot is required to connect again. This machine has a back-linking feature, the device will automatically connect after a successful turn on the Bluetooth connection again.

Tips: If the connection fails, please restart or shutdown or battery may be low, please charge.

Bluetooth music playback: After a successful connection, the product can play music in the mobile phone, computer or other Bluetooth devices during playback, you can use the play / pause / volume up / volume down three buttons to control playback. The " Bluetooth connection" voice prompts and the long bright blue LED lights, long button ▶⏸ for 1-2 seconds then disconnect the Bluetooth speaker connection, then other Bluetooth devices can be paired to search for the product, if the length of pressing the key ▶⏸ is greater than 2 seconds , then Bluetooth connection and a " beep" tone , which means that the internal Bluetooth pairing list has been cleared , then shut

down and then boot without back -linking function. To be repaired to search and select the connection.

Bluetooth phone: After successfully paired with a Bluetooth phone when there is an incoming call, just press  to answer the call and you can talk with each other instead of bringing the phone , and then long press  hang up the phone to end the call.

AUX audio playback: The accessory audio cable were inserted into the speaker AUX audio input interface , such as a music player and computer audio jack , Bluetooth function will automatically disconnect , blue LED light off red LED lights on for long time, when they heard " external player " after the tone, enter AUX mode.

Battery indicator and charging: In the normal voltage, the power indicator will not lit. When the battery is low, the red power light flashes; When charging, the green power light flashes; when charge to full power , green power indicator light on.

Precautions

In order to properly use the product and ensure good performance, please carefully read and follow below:

- 1 . Keep and use the product at normal temperature environment;

- 2 . Do not severely impact the mainframe;
- 3 . In order to prolong the life of the product , do not frequently switch on, switch off the machine at an interval of at least 5 seconds ;If happens staccato , pauses and similar problem when the product is connected with the Bluetooth device to play music , adjust the orientation and avoid obstacles ;
4. When playing music , use the built-in player in the computer or other portable device, it may not use the Bluetooth audio play / pause function ;
5. electricity shortage will affect the distance or Bluetooth is easy to disconnect , please charge ; and after the Bluetooth device disconnected , wait 20 seconds (two Bluetooth devices stop responding) , before reconnecting ;
6. Bluetooth module of this product can control most Bluetooth devices , individual brands Bluetooth devices cannot been controlled, the connection must be set manually ;
7. When using a computer connected to the headphone output AUX input, appropriate to reduce the volume of your computer in order to avoid serious distortion of the speaker (audio output amplitude is relatively large computers, pay attention to other cases in the same situation) ;
- 8 .Before use this new products, you can use the supplied USB cable to charge the machine and make sure that

charge for more than 10 hours. Make sure the charging voltage meets the following criteria: DC5V, $\geq 500\text{mA}$

Warranty

1. Danger of explosion if battery is incorrectly replaced.
2. Replace only with the same or equivalent type.
3. Batteries (battery pack or batteries installed) shall not be exposed to excessive heat such as sunshine, fire or the like.
4. Danger of explosion if battery is incorrectly replaced. Replace only with the same or equivalent type.

FCC Statement:

Note: This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful

interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.