

Motion Sensor



Battery-powered SuperLink motion sensor featuring versatile installation.

Mechanical

Dimensions	Device with wall mount: 93.5 x 22.5 x 24.7 mm (3.7 x 0.89 x 0.97") Device with corner mount: 93.5 x 22.5 x 27.9 mm (3.7 x 0.89 x 1.1")
Weight	45 g (1.6 oz)
Enclosure material	Polycarbonate, high-density polyethylene (HDPE)
Mount material	Polycarbonate
Mounting	Adhesive and screw mount

Hardware

Max. power consumption	22.6mW
Supported voltage range	3V
Power method	Lithium battery CR123A
Buttons	(1) Factory-reset (1) Function button (1) Tamper switch
LEDs	(1) Status: R/B/W (1) Signal: B/R
Ambient operating temperature	0 to 40° C (32 to 104° F)
Ambient operating humidity	10 to 90% noncondensing
Certifications	FCC, IC, CE

Performance

Connectivity	SuperLink (Proprietary)
Operating frequency	US: 915.6–927.6 MHz EU: 865.1–869.5 MHz
Antenna gain	SuperLink: 1 dBi
Max. TX power	SuperLink: 14 dBm
Max. range	SuperLink: 2 km (1.2 mi) line of sight
Sensor features	Horizontal PIR Sensor Vertical PIR Sensor

Software

Web application	UniFi Protect
Mobile app	UniFi Protect iOS™ and Android™



