



FCC Radio Test Report

FCC ID: TLZ-XM612PUR

This report concerns: Original Grant

Project No.	: 2603H008
Equipment	: IEEE 802.11 a/b/g/n/ac/ax Wi-Fi6 + Bluetooth 6.0 Combo LGA Module
Brand Name	: AzureWave
Test Model	: AW-XM612-PUR
Series Model	: N/A
Applicant	: AzureWaveTechnologies, Inc.
Address	: 8F., No.94, Baozhong Rd., Xindian Dist., New Taipei City 23144, Taiwan
Manufacturer	: AzureWaveTechnologies, Inc.
Address	: 8F., No.94, Baozhong Rd., Xindian Dist., New Taipei City 23144, Taiwan
Date of Receipt	: Mar. 09, 2026
Date of Test	: Mar. 09, 2026~Apr. 23, 2026
Issued Date	: May 28, 2026
Test Sample	: Engineering Sample No.: SH920260306204 for conducted; SH920260306203 for radiation.
Standard(s)	: FCC CFR Title 47, Part 15, Subpart C

The above equipment has been tested and found compliance with the requirement of the relative standards by BTL Inc. (Shanghai)

Grani Zhou

Prepared by : Grani Zhou

Riley Wei

Approved by : Riley Wei

Add: No. 29, Jintang Road, Tangzhen Industry Park, Pudong New Area, Shanghai 201210,
People's Republic of China.

Tel: +86-021-61765666

Web: www.newbtl.com

Service mail: btl_qa@newbtl.com

Declaration

BTL represents to the client that testing is done in accordance with standard procedures as applicable and that test instruments used has been calibrated with standards traceable to international standard(s) and/or national standard(s).

BTL's reports apply only to the specific samples tested under conditions. It is manufacturer's responsibility to ensure that additional production units of this model are manufactured with the identical electrical and mechanical components. BTL assumes no responsibility for the data provided by the customer, any statements, inferences or generalizations drawn by the customer or others from the reports issued by BTL.

The report must not be used by the client to claim product certification, approval, or endorsement by A2LA or any agency of the U.S. Government.

This report is the confidential property of the client. As a mutual protection to the clients, the public and ourselves, the test report shall not be reproduced, except in full, without our written approval.

BTL's laboratory quality assurance procedures are in compliance with the ISO/IEC 17025: 2017 requirements, and accredited by the conformity assessment authorities listed in this test report.

BTL is not responsible for the sampling stage, so the results only apply to the sample as received.

The information, data and test plan are provided by manufacturer which may affect the validity of results, so it is manufacturer's responsibility to ensure that the apparatus meets the essential requirements of applied standards and in all the possible configurations as representative of its intended use.

Limitation

For the use of the authority's logo is limited unless the Test Standard(s)/Scope(s)/Item(s) mentioned in this test report is (are) included in the conformity assessment authorities acceptance respective.

Please note that the measurement uncertainty is provided for informational purpose only and are not use in determining the Pass/Fail results.

Table of Contents	Page
REPORT ISSUED HISTORY	6
1 . APPLICABLE STANDARDS	7
2 . SUMMARY OF TEST RESULTS	7
2.1 TEST FACILITY	8
2.2 MEASUREMENT UNCERTAINTY	8
NOTE: UNLESS SPECIFICALLY MENTIONED, THE UNCERTAINTY OF MEASUREMENT HAS NOT BEEN TAKEN INTO ACCOUNT TO DECLARE THE COMPLIANCE OR NON-COMPLIANCE TO THE SPECIFICATION.	8
2.3 TEST ENVIRONMENT CONDITIONS	8
3 . GENERAL INFORMATION	9
3.1 GENERAL DESCRIPTION OF EUT	9
3.2 DESCRIPTION OF TEST MODES	11
3.3 PARAMETERS OF TEST SOFTWARE	12
3.4 DUTY CYCLE	13
3.5 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED	14
3.6 SUPPORT UNITS	14
3.7 CUSTOMER INFORMATION DESCRIPTION	14
4 . AC POWER LINE CONDUCTED EMISSIONS	15
4.1 LIMIT	15
4.2 TEST PROCEDURE	15
4.3 DEVIATION FROM TEST STANDARD	15
4.4 TEST SETUP	16
4.5 EUT OPERATION CONDITIONS	16
4.6 TEST RESULTS	16
5 . RADIATED EMISSIONS	17
5.1 LIMIT	17
5.2 TEST PROCEDURE	18
5.3 DEVIATION FROM TEST STANDARD	19
5.4 TEST SETUP	19
5.5 EUT OPERATION CONDITIONS	20
5.6 TEST RESULTS - 9 KHZ TO 30 MHZ	20
5.7 TEST RESULTS - 30 MHZ TO 1000 MHZ	20

Table of Contents	Page
5.8 TEST RESULTS - ABOVE 1000 MHZ	20
6 . BANDWIDTH	21
6.1 LIMIT	21
6.2 TEST PROCEDURE	21
6.3 DEVIATION FROM STANDARD	21
6.4 TEST SETUP	21
6.5 EUT OPERATION CONDITIONS	21
6.6 TEST RESULTS	21
7 . MAXIMUM OUTPUT POWER	22
7.1 LIMIT	22
7.2 TEST PROCEDURE	22
7.3 DEVIATION FROM STANDARD	22
7.4 TEST SETUP	22
7.5 EUT OPERATION CONDITIONS	22
7.6 TEST RESULTS	22
8 . CONDUCTED SPURIOUS EMISSIONS	23
8.1 LIMIT	23
8.2 TEST PROCEDURE	23
8.3 DEVIATION FROM STANDARD	23
8.4 TEST SETUP	23
8.5 EUT OPERATION CONDITIONS	23
8.6 TEST RESULTS	23
9 . POWER SPECTRAL DENSITY	24
9.1 LIMIT	24
9.2 TEST PROCEDURE	24
9.3 DEVIATION FROM STANDARD	24
9.4 TEST SETUP	24
9.5 EUT OPERATION CONDITIONS	24
9.6 TEST RESULTS	24
10 . MEASUREMENT INSTRUMENTS LIST	25
11 . EUT TEST PHOTO	27
APPENDIX A - AC POWER LINE CONDUCTED EMISSIONS	32
APPENDIX B - RADIATED EMISSION - 9 KHZ TO 30 MHZ	35

Table of Contents	Page
APPENDIX C - RADIATED EMISSION - 30 MHZ TO 1000 MHZ	40
APPENDIX D - RADIATED EMISSION- ABOVE 1000 MHZ	43
APPENDIX E - BANDWIDTH	86
APPENDIX F - MAXIMUM OUTPUT POWER	91
APPENDIX G - CONDUCTED SPURIOUS EMISSIONS	96
APPENDIX H - POWER SPECTRAL DENSITY	105

REPORT ISSUED HISTORY

Report No.	Version	Description	Issued Date	Note
BTL-FCCP-1-2603H008	R00	Original Report.	May 21, 2026	Invalid
BTL-FCCP-1-2603H008	R01	This report updated the addresses of the applicant and manufacturer, equipment name, brand name, EUT test photo and note b in Clause 7.2. It is a revision of the report with serial number BTL-FCCP-1-2603H008 R00. This is a newly released report, replacing the BTL-FCCP-1-2603H008 R00 report.	May 28, 2026	Valid

1. APPLICABLE STANDARDS

According to the specifications of the manufacturer, the EUT must comply with the requirements of the following standards:

ANSI C63.10-2020+Cor. 1-2023.

The following reference test guidance is not within the scope of accreditation of A2LA:

KDB 558074 D01 15.247 Meas Guidance v05r02

KDB 662911 D01 Multiple Transmitter Output v02r01

2. SUMMARY OF TEST RESULTS

Test procedures according to the technical standard(s):

FCC CFR Title 47, Part 15, Subpart C				
Standard(s) Section	Test Item	Test Result	Judgment	Remark
15.207	AC Power Line Conducted Emissions	APPENDIX A	PASS	-----
15.247(d) 15.205(a) 15.209(a)	Radiated Emissions	APPENDIX B APPENDIX C APPENDIX D	PASS	-----
15.247(a)(2)	Bandwidth	APPENDIX E	PASS	-----
15.247(b)(3)	Maximum Output Power	APPENDIX F	PASS	-----
15.247(d)	Conducted Spurious Emissions	APPENDIX G	PASS	-----
15.247(e)	Power Spectral Density	APPENDIX H	PASS	-----
15.203	Antenna Requirement	-----	PASS	Note(2)

Note:

(1) "N/A" denotes test is not applicable in this test report.

(2) The device what use a permanently attached antenna were considered sufficient to comply with the provisions of 15.203.

2.1 TEST FACILITY

The test facilities used to collect the test data in this report is at the location of No. 29, Jintang Road, Tangzhen Industry Park, Pudong New Area, Shanghai 201210, People's Republic of China.

BTL's Registration Number for FCC: 964234

BTL's Designation Number for FCC: CN1374

2.2 MEASUREMENT UNCERTAINTY

ISO/IEC 17025 requires that an estimate of the measurement uncertainties associated with the emissions test results be included in the report. The measurement uncertainties given below are based on a 95% confidence level (based on a coverage factor (k=2))

The BTL measurement uncertainty as below table:

A. Radiated emissions test:

Test Site	Method	Measurement Frequency Range	Ant. H / V	U, (dB)
SH-CB02	CISPR	9 KHz~30 MHz	-	2.30
		30 MHz~200 MHz	V	4.48
		30 MHz~200 MHz	H	3.16
		200 MHz~1,000 MHz	V	4.70
		200 MHz~1,000 MHz	H	3.82
		1GHz ~ 6GHz	-	3.94
		6GHz ~ 18GHz	-	4.62
		18 GHz ~ 26.5 GHz	-	2.84
		26.5 GHz~40 GHz	-	2.90

Note: unless specifically mentioned, the uncertainty of measurement has not been taken into account to declare the compliance or non-compliance to the specification.

2.3 TEST ENVIRONMENT CONDITIONS

Test Item	Temperature	Humidity	Test Voltage	Tested By
AC Power Line Conducted Emissions	16.7°C	45%	DC 5V	Don Tang
Radiated Emissions-9kHz to 30 MHz	20.2°C	48%	DC 5V	Ellie Wei
Radiated Emissions-30MHz to 1000MHz	20°C	48%	DC 5V	Ellie Wei
Radiated Emissions-Above 1000MHz	19.5°C~23°C	42%~52%	DC 5V	Ellie Wei
Bandwidth	21.1°C	47%	DC 5V	Noel Kuai
Maximum Output Power	21.1°C	47%	DC 5V	Noel Kuai
Conducted Spurious Emissions	21.1°C	47%	DC 5V	Noel Kuai
Power Spectral Density	21.1°C	47%	DC 5V	Noel Kuai

3. GENERAL INFORMATION

3.1 GENERAL DESCRIPTION OF EUT

Equipment	IEEE 802.11 a/b/g/n/ac/ax Wi-Fi6 + Bluetooth 6.0 Combo LGA Module
Brand Name	AzureWave
Test Model	AW-XM612-PUR
Series Model	N/A
Model Difference(s)	N/A
Software Version	N/A
Hardware Version	N/A
Power Source	Supplied from PC USB port.
Power Rating	DC 5V
Operation Frequency	2412 MHz ~ 2462 MHz
Modulation Type	IEEE 802.11b: DSSS IEEE 802.11g: OFDM IEEE 802.11n: OFDM IEEE 802.11ax: OFDMA
Bit Rate of Transmitter	IEEE 802.11b: 11/5.5/2/1 Mbps IEEE 802.11g: 54/48/36/24/18/12/9/6 Mbps IEEE 802.11n: up to 144.4 Mbps IEEE 802.11ax: up to 286.8 Mbps
Maximum Output Power	IEEE 802.11b: 25.31 dBm (0.3396 W)

Note:

1. For a more detailed features description, please refer to the manufacturer's specifications or the user's manual.

2. Channel List:

CH01 - CH11 for IEEE 802.11b, IEEE 802.11g, IEEE 802.11n(HT20), IEEE 802.11ax(HE20)							
Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
01	2412	04	2427	07	2442	10	2457
02	2417	05	2432	08	2447	11	2462
03	2422	06	2437	09	2452		

3. Antenna Specification:

Ant.	Manufacturer	Model Name	Antenna Type	Connector	Gain (dBi)
1	ARISTOTLEENT ERPRISES INC.	RFA-27-C38H1M HF4C198	Dipole	IPEX	3
2	ARISTOTLEENT ERPRISES INC.	RFA-27-C38H1M HF4C198	Dipole	IPEX	3

Ant.	Manufacturer	Model Name	Antenna Type	Connector	Gain (dBi)
1	ARISTOTLEENT ERPRISES INC.	RFA-27-JP326M HF4C198	PIFA	IPEX	3.5
2	ARISTOTLEENT ERPRISES INC.	RFA-27-JP326M HF4C198	PIFA	IPEX	3.5

Note:

- 1) This EUT supports MIMO 2X2, any transmit signals are correlated with each other, so Directional gain= $G_{ANT}+10\log(N)$ dBi, that is Directional gain= $3.5+10\log(2)$ dBi=6.51. So, the output power limit is $30-(6.51-6)=29.49$, the power spectral density limit is $8-(6.51-6)=7.49$.

4. Table for Antenna Configuration:

Operating Mode	Ant. 1	Ant. 2	Ant. 1 + Ant. 2
TX Mode			
IEEE 802.11b	√	√	√
IEEE 802.11g	√	√	√
IEEE 802.11n(HT20)	√	√	√
IEEE 802.11ax(HE20)	√	√	√

3.2 DESCRIPTION OF TEST MODES

The test system was pre-tested based on the consideration of all possible combinations of EUT operation mode.

Pretest Mode	Description
Mode 1	TX B Mode Channel 01/06/11
Mode 2	TX G Mode Channel 01/06/11
Mode 3	TX N(HT20) Mode Channel 01/06/11
Mode 4	TX AX(HE20) Mode Channel 01/06/11

Following mode(s) was (were) found to be the worst case(s) and selected for the final test.

AC power line conducted emissions test	
Final Test Mode	Description
Mode 1	TX B Mode Channel 06

Radiated emissions test - Below 1GHz	
Final Test Mode	Description
Mode 1	TX B Mode Channel 06

Radiated emissions test- Above 1GHz	
Final Test Mode	Description
Mode 1	TX B Mode Channel 01/06/11
Mode 2	TX G Mode Channel 01/06/11
Mode 3	TX N(HT20) Mode Channel 01/06/11
Mode 4	TX AX(HE20) Mode Channel 01/06/11

Conducted test	
Final Test Mode	Description
Mode 1	TX B Mode Channel 01/06/11
Mode 2	TX G Mode Channel 01/06/11
Mode 3	TX N(HT20) Mode Channel 01/06/11
Mode 4	TX AX(HE20) Mode Channel 01/06/11

NOTE:

- (1) All the bit rate of transmitter have been tested and found the lowest rate is found to be the worst case and recorded.
- (2) For AC power line conducted emissions and radiated emission below 1 GHz test, the TX B Mode Channel 06 is found to be the worst case and recorded.
- (3) For radiated emission Harmonic 18-26.5GHz test, only tested the worst case and recorded.
- (4) Both antennas are evaluated, and the report only records the data of the worst antenna(RFA-27-JP326MHF4C198).
- (5) The radiated spurious test was conducted in the X/Y/Z three-axis mode, but only the worst X-axis mode results are listed in this report.
- (6) IEEE 802.11ax mode only support full RU, so only the full RU is evaluated and measured inside report.

3.3 PARAMETERS OF TEST SOFTWARE

Test Software Version	IPOP V4.0		
Frequency (MHz)	2412	2437	2462
IEEE 802.11b	19	24	19
IEEE 802.11g	16	20	16
IEEE 802.11n(HT20)	16	20	16
IEEE 802.11ax(HE20)	17	22	17


3.4 DUTY CYCLE

If duty cycle is $\geq 98\%$, duty factor is not required.

If duty cycle is $< 98\%$, duty factor shall be considered.

The output power = measured power + duty factor.


IEEE 802.11b



Duty cycle = 8.604 ms / 8.691 ms = 98.99%

Duty Factor = $10 \log(1/\text{Duty cycle}) = 0.00$


IEEE 802.11g



Duty cycle = 0.180 ms / 0.279 ms = 64.55%

Duty Factor = $10 \log(1/\text{Duty cycle}) = 1.90$


IEEE 802.11n(HT20)



Duty cycle = 0.109 ms / 0.208 ms = 52.44%

Duty Factor = $10 \log(1/\text{Duty cycle}) = 2.80$

IEEE 802.11ax(HE20)



Duty cycle = 0.557 ms / 0.659 ms = 84.62%

Duty Factor = $10 \log(1/\text{Duty cycle}) = 0.73$

NOTE:

For IEEE 802.11b:

For radiated emissions frequency above 1 GHz, the resolution bandwidth of test receiver/spectrum analyzer is 1 MHz and the video bandwidth is 1 kHz.

For IEEE 802.11g:

For radiated emissions frequency above 1 GHz, the resolution bandwidth of test receiver/spectrum analyzer is 1 MHz and the video bandwidth is 3.9 kHz.


For IEEE 802.11n(HT20):

For radiated emissions frequency above 1 GHz, the resolution bandwidth of test receiver/spectrum analyzer is 1 MHz and the video bandwidth is 5.1 kHz.

For IEEE 802.11ax(HE20):

For radiated emissions frequency above 1 GHz, the resolution bandwidth of test receiver/spectrum analyzer is 1 MHz and the video bandwidth is 2 kHz.

3.5 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED



3.6 SUPPORT UNITS

Item	Equipment	Brand	Model No.	Series No.
A	Notebook	Lenovo	V310-14ISK	LR07GZNB

Item	Cable Type	Shielded Type	Ferrite Core	Length
1	USB Cable	NO	NO	0.8m

3.7 CUSTOMER INFORMATION DESCRIPTION

- 1) The antenna gain is provided by the manufacturer.
- 2) Except for AC power line conducted emissions and radiated emissions, the results of all test items include cable losses. All cable losses are provided by the testing laboratory.

4. AC POWER LINE CONDUCTED EMISSIONS

4.1 LIMIT

Frequency of Emission (MHz)	Limit (dB μ V)	
	Quasi-peak	Average
0.15 - 0.5	66 to 56*	56 to 46*
0.5 - 5.0	56	46
5.0 - 30.0	60	50

NOTE:

- (1) The tighter limit applies at the band edges.
- (2) The limit of " * " marked band means the limitation decreases linearly with the logarithm of the frequency in the range.

4.2 TEST PROCEDURE

- a. The EUT was placed 0.8 meters from the horizontal ground plane with EUT being connected to the power mains through a line impedance stabilization network (LISN). All other support equipment powered from additional LISN(s). The LISN provide 50 Ohm/ 50uH of coupling impedance for the measuring instrument.
- b. Interconnecting cables that hang closer than 40 cm to the ground plane shall be folded back and forth in the center forming a bundle 30 to 40 cm long.
- c. I/O cables that are not connected to a peripheral shall be bundled in the center. The end of the cable may be terminated, if required, using the correct terminating impedance. The overall length shall not exceed 1 m.
- d. LISN at least 80 cm from nearest part of EUT chassis.
- e. For the actual test configuration, please refer to the related Item -EUT Test Photos.


The following table is the setting of the receiver:

Receiver Parameters	Setting
Start Frequency	0.15 MHz
Stop Frequency	30 MHz
IF Bandwidth	9 kHz

4.3 DEVIATION FROM TEST STANDARD

No deviation.

4.4 TEST SETUP



4.5 EUT OPERATION CONDITIONS

EUT was programmed to be in continuously transmitting mode.

4.6 TEST RESULTS

Please refer to the APPENDIX A.

5. RADIATED EMISSIONS

5.1 LIMIT

In case the emission fall within the restricted band specified on 15.205(a), then the 15.209(a) limit in the table below has to be followed.

LIMITS OF RADIATED EMISSION MEASUREMENT (9 kHz-1000 MHz)

Frequency (MHz)	Field Strength (microvolts/meter)	Measurement Distance (meters)
0.009-0.490	2400/F(kHz)	300
0.490-1.705	24000/F(kHz)	30
1.705-30.0	30	30
30-88	100	3
88-216	150	3
216-960	200	3
Above 960	500	3

LIMITS OF RADIATED EMISSION MEASUREMENT (Above 1000 MHz)

Frequency (MHz)	(dBuV/m at 3 m)	
	Peak	Average
Above 1000	74	54

NOTE:

- (1) The limit for radiated test was performed according to FCC CFR Title 47, Part 15, Subpart C.
- (2) The tighter limit applies at the band edges.
- (3) Emission level (dBuV/m)=20log Emission level (uV/m).

5.2 TEST PROCEDURE

- a. The measuring distance of 3 m shall be used for measurements. The EUT was placed on the top of a rotating table 0.8 meter above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.(below 1 GHz)
- b. The measuring distance of 3 m shall be used for measurements. The EUT was placed on the top of a rotating table 1.5 meter above the ground at a 3 meter semi-anechoic chamber. The table was rotated 360 degrees to determine the position of the highest radiation.(above 1 GHz)
- c. The height of the equipment or of the substitution antenna shall be 0.8m or 1.5m; the height of the test antenna shall vary between 1 m to 4 m. Both horizontal and vertical polarizations of the antenna are set to make the measurement.
- d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights find the maximum reading (used Bore sight function).
- e. The receiver system was set to peak and average detect function and specified bandwidth with maximum hold mode when the test frequency is above 1 GHz.
- f. The initial step in collecting radiated emission data is a receiver peak detector mode pre-scanning the measurement frequency range. Significant peaks are then marked and then Quasi Peak detector mode re-measured.
- g. All readings are Peak unless otherwise stated QP in column of Note. Peak denotes that the Peak reading compliance with the QP Limits and then QP Mode measurement didn't perform.
(below 1 GHz)
- h. All readings are Peak Mode value unless otherwise stated AVG in column of Note. If the Peak Mode Measured value compliance with the Peak Limits and lower than AVG Limits, the EUT shall be deemed to meet both Peak & AVG Limits and then only Peak Mode was measured, but AVG Mode didn't perform. (above 1 GHz)
- i. For the actual test configuration, please refer to the related Item -EUT Test Photos.

The following table is the setting of the receiver:

Spectrum Parameters	Setting
Start ~ Stop Frequency	9 kHz~150 kHz for RBW 200 Hz
Start ~ Stop Frequency	0.15 MHz~30 MHz for RBW 9 kHz
Start ~ Stop Frequency	30 MHz~1000 MHz for RBW 100 kHz

Spectrum Parameters	Setting
Start Frequency	1000 MHz
Stop Frequency	10th carrier harmonic
RBW / VBW (Emission in restricted band)	1 MHz / 3 MHz for PK value 1 MHz / 1/T Hz for AVG value


Receiver Parameters	Setting
Start ~ Stop Frequency	9 kHz~90 kHz for PK/AVG detector
Start ~ Stop Frequency	90 kHz~110 kHz for QP detector
Start ~ Stop Frequency	110 kHz~490 kHz for PK/AVG detector
Start ~ Stop Frequency	490 kHz~30 MHz for QP detector
Start ~ Stop Frequency	30 MHz~1000 MHz for QP detector
Start ~ Stop Frequency	1 GHz~26.5 GHz for PK/AVG detector

5.3 DEVIATION FROM TEST STANDARD


No deviation.


5.4 TEST SETUP

9 kHz to 30 MHz



30 MHz to 1 GHz





5.5 EUT OPERATION CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

5.6 TEST RESULTS - 9 KHZ TO 30 MHZ

Please refer to the APPENDIX B.

Remark:

- (1) Distance extrapolation factor = $40 \log (\text{specific distance} / \text{test distance})$ (dB).
- (2) Limit line = specific limits (dBuV) + distance extrapolation factor.

5.7 TEST RESULTS - 30 MHZ TO 1000 MHZ

Please refer to the APPENDIX C.

5.8 TEST RESULTS - ABOVE 1000 MHZ

Please refer to the APPENDIX D.

Remark:

- (1) No limit: This is fundamental signal, the judgment is not applicable.
For fundamental signal judgment was referred to Peak output test.

6. BANDWIDTH

6.1 LIMIT

Section	Test Item	Limit
FCC 15.247(a)(2)	6 dB Bandwidth	Minimum 500 kHz
	99% Emission Bandwidth	-

6.2 TEST PROCEDURE

- The EUT was directly connected to the spectrum analyzer and antenna output port as show in the block diagram below.
- The following table is the setting of the spectrum analyzer:

For 6 dB Bandwidth:

Spectrum Parameters	Setting
Span Frequency	> Measurement Bandwidth
RBW	100 kHz
VBW	300 kHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

For 99% Emission Bandwidth:

Spectrum Parameters	Setting
Span Frequency	Between 1.5 times and 5.0 times the OBW
RBW	300 kHz For 20MHz 1 MHz For 40MHz
VBW	1 MHz For 20MHz 3 MHz For 40MHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

6.3 DEVIATION FROM STANDARD

No deviation.

6.4 TEST SETUP



6.5 EUT OPERATION CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

6.6 TEST RESULTS

Please refer to the APPENDIX E.

7. MAXIMUM OUTPUT POWER

7.1 LIMIT

Section	Test Item	Limit
FCC 15.247(b)(3)	Maximum Output Power	1.0000 Watt or 30.00 dBm


7.2 TEST PROCEDURE

- The EUT was directly connected to the peak power analyzer and antenna output port as show in the block diagram below.
- The maximum conducted output power was performed in accordance with method 11.9.2.3.1 (for AVG power) of ANSI C63.10-2020+Cor. 1-2023 and FCC KDB 662911 D01 v02r01 Multiple Transmitter Output.

7.3 DEVIATION FROM STANDARD

No deviation.

7.4 TEST SETUP



7.5 EUT OPERATION CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

7.6 TEST RESULTS

Please refer to the APPENDIX F.

8. CONDUCTED SPURIOUS EMISSIONS

8.1 LIMIT

In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak Output Power limits. If the transmitter complies with the Output Power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in Section 15.209(a) is not required.

8.2 TEST PROCEDURE


- The EUT was directly connected to the spectrum analyzer and antenna output port as show in the block diagram below.
- The following table is the setting of the spectrum analyzer:

Spectrum Parameters	Setting
Start Frequency	30 MHz
Stop Frequency	26.5 GHz
RBW	100 kHz
VBW	300 kHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

8.3 DEVIATION FROM STANDARD

No deviation.

8.4 TEST SETUP



8.5 EUT OPERATION CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

8.6 TEST RESULTS

Please refer to the APPENDIX G.

9. POWER SPECTRAL DENSITY

9.1 LIMIT

Section	Test Item	Limit
FCC 15.247(e)	Power Spectral Density	8 dBm (in any 3 kHz)

9.2 TEST PROCEDURE


- The EUT was directly connected to the spectrum analyzer and antenna output port as show in the block diagram below.
- The following table is the setting of the spectrum analyzer:

Spectrum Parameters	Setting
Span Frequency	25 MHz (20 MHz) / 60 MHz (40 MHz)
RBW	3 kHz
VBW	10 kHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

9.3 DEVIATION FROM STANDARD

No deviation.

9.4 TEST SETUP



9.5 EUT OPERATION CONDITIONS

The EUT was programmed to be in continuously transmitting mode.

9.6 TEST RESULTS

Please refer to the APPENDIX H.

10. MEASUREMENT INSTRUMENTS LIST

AC Power Line Conducted Emissions					
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	TWO-LINE V-NETWORK	R&S	ENV216	101340	Jul. 04, 2026
2	Test Cable	Regal Way	RWLP50-104-NMS M-10M	20260228-001	Mar. 12, 2027
3	EMI Test Receiver	R&S	ESR3	100082	Dec.11, 2026
4	50Ω Terminator	SHX	TF2-1G-A	17051602	Dec. 27, 2026
5	50Ω coaxial switch	Anritsu	MP59B	6201750902	Dec. 26, 2026
6	Measurement Software	Farad	EZ-EMC Ver.NB-03A1-01	N/A	N/A

Radiated Emissions - 9 kHz to 30 MHz					
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	Loop Antenna	EMCI	EMCI LPA600	275	Feb. 28, 2027
2	MXE EMI Receiver	Keysight	N9038A	MY56400088	Dec. 26, 2026
3	Measurement Software	Farad	EZ-EMC Ver.NB-03A1	N/A	N/A
4	Test Cable	Regal Way	RWLP50-104-SMS M-0.8M	20260228 001	Mar.12.2027
5	Test Cable	Regal Way	RWLP50-104-SMS M-7M	20260228 003	Mar.12.2027
6	Test Cable	Regal Way	RWLP50-104-SMS M-2.5M	20260228 005	Mar.12.2027
7	Pre-Amplifier	emci	EMC9135	980401	Dec. 26, 2026

Radiated Emissions - 30 MHz to 1 GHz					
Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	Antenna	Schwarzbeck	VULB 9168	1467	Feb.6.2027
2	Pre-Amplifier	emci	EMC9135	980401	Dec. 26, 2026
3	MXE EMI Receiver	Keysight	N9038A	MY56400088	Dec. 26, 2026
4	Test Cable	Regal Way	RWLP50-104-SMS M-0.8M	20260228 001	Mar.12.2027
5	Test Cable	Regal Way	RWLP50-104-SMS M-7M	20260228 003	Mar.12.2027
6	Test Cable	Regal Way	RWLP50-104-SMS M-2.5M	20260228 005	Mar.12.2027
7	Measurement Software	Farad	EZ-EMC Ver.NB-03A1	N/A	N/A

Radiated Emissions - 1GHz-18GHz

Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	Double-Ridged Waveguide Horn Antenna	ETS-Lindgren	BBHA 9120D	9120D-1817	Aug. 7, 2026
2	Pre-Amplifier	emci	EMC118A45SE	980910	Dec. 26, 2026
3	EXA Spectrum Analyzer	Keysight	N9010A	MY56480559	Dec. 26, 2026
4	Test Cable	Regal Way	RWLP50-104-SMS M-0.8M	20260228 001	Mar.12.2027
5	Test Cable	Regal Way	RWLP50-104-SMS M-7M	20260228 003	Mar.12.2027
6	Test Cable	Regal Way	RWLP50-104-SMS M-2.5M	20260228 005	Mar.12.2027
7	Measurement Software	Farad	EZ-EMC Ver.NB-03A1	N/A	N/A

Radiated Emissions – Above 18GHz

Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	Antenna	Schwarzbeck	BBHA9170	9170-651	Feb. 7, 2027
2	Pre-Amplifier	EMC INSTRUMENT	EMC184045B	980265	Dec. 11, 2026
3	Test Cable	Regal Way	RWLP50-102-KMK M-0.8M	20250807-002	Mar. 12, 2027
4	Test Cable	Regal Way	RWLP50-102-KMK M-4M	20250807-001	Mar. 12, 2027
5	EXA Spectrum Analyzer	Keysight	N9010A	MY56480559	Dec. 26, 2026
6	Measurement Software	Farad	EZ-EMC Ver.NB-03A1	N/A	N/A

Bandwidth

Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	EXA Spectrum Analyzer	Keysight	N9020B	MY57120173	Jul. 04, 2026
2	BTL Conducted Test	BTL	20260106	N/A	N/A

Maximum Output Power

Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	Peak Power Analyzer	Keysight	8990B	MY51000507	Dec. 26, 2026
2	Wideband Power Sensor	Keysight	N1923A	MY58310003	Dec. 26, 2026

Antenna Conducted Spurious Emissions

Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	EXA Spectrum Analyzer	Keysight	N9020B	MY57120173	Jul. 04, 2026
2	BTL Conducted Test	BTL	20260106	N/A	N/A

Power Spectral Density


Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Calibrated until
1	EXA Spectrum Analyzer	Keysight	N9020B	MY57120173	Jul. 04, 2026
2	BTL Conducted Test	BTL	20260106	N/A	N/A

Remark: "N/A" denotes no model name, serial no. or calibration specified.

All calibration period of equipment list is one year.


11. EUT TEST PHOTO



AC Power Line Conducted Emissions Test Photos



Radiated Emissions Test Photos



9 kHz to 30 MHz





Radiated Emissions Test Photos**30 MHz to 1 GHz**

Radiated Emissions Test Photos


1 GHz to 18GHz



Radiated Emissions Test Photos**Above 18GHz**

APPENDIX A - AC POWER LINE CONDUCTED EMISSIONS

Test Mode	TX B Mode Channel 06	Phase	Line
-----------	----------------------	-------	------




No.	Mk.	Freq.	Reading	Correct	Measure-	Limit	Margin		
		MHz	Level	Factor	ment			Detector	Comment
			dBuV	dB	dBuV	dBuV	dB		
1		0.7485	32.40	9.65	42.05	56.00	-13.95	QP	
2		0.7485	27.20	9.65	36.85	46.00	-9.15	AVG	
3		0.8880	31.80	9.66	41.46	56.00	-14.54	QP	
4		0.8880	25.60	9.66	35.26	46.00	-10.74	AVG	
5		1.2615	34.00	9.69	43.69	56.00	-12.31	QP	
6		1.2615	27.10	9.69	36.79	46.00	-9.21	AVG	
7		2.3978	36.90	9.71	46.61	56.00	-9.39	QP	
8	*	2.3978	29.20	9.71	38.91	46.00	-7.09	AVG	
9		6.2835	34.20	9.88	44.08	60.00	-15.92	QP	
10		6.2835	28.60	9.88	38.48	50.00	-11.52	AVG	
11		9.0173	33.00	9.97	42.97	60.00	-17.03	QP	
12		9.0173	26.70	9.97	36.67	50.00	-13.33	AVG	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode Channel 06	Phase	Neutral
-----------	----------------------	-------	---------



No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Margin		
		MHz	dBuV	dB	dBuV	dBuV	dB	Detector	Comment
1		0.6810	33.40	9.74	43.14	56.00	-12.86	QP	
2		0.6810	17.70	9.74	27.44	46.00	-18.56	AVG	
3		0.9510	32.00	9.73	41.73	56.00	-14.27	QP	
4		0.9510	18.60	9.73	28.33	46.00	-17.67	AVG	
5		2.2492	31.90	9.78	41.68	56.00	-14.32	QP	
6		2.2492	23.90	9.78	33.68	46.00	-12.32	AVG	
7		6.1192	33.10	9.98	43.08	60.00	-16.92	QP	
8		6.1192	27.10	9.98	37.08	50.00	-12.92	AVG	
9		8.7045	34.20	10.07	44.27	60.00	-15.73	QP	
10	*	8.7045	28.30	10.07	38.37	50.00	-11.63	AVG	
11		11.0963	33.50	10.13	43.63	60.00	-16.37	QP	
12		11.0963	27.80	10.13	37.93	50.00	-12.07	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

APPENDIX B - RADIATED EMISSION - 9 KHZ TO 30 MHZ

Test Mode	TX B Mode Channel 06	Polarization	Vertical
-----------	----------------------	--------------	----------




No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor	Measure- ment dBuV/m	Limit dBuV/m	Over dB	Detector	Comment
1	*	0.0090	0.88	70.34	71.22	128.52	-57.30	AVG	
2		0.0533	4.09	40.54	44.63	113.07	-68.44	AVG	
3		0.1004	8.01	28.56	36.57	107.57	-71.00	QP	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode Channel 06	Polarization	Horizontal
-----------	----------------------	--------------	------------




No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over		
		MHz	dBuV		dBuV/m	dBuV/m	dB	Detector	Comment
1	*	0.0090	3.32	70.34	73.66	128.52	-54.86	AVG	
2		0.1005	8.63	28.54	37.17	107.56	-70.39	QP	
3		0.1467	4.81	23.93	28.74	104.28	-75.54	AVG	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
- (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode Channel 06	Polarization	Vertical
-----------	----------------------	--------------	----------




No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over		
		MHz	dBuV		dBuV/m	dBuV/m	dB	Detector	Comment
1	*	0.1948	35.34	20.07	55.41	101.81	-46.40	AVG	
2		7.1200	20.11	-1.24	18.87	69.54	-50.67	QP	
3		17.6421	20.31	-3.11	17.20	69.54	-52.34	QP	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode Channel 06	Polarization	Horizontal
-----------	----------------------	--------------	------------



No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over		
		MHz	dBuV		dBuV/m	dBuV/m	dB	Detector	Comment
1	*	0.1948	35.54	20.07	55.61	101.81	-46.20	AVG	
2		13.6721	20.60	-2.36	18.24	69.54	-51.30	QP	
3		28.1941	19.63	-4.92	14.71	69.54	-54.83	QP	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

APPENDIX C - RADIATED EMISSION - 30 MHZ TO 1000 MHZ

Test Mode	TX B Mode Channel 06	Polarization	Vertical
-----------	----------------------	--------------	----------




No. Mk.	Freq. MHz	Reading Level dBuV	Correct Factor	Measure- ment dBuV/m	Limit dBuV/m	Over dB	Detector	Comment
1 *	48.4300	48.79	-17.34	31.45	40.00	-8.55	peak	
2	76.0750	48.08	-20.65	27.43	40.00	-12.57	peak	
3	800.1800	40.19	-7.80	32.39	46.00	-13.61	peak	
4	854.9850	33.50	-6.52	26.98	46.00	-19.02	peak	
5	917.0650	33.77	-6.14	27.63	46.00	-18.37	peak	
6	948.5900	33.51	-5.97	27.54	46.00	-18.46	peak	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode Channel 06	Polarization	Horizontal
-----------	----------------------	--------------	------------



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor	Measure- ment dBuV/m	Limit dBuV/m	Over dB	Detector	Comment
1	*	799.6950	41.23	-7.80	33.43	46.00	-12.57	peak	
2		824.9150	33.64	-7.18	26.46	46.00	-19.54	peak	
3		850.6200	32.95	-6.56	26.39	46.00	-19.61	peak	
4		876.3250	33.51	-6.39	27.12	46.00	-18.88	peak	
5		900.0900	37.02	-6.25	30.77	46.00	-15.23	peak	
6		936.9500	33.20	-6.03	27.17	46.00	-18.83	peak	

REMARKS:


(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

APPENDIX D - RADIATED EMISSION- ABOVE 1000 MHZ

Test Mode	TX B Mode 2412 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1 *	2390.0000	44.80	3.93	48.73	74.00	-25.27	Peak	
2	2483.5000	43.48	4.22	47.70	74.00	-26.30	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2412 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7989.5500	47.17	4.72	51.89	74.00	-22.11	Peak	
2	9999.8000	50.54	4.68	55.22	74.00	-18.78	Peak	
3 *	9999.8000	45.91	4.68	50.59	54.00	-3.41	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2412 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	52.66	3.93	56.59	74.00	-17.41	Peak	
2 *	2390.0000	46.49	3.93	50.42	54.00	-3.58	AVG	
3	2483.5000	45.10	4.22	49.32	74.00	-24.68	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2412 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	4824.1500	49.75	-1.69	48.06	74.00	-25.94	Peak	
2 *	9998.9500	45.78	4.68	50.46	74.00	-23.54	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2437 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7982.7500	46.64	4.70	51.34	74.00	-22.66	Peak	
2	9998.1000	50.37	4.68	55.05	74.00	-18.95	Peak	
3 *	9998.1000	45.20	4.68	49.88	54.00	-4.12	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2437 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	4873.4500	47.94	-1.58	46.36	74.00	-27.64	Peak	
2 *	9999.8000	46.91	4.68	51.59	74.00	-22.41	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2462 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	42.90	3.93	46.83	74.00	-27.17	Peak	
2 *	2483.5000	46.64	4.22	50.86	74.00	-23.14	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2462 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

86.9 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7980.2000	46.77	4.70	51.47	74.00	-22.53	Peak	
2 *	10000.6500	48.65	4.68	53.33	74.00	-20.67	Peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
 (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2462 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	44.08	3.93	48.01	74.00	-25.99	Peak	
2	2483.5000	53.14	4.22	57.36	74.00	-16.64	Peak	
3 *	2483.5000	48.50	4.22	52.72	54.00	-1.28	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2462 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	4923.6000	46.99	-1.48	45.51	74.00	-28.49	Peak	
2 *	9999.8000	47.02	4.68	51.70	74.00	-22.30	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2412 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1 *	2390.0000	47.31	3.93	51.24	74.00	-22.76	Peak	
2	2483.5000	43.65	4.22	47.87	74.00	-26.13	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2412 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

86.9 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7974.2500	44.75	4.69	49.44	74.00	-24.56	Peak	
2 *	9998.9500	48.86	4.68	53.54	74.00	-20.46	Peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2412 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	55.63	3.93	59.56	74.00	-14.44	Peak	
2 *	2390.0000	44.16	3.93	48.09	54.00	-5.91	AVG	
3	2483.5000	46.31	4.22	50.53	74.00	-23.47	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2412 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

86.9 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	4824.1500	46.70	-1.69	45.01	74.00	-28.99	Peak	
2 *	9999.8000	45.80	4.68	50.48	74.00	-23.52	Peak	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2437 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------



No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over	
		MHz	dBuV		dBuV/m	dBuV/m	dB	Detector Comment
1		7990.400	46.55	4.72	51.27	74.00	-22.73	peak
2		9998.950	49.65	4.68	54.33	74.00	-19.67	peak
3	*	9998.950	44.55	4.68	49.23	54.00	-4.77	AVG


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2437 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7970.8500	42.67	4.68	47.35	74.00	-26.65	Peak	
2 *	10000.6500	47.15	4.68	51.83	74.00	-22.17	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2462 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	43.18	3.93	47.11	74.00	-26.89	Peak	
2 *	2483.5000	49.35	4.22	53.57	74.00	-20.43	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2462 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7991.2500	46.86	4.72	51.58	74.00	-22.42	Peak	
2 *	9999.8000	49.01	4.68	53.69	74.00	-20.31	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2462 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	45.48	3.93	49.41	74.00	-24.59	Peak	
2	2483.5000	55.21	4.22	59.43	74.00	-14.57	Peak	
3 *	2483.5000	45.12	4.22	49.34	54.00	-4.66	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX G Mode 2462 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7999.7500	42.52	4.74	47.26	74.00	-26.74	Peak	
2 *	9998.9500	46.38	4.68	51.06	74.00	-22.94	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2412 MHz	Polarization	Vertical
-----------	--------------------------	--------------	----------

130 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1 *	2390.0000	46.93	3.93	50.86	74.00	-23.14	Peak	
2	2483.5000	43.70	4.22	47.92	74.00	-26.08	Peak	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2412 MHz	Polarization	Vertical
-----------	--------------------------	--------------	----------



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor	Measure- ment dBuV/m	Limit dBuV/m	Over dB	Detector	Comment
1		7246.650	39.45	3.01	42.46	54.00	-11.54	AVG	
2		7246.650	53.25	3.01	56.26	74.00	-17.74	peak	
3	*	9999.800	46.63	4.68	51.31	54.00	-2.69	AVG	
4		9999.800	50.69	4.68	55.37	74.00	-18.63	peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2412 MHz	Polarization	Horizontal
-----------	--------------------------	--------------	------------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	57.04	3.93	60.97	74.00	-13.03	Peak	
2 *	2390.0000	45.71	3.93	49.64	54.00	-4.36	AVG	
3	2483.5000	46.45	4.22	50.67	74.00	-23.33	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2412 MHz	Polarization	Horizontal
-----------	--------------------------	--------------	------------

86.9 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7235.6000	55.72	2.98	58.70	74.00	-15.30	Peak	
2 *	7235.6000	39.68	2.98	42.66	54.00	-11.34	AVG	
3	9999.8000	47.93	4.68	52.61	74.00	-21.39	Peak	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2437 MHz	Polarization	Vertical
-----------	--------------------------	--------------	----------



No.	Mk.	Freq.	Reading Level	Correct Factor	Measurement	Limit	Over	
		MHz	dBuV		dBuV/m	dBuV/m	dB	Detector Comment
1		7308.700	50.96	3.19	54.15	74.00	-19.85	peak
2		7308.700	46.23	3.19	49.42	54.00	-4.58	AVG
3		9999.800	50.81	4.68	55.49	74.00	-18.51	peak
4	*	9999.800	46.86	4.68	51.54	54.00	-2.46	AVG


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2437 MHz	Polarization	Horizontal
-----------	--------------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7313.8000	56.68	3.20	59.88	74.00	-14.12	Peak	
2 *	7313.8000	40.49	3.20	43.69	54.00	-10.31	AVG	
3	10000.6500	46.04	4.68	50.72	74.00	-23.28	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2462 MHz	Polarization	Vertical
-----------	--------------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	43.70	3.93	47.63	74.00	-26.37	Peak	
2 *	2483.5000	47.59	4.22	51.81	74.00	-22.19	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2462 MHz	Polarization	Vertical
-----------	--------------------------	--------------	----------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7382.6500	47.69	3.39	51.08	74.00	-22.92	Peak	
2 *	9999.8000	49.25	4.68	53.93	74.00	-20.07	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2462 MHz	Polarization	Horizontal
-----------	--------------------------	--------------	------------

130 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	45.94	3.93	49.87	74.00	-24.13	Peak	
2	2483.5000	59.16	4.22	63.38	74.00	-10.62	Peak	
3 *	2483.5200	44.56	4.22	48.78	54.00	-5.22	AVG	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
 (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX N(HT20) Mode 2462 MHz	Polarization	Horizontal
-----------	--------------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7379.2500	53.19	3.38	56.57	74.00	-17.43	Peak	
2 *	7379.2500	38.43	3.38	41.81	54.00	-12.19	AVG	
3	9999.8000	46.70	4.68	51.38	74.00	-22.62	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2412 MHz	Polarization	Vertical
-----------	---------------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1 *	2390.0000	48.33	3.93	52.26	74.00	-21.74	Peak	
2	2483.5000	43.02	4.22	47.24	74.00	-26.76	Peak	
3	2494.2430	46.14	4.25	50.39	74.00	-23.61	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2412 MHz	Polarization	Vertical
-----------	---------------------------	--------------	----------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7971.7000	46.43	4.68	51.11	74.00	-22.89	Peak	
2	9999.8000	49.67	4.68	54.35	74.00	-19.65	Peak	
3 *	9999.8000	39.76	4.68	44.44	54.00	-9.56	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2412 MHz	Polarization	Horizontal
-----------	---------------------------	--------------	------------

130 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	60.32	3.93	64.25	74.00	-9.75	Peak	
2 *	2390.0000	45.85	3.93	49.78	54.00	-4.22	AVG	
3	2483.5000	47.37	4.22	51.59	74.00	-22.41	Peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2412 MHz	Polarization	Horizontal
-----------	---------------------------	--------------	------------




No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor	Measure- ment dBuV/m	Limit dBuV/m	Over dB	Detector	Comment
1		4826.700	44.46	-1.68	42.78	74.00	-31.22	peak	
2	*	9999.800	45.00	4.68	49.68	74.00	-24.32	peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
- (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2437 MHz	Polarization	Vertical
-----------	---------------------------	--------------	----------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7307.8500	53.01	3.18	56.19	74.00	-17.81	Peak	
2	7307.8500	42.19	3.18	45.37	54.00	-8.63	AVG	
3	9999.8000	49.94	4.68	54.62	74.00	-19.38	Peak	
4 *	9999.8000	44.54	4.68	49.22	54.00	-4.78	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2437 MHz	Polarization	Horizontal
-----------	---------------------------	--------------	------------

86.9 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7307.8500	51.82	3.18	55.00	74.00	-19.00	Peak	
2 *	7307.8500	41.54	3.18	44.72	54.00	-9.28	AVG	
3	10000.6500	44.99	4.68	49.67	74.00	-24.33	Peak	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2462 MHz	Polarization	Vertical
-----------	---------------------------	--------------	----------

130 dBuV/m



No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	42.98	3.93	46.91	74.00	-27.09	Peak	
2	2483.5000	51.02	4.22	55.24	74.00	-18.76	Peak	
3 *	2483.5000	38.22	4.22	42.44	54.00	-11.56	AVG	


REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2462 MHz	Polarization	Vertical
-----------	---------------------------	--------------	----------

86.9 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	7971.7000	45.27	4.68	49.95	74.00	-24.05	Peak	
2 *	10002.3500	48.93	4.68	53.61	74.00	-20.39	Peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
 (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2462 MHz	Polarization	Horizontal
-----------	---------------------------	--------------	------------

130 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	2390.0000	45.07	3.93	49.00	74.00	-25.00	Peak	
2	2483.5000	59.00	4.22	63.22	74.00	-10.78	Peak	
3 *	2483.5000	46.46	4.22	50.68	54.00	-3.32	AVG	
4	2487.4600	60.56	4.23	64.79	74.00	-9.21	Peak	
5	2487.4600	45.19	4.23	49.42	54.00	-4.58	AVG	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
- (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX AX(HE20) Mode 2462 MHz	Polarization	Horizontal
-----------	---------------------------	--------------	------------

86.9 dBuV/m




No.	Freq. MHz	Reading Level dBuV/m	Correct Factor dB	Measure ment dBuV/m	Limit dBuV/m	Margin dB	Detector	Comment
1	8038.0000	41.68	4.67	46.35	74.00	-27.65	Peak	
2 *	9999.8000	44.72	4.68	49.40	74.00	-24.60	Peak	

REMARKS:

(1) Measurement Value = Reading Level + Correct Factor.

(2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2437 MHz	Polarization	Vertical
-----------	--------------------	--------------	----------




No.	Mk.	Freq.	Reading Level	Correct Factor	Measure-ment	Limit	Over		
		MHz	dBuV		dBuV/m	dBuV/m	dB	Detector	Comment
1		19363.400	55.86	-8.48	47.38	74.00	-26.62	peak	
2	*	26496.175	49.16	1.07	50.23	74.00	-23.77	peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
- (2) Margin Level = Measurement Value - Limit Value.

Test Mode	TX B Mode 2437 MHz	Polarization	Horizontal
-----------	--------------------	--------------	------------



No.	Mk.	Freq. MHz	Reading Level dBuV	Correct Factor	Measure- ment dBuV/m	Limit dBuV/m	Over dB	Detector	Comment
1		20798.200	55.70	-7.22	48.48	74.00	-25.52	peak	
2	*	26339.350	50.00	0.56	50.56	74.00	-23.44	peak	

REMARKS:

- (1) Measurement Value = Reading Level + Correct Factor.
- (2) Margin Level = Measurement Value - Limit Value.

APPENDIX E - BANDWIDTH

Test Mode	TX B Mode
-----------	-----------

Channel	Frequency (MHz)	6 dB Bandwidth (MHz)	99 % Occupied Bandwidth (MHz)	6 dB Bandwidth Min. Limit (MHz)	Result
01	2412	9.053	13.635	0.5	Complies
06	2437	8.562	14.325	0.5	Complies
11	2462	9.076	15.087	0.5	Complies

CH01



CH06



6 dB Bandwidth



CH11




99 % Occupied Bandwidth



Test Mode	TX G Mode
-----------	-----------


Channel	Frequency (MHz)	6 dB Bandwidth (MHz)	99 % Occupied Bandwidth (MHz)	6 dB Bandwidth Min. Limit (MHz)	Result
01	2412	16.480	23.077	0.5	Complies
06	2437	16.460	24.230	0.5	Complies
11	2462	16.480	25.237	0.5	Complies

CH01




CH06

6 dB Bandwidth



CH11



99 % Occupied Bandwidth

