

RF Exposure evaluation
For FCC ID: TUVET-7341A

According to 447498 D04 Interim General RF Exposure Guidance V01

$$P_{th} \text{ (mW)} = \begin{cases} ERP_{20 \text{ cm}} (d/20 \text{ cm})^x & d \leq 20 \text{ cm} \\ ERP_{20 \text{ cm}} & 20 \text{ cm} < d \leq 40 \text{ cm} \end{cases} \quad (\text{B.1})$$

where

$$x = -\log_{10} \left(\frac{60}{ERP_{20 \text{ cm}} f} \right)$$

and f is in GHz, d is the separation distance (cm), and $ERP_{20 \text{ cm}}$ is per Formula (B.1).
The example values shown in Table B.2 are for illustration only.

$$P_{th} \text{ (mW)} = ERP_{20 \text{ cm}} \text{ (mW)} = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

Table B.2—Example Power Thresholds (mW)

	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
Frequency (MHz)	300	39	65	88	110	129	148	166	184	201
	450	22	44	67	89	112	135	158	180	203
	835	9	25	44	66	90	116	145	175	207
	1900	3	12	26	44	66	92	122	157	195
	2450	3	10	22	38	59	83	111	143	179
	3600	2	8	18	32	49	71	96	125	158
	5800	1	6	14	25	40	58	80	106	136

$$E_{irp} = p_t \times g_t = (EXd)^2/30$$

Where:

p_t = transmitter output power in watts,

g_t = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, --- $10^{((\text{dBuV/m})/20)/10^6}$

d = measurement distance in meters (m) --- 3m

$$\text{So } p_t = (EXd)^2/30 \times g_t$$

Ant gain = 2.34dBi So Ant numeric gain = 1.71

Field strength = 90.17dB μ V/m @3m@2402MHz

$$\text{So } P_t = \{ [10^{(90.17/20)}/10^6 \times 3]^2 / (30 \times 1.71) \} \times 1000\text{mW} = 0.18\text{mW} < 2.79\text{mW}$$

Then SAR evaluation is not required.

2.4GHz and BT cannot be transmitted simultaneously.