



As an ENERGY STAR® Partner, DT Research Inc. follows the EPA's product qualification and certification process to ensure the products marked with the ENERGY STAR® logo are ENERGY STAR® qualified for energy efficiency.

The ENERGY STAR® program specifications for computers were to promote energy efficiency and reduce air pollution through more energy-efficient equipment in homes, offices, and factories. One way products achieve this goal is by using the Microsoft Windows power management feature to reduce power consumption when the product is not in use. The power management feature enables the computer to initiate a low-power or "sleep" mode after a period of user inactivity.

To take advantage of these potential energy savings, users should use the default power management settings that are provided with ENERGY STAR qualified computers. The default power management settings on ENERGY STAR® qualified computers are preset to behave in the following ways :

- Turn off display after 10 minutes of user inactivity.
- Initiate a low power sleep mode for the computer after 30 minutes of user inactivity.
- Briefly press the power button will bring the computer out of sleep mode.

Additional information on the ENERGY STAR® program, its environmental benefits and the potential energy and financial savings of the power management feature can be found on the EPA ENERGY STAR® Power Management Web site at <http://www.energystar.gov/powermanagement>.

For the product take-back service information, please visit:
<http://www.dtresearch.com.tw/zh/About/csr.html>



BASIC OPERATION GUIDE

DT301YA

INTRODUCTION

Thank you for acquiring the DT301YA, part of DT Research's line of Rugged Tablets. Featuring a slim yet robust enclosure, the DT301YA with 10.1" TFT display is powered by an Intel® Core™ Ultra processor, offering optimal combinations of performance and power savings. The DT301YA is available with Microsoft® Windows® operating system. The software operating system features web browser, client/ server computing software, media player, accessories, and applications support.

PACKAGE CONTENTS

- One DT301YA with battery pack and handstrap
- AC-DC power adapter with power cord
- Basic operation guide

* If your DT301YA contains camera or barcode scanner, please refer to the Tablet Modules Basic Operation Guide for detailed operation.



Input/ Output Ports

A Headphone jack	E DC-in jack
B LAN port	F Latest USB/charging
C USB 3.0 port	G Front camera (optional)
D Smart card reader	H Back camera (optional)

Button Functions

BUTTON	ACTION
1	Power button
2	Programmable buttons
3	Battery latch *Push the switch up to unlock the latch, then slide the latch left to remove the battery.

PRECAUTIONS

- Always exercise care when operating and handling the DT301YA.
- Do NOT apply excessive pressure to the display screen.
- We recommend using the Digital Pen (optional) to keep the screen clean.
- Avoid prolonged exposure of the display panel to any strong heat source. Wherever possible, the DT301YA should face away from direct light to reduce glare.
- If the AC-DC power adapter is used to recharge or power the tablet, do NOT use any AC-DC adapter other than the one provided or acquired from the manufacturer or its partners.
- In the unlikely event that smoke, abnormal noise, or strange odor is present, immediately power off the DT301YA and disconnect all power sources. Report the problem to your device provider immediately.
- Never attempt to disassemble the DT301YA, as this will void the warranty.

NOTE:

To obtain protection consistent with any IP rating for the device, the I/O (audio, power, USB, card reader, etc.) port doors must be closed. If the IP protection is compromised by mishandling or misuse, such as by leaving port doors open or improperly closed, any resulting product damage will not be covered under any DT Research warranty.

BASIC FEATURES

The DT301YA rugged tablet integrates a bright display, USB ports, and embedded networking elements such as wireless LAN .

A DT301YA typically integrates an 802.11be wireless LAN (WLAN) adapter that may connect to other wireless devices or access points. If your DT301YA does not come with such a network adapter, please consult your device provider to establish the desired network connectivity.

OPERATION

Powering ON and OFF

To activate the DT301YA, push and quickly release the Power Button. The display will come on in a few seconds. To put the DT301YA in Standby mode, push and quickly release the Power Button. To turn the DT301YA off for extended storage, power off safely using any software function that “shuts down computer” provided in the software operating system.

NOTE:

The battery pack shipped with your tablet may be low in power—please use the AC-DC adapter with the DT301YA when setting up for the first time to fully charge the battery pack, or use the optional battery charger kit.

NOTE:

When the battery pack is charging, the blue-colored Battery LED should blink slowly. If plugging in the AC-DC adapter does not trigger this blinking activity and the LED stays dark, the battery pack(s) may have been drained substantially. Try unplugging/ replugging the AC-DC adapter to the DT301Y a few times to activate the charging process.

NOTE:

To conserve power, use (push and quick release) the Power Button to put the tablet in “Standby” mode while not in use. Pushing briefly on the same button will wake up the system within seconds.

NOTE:

For DT301YA, avoid using the Power Button (“hold 4+ seconds” feature) to turn off the tablet—this form of hardware shutdown is intended to be a means of recovery from lockups, and not as normal operation.

Start Up

If the power up (from Standby mode or otherwise) is successful, the appropriate interface will be displayed after a launch sequence of several seconds. The wireless LAN connection may take 10 to 15 seconds to be established.

Configuring the Mobile Tablet

The DT301YA may be configured using the utilities and methods dictated by the software operating system. The DT301YA should be configurable for various properties such as user profiles, network features, and several system elements.

Wireless Networking

Wireless LAN

The DT301YA is often delivered with an embedded (user-inaccessible) 802.11be WLAN adapter equipped with a hidden custom antenna.

- Through the support of typical WLAN adapters, the DT301YA should be able to detect all 802.11 access points in the vicinity for you to select the access point of your choice for connection.
- The SSID and WEP/WPA/WPA2 (if enabled) parameters on the DT301YA and the access points have to match. The SSID is case-sensitive and it is recommended that you enable WEP/WPA/WPA2 encryption (or advanced alternatives) for secure access.
- When WEP/WPA/WPA2 is enabled, you may need to consult your network administrator or your networking equipment literature to properly configure associated settings such as Authentication mode, etc.
- Refer to the access point operating manuals for setting up the 802.11 access points.

USING THE TABLET

To Hold the Tablet

Left hand: grip the left back side of the tablet with your left hand four index fingers, with thumb resting on the top of the back side of the tablet and palm securely against the back.

Right hand: grip the right back side of the tablet with your right hand four index fingers, with thumb resting on the top of the back side of the tablet and palm securely against the back.




Peripherals Support

Through its USB ports, the DT301YA supports a wide range of USB-based peripherals. These peripherals are applicable for software installation, applications storage, data storage, and system software recovery and updates.

Replacing the Battery Pack

1. Slide the battery latch to the unlocked position.
2. Lift the battery pack off the compartment.
3. Fit another battery pack into place.
4. Slide the latch to the locked position.
5. If you want to purchase extra battery packs, please contact your dealers, or visit our Support page:
<https://www.dtresearch.com/en/Support/contact.html>



CAUTION:

- Disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion.
- Leaving a battery in an extremely high temperature surrounding environment that can result in an explosion or the leakage of flammable liquid or gas.

Battery Guidelines and Warnings

DT Research tablets and laptops are powered by lithium polymer battery packs in proprietary form factors. Battery configurations for the DT Research devices include internal (bridge or backup), removable or swappable implementations.

Battery usage cycles, or duration between necessary re-charge, vary with a number of factors, including device model, device usage pattern and battery health/aging. The DTR battery packs may be charged while attached to the device or when separated from the device and docked in proprietary battery charging cradles. Following the guidelines on good practice below can help to keep a battery pack healthy and prolong battery usage cycles and battery lifespan.

- For battery safety and optimal functionality and performance, we suggest charging the battery pack between 10 °C to 30 °C (50 °F to 86 °F).
- Avoid exposing the battery pack to extreme low temperatures or environmental conditions, low temperatures will cause shortened operating time and voltage instability, affecting the ability of the battery to deliver a consistent voltage. The appropriate operating temperature for the battery is 0 °C to 50 °C (32 °F to 122 °F).
- The battery is a consumable item, the rate of battery deterioration depends on the usage environment. Please be aware that improper usage may accelerate the aging process of the battery, thereby affecting its performance and lifespan. We suggest to replace the battery pack if signs of degradation or reduced performance occur.
- Avoid high heat conditions during operation, idle, charging, and storage states.
- Avoid letting the battery pack remain in very highly charged state or overly low charged state for extensive periods of time. Keeping the battery capacity between 30% and 80% of maximum capacity is recommended. The prevailing battery level(s) can be read from the Battery utility within the Windows operating system.
- Avoid letting the battery be over-discharged or depleted. Over-discharge can occur when a fully-discharged (0% level or thereabouts) battery pack is allowed to remain in such a state for an extended period of time (weeks or months). The embedded battery controls enter a protection mode and recharging will be prevented for safety reasons. To reduce the likelihood of over-discharge, consider recharging idle batteries regularly to some level between 30% to 80% of capacity.

- For long term storage, it is recommended that removable battery packs be stored separated from the device. Otherwise, the system should be placed in Shutdown mode. The battery level will decrease with time and it is recommended that the battery packs be monitored or recharged every 2 to 3 months to maintain battery health. The targeted battery level should be within 30% to 80% of maximum capacity.

Product End-of-Life Notice

For reuse and recycling facilities, please visit below link to get disassembly instructions:

<http://www.dtresearch.com.tw/zh/About/csr.html> or

http://www.dtresearch.com.tw/EPEAT/DT301Y_Product_End-of-Life_Disassembly_Instructions.pdf

RF Exposure Information (RED & UKCA)

To be protected against all verified adverse effects, the separation distance of at least 0mm must be maintained between the antenna of the radio having max. 4.0dBi antenna and all persons.

Hereby, [DT Research, Inc.] declares that the radio equipment type [DT301YA, DT311YA] is in compliance with Directive 2014/53/EU and UK Radio Equipment Regulations 2017. The full text of the EU and UK declaration of conformity is available at the following internet address: <http://www.dtresearch.com>.

The functions of Wireless Access Systems including Radio Local Area Networks(WAS/RLANs) within the band 5150-5350 MHz and 5945-6425MHz for this device are restricted to indoor use only within all European Union countries (BE/BG/CZ/DK/DE/EE/IE/EL/ES/FR/HR/ IT/CY/LV/LT/LU/HU/MT/NL/AT/PL/PT/RO/SI/SK/FI/SE/TR/N O/CH/IS/LI/UK(NI).

Maximum EIRP for EU

Wireless Band/Frequency:	Model: DT301YA	Model: DT311YA
Bluetooth:2402MHz-2480MHz	17.79dBm	16.39dBm
Bluetooth LE:2402MHz-2480MHz	17.60dBm	16.20dBm
Wifi: 2412MHz-2472MHz/2422MHz-2462MHz	19.96dBm	18.66dBm
Wifi: 5150MHz-5725MHz	19.39dBm	20.00dBm
Wifi: 5725MHz-5875MHz	13.25dBm	13.89dBm
Wifi: 5925MHz-6425MHz	19.27dBm	18.52dBm

This equipment complies with Directive 2014/53/EU and UK Radio Equipment Regulations 2017 radiation exposure limits set forth for an uncontrolled environment. End user must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The portable device is designed to meet the requirements for exposure to radio waves established by European Union market(France). These requirements set a SAR limit of 2W/kg averaged over one gram of tissue. The highest SAR value 0.94 W/kg reported under this standard during product certification for use when properly worn on the body.

The equipment has been tested with radios set to their highest transmission levels with following setup:

Mode	use against the head	worn or carried against the torso of the body	Worn on limbs
Separation	/	0 mm	/
SAR Value	/	0.94 W/kg	/
Sar Limit	2W/kg (over 10 g)	2W/kg (over 10 g)	4W/kg (over 10 g)

Body-worn accessories (e.g., carry case, belt clip) containing metallic components which has not been tested or certified may change the RF performance of the device, including its compliance with RF exposure. User shall avoid using such accessories and should operate at least the above stated separation distance to maintain RF exposure compliance.



Operating authorizations must exist to operate the product in the following member states of the European Union, refer to the table below.

				
AT	BE	BG	CH	CY
CZ	DE	DK	EE	EL
ES	FI	FR	HR	HU
IE	IS	IT	LI	LT
LU	LV	MT	NL	NO
PL	PT	RO	SE	SI
SK	TR	UK(NI)		



Importer Name: Concept International GmbH

Importer Address: Zweibrückenstr. 5-7 80331 München Germany

Federal Communication Commission Interference

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.

RF Exposure Compliance

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End user must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The portable device is designed to meet the requirements for exposure to radio waves established by the FCC. These requirements set a SAR limit of 1.6 W/kg averaged over one gram of tissue. The highest SAR value reported under this standard during product certification for use when properly worn on the body, with 0mm separation.

FCC ID Label is in removable battery compartment, it could be easily found by removing the battery cover.

Indoor Client 6CD statement

- a. That this device will only associate and connect with a low-power indoor Access Point, subordinate device, or standard access point and never directly link to any other client devices.
- b. This device will always initiate transmission under the control of a low-power indoor AP, subordinate or standard AP except for brief communications before joining a network. These quick messages will only occur if the client has detected an indoor AP, subordinate, or standard access point operating on a channel. These brief messages will have a time-out mechanism such that if it does not receive a response from an AP it will not continually repeat the request.
- c. This device when associated and connected with a low-power indoor access point, subordinate or standard access point device, will operate at a power lower as advertised by the indoor access point, subordinate, or standard access point (at some point in time testing will be required but FCC will provide advance notice before the requirement takes affect):
 - i. lower or equal to the power advertised by the low-power indoor access point or subordinate and never above the maximum output power allowed by the FCC grant for clients associated with indoor clients or subordinates.
 - ii. lower than or 6 dB below the power advertised by the standard access point.
- d. We acknowledging the device is prohibited for control of or communications with unmanned aircraft systems. including drones.

Supplier's Declaration of Conformity

47 CFR § 2.1077 Compliance Information

Unique Identifier Trade Name:

Model No.: DT301YA

Responsible Party – U.S. Contact Information

DT Research, Inc.

2000 Concourse Drive, San Jose, CA 95131

<http://www.dtresearch.com>



IC Compliance Statement

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

This equipment complies with IC RSS-102 radiation exposure limits set forth for an uncontrolled environment.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) L'appareil ne doit pas produire de brouillage;
- (2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Cet équipement est conforme aux limites d'exposition aux radiations IC CNR-102 établies pour un environnement non contrôlé.

This Class [B] digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe [B] est conforme à la norme NMB-003 du Canada.

RF Exposure Compliance

This equipment complies with ISED radiation exposure limits set forth for an uncontrolled environment. End user must follow the specific operating instructions for satisfying RF exposure compliance. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

The portable device is designed to meet the requirements for exposure to radio waves established by the ISED. These requirements set a SAR limit of 1.6 W/kg averaged over one gram of tissue. The highest SAR value reported under this standard during product certification for use when properly worn on the body, with 0mm separation.

Cet équipement est conforme aux limites d'exposition aux rayonnements ISED établies pour un environnement non contrôlé. L'utilisateur final doit suivre les instructions spécifiques pour satisfaire les normes. Cet émetteur ne doit pas être co-implanté ou fonctionner en conjonction avec toute autre antenne ou transmetteur.

Le dispositif portatif est conçu pour répondre aux exigences d'exposition aux ondes radio établie par le développement énergétique DURABLE. Ces exigences un SAR limite de 1,6 W/kg en moyenne pour un gramme de tissu. La valeur SAR la plus élevée signalée en vertu de cette norme lors de la certification de produit à utiliser lorsqu'il est correctement porté sur le corps, avec une séparation de 0mm.

The functions of Wireless Access Systems including Radio Local Area Networks(WAS/RLANs) within the band 5150-5250 MHz for this device are restricted to indoor use only.

Les fonctions des systèmes d'accès sans fil, y compris les réseaux locaux radioélectriques (WAS/RLAN), dans la bande 5150-5250 MHz de cet appareil sont limitées à une utilisation en intérieur.

IC Wi-Fi 6E Statement:

- a. Devices shall automatically stop transmitting if there is an absence of information to transmit or an operational failure. Note that the intention is not to prohibit either the transmission of control or signalling information, or the use of repetitive codes, where one or both are required by the technology. An explanation of how transmitting is stopped shall be included in the certification filing.
- b. Devices shall not be used for control of or communications with unmanned aircraft systems.
- c. Devices shall not be used on oil platforms.
- d. Devices shall not be used on aircraft.
- e. Devices shall not be used on aircraft, except for the low-power indoor access points, indoor subordinate devices, low-power client devices, and very low-power devices operating in the 5925-6425 MHz band, that may be used on large aircraft as defined in the Canadian Aviation Regulations, while flying above 3,048 metres(10,000 feet).
- f. Except for very low-power devices, devices shall not be used on trains.
- g. Except for very low-power devices, devices shall not be used on maritime vessels.
- h. Except for very low-power devices, devices shall not be used on automobiles.
- i. Client devices shall not be capable of initiating a network.
- j. Low-power indoor access points, indoor subordinate devices, low-power client devices, and very low-power devices operating in the 5925-6425 MHz band may be used on large aircraft, as defined in the Canadian Aviation Regulations, while flying above 3,048 metres (10,000 feet).

a. Les dispositifs doivent automatiquement cesser de transmettre s'il n'y a pas d'informations à transmettre ou s'il y a une défaillance opérationnelle. Il convient de noter que l'intention n'est pas d'interdire la transmission d'informations de contrôle ou de signalisation, ou l'utilisation de codes répétitifs, lorsque l'un ou l'autre est requis par la technologie. Une explication de la manière dont la transmission est interrompue doit être incluse dans le dossier de certification.

b. Les dispositifs ne doivent pas être utilisés pour contrôler les systèmes d'aéronefs sans pilote ou pour communiquer avec eux.

c. Les dispositifs ne doivent pas être utilisés sur des plates-formes pétrolières.

d. Les dispositifs ne doivent pas être utilisés sur des aéronefs.

e. Les dispositifs ne doivent pas être utilisés à bord des aéronefs, à l'exception des points d'accès intérieurs de faible puissance, des dispositifs subordonnés intérieurs, des dispositifs clients de faible puissance et des dispositifs de très faible puissance fonctionnant dans la bande 5925-6425 MHz, qui peuvent être utilisés à bord des grands aéronefs, tels que définis dans le règlement de l'aviation canadienne, lorsqu'ils volent à plus de 3 048 mètres (10 000 pieds).

f. À l'exception des dispositifs de très faible puissance, les dispositifs ne doivent pas être utilisés dans les trains.

g. À l'exception des dispositifs de très faible puissance, les dispositifs ne doivent pas être utilisés sur les navires maritimes.

h. À l'exception des dispositifs de très faible puissance, les dispositifs ne doivent pas être utilisés sur les automobiles.

i. Les dispositifs clients ne doivent pas être en mesure d'initier un réseau.

j. Les points d'accès intérieurs de faible puissance, les dispositifs subordonnés intérieurs, les dispositifs clients de faible puissance et les dispositifs de très faible puissance fonctionnant dans la bande 5925-6425 MHz peuvent être utilisés à bord de grands aéronefs, tels que définis dans le Règlement de l'aviation canadien, lorsqu'ils volent à plus de 3 048 mètres (10 000 pieds) d'altitude.