

**IEEE C95.1 2005
KDB 447498 D01 V06
47 C.F.R. Part 1, Subpart I, Section 1.1310
47 C.F.R. Part 2, Subpart J, Section 2.1091**

RF EXPOSURE REPORT

For

Bicycle Power Meter

Model: Power Pro-R, Power Pro-L

Trade Name: GIANT

Issued to

**Giant Manufacturing Co., Ltd.
No.19, Shunfan Rd., Dajia Dist., Taichung City 437, Taiwan (R.O.C.)**

Issued by

**Compliance Certification Services Inc.
Wugu Laboratory
No.11, Wugong 6th Rd., Wugu Dist.,
New Taipei City 24891, Taiwan. (R.O.C.)
<http://www.ccsrf.com>
Issued Date: April 17, 2018**



Revision History

Rev.	Issue Date	Revisions	Effect Page	Revised By
00	April 17, 2018	Initial Issue	ALL	Doris Chu

TABLE OF CONTENTS

1. TEST RESULT CERTIFICATION	4
2. LIMIT	5
3. EUT SPECIFICATION	5
4. TEST RESULTS	6
5. MAXIMUM PERMISSIBLE EXPOSURE.....	7

1. TEST RESULT CERTIFICATION

We hereby certify that:

The above equipment was tested by Compliance Certification Services Inc. The test data, data evaluation, test procedures, and equipment configurations shown in this report were made in accordance with the procedures given in ANSI C63.10: 2013 and the energy emitted by the sample EUT tested as described in this report is in compliance with the requirements of FCC Rules Part 15.207, 15.209, 15.247.

The test results of this report relate only to the tested sample EUT identified in this report.


APPLICABLE STANDARDS	
STANDARD	TEST RESULT
IEEE C95.1 2005 KDB 447498 D03 47 C.F.R. Part 1, Subpart I, Section 1.1310 47 C.F.R. Part 2, Subpart J, Section 2.1091	No non-compliance noted

Approved by:



Sam Chuang
Manager
Compliance Certification Services Inc.

Tested by:



Doris Chu
Report coordinator
Compliance Certification Services Inc.

2. LIMIT

According to §15.247(i), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See § 1.1307(b)(1) of this chapter.

3. EUT SPECIFICATION

EUT	Bicycle Power Meter				
Model	Power Pro-R, Power Pro-L				
Model Discrepancy	The two models use the same module, the difference for the fix location				
Trade Name	GIANT				
Frequency band (Operating)	☒ Bluetooth 4.0: 2402 ~ 2480MHz ANT+: 2401MHz ~ 2480MHz ☐ Others				
Device category	☐ Portable (<20cm separation) ☒ Mobile (>20cm separation) ☐ Others				
Exposure classification	☐ Occupational/Controlled exposure (S = 5mW/cm ²) ☒ General Population/Uncontrolled exposure (S=1mW/cm ²)				
Antenna Specification	Bluetooth 4.0: 0.00 dBi (Numeric gain: 1.00) ANT+: 0.00 dBi (Numeric gain: 1.00) Type: Monopole Antenna				
Max tune up Power	<table border="1"> <tr> <td>Bluetooth 4.0:</td><td>0.00dBm (1.000mW)</td></tr> <tr> <td>ANT+:</td><td>-4.00dBm (0.398mW)</td></tr> </table>	Bluetooth 4.0:	0.00dBm (1.000mW)	ANT+:	-4.00dBm (0.398mW)
Bluetooth 4.0:	0.00dBm (1.000mW)				
ANT+:	-4.00dBm (0.398mW)				
Evaluation applied	☒ MPE Evaluation* ☐ SAR Evaluation ☐ N/A				

4. TEST RESULTS

No non-compliance noted.

Calculation

Given $E = \frac{\sqrt{30 \times P \times G}}{d}$ & $S = \frac{E^2}{377}$

Where E = Field strength in Volts / meter

P = Power in Watts

G = Numeric antenna gain

d = Distance in meters

S = Power density in milliwatts / square centimeter

Combining equations and re-arranging the terms to express the distance as a function of the remaining variables yields:

$$S = \frac{30 \times P \times G}{377 d^2}$$

Changing to units of mW and cm, using:

$$P \text{ (mW)} = P \text{ (W)} / 1000 \text{ and}$$

$$d \text{ (cm)} = d \text{ (m)} / 100$$

Yields

$$S = \frac{30 \times (P / 1000) \times G}{377 \times (d / 100)^2} = 0.0796 \times \frac{P \times G}{d^2} \quad \textbf{Equation 1}$$

Where d = Distance in cm

P = Power in mW

G = Numeric antenna gain

S = Power density in mW / cm²

5. MAXIMUM PERMISSIBLE EXPOSURE

Substituting the MPE safe distance using $d = 20$ cm into Equation 1:

$$S = 0.000199 \times P \times G$$

Where P = Power in mW

G = Numeric antenna gain

S = Power density in mW / cm²

Bluetooth 4.0:

Ch.	Frq.(MHz)	P (mW)	Gain (num.)	D (cm)	Power density in mW / cm ²	Limit (mW/cm ²)
0	2402	1.000	1	20	0.0002	1.000

ANT+:

Ch.	Frq.(MHz)	P (mW)	Gain (num.)	D (cm)	Power density in mW / cm ²	Limit (mW/cm ²)
1	2401	0.398	1	20	0.0001	1.000