

FCC GSM/WCDMA REPORT

FCC Certification

Applicant Name:

LG Electronics MobileComm U.S.A., Inc.

Date of Issue:

March 22, 2017

Location:

HCT CO., LTD.,

Address:

1000 Sylvan Avenue, Englewood Cliffs NJ 07632

74, Seoicheon-ro 578beon-gil, Majang-myeon,
Icheon-si, Gyeonggi-do, 17383, Rep. of KOREA

Report No.: HCT-R-1703-F015

HCT FRN: 0005866421

FCC ID:

ZNFM320F

APPLICANT:

LG Electronics MobileComm U.S.A., Inc.

According to the Evaluation report, all of the data contained herein is reused from the reference FCC ID: ZNFM320H report.

FCC Model(s):

LG-M320F

Additional FCC Model(s):

LGM320F, M320F, LG-M320AR, LGM320AR, M320AR

EUT Type:

Portable Handset

FCC Classification:

Licensed Portable Transmitter Held to Ear (PCE)

FCC Rule Part(s):

§22, §24, §27, §2

Mode	Tx Frequency (MHz)	Rx Frequency (MHz)	Emission Designator	ERP	
				Max. Power (W)	Max. Power (dBm)
GSM850	824.2 – 848.8	869.2 – 893.8	249 KGXW	0.766	28.84
GSM850 EDGE			256 KG7W	0.198	22.97
WCDMA850	826.4 – 846.6	871.4 – 891.6	4M18F9W	0.087	19.41

Mode	Tx Frequency (MHz)	Rx Frequency (MHz)	Emission Designator	EIRP	
				Max. Power (W)	Max. Power (dBm)
GSM1900	1850.2 – 1909.8	1930.2 – 1989.8	250 KGXW	1.434	31.57
GSM1900 EDGE			254 KG7W	0.555	27.45
WCDMA1900	1852.4 – 1907.6	1932.4 – 1987.6	4M18F9W	0.231	23.65
WCDMA1700	1712.4 – 1752.6	2112.4 – 2152.6	4M18F9W	0.223	23.48

The measurements shown in this report were made in accordance with the procedures specified in CFR47 section §2.947. I assume full responsibility for the accuracy and completeness of these measurements, and for the qualifications of all persons taking them.

HCT CO., LTD. Certifies that no party to this application has subject to a denial of Federal benefits that includes FCC benefits pursuant to section 5301 of the Anti-Drug Abuse Act of 1998, 21 U.S.C. 853(a)



Report prepared by : Jeong Ho Kim
Engineer of Telecommunication Testing Center



Report approved by : Jong Seok Lee
Manager of Telecommunication Testing Center

This report only responds to the tested sample and may not be reproduced, except in full, without written approval of the HCT Co., Ltd.

Version

TEST REPORT NO.	DATE	DESCRIPTION
HCT-R-1703-F015	March 22, 2017	- First Approval Report

Table of Contents

1. GENERAL INFORMATION	4
2. INTRODUCTION	5
2.1. EUT DESCRIPTION.....	5
2.2. MEASURING INSTRUMENT CALIBRATION.....	5
2.3. TEST FACILITY	5
3. DESCRIPTION OF TESTS	6
3.1 ERP/EIRP RADIATED POWER AND RADIATED SPURIOUS EMISSIONS.....	6
3.2 PEAK- TO- AVERAGE RATIO	7
3.3 OCCUPIED BANDWIDTH.	9
3.4 SPURIOUS AND HARMONIC EMISSIONS AT ANTENNA TERMINAL.....	10
3.5 FREQUENCY STABILITY / VARIATION OF AMBIENT TEMPERATURE	11
4. LIST OF TEST EQUIPMENT	12
5. MEASUREMENT UNCERTAINTY	13
6. SUMMARY OF TEST RESULTS	14
7. SAMPLE CALCULATION	15
8. TEST DATA	16
8.1 EFFECTIVE RADIATED POWER	16
8.2 EQUIVALENT ISOTROPIC RADIATED POWER	17
8.3 RADIATED SPURIOUS EMISSIONS	19
8.3.1 RADIATED SPURIOUS EMISSIONS (GSM850)	19
8.3.2 RADIATED SPURIOUS EMISSIONS(GSM1900)	20
8.3.3 RADIATED SPURIOUS EMISSIONS (WCDMA850)	21
8.3.4 RADIATED SPURIOUS EMISSIONS (WCDMA1900)	22
8.3.5 RADIATED SPURIOUS EMISSIONS (WCDMA1700)	23
8.4 PEAK-TO-AVERAGE RATIO	24
8.5 OCCUPIED BANDWIDTH	25
8.6 CONDUCTED SPURIOUS EMISSIONS	26
8.6.1 BAND EDGE.....	26
8.7 FREQUENCY STABILITY / VARIATION OF AMBIENT TEMPERATURE	27
8.7.1 FREQUENCY STABILITY (GSM850)	27
8.7.2 FREQUENCY STABILITY (GSM1900)	28
8.7.3 FREQUENCY STABILITY (WCDMA850)	29
8.7.4 FREQUENCY STABILITY (WCDMA1900)	30
8.7.5 FREQUENCY STABILITY (WCDMA1700)	31
9. TEST PLOTS.....	32

MEASUREMENT REPORT

1. GENERAL INFORMATION

Applicant Name: LG Electronics MobileComm U.S.A., Inc.

Address: 1000 Sylvan Avenue, Englewood Cliffs NJ 07632

FCC ID: ZNFM320F

Application Type: Certification

FCC Classification: Licensed Portable Transmitter Held to Ear (PCE)

FCC Rule Part(s): §22, §24, §27, §2

EUT Type: Portable Handset

FCC Model(s): LG-M320F

Additional FCC Model(s): LGM320F, M320F, LG-M320AR, LGM320AR, M320AR

Tx Frequency: 824.20 - 848.80 MHz (GSM850)
826.40 - 846.60 MHz (WCDMA850)
1 850.20 - 1 909.80 MHz (GSM1900)
1 852.4 - 1 907.6 MHz (WCDMA1900)
1 712.4 - 1 752.6 MHz (WCDMA1700)

Rx Frequency: 869.20 - 893.80 MHz (GSM850)
871.40 - 891.60 MHz (WCDMA850)
1 930.20 - 1 989.80 MHz (GSM1900)
1 932.4 - 1 987.6 MHz (WCDMA1900)
2 112.4 - 2 152.6 MHz (WCDMA1700)

Max. RF Output Power: 0.766 W GSM850 (28.84 dBm) / 1.434 W GSM1900 (31.57 dBm)
0.198 W GSM850 EDGE (22.97 dBm) / 0.555 W GSM1900 EDGE (27.45 dBm)
0.087 W WCDMA850 (19.41 dBm) / 0.231 W WCDMA1900 (23.65 dBm)
0.223 W WCDMA1700 (23.48 dBm)

Emission Designator(s): 249 KGXW (GSM850) 250 KGXW (GSM1900)
256 KG7W (GSM850 EDGE) 254 KG7W (GSM1900 EDGE)
4M18F9W (WCDMA850) 4M18F9W (WCDMA1900)
4M18F9W (WCDMA1700)

Date(s) of Tests: January 03, 2017 ~ February 23, 2017

Antenna Specification: Manufacturer: AT&C Co.LTD.
Antenna type: PIFA Antenna (Planar Inverted F)
Peak Gain: GSM850/ WCDMA850 : -0.7 dBi dBi
GSM1900/ WCDMA1900 :1.6 dBi
WCDMA1700 : 0.5 dBi

2. INTRODUCTION

2.1. EUT DESCRIPTION

The LG Electronics MobileComm U.S.A., Inc. LG-M320F Portable Handset consists of GPRS Class12, EDGE12, GSM850, GSM1900, WCDMA850, WCDMA1900, WCDMA1700, HSDPA, HSUPA, DC-HSDPA and HSPA+.

2.2. MEASURING INSTRUMENT CALIBRATION

The measuring equipment, which was utilized in performing the tests documented herein, has been calibrated in accordance with the manufacturer's recommendations for utilizing calibration equipment, which is traceable to recognized national standards.

2.3. TEST FACILITY

The Fully-anechoic chamber and conducted measurement facility used to collect the radiated data are located at the **74, Seoicheon-ro 578beon-gil, Majang-myeon, Icheon-si, Gyeonggi-do, 17383, Rep. of KOREA.**

3. DESCRIPTION OF TESTS

3.1 ERP/EIRP RADIATED POWER AND RADIATED SPURIOUS EMISSIONS

Note: ERP(Effective Radiated Power), EIRP(Effective Isotropic Radiated Power)

Test Procedure

Radiated emission measurements are performed in the Fully-anechoic chamber. The equipment under test is placed on a non-conductive table 3-meters away from the receive antenna in accordance with ANSI/TIA-603-D-2010 Clause 2.2.17. The turntable is rotated through 360 degrees, and the receiving antenna scans in order to determine the level of the maximized emission. The level and position of the maximized emission is recorded with the spectrum analyzer using RMS detector.

A half wave dipole is then substituted in place of the EUT. For emissions above 1GHz, a horn antenna is substituted in place of the EUT. The substitute antenna is driven by a signal generator and the previously recorded signal was duplicated.

The power is calculated by the following formula;

$$P_{d(dBm)} = P_{g(dBm)} - \text{cable loss (dB)} + \text{antenna gain (dB)}$$

Where: P_d is the dipole equivalent power and P_g is the generator output power into the substitution antenna.

The maximum EIRP is calculated by adding the forward power to the calibrated source plus its appropriate gain value. These steps are repeated with the receiving antenna in both vertical and horizontal polarization. the difference between the gain of the horn and an isotropic antenna are taken into consideration

Radiated spurious emissions

1. Frequency Range : 9 kHz ~ 10th Harmonics of highest channel fundamental frequency.
2. The EUT was setup to maximum output power. The 100 kHz RBW was used to scan from 30 MHz to 1 GHz. Also, the 1 MHz RBW was used to scan from 1 GHz to 10 GHz(GSM850/WCDMA850) or 20 GHz(GSM1900/WCDMA1900/WCDMA1700). The high, low and a middle channel were tested for out of band measurements.

3.2 PEAK- TO- AVERAGE RATIO

Test Procedure

Peak to Average Power Ratio is tested in accordance with KDB971168 D01 Power Meas License Digital Systems v02r02, October 17, 2014, Section 5.7.

- Section 5.7.1 CCDF Procedure for PAPR

- a) Set resolution/measurement bandwidth $\geq$ signal's occupied bandwidth;
- b) Set the number of counts to a value that stabilizes the measured CCDF curve;
- c) Set the measurement interval as follows:
 - 1) for continuous transmissions, set to 1 ms,
 - 2) for burst transmissions, employ an external trigger that is synchronized with the EUT burst timing sequence, or use the internal burst trigger with a trigger level that allows the burst to stabilize and set the measurement interval to a time that is less than or equal to the burst duration.
- d) Record the maximum PAPR level associated with a probability of 0.1%.

- Section 5.7.2 Alternate Procedure for PAPR

Use one of the procedures presented in 5.1 to measure the total peak power and record as P_{Pk} . Use one of the applicable procedures presented 5.2 to measure the total average power and record as P_{Avg} . Determine the P.A.R. from: $P.A.R_{(dB)} = P_{Pk (dBm)} - P_{Avg (dBm)}$ (P_{Avg} = Average Power + Duty cycle Factor)

5.1.1 Peak power measurements with a spectrum/signal analyzer or EMI receiver

The following procedure can be used to determine the total peak output power.

- a) Set the RBW $\geq$ OBW.
- b) Set VBW $\geq 3 \times$ RBW.
- c) Set span $\geq 2 \times$ RBW
- d) Sweep time = auto couple.
- e) Detector = peak.
- f) Ensure that the number of measurement points $\geq$ span/RBW.
- g) Trace mode = max hold.
- h) Allow trace to fully stabilize.
- i) Use the peak marker function to determine the peak amplitude level.

5.2.2 Procedures for use with a spectrum/signal analyzer when EUT cannot be configured to transmit continuously and sweep triggering/signal gating cannot be properly implemented

If the EUT cannot be configured to transmit continuously (burst duty cycle < 98%), then one of the following procedures can be used. The selection of the applicable procedure will depend on the characteristics of the measured burst duty cycle.

Measure the burst duty cycle with a spectrum/signal analyzer or EMC receiver can be used in zero-span mode if the response time and spacing between bins on the sweep are sufficient to permit accurate measurement of the burst on/off time of the transmitted signal.

5.2.2.2 Constant burst duty cycle


If the measured burst duty cycle is constant (i.e., duty cycle variations are less than ± 2 percent), then:

- a) Set span to at least 1.5 times the OBW.
- b) Set RBW = 1-5% of the OBW, not to exceed 1 MHz.
- c) Set VBW $\geq 3 \times$ RBW.
- d) Number of points in sweep $\geq 2 \times$ span / RBW. (This gives bin-to-bin spacing $\leq$ RBW/2, so that narrowband signals are not lost between frequency bins.)
- e) Sweep time = auto.
- f) Detector = RMS (power averaging).
- g) Set sweep trigger to "free run".
- h) Trace average at least 100 traces in power averaging (i.e., RMS) mode.
- i) Compute power by integrating the spectrum across the OBW of the signal using the instrument's band power measurement function with band limits set equal to the OBW band edges. If the instrument does not have a band power function, sum the spectrum levels (in power units) at intervals equal to the RBW extending across the entire OBW of the spectrum.
- j) Add $10 \log (1/x)$, where x is the duty cycle, to the measured power in order to compute the average power during the actual transmission times (because the measurement represents an average over both the on and off times of the transmission).

For example, add $10 \log (1/0.25) = 6$ dB if the duty cycle is a constant 25%.

3.3 OCCUPIED BANDWIDTH.

Test set-up



(Configuration of conducted Emission measurement)

The width of a frequency band such that, below the lower and above the upper frequency limits, the mean powers emitted are each equal to a specified percentage 0.5 % of the total mean power of a given emission.

Test Procedure

OBW is tested in accordance with KDB971168 D01 Power Meas License Digital Systems v02r02, October 17, 2014, Section 4.2.

The EUT makes a call to the communication simulator. The power was measured with R&S Spectrum Analyzer. All measurements were done at 3 channels(low, middle and high operational range.)

The conducted occupied bandwidth used the power splitter via EUT RF power connector between simulation base station and spectrum analyzer.

The communication simulator station system controlled a EUT to export maximum output power under transmission mode and specific channel frequency. Use OBW measurement function of Spectrum analyzer to measure 99 % occupied bandwidth

3.4 SPURIOUS AND HARMONIC EMISSIONS AT ANTENNA TERMINAL.

Test Procedure

Spurious and harmonic emissions at antenna terminal is tested in accordance with KDB971168 D01 Power Meas License Digital Systems v02r02, October 17, 2014, Section 6.0.

The level of the carrier and the various conducted spurious and harmonic frequencies is measured by means of a calibrated spectrum analyzer.

On any frequency outside a licensee's frequency block, the power of any emission shall be attenuated below the transmitter power (P) by at least $43 + 10 \log(P)$ dB. The RBW settings used in the testing are greater than 1 % of the occupied bw. The 1 MHz RBW was used to scan from 10 MHz to 10 GHz. (GSM1900 Mode: 10 MHz to 20 GHz). A display line was placed at - 13 dBm to show compliance. The high, lowest and a middle channel were tested for out of band measurements.

Measurements of all out of band are made on RBW = 1MHz and VBW $\geq$ 3 MHz in the worst case despite RBW = 100 kHz and VBW $\geq$ 300 kHz upon 1 GHz.

- RBW = 1 MHz
- VBW $\geq$ 3 MHz
- Detector = Peak
- Trace Mode = max hold
- Sweep time = auto
- Number of points in sweep $\geq 2 * \text{Span} / \text{RBW}$

- Band Edge Requirement : According to FCC 22.917, 24.238, 27.53 specified that power of any emission outside of The authorized operating frequency ranges must be attenuated below the transmitting power (P) by a factor of at least $43 + 10 \log(P)$ dB. In the 1 MHz bands immediately outside and adjacent to the frequency block a resolution bandwidth of at least one percent of the emission bandwidth of the fundamental emission of the transmitter may be employed.

All measurements were done at 2 channels(low and high operational frequency range.)

The band edge measurement used the power splitter via EUT RF power connector between simulation base station and spectrum analyzer.

In GSM mode, the center frequency of spectrum set to the band edge frequency. The span is 1MHz (RBW = at least 1 % of the EBW, VBW $\geq 3*RBW$, Detector = Average).


In WCDMA mode, the center frequency of spectrum set to the band edge frequency. The span is 7MHz (RBW = at least 1% of the EBW, $\geq 3*RBW$, Detector = Average).

NOTES: The analyzer plot offsets were determined by below conditions.

- For GSM850 and WCDMA850, total offset 26.9 dB = 20 dB attenuator + 6 dB Splitter + 0.9 dB RF cables.
- For GSM1900 and WCDMA1900, total offset 27.35 dB = 20 dB attenuator + 6 dB Splitter + 1.35 dB RF cables.
- For WCDMA1700, total offset 27.15 dB = 20 dB attenuator + 6 dB Splitter + 1.15 dB RF cables.

3.5 FREQUENCY STABILITY / VARIATION OF AMBIENT TEMPERATURE

Test Set-up



* Nominal Operating Voltage

Test Procedure

Frequency stability is tested in accordance with ANSI/TIA-603-D-2010 section 2.2.2.

The frequency stability of the transmitter is measured by:

- a.) **Temperature:** The temperature is varied from - 30 °C to + 50 °C using an environmental chamber.
- b.) **Primary Supply Voltage:** The primary supply voltage is varied from battery end point to 100 % of the voltage normally at the input to the device or at the power supply terminals if cables are not normally supplied.

Specification — the frequency stability shall be sufficient to ensure that the fundamental emission stays within the authorized frequency block(GSM1900/WCDMA1900/WCDMA1700). The frequency stability of the transmitter shall be maintained within $\pm 0.00025\%$ (± 2.5 ppm) of the center frequency(GSM850/WCDMA850).

Time Period and Procedure:

The carrier frequency of the transmitter is measured at room temperature (20°C to provide a reference).

1. The equipment is turned on in a "standby" condition for one minute before applying power to the transmitter. Measurement of the carrier frequency of the transmitter is made within one minute after applying power to the transmitter.
2. Frequency measurements are made at 10°C intervals ranging from -30°C to +50°C. A period of at least one half-hour is provided to allow stabilization of the equipment at each temperature level.

NOTE: The EUT is tested down to the battery endpoint.

4. LIST OF TEST EQUIPMENT

Manufacture	Model/ Equipment	Serial Number	Calibration Date	Calibration Interval	Calibration Due
REOHDE & SCHWARZ	SCU 18 / AMPLIFIER	10094	09/07/2016	Annual	09/07/2017
Wainwright	WHK1.2/15G-10EF/H.P.F	4	04/11/2016	Annual	04/11/2017
Wainwright	WHK3.3/18G-10EF/H.P.F	2	04/11/2016	Annual	04/11/2017
Hewlett Packard	11667B / Power Splitter	10545	02/15/2017	Annual	02/15/2018
Hewlett Packard	11667B / Power Splitter	11275	04/29/2016	Annual	04/29/2017
Agilent	E3632A/DC Power Supply	KR75303243	07/12/2016	Annual	07/12/2017
Schwarzbeck	UHAP/ Dipole Antenna	557	03/23/2015	Biennial	03/23/2017
Schwarzbeck	UHAP/ Dipole Antenna	558	03/23/2015	Biennial	03/23/2017
EXP	EX-TH400/ Chamber	None	05/31/2016	Annual	05/31/2017
Schwarzbeck	BBHA 9120D/ Horn Antenna	147	09/09/2016	Biennial	09/09/2018
Schwarzbeck	BBHA 9120D/ Horn Antenna	1299	05/15/2015	Biennial	05/15/2017
Schwarzbeck	BBHA 9170/ Horn Antenna(15~40GHz)	BBHA9170342	04/30/2015	Biennial	04/30/2017
Schwarzbeck	BBHA 9170/ Horn Antenna(15~35GHz)	BBHA9170124	04/30/2015	Biennial	04/30/2017
Agilent	N9020A/Signal Analyzer	MY52090906	05/13/2016	Annual	05/13/2017
Hewlett Packard	8493C/ATTENUATOR	17280	06/22/2016	Annual	06/22/2017
REOHDE & SCHWARZ	FSV40/Spectrum Analyzer	1307.9002K40-100931-NK	06/15/2016	Annual	06/15/2017
Agilent	8960 (E5515C)/ Base Station(Now)	MY48360800	10/19/2016	Annual	10/19/2017
Schwarzbeck	FMZB1513/ Loop Antenna(9kHz~30MHz)	1513-175	02/23/2016	Biennial	02/23/2018
Schwarzbeck	VULB9160/ Bilog Antenna	3150	09/30/2016	Biennial	09/30/2018
Schwarzbeck	VULB9160/ Bilog Antenna	3368	10/14/2016	Biennial	10/14/2018
Anritsu Corp.	MT8820C/Wideband Radio Communication Tester	6200576565	07/05/2016	Annual	07/05/2017
Anritsu Corp.	MT8820C/Wideband Radio Communication Tester	6201026545	02/13/2017	Annual	02/13/2018

5. MEASUREMENT UNCERTAINTY

The measurement uncertainties shown below were calculated in accordance with the requirements of ANSI C63.4:2014.

All measurement uncertainty values are shown with a coverage factor of $k = 2$ to indicate a 95 % level of confidence. The measurement data shown herein meets or exceeds the U_{CISPR} measurement uncertainty values specified in CISPR 16-4-2 and, thus, can be compared directly to specified limits to determine compliance.

Parameter	Expanded Uncertainty ($\pm$ dB)
Conducted Disturbance (150 kHz ~ 30 MHz)	1.82
Radiated Disturbance (9 kHz ~ 30 MHz)	3.40
Radiated Disturbance (30 MHz ~ 1 GHz)	4.80
Radiated Disturbance (1 GHz ~ 18 GHz)	6.07

6. SUMMARY OF TEST RESULTS

FCC Part Section(s)	Test Description	Test Limit	Test Condition	Test Result
2.1049	Occupied Bandwidth	N/A	CONDUCTED	PASS
2.1051, 22.917(a), 24.238(a), 27.53(h)	Band Edge / Spurious and Harmonic Emissions at Antenna Terminal.	< 43 + 10log10 (P[Watts]) at Band Edge and for all out-of-band emissions		PASS
2.1046	* Conducted Output Power	-		PASS
24.232(d), 27.50(d)(5)	Peak- to- Average Ratio	< 13 dB		PASS
2.1055, 22.355	Frequency stability / variation of ambient temperature	< 2.5 ppm (Part22)		PASS
24.235, 27.54		Emission must remain in band (Part24, 27)		PASS
22.913(a)(2)	Effective Radiated Power	< 7 Watts max. ERP	RADIATED	PASS
24.232(c)	Equivalent Isotropic Radiated Power	< 2 Watts max. EIRP		PASS
27.50(d)(4)	Equivalent Isotropic Radiated Power	<1 Watts max. EIRP		PASS
2.1053, 22.917(a), 24.238(a), 27.53(h)	Radiated Spurious and Harmonic Emissions	< 43 + 10log10 (P[Watts]) for all out-of band emissions		PASS

*: See SAR Report

7. SAMPLE CALCULATION

A. ERP Sample Calculation

Mode	Ch./ Freq.		Measured Level(dBm)	Substitute LEVEL(dBm)	Ant. Gain (dBd)	C.L	Pol.	Limit	ERP	
	channel	Freq.(MHz)						W	W	dBm
GSM850	128	824.20	-21.37	38.40	-10.61	0.95	H	< 7.00	0.483	26.84

ERP = Substitute LEVEL(dBm) + Ant. Gain – CL(Cable Loss)

- 1) The EUT mounted on a non-conductive turntable is 2.5 meter above test site ground level.
- 2) During the test , the turn table is rotated until the maximum signal is found.
- 3) Record the field strength meter's level.
- 4) Replace the EUT with dipole/Horn antenna that is connected to a calibrated signal generator.
- 5) Increase the signal generator output till the field strength meter's level is equal to the item (3).
- 6) The signal generator output level with Ant. Gain and cable loss are the rating of effective radiated power (**ERP**).

B. Emission Designator

GSM Emission Designator

Emission Designator = 249KGXW

GSM BW = 249 kHz

G = Phase Modulation

X = Cases not otherwise covered

W = Combination (Audio/Data)

EDGE Emission Designator

Emission Designator = 249KG7W

GSM BW = 249 kHz

G = Phase Modulation

7 = Quantized/Digital Info

W = Combination (Audio/Data)

WCDMA Emission Designator

Emission Designator = 4M17F9W

WCDMA BW = 4.17 MHz

F = Frequency Modulation

9 = Composite Digital Info

W = Combination (Audio/Data)

8. TEST DATA

8.1 EFFECTIVE RADIATED POWER

(GSM850 Mode)

Mode	Ch./ Freq.		Measured Level (dBm)	Substitute LEVEL (dBm)	Ant. Gain (dBd)	C.L	Pol.	Limit	ERP	
	channel	Freq.(MHz)						W	W	dBm
GSM850	128	824.2	-21.42	41.10	-10.59	1.67	H	< 7.00	0.766	28.84
	190	836.6	-22.62	40.98	-10.54	1.68	H		0.751	28.76
	251	848.8	-23.03	39.98	-10.48	1.69	H		0.604	27.81
EDGE	128	824.2	-27.29	35.23	-10.59	1.67	H		0.198	22.97

(WCDMA850 Mode)

Mode	Ch./ Freq.		Measured Level (dBm)	Substitute LEVEL (dBm)	Ant. Gain (dBd)	C.L	Pol.	Limit	ERP	
	channel	Freq.(MHz)						W	W	dBm
WCDMA850	4132	826.4	-31.20	31.57	-10.58	1.67	H	< 7.00	0.085	19.32
	4183	836.6	-31.97	31.63	-10.54	1.68	H		0.087	19.41
	4233	846.6	-32.11	31.13	-10.50	1.69	H		0.078	18.94

Note: Standard batteries are the only options for this phone.

NOTES:

Effective Radiated Power Output Measurements by Substitution Method according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:

The EUT was placed on a non-conductive styrofoam resin table 3-meters from the receive antenna. Turntable rotation was adjusted for the highest reading on the receive spectrum analyzer. For WCDMA, GSM signals, RBW = 1-5% of the OBW, not to exceed 1MHz, VBW $\geq 3 \times$ RBW, Detector = RMS. A half-wave dipole was substituted in place of the EUT. This dipole antenna was driven by a signal generator and the level of the signal generator was adjusted to obtain the same receive spectrum analyzer reading. The conducted power at the terminals of the dipole is measured. The ERP is recorded.

This device was tested under all configurations and the highest power is reported in WCDMA mode with HSDPA Inactive at 12.2 kbps RMC and TPC bits all set to "1" and in GSM mode using a Power Control Level of "0" in the PCS Band and "5" in the Cellular Band. This unit was tested with its standard battery. Also, we have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna. The worst case of the EUT is x plane in GSM850 and WCDMA850 mode. Also worst case of detecting Antenna is in horizontal polarization in GSM850 and WCDMA850 mode.

The EDGE mode testing were performed using 1Tx because 1Tx is highest power in EDGE mode.

8.2 EQUIVALENT ISOTROPIC RADIATED POWER

(GSM1900 Mode)

Mode	Ch./ Freq.		Measured Level (dBm)	Substitute LEVEL (dBm)	Ant. Gain (dBi)	C.L	Pol.	Limit	EIRP	
	channel	Freq.(MHz)						W	W	dBm
GSM1900	512	1850.2	-9.73	23.88	9.82	2.54	H	< 2.00	1.306	31.16
	661	1880.0	-9.65	24.23	9.91	2.57	H		1.434	31.57
	810	1909.8	-11.10	23.14	10.00	2.60	H		1.132	30.54
EDGE	661	1880.0	-13.77	20.11	9.91	2.57	H		0.555	27.45

Note: Standard batteries are the only options for this phone.

NOTES:

Equivalent Isotropic Radiated Power Measurements by Substitution Method
according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:

The EUT was placed on a non-conductive styrofoam resin table 3-meters from the receive antenna. Turntable rotation was adjusted for the highest reading on the receive spectrum analyzer. For GSM signals, RBW = 1-5% of the OBW, not to exceed 1MHz, VBW $\geq 3 \times$ RBW, Detector = RMS. A Horn antenna was substituted in place of the EUT. This Horn antenna was driven by a signal generator and the level of the signal generator was adjusted to obtain the same receive spectrum analyzer reading. The conducted power at the terminals of the Horn antenna is measured. The difference between the gain of the horn and an isotropic antenna is taken into consideration and the EIRP is recorded.

This device was tested under all configurations and the highest power is reported in GSM mode using a Power Control Level of "0" in the PCS Band and "5" in the Cellular Band. This unit was tested with its standard battery. Also, we have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna. The worst case of the EUT is x plane in GSM1900 mode. Also worst case of detecting Antenna is in horizontal polarization in GSM1900 mode.

The EDGE mode testing were performed using 1Tx because 1Tx is highest power in EDGE mode.

(WCDMA1900 Mode)

Mode	Ch./ Freq.		Measured Level (dBm)	Substitute LEVEL (dBm)	Ant. Gain (dBi)	C.L	Pol.	Limit	EIRP	
	channel	Freq.(MHz)						W	W	dBm
WCDMA1900	9262	1852.4	-17.75	15.86	9.82	2.54	H	< 2.00	0.206	23.14
	9400	1880.0	-17.57	16.31	9.91	2.57	H		0.231	23.65
	9538	1907.6	-18.41	15.83	10.00	2.60	H		0.210	23.23

(WCDMA1700 Mode)

Mode	Ch./ Freq.		Measured Level (dBm)	Substitute LEVEL (dBm)	Ant. Gain (dBi)	C.L	Pol.	Limit	EIRP	
	channel	Freq.(MHz)						W	W	dBm
WCDMA1700	1312	1712.4	-19.30	14.04	9.37	2.45	V	< 1.00	0.125	20.96
	1412	1732.4	-18.49	14.83	9.44	2.47	V		0.151	21.80
	1513	1752.6	-16.88	16.44	9.51	2.47	V		0.223	23.48

Note: Standard batteries are the only options for this phone.

NOTES:
Equivalent Isotropic Radiated Power Measurements by Substitution Method

according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:

The EUT was placed on a non-conductive styrofoam resin table 3-meters from the receive antenna. Turntable rotation was adjusted for the highest reading on the receive spectrum analyzer. For WCDMA signals, rotation was adjusted for the highest reading on the receive spectrum analyzer. For WCDMA signals, RBW = 1-5% of the OBW, not to exceed 1MHz, VBW ≥ 3 x RBW, Detector = RMS. A Horn antenna was substituted in place of the EUT. This Horn antenna was driven by a signal generator and the level of the signal generator was adjusted to obtain the same receive spectrum analyzer reading. The conducted power at the terminals of the Horn antenna is measured. The difference between the gain of the horn and an isotropic antenna is taken into consideration and the EIRP is recorded.

This device was tested under all configurations and the highest power is reported in WCDMA mode with HSDPA Inactive at 12.2 kbps RMC and TPC bits all set to "1". This unit was tested with its standard battery. Also, we have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna. The worst case of the EUT is x plane in WCDMA1900 and WCDMA1700 (z plane) mode. Also worst case of detecting Antenna is in horizontal polarization in WCDMA1900 and WCDMA1700 (vertical polarization) mode.

8.3 RADIATED SPURIOUS EMISSIONS

8.3.1 RADIATED SPURIOUS EMISSIONS (GSM850)

- ☒ MEASURED OUTPUT POWER: 28.84 dBm = 0.766 W
☒ MODULATION SIGNAL: GSM850
☒ DISTANCE: 3 meters
☒ LIMIT: $43 + 10 \log_{10}(W) =$ 41.84 dBc

Ch.	Freq.(MHz)	Measured Level [dBm]	Ant. Gain (dBd)	Substitute Level [dBm]	C.L	Pol.	ERP (dBm)	dBc
128 (824.2)	1,648.40	-48.34	9.15	-59.04	1.17	H	-51.06	79.90
	2,472.60	-43.68	10.92	-51.00	1.18	H	-41.26	70.10
	3,296.80	-54.99	11.93	-62.47	1.40	H	-51.94	80.78
	4,121.00	-50.96	12.73	-56.19	1.88	H	-45.34	74.18
190 (836.6)	1,673.20	-48.38	9.23	-59.07	1.17	H	-51.01	79.85
	2,509.80	-45.26	10.96	-52.89	1.24	V	-43.17	72.01
	3,346.40	-56.04	12.02	-63.76	1.45	V	-53.19	82.03
	4,183.00	-48.85	12.74	-54.20	1.94	V	-43.40	72.24
251 (848.8)	1,697.60	-49.28	9.30	-59.98	1.16	H	-51.84	80.68
	2,546.40	-45.05	10.98	-52.51	1.21	H	-42.74	71.58
	3,395.20	-54.01	12.14	-61.63	1.49	V	-50.98	79.82
	4,244.00	-49.33	12.74	-54.74	1.97	H	-43.97	72.81

- NOTES:**
1. Radiated Spurious Emission Measurements at 3 meters by Substitution Method according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:
 2. We are performed all frequency to 10th harmonics from 9 kHz. Measurements above show only up to 3 maximum emissions noted, or would be lesser if no specific emissions from the EUT are recorded (ie: margin > 20 dB from the applicable limit) and considered that's already beyond the background noise floor.
 3. We have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna.

8.3.2 RADIATED SPURIOUS EMISSIONS(GSM1900)

- MEASURED OUTPUT POWER: 31.57 dBm = 1.434 W
 ■ MODULATION SIGNAL: GSM1900
 ■ DISTANCE: 3 meters
 ■ LIMIT: $43 + 10 \log_{10} (W) =$ 44.57 dBc

Ch.	Freq.(MHz)	<u>Measured Level</u> [dBm]	Ant. Gain (dBi)	<u>Substitute</u> <u>Level</u> [dBm]	C.L	Pol.	EIRP (dBm)	dBc
512 (1850.2)	3,700.40	-52.11	12.52	-58.15	1.69	V	-47.32	78.89
	5,550.60	-43.02	13.29	-43.58	2.82	V	-33.11	64.68
	7,400.80	-53.95	11.72	-49.59	3.85	V	-41.72	73.29
	9,251.00	-49.63	11.49	-40.48	4.72	H	-33.71	65.28
661 (1880.0)	3,760.00	-54.38	12.56	-60.21	1.67	H	-49.32	80.89
	5,640.00	-44.75	13.30	-44.89	2.90	V	-34.49	66.06
	7,520.00	-54.99	11.70	-50.71	3.98	V	-42.99	74.56
	9,400.00	-51.10	11.43	-41.89	4.63	H	-35.09	66.66
	11,280.00	-55.97	11.06	-44.33	5.46	H	-38.73	70.30
810 (1909.8)	3,819.60	-54.77	12.60	-60.28	1.65	H	-49.33	80.90
	5,729.40	-47.52	13.31	-46.59	2.92	V	-36.20	67.77
	7,639.20	-53.14	11.61	-49.03	3.99	H	-41.41	72.98
	9,549.00	-52.68	11.35	-44.01	4.77	H	-37.43	69.00

- NOTES:**
1. Radiated Spurious Emission Measurements at 3 meters by Substitution Method according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:
 2. We are performed all frequency to 10th harmonics from 9 kHz. Measurements above show only up to 3 maximum emissions noted, or would be lesser if no specific emissions from the EUT are recorded (ie: margin > 20 dB from the applicable limit) and considered that's already beyond the background noise floor.
 3. We have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna.

8.3.3 RADIATED SPURIOUS EMISSIONS (WCDMA850)

- MEASURED OUTPUT POWER: 19.41 dBm = 0.087 W
- MODULATION SIGNAL: WCDMA850
- DISTANCE: 3 meters
- LIMIT: $43 + 10 \log_{10} (W) =$ 32.41 dBc

Ch.	Freq.(MHz)	<u>Measured Level</u> [dBm]	Ant. Gain (dBd)	<u>Substitute</u> <u>Level</u> [dBm]	C.L	Pol.	ERP (dBm)	dBc
4,132 (826.4)	1,652.80	-57.00	9.17	-67.74	1.17	H	-59.74	79.15
	2,479.20	-57.45	10.93	-64.82	1.18	H	-55.07	74.48
	3,305.60	-56.49	11.95	-64.02	1.41	H	-53.48	72.89
4,183 (836.6)	1,673.20	-56.34	9.24	-67.04	1.17	V	-58.97	78.38
	2,509.80	-57.90	10.96	-65.66	1.24	V	-55.94	75.35
	3,346.40	-56.73	12.03	-64.46	1.45	H	-53.88	73.29
4,233 (846.6)	1,693.20	-57.16	9.30	-67.86	1.16	H	-59.72	79.13
	2,539.80	-55.92	10.98	-63.48	1.21	V	-53.71	73.12
	3,386.40	-55.78	12.12	-63.53	1.48	H	-52.89	72.30

- NOTES:**
1. Radiated Spurious Emission Measurements at 3 meters by Substitution Method according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:
 2. We are performed all frequency to 10th harmonics from 9 kHz. Measurements above show only up to 3 maximum emissions noted, or would be lesser if no specific emissions from the EUT are recorded (ie: margin > 20 dB from the applicable limit) and considered that's already beyond the background noise floor.
 3. We have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna.

8.3.4 RADIATED SPURIOUS EMISSIONS (WCDMA1900)

- MEASURED OUTPUT POWER: 23.65 dBm = 0.231 W
- MODULATION SIGNAL: WCDMA1900
- DISTANCE: 3 meters
- LIMIT: $43 + 10 \log_{10} (W) =$ 36.65 dBc

Ch.	Freq.(MHz)	<u>Measured Level</u> [dBm]	Ant. Gain (dBi)	<u>Substitute</u> <u>Level</u> [dBm]	C.L	Pol.	EIRP (dBm)	dBc
9262 (1852.4)	3,704.80	-57.35	12.52	-63.12	1.68	V	-52.28	75.93
	5,557.20	-52.57	13.29	-53.00	2.82	V	-42.53	66.18
	7,409.60	-55.21	11.72	-50.56	3.89	V	-42.73	66.38
9400 (1880.0)	3,760.00	-55.08	12.56	-60.90	1.67	H	-50.01	73.66
	5,640.00	-54.14	13.30	-54.29	2.90	V	-43.89	67.54
	7,520.00	-55.40	11.70	-51.13	3.98	V	-43.41	67.06
9538 (1907.6)	3,815.20	-56.17	12.60	-61.67	1.66	V	-50.73	74.38
	5,722.80	-53.45	13.31	-52.35	2.91	V	-41.95	65.60
	7,630.40	-53.93	11.62	-49.90	3.98	H	-42.26	65.91

- NOTES:**
1. Radiated Spurious Emission Measurements at 3 meters by Substitution Method according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:
 2. We are performed all frequency to 10th harmonics from 9 kHz. Measurements above show only up to 3 maximum emissions noted, or would be lesser if no specific emissions from the EUT are recorded (ie: margin > 20 dB from the applicable limit) and considered that's already beyond the background noise floor.
 3. We have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna.

8.3.5 RADIATED SPURIOUS EMISSIONS (WCDMA1700)

- MEASURED OUTPUT POWER: 23.48 dBm = 0.223 W
- MODULATION SIGNAL: WCDMA1700
- DISTANCE: 3 meters
- LIMIT: $43 + 10 \log_{10} (W) =$ 36.48 dBc

Ch.	Freq.(MHz)	<u>Measured Level</u> [dBm]	Ant. Gain (dBi)	<u>Substitute</u> <u>Level</u> [dBm]	C.L	Pol.	EIRP (dBm)	dBc
1312 (1712.4)	3,424.80	-46.87	12.20	-54.16	1.49	H	-43.45	66.93
	5,137.20	-52.33	12.77	-53.19	2.50	H	-42.92	66.40
	6,849.60	-54.74	12.04	-50.71	3.49	V	-42.16	65.64
1412 (1732.4)	3,464.80	-46.36	12.28	-53.25	1.49	H	-42.46	65.94
	5,197.20	-51.95	12.86	-52.99	2.56	H	-42.70	66.18
	6,929.60	-56.48	11.87	-51.88	3.53	V	-43.54	67.02
1513 (1752.6)	3,505.20	-43.44	12.35	-49.97	1.54	H	-39.16	62.64
	5,257.80	-48.91	12.94	-50.73	2.63	V	-40.42	63.90
	7,010.40	-51.90	11.73	-49.38	3.64	H	-41.29	64.77

- NOTES:**
1. Radiated Spurious Emission Measurements at 3 meters by Substitution Method according to ANSI/TIA/EIA-603-D-2010 June 24, 2010:
 2. We are performed all frequency to 10th harmonics from 9 kHz. Measurements above show only up to 3 maximum emissions noted, or would be lesser if no specific emissions from the EUT are recorded (ie: margin > 20 dB from the applicable limit) and considered that's already beyond the background noise floor.
 3. We have done x, y, z planes in EUT and horizontal and vertical polarization in detecting antenna.

8.4 PEAK-TO-AVERAGE RATIO

Band	Ch.	Measured P _{PK} (dBm)	Measured P _{AVG} (dBm)	P _{AVG} (Duty Cycle)			P.A.R. = P _{PK} - P _{AVG} (dB)	Limit (dB)	Pass / Fail
				T _{XTotal} (ms)	T _{XOn} (ms)	Factor (dB)			
GSM1900	661	30.632	21.28	4.616	0.5475	9.26	0.093	13	Pass
GSM1900 EDGE	661	29.674	16.56	4.616	0.5475	9.26	3.855		
WCDMA1900	9400	CCDF Procedure					3.08		
WCDMA1700	1412						2.95		

- Plots of the EUT's Peak- to- Average Ratio are shown Page 41 ~ 45.

NOTES:

Peak to Average Power Ratio was tested in accordance with KDB971168 D01 Power Meas License Digital Systems v02r02, October 17, 2014, Section 5.7.

Only GSM(include EDGE) Mode was tested by Section 5.7.2 Alternate Procedure

$P.A.R_{(dB)} = P_{PK} (dBm) - P_{AVG} (dBm)$ (P_{AVG} = Average Power + Duty cycle Factor)

Duty cycle Factor = $10 \log (1/x)$, $x = T_{XOn} / T_{XTotal}$

8.5 OCCUPIED BANDWIDTH

Band	Channel	Frequency(MHz)	Data (GSM: kHz / WCDMA : MHz)
GSM850	128	824.20	245.06
	190	836.60	248.64
	251	848.80	245.62
GSM850 EDGE	190	836.6	255.59
GSM1900	512	1,850.20	246.16
	661	1,880.00	247.05
	810	1,909.80	250.45
GSM1900 EDGE	810	1909.8	254.24
WCDMA850	4132	826.40	4.1753
	4183	836.60	4.1755
	4233	846.60	4.1676
WCDMA1900	9262	1852.40	4.1719
	9400	1880.00	4.1687
	9538	1907.60	4.1758
WCDMA1700	1312	1712.40	4.1733
	1412	1732.40	4.1810
	1513	1752.60	4.1533

- Plots of the EUT's Occupied Bandwidth are shown Page 33 ~ 41.

8.6 CONDUCTED SPURIOUS EMISSIONS

■ FACTORS FOR FREQUENCY

Frequency Range (GHz)	Factor [dB]
0.03 – 1	27.145
1 – 5	26.960
5 – 10	27.542
10 – 15	28.439
15 – 20	29.144
Above 20	30.148

NOTES:

Factor(dB) = Cable Loss + Attenuator + Power Splitter

Band	Channel	Frequency of Maximum Harmonic (GHz)	Factor (dB)	Measurement Maximum Data (dBm)	Result	(dBm)
GSM850	128	5.3271	27.542	-59.503	-31.961	-13.00
	190	3.6705	26.960	-59.323	-32.363	
	251	3.7069	26.960	-59.614	-32.654	
GSM1900	512	16.6410	29.144	-55.829	-26.685	
	661	18.8940	29.144	-55.713	-26.569	
	810	19.2575	29.144	-55.237	-26.093	
WCDMA850	4132	3.6945	26.960	-66.793	-39.833	
	4183	3.7403	26.960	-67.015	-40.055	
	4233	3.7119	26.960	-66.774	-39.814	
WCDMA1900	9262	18.66922	29.144	-61.653	-32.509	
	9400	19.28898	29.144	-61.777	-32.633	
	9538	18.91147	29.144	-61.246	-32.102	
WCDMA1700	1312	18.89247	29.144	-61.768	-32.624	
	1412	18.96647	29.144	-61.872	-32.728	
	1513	18.94197	29.144	-61.587	-32.443	

NOTES:

1. Result (dBm) = Measurement Maximum Data (dBm) + Factor (dB)

- Plots of the EUT's Conducted Spurious Emissions are shown Page 63 ~ 75.

8.6.1 BAND EDGE


- Plots of the EUT's Band Edge are shown Page 45 ~ 63.

8.7 FREQUENCY STABILITY / VARIATION OF AMBIENT TEMPERATURE

8.7.1 FREQUENCY STABILITY (GSM850)

- OPERATING FREQUENCY: 836,600,000 Hz
- CHANNEL: 190
- REFERENCE VOLTAGE: 3.85 VDC
- DEVIATION LIMIT: ± 0.000 25 % or 2.5 ppm


Voltage (%)	Power (VDC)	Temp. (°C)	Frequency (Hz)	Frequency Error (Hz)	Deviation (%)	ppm
100%	3.85	+20(Ref)	836 600 010	0.00	0.000 000	0.0000
100%		-30	836 600 020	9.78	0.000 001	0.0117
100%		-20	836 600 020	9.77	0.000 001	0.0117
100%		-10	836 600 020	10.08	0.000 001	0.0120
100%		0	836 600 022	12.16	0.000 001	0.0145
100%		+10	836 600 020	9.68	0.000 001	0.0116
100%		+30	836 600 021	10.71	0.000 001	0.0128
100%		+40	836 600 017	6.67	0.000 001	0.0080
100%		+50	836 600 017	6.99	0.000 001	0.0084
Batt. Endpoint	3.60	+20	836 600 005	-5.34	-0.000 001	-0.0064



8.7.2 FREQUENCY STABILITY (GSM1900)

- OPERATING FREQUENCY: 1880,000,000 Hz
- CHANNEL: 661
- REFERENCE VOLTAGE: 3.85 VDC
- DEVIATION LIMIT: Emission must remain in band


Voltage (%)	Power (VDC)	Temp. (°C)	Frequency (Hz)	Frequency Error (Hz)	Deviation (%)	ppm
100%	3.85	+20(Ref)	1880 000 017	0.00	0.000 000	0.0000
100%		-30	1880 000 032	15.44	0.000 001	0.0082
100%		-20	1880 000 032	15.36	0.000 001	0.0082
100%		-10	1880 000 032	14.88	0.000 001	0.0079
100%		0	1880 000 032	15.59	0.000 001	0.0083
100%		+10	1880 000 033	15.97	0.000 001	0.0085
100%		+30	1880 000 030	13.30	0.000 001	0.0071
100%		+40	1880 000 023	6.35	0.000 000	0.0034
100%		+50	1880 000 024	7.35	0.000 000	0.0039
Batt. Endpoint	3.60	+20	1880 000 024	6.70	0.000 000	0.0036



8.7.3 FREQUENCY STABILITY (WCDMA850)

- OPERATING FREQUENCY: 836,600,000 Hz
- CHANNEL: 4183
- REFERENCE VOLTAGE: 3.85 VDC
- DEVIATION LIMIT: ± 0.000 25 % or 2.5 ppm


Voltage (%)	Power (VDC)	Temp. (°C)	Frequency (Hz)	Frequency Error (Hz)	Deviation (%)	ppm
100%	3.85	+20(Ref)	836 599 996	0.00	0.000 000	0.0000
100%		-30	836 599 992	-3.61	0.000 000	-0.0043
100%		-20	836 599 992	-4.36	-0.000 001	-0.0052
100%		-10	836 599 992	-4.28	-0.000 001	-0.0051
100%		0	836 599 992	-4.02	0.000 000	-0.0048
100%		+10	836 599 992	-4.31	-0.000 001	-0.0052
100%		+30	836 599 991	-5.46	-0.000 001	-0.0065
100%		+40	836 599 992	-3.57	0.000 000	-0.0043
100%		+50	836 599 992	-3.61	0.000 000	-0.0043
Batt. Endpoint	3.60	+20	836 599 993	-3.40	0.000 000	-0.0041



8.7.4 FREQUENCY STABILITY (WCDMA1900)

- OPERATING FREQUENCY: 1,880,000,000 Hz
- CHANNEL: 9400
- REFERENCE VOLTAGE: 3.85 VDC
- DEVIATION LIMIT: Emission must remain in band


Voltage (%)	Power (VDC)	Temp. (°C)	Frequency (Hz)	Frequency Error (Hz)	Deviation (%)	ppm
100%	3.85	+20(Ref)	1879 999 991	0.00	0.000 000	0.0000
100%		-30	1879 999 986	-4.99	0.000 000	-0.0027
100%		-20	1879 999 982	-9.20	0.000 000	-0.0049
100%		-10	1879 999 983	-7.95	0.000 000	-0.0042
100%		0	1879 999 983	-8.01	0.000 000	-0.0043
100%		+10	1879 999 982	-9.38	0.000 000	-0.0050
100%		+30	1879 999 981	-10.10	-0.000 001	-0.0054
100%		+40	1879 999 984	-6.95	0.000 000	-0.0037
100%		+50	1879 999 985	-5.90	0.000 000	-0.0031
Batt. Endpoint	3.60	+20	1879 999 985	-5.86	0.000 000	-0.0031



8.7.5 FREQUENCY STABILITY (WCDMA1700)

- OPERATING FREQUENCY: 1,732,400,000 Hz
- CHANNEL: 1412
- REFERENCE VOLTAGE: 3.85 VDC
- DEVIATION LIMIT: Emission must remain in band

Voltage (%)	Power (VDC)	Temp. (°C)	Frequency (Hz)	Frequency Error (Hz)	Deviation (%)	ppm
100%	3.85	+20(Ref)	1732 399 993	0.00	0.000 000	0.0000
100%		-30	1732 399 988	-5.04	0.000 000	-0.0029
100%		-20	1732 399 991	-2.66	0.000 000	-0.0015
100%		-10	1732 399 989	-4.46	0.000 000	-0.0026
100%		0	1732 399 990	-3.64	0.000 000	-0.0021
100%		+10	1732 399 998	4.89	0.000 000	0.0028
100%		+30	1732 399 988	-5.41	0.000 000	-0.0031
100%		+40	1732 399 998	5.06	0.000 000	0.0029
100%		+50	1732 399 989	-4.26	0.000 000	-0.0025
Batt. Endpoint	3.60	+20	1732 399 990	-3.34	0.000 000	-0.0019




9. TEST PLOTS

■ GSM850 MODE (128 CH.) Occupied Bandwidth



■ GSM850 MODE (190 CH.) Occupied Bandwidth




■ GSM850 MODE (251 CH.) Occupied Bandwidth




■ GSM850 EDGE (190 CH.) Occupied Bandwidth




■ GSM1900 MODE (512 CH.) Occupied Bandwidth




■ GSM1900 MODE (661 CH.) Occupied Bandwidth




■ GSM1900 MODE (810 CH.) Occupied Bandwidth



■ GSM1900 EDGE (810 CH.) Occupied Bandwidth



■ WCDMA850 MODE (4132 CH.) Occupied Bandwidth




■ WCDMA850 MODE (4183 CH.) Occupied Bandwidth




■ WCDMA850MODE (4233 CH.) Occupied Bandwidth



■ WCDMA1900 MODE (9262 CH.) Occupied Bandwidth




■ WCDMA1900 MODE (9400 CH.) Occupied Bandwidth



■ WCDMA1900 MODE (9538 CH.) Occupied Bandwidth



■ WCDMA1700 MODE (1312 CH.) Occupied Bandwidth



■ WCDMA1700 MODE (1412 CH.) Occupied Bandwidth



■ WCDMA1700 MODE (1513 CH.) Occupied Bandwidth




■ GSM1900 MODE (661 CH.) Peak-to-Average Ratio P_{PK}




■ GSM1900 MODE (661 CH.) Peak-to-Average Ratio P_{Avg}



■ GSM1900 MODE (661 CH.) Peak-to-Average Ratio Duty



■ GSM1900 EDGE (661 CH.) Peak-to-Average Ratio Duty




■ GSM1900 EDGE (661 CH.) Peak-to-Average Ratio P_{pk}



■ GSM1900 EDGE (661 CH.) Peak-to-Average Ratio P_{Avg}




■ WCDMA1900 MODE (9400 CH.) Peak-to-Average Ratio




■ WCDMA1700 MODE (1412 CH.) Peak-to-Average Ratio



■ GSM850 MODE (128 CH.) Block Edge 1




■ GSM850 MODE (128 CH.) Block Edge 2




■ GSM850 MODE (128 CH.) Block Edge 3



■ GSM850 MODE (251 CH.) Block Edge 1




■ GSM850 MODE (251 CH.) Block Edge 2




■ GSM850 MODE (251 CH.) Block Edge 3




■ EDGE MODE (128 CH.) Block Edge 1




■ EDGE MODE (128 CH.) Block Edge 2




■ EDGE MODE (128 CH.) Block Edge 3




■ EDGE MODE (251 CH.) Block Edge 1




■ EDGE MODE (251 CH.) Block Edge 2




■ EDGE MODE (251 CH.) Block Edge 3



■ GSM1900 MODE (512 CH.) Block Edge 1



■ GSM1900 MODE (512 CH.) Block Edge 2




■ GSM1900 MODE (512 CH.) Block Edge 3




Note : We used a narrower RBW in order to increase accuracy.

Calculation = Reading Value + $10 \cdot \log(1 \text{ MHz}/100 \text{ kHz}) \text{ dB}$ = $-50.935 \text{ dBm} + 10 \text{ dB}$ = **-40.935 dBm**

■ GSM1900 MODE (810 CH.) Block Edge 1



■ GSM1900 MODE (810 CH.) Block Edge 2




■ GSM1900 MODE (810 CH.) Block Edge 3




Note : We used a narrower RBW in order to increase accuracy.

Calculation = Reading Value + $10 \cdot \log(1 \text{ MHz}/100 \text{ kHz}) \text{ dB} = -50.095 \text{ dBm} + 10 \text{ dB} = \mathbf{-40.095 \text{ dBm}}$


■ EDGE MODE (512 CH.) Block Edge 1



■ EDGE MODE (512 CH.) Block Edge 2




■ EDGE MODE (512 CH.) Block Edge 3




Note : We used a narrower RBW in order to increase accuracy.

Calculation = Reading Value + $10 \cdot \log(1 \text{ MHz}/100 \text{ kHz}) \text{ dB}$ = $-46.720 \text{ dBm} + 10 \text{ dB}$ = **-36.720 dBm**

■ EDGE MODE (810 CH.) Block Edge 1



■ EDGE MODE (810 CH.) Block Edge 2



■ EDGE MODE (810 CH.) Block Edge 3



Note : We used a narrower RBW in order to increase accuracy.

Calculation = Reading Value + $10 \cdot \log(1 \text{ MHz}/100 \text{ kHz})$ dB = -47.023 dBm + 10 dB = **-37.023 dBm**

■ WCDMA850 MODE (4132 CH.) Block Edge



■ WCDMA850 MODE (4132 CH.) – 4 MHz Span



■ WCDMA850MODE (4233 CH.) Block Edge




■ WCDMA850MODE (4233 CH.) – 4 MHz Span



■ WCDMA1900 MODE (9262 CH.) Block Edge



■ WCDMA1900 MODE (9262 CH.) – 4 MHz Span



■ WCDMA1900 MODE (9538 CH.) Block Edge



■ WCDMA1900 MODE (9538 CH.) – 4 MHz Span



■ WCDMA1700 MODE (1312 CH.) Block Edge



■ WCDMA1700 MODE (1312 CH.) – 4 MHz Span




■ WCDMA1700 MODE (1513 CH.) Block Edge




■ WCDMA1700 MODE (1513 CH.) – 4 MHz Span




■ GSM850 MODE (128 CH.) Conducted Spurious Emissions




■ GSM850 MODE (190 CH.) Conducted Spurious Emissions




■ GSM850 MODE (251 CH.) Conducted Spurious Emissions




■ GSM1900 MODE (512 CH.) Conducted Spurious Emissions1




■ GSM1900 MODE (512 CH.) Conducted Spurious Emissions2




■ GSM1900 MODE (661 CH) Conducted Spurious Emissions1




■ GSM1900 MODE (661 CH.) Conducted Spurious Emissions2



■ GSM1900 MODE (810 CH.) Conducted Spurious Emissions1



■ GSM1900 MODE (810 CH.) Conducted Spurious Emissions2



■ WCDMA850 MODE (4132 CH.) Conducted Spurious Emissions




■ WCDMA850 MODE (4183 CH.) Conducted Spurious Emissions




■ WCDMA850MODE (4233 CH.) Conducted Spurious Emissions




■ WCDMA1900 MODE (9262 CH.) Conducted Spurious Emissions1




■ WCDMA1900 MODE (9262 CH.) Conducted Spurious Emissions2




■ WCDMA1900 MODE (9400 CH.) Conducted Spurious Emissions1




■ WCDMA1900 MODE (9400 CH.) Conducted Spurious Emissions2




■ WCDMA1900 MODE (9538 CH.) Conducted Spurious Emissions1




■ WCDMA1900 MODE (9538 CH.) Conducted Spurious Emissions2




■ WCDMA1700 MODE (1312 CH.) Conducted Spurious Emissions1




■ WCDMA1700 MODE (1312 CH.) Conducted Spurious Emissions2




■ WCDMA1700 MODE (1412 CH.) Conducted Spurious Emissions1



■ WCDMA1700 MODE (1412 CH.) Conducted Spurious Emissions2



■ WCDMA1700 MODE (1513 CH.) Conducted Spurious Emissions1



■ WCDMA1700 MODE (1513 CH.) Conducted Spurious Emissions2

