

TEST REPORT

Product Name : Smart Camera
Model Number : MJSXJ29CM

Prepared for : Xiaomi Communications Co., Ltd.
Address : #019, 9th Floor, Building 6, 33 Xi'erqi Middle Road, Haidian District, Beijing, 100085, China

Prepared by : EMTEK (SHENZHEN) CO., LTD.
Address : Building 69, Majialong Industry Zone, Nanshan District, Shenzhen, Guangdong, China

Tel: (0755) 26954280
Fax: (0755) 26954282

Report Number : ENS2512220319W01702R
Date(s) of Tests : April 9, 2026 to May 8, 2026
Date of issue : May 9, 2026

TABLE OF CONTENTS

1 EUT TECHNICAL DESCRIPTION	5
2 SUMMARY OF TEST RESULT	7
3 TEST METHODOLOGY	8
3.1 GENERAL DESCRIPTION OF APPLIED STANDARDS	8
3.2 MEASUREMENT EQUIPMENT USED	8
3.3 DESCRIPTION OF TEST MODES	9
3.4 SUPPORT EQUIPMENT	10
4 FACILITIES AND ACCREDITATIONS	11
4.1 FACILITIES	11
4.2 LABORATORY ACCREDITATIONS AND LISTINGS	11
5 TEST SYSTEM UNCERTAINTY	12
6 WIRELESS MODULE VOLTAGE TEST IN EXTREME CONDITIONS	13
6.1 Applicable Standard	13
6.2 Test Configuration	13
6.3 Test Results	13
7 TEST REQUIREMENTS	14
7.1 ANTENNA POWER	14
7.2 FREQUENCY ERROR	17
7.3 OCCUPIED BANDWIDTH (99%)&SPREADING BANDWIDTH (90%)&SPREAD FACTOR	28
7.4 SPURIOUS EMISSIONS OF TX	49
7.5 SPURIOUS EMISSIONS OF RX	95
7.6 INTERFERENCE PREVENTION FUNCTION	116
7.7 CARRIER SENSE CAPABILITY	117
7.8 RF ACCESSIBILITY	119
8 APPENDIX PHOTOGRAPHS OF TEST SETUP	120

Modified Information

Version	Report No.	Revision Date	Summary
Ver.1.0	ENS2512220319W01702R	/	Original Report

TEST RESULT CERTIFICATION

Applicant : Xiaomi Communications Co., Ltd.

Address : #019, 9th Floor, Building 6, 33 Xi'erqi Middle Road, Haidian District, Beijing,
100085, China

Manufacturer : Xiaomi Communications Co., Ltd.

Address : #019, 9th Floor, Building 6, 33 Xi'erqi Middle Road, Haidian District, Beijing,
100085, China

EUT : Smart Camera

Model Name : MJSXJ29CM

Trademark : Xiaomi

Measurement Procedure Used:


APPLICABLE STANDARDS		
STANDARD	Test Procedure	TEST RESULT
Item 19 of Article 2 Paragraph 1	MIC public notice 88:2004, annex 43	PASS

The device described above is tested by EMTEK (SHENZHEN) CO., LTD. to determine the maximum emission levels emanating from the device and the severe levels of the device can endure and its performance criterion. The measurement results are contained in this test report and EMTEK (SHENZHEN) CO., LTD. is assumed full of responsibility for the accuracy and completeness of these measurements. Also, this report shows that the EUT (Equipment Under Test) was measured according to the test methods of Ordinance Concerning Technical Regulations Conformity Certification etc. of Specified Radio Equipment in Annex 1, the Ministry of Internal Affairs and Communication notification in Annex "43" of Article 88, Paragraph 1 or the test method more than equivalent and the result is technically compliant with the ARIB STD T-66 requirements.

The test results of this report relate only to the tested sample identified in this report

Date of Test : April 9, 2026 to May 8, 2026

Prepared by : 
Yu Xiaolan /Editor

Reviewer : 
Xia Lili/Supervisor

Approved & Authorized Signer : 
Wang Li /Manager

1 EUT TECHNICAL DESCRIPTION

Characteristics	Description
Device Type:	2.4G WiFi
Product:	Smart Camera
Model Number:	MJSXJ29CM
Test Sample S/N:	N/A
Variant Number:	N/A
IEEE 802.11 WLAN Mode Supported:	802.11b 802.11g 802.11n/ax(20MHz channel bandwidth) 802.11n/ax(40MHz channel bandwidth)
Modulation:	DSSS with DBPSK/DQPSK/CCK for 802.11b; OFDM with BPSK/QPSK/16QAM/64QAM for 802.11g/n; OFDMA with BPSK/QPSK/16QAM/64QAM/256QAM/1024QAM for 802.11ax
Operating Frequency Range:	2412-2472MHz for 802.11b/g/n(HT20)/ax(HE20) 2422-2462MHz for 802.11n(HT40)/ax(HE40)
Number of Channels:	13 channels for 802.11b/g/n(HT20)/ax(HE20) 9 Channels for 802.11n(HT40)/ax(HE40)
Rated Antenna power:	IEEE 802.11b: 2412-2472 MHz: 10 mW/MHz IEEE 802.11g: 2412-2472 MHz: 1 mW/MHz IEEE 802.11n (HT20): 2412-2472 MHz: 1 mW/MHz IEEE 802.11n (HT40): 2422-2462 MHz: 1 mW/MHz IEEE 802.11ax (HE20): 2412-2472 MHz: 1 mW/MHz IEEE 802.11ax (HE40): 2422-2462 MHz: 1 mW/MHz
Antenna Port:	☒ Antenna port 1,
Antenna Type:	☒ ANT 1: Internal antenna
Antenna Gain:	☒ ANT 1: 1.50dBi (Note: The antenna information is provided by the customers, which will have a certain impact on the test results.)
Power Supply:	DC 5V from adapter
Adapter 1:	MODEL:A319-050200U-US2 INPUT:100-240V~50/60Hz Max 0.3A OUTPUT:5V/2A
Adapter 2:	MODEL:S010-1A050200VUU INPUT:100-240V~50/60Hz Max 0.3A OUTPUT:5V/2A
Test Voltage:	AC 100V/50Hz
Temperature Range:	-10°C ~ +40°C
Software Version:	5.3.3_0948

Hardware Version:

LSAM130D1-1

Note: for more details, please refer to the User's manual of the EUT.

2 SUMMARY OF TEST RESULT

Clause	Test Parameter	Verdict	Remark
Item 19 of Article 2 Paragraph 1	Antenna Power	Pass	
Item 19 of Article 2 Paragraph 1	Frequency Error	Pass	
Item 19 of Article 2 Paragraph 1	Occupied Bandwidth (99%)	Pass	
Item 19 of Article 2 Paragraph 1	Spreading Bandwidth (90%)&Spread Factor	Pass	
Item 19 of Article 2 Paragraph 1	Spurious Emissions of Tx	Pass	
Item 19 of Article 2 Paragraph 1	Spurious Emissions of Rx	Pass	
Item 19 of Article 2 Paragraph 1	Interference Prevention Function	Pass	
Item 19 of Article 2 Paragraph 1	Carrier sense capability	Pass	
Item 19 of Article 2 Paragraph 1	RF accessibility	Pass	

3 TEST METHODOLOGY

3.1 GENERAL DESCRIPTION OF APPLIED STANDARDS

According to its specifications, the EUT must comply with the requirements of the following standards:

Item 19 of Article 2 Paragraph 1 of the TELEC rules for 2.4GHz band wide-band low-power data communication system. All measurements contained in this report were conducted with test method for radio equipment specified in MIC public notice 88:2004, annex 43 for certification. And measuring method for electric field intensity of radio station with remarkably weak radiowave transmitted.

3.2 MEASUREMENT EQUIPMENT USED

3.2.1 Radio Frequency Test Equipment

Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Calibration Body	Calibration Method
Wideband Radio Communication Tester	R&S	CMW500	171168	2025/9/9	LISAI	(c)
Spectrum Analyzer	R&S	FSV3044	101289	2025/12/16	LISAI	(c)
Signal Analyzer	Agilent	N9010A	MY53470879	2025/5/10	LISAI	(c)
Analog Signal Generator	R&S	SMB100A	183237	2025/9/9	LISAI	(c)
Vector Signal Generator	R&S	SMM100A	101808	2025/9/9	LISAI	(c)
RF Control Unit(Power Meter)	Tonscend	JS0806-2	22C8060567	2025/9/9	LISAI	(c)
Temperature&Humidity Chamber	ESPEC	EL-02KA	12107166	2025/5/10	N/A	N/A

Remark:

(a) Calibration conducted by the National Institute of Information and Communications Technology (NICT) in Japan (hereinafter referred to as "NICT") or a designated calibration agency under Article 102-18 paragraph (1) in JRL.

(b) Correction conducted pursuant to the provisions of Article 135 or Article 144 of the Measurement Act (Act No. 51 of 1992).

(c) Calibration conducted in countries except Japan, which shall be equivalent to the calibration conducted by the NICT or a designated calibration agency under Article 102-18 paragraph (1).

(d) Calibration, etc. conducted by using measuring instruments and other equipment listed in the right column of appended table No. 3, which shall have been given any type of calibration, etc. listed above from (a) to (c).

From JRL Article 24-2, paragraph 4, Item 2

Notice: Calibration duration for above equipments is 1 year.

3.3 DESCRIPTION OF TEST MODES

The EUT has been tested under its typical operating condition.

The EUT configuration for testing is installed on RF field strength measurement to meet the Commissions requirement and operating in a manner which intends to maximize its emission characteristics in a continuous normal application.

The Transmitter was operated in the normal operating mode. The TX frequency was fixed which was for the purpose of the measurements.

Test of channel included the lowest and middle and highest frequency to perform the test, then record on this report.

Pre-defined engineering program for regulatory testing used to control the EUT for staying in continuous transmitting and receiving mode is programmed.

Frequency and Channels list for 802.11b/g/n(HT20)/ax(HE20):

Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
1	2412	6	2437	11	2462
2	2417	7	2442	12	2467
3	2422	8	2447	13	2472
4	2427	9	2452		
5	2432	10	2457		

Frequency and Channels list for 802.11n(HT40)/ax(HE40):

Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
3	2422	6	2437	9	2452
4	2427	7	2442	10	2457
5	2432	8	2447	11	2462

Test Frequency and Channels for 802.11b/g/n(HT20)/ax(HE20):

Lowest Frequency		Middle Frequency		Highest Frequency	
Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
1	2412	7	2442	13	2472

Test Frequency and channels for 802.11n(HT40)/ax(HE40):

Lowest Frequency		Middle Frequency		Highest Frequency	
Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
3	2422	7	2442	11	2462

3.4 SUPPORT EQUIPMENT

EUT Cable List and Details			
Cable Description	Length (m)	Shielded/Unshielded	With / Without Ferrite
/	/	/	/

Auxiliary Cable List and Details			
Cable Description	Length (m)	Shielded/Unshielded	With / Without Ferrite
/	/	/	/

Auxiliary Equipment List and Details			
Description	Manufacturer	Model	Serial Number
/	/	/	/

Notes:

1. All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.
2. Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.
3. Unless otherwise denoted as EUT in [Remark] column, device(s) used in tested system is a support equipment

4 FACILITIES AND ACCREDITATIONS

4.1 FACILITIES

All measurement facilities used to collect the measurement data are located at Building 69, Majialong Industry Zone, Nanshan District, Shenzhen, Guangdong, China. The sites are constructed in conformance with the requirements of ANSI C63.7, ANSI C63.4 and CISPR Publication 22."

4.2 LABORATORY ACCREDITATIONS AND LISTINGS

Site Description

EMC Lab. : The Certificate Registration Number is L2291.
The Laboratory has been assessed and proved to be in compliance with CNAS-CL01 (identical to ISO/IEC 17025:2017)

3m Chamber #1 : Certificated by VCCI, Japan
Registration No.: R-12777
Registration No.: G-20141

10m Chamber : Certificated by VCCI, Japan
Registration No.: R-14410

Shielding Room #1 : Certificated by VCCI, Japan
Registration No.: C-13065
Registration No.: T-11318

Name of Firm : EMTEK (SHENZHEN) CO., LTD.

Site Location : Building 69, Majialong, Industry Zone, Nanshan District, Shenzhen, Guangdong, China

5 TEST SYSTEM UNCERTAINTY

The following measurement uncertainty levels have been estimated for tests performed on the apparatus:

Parameter	Uncertainty
Frequency error	$\pm 1.9\%$
Occupied Bandwidth	$\pm 1.9\text{KHz}$
Transmitter output power	$\pm 1.18\text{dB}$
Conducted spurious emissions	$\pm 3.3\text{dB}$
Radiated spurious emissions	$\pm 4.5\text{dB}$
Temperature	$\pm 1.2^\circ\text{C}$
Humidity	$\pm 3\%$
DC voltages	$\pm 0.25\text{V}$
Time	$\pm 1\%$

Measurement Uncertainty for a level of Confidence of 95%


6 WIRELESS MODULE VOLTAGE TEST IN EXTREME CONDITIONS

6.1 Applicable Standard


When there is a fluctuation of $\pm 10\%$ input voltage from external power to the test equipment. If the fluctuation of input voltage to the circuit of the radio part (excl. power) in the test equipment is confirmed below $\pm 1\%$, Measurement shall be tested with the rated voltage.

6.2 Test Configuration

Config A



Config B



6.3 Test Results

Test Sample DC Input Voltage	4.5V	5V	5.5V
Input Voltage To The Circuit	3.30	3.30	3.30
Module Rated Voltage	3.30	3.30	3.30
The Deviation of Module Voltage (%)	0.00%	0.00%	0.00%

Note: In extreme conditions, The test sample module power is confirmed below $\pm 1\%$.

7 TEST REQUIREMENTS

7.1 ANTENNA POWER

7.1.1 Applicable Standard


According to Equipment Regulations, art. 49.20.

7.1.2 Conformance Limit

The max permitted antenna power density shall not exceed 10mW/MHz and deviation of power density shall be within +20% of declared power density.

Eirp: not exceed 12.14dBm/ MHz(OFDM.DS form 2400-2483.5 MHz)

7.1.3 Test Setup Block Diagram



7.1.4 Test Procedure

Set the EUT on the test frequency and the consecutive TX mode or continuous (constant period, constant burst length) burst TX mode.

In case of spreading code used, set on the test spreading code, then the modulation is performed with standard coding test signal.

(1) Measure the equivalent noise bandwidth at the spectrum analyzer for resolution bandwidth of 1 MHz, then read the value correcting the resolution bandwidth on the 1 MHz equivalent bandwidth. In case of a spreading bandwidth lower than 1 MHz, however, perform the correction only for a higher value than "Spreading bandwidth (MHz) / Equivalent noise bandwidth (MHz)".

(2) The attenuation value of the attenuator shall be set to achieve the optimal operating input level at the spectrum analyzer.

(3) Spectrum analyzer for seeking the maximum antenna power is set as below.

Central Frequency	Test frequency
Sweeping Bandwidth	Approx. twice the Occupied Bandwidth
Resolution Bandwidth	1 MHz
Video Bandwidth	Approx. twice the resolution bandwidth (2MHz)
Y-Axis Scale	10 dB/Div
Sweep Time	Minimum time to assure the measurement accuracy (In case of burst wave, 1 burst per 1 sample)
Trigger Condition	Free run
Data points	More than 400 points
Sweep Mode	Consecutive sweep
Phase-Detection Mode	Positive peak
Display mode	Max-hold

(4) Spectrum analyzer for measuring the antenna power is set as below. In this case, calibrate the indication of the RF Power Meter on the output of the EUT with the RF Power Meter connected to the IF output of the spectrum analyzer.

Central Frequency	Frequency to achieve the maximum power (sought frequency)
Sweeping Bandwidth	0 Hz
Resolution Bandwidth	1 MHz
Video Bandwidth	Same level as the resolution bandwidth
Sweep Mode	Consecutive sweep
Phase-Detection Mode	Sample

Measurement Procedure

(1) No frequency hopping systems:

- Configure the settings of the spectrum analyzer to 2(3).
- After repeating sweeps (until no display changes are found), measure the maximum power frequency per MHz.
- Connect the high frequency power meter to the IF output of the spectrum analysers.
- Configure the settings of the spectrum analyzer to 2(4).
- Set the antenna power as follows:
 - Continuous waves: value indicated on the high frequency power meter, corrected according to 2(1).
 - Burst waves: value similarly corrected in the case of continuous waves and value calculated from the average power within bursts from rates of transmission times (i.e. correction on the duty-cycle, to find the average within the transmit burst)

7.1.5 Environmental Conditions

Temperature:	24.1°C
Relative Humidity:	46%
ATM Pressure:	1011 mbar

7.1.6 Test Results

Test Condition	Test Mode	Antenna	Frequency [MHz]	Result (dBm/MHz)	Result (mW/MHz)	Limit (mW/MHz)	Verdict
NTNV	11B	Ant1	2412	5.17	3.2885	≤10	PASS
NTNV	11B	Ant1	2442	4.73	2.9717	≤10	PASS
NTNV	11B	Ant1	2472	3.89	2.4491	≤10	PASS
NTNV	11G	Ant1	2412	-3.85	0.4121	≤10	PASS
NTNV	11G	Ant1	2442	-4.03	0.3954	≤10	PASS
NTNV	11G	Ant1	2472	-4.93	0.3214	≤10	PASS
NTNV	11N20SISO	Ant1	2412	-4.47	0.3573	≤10	PASS
NTNV	11N20SISO	Ant1	2442	-4.46	0.3581	≤10	PASS
NTNV	11N20SISO	Ant1	2472	-5.88	0.2582	≤10	PASS
NTNV	11N40SISO	Ant1	2422	-6.84	0.2070	≤5	PASS
NTNV	11N40SISO	Ant1	2442	-4.88	0.3251	≤5	PASS
NTNV	11N40SISO	Ant1	2462	-5.28	0.2965	≤5	PASS
NTNV	11AX20SISO	Ant1	2412	-3.80	0.4169	≤10	PASS
NTNV	11AX20SISO	Ant1	2442	-3.86	0.4111	≤10	PASS
NTNV	11AX20SISO	Ant1	2472	-4.88	0.3251	≤10	PASS
NTNV	11AX40SISO	Ant1	2422	-5.15	0.3055	≤5	PASS
NTNV	11AX40SISO	Ant1	2442	-4.62	0.3451	≤5	PASS
NTNV	11AX40SISO	Ant1	2462	-5.51	0.2812	≤5	PASS

Test Condition	Test Mode	Antenna	Frequency [MHz]	Result (dBm/MHz)	EIRP (dBm/MHz)	Limit(dBm/MHz)	Verdict
NTNV	11B	Ant1	2412	5.17	6.67	≤12.14	PASS
NTNV	11B	Ant1	2442	4.73	6.23	≤12.14	PASS
NTNV	11B	Ant1	2472	3.89	5.39	≤12.14	PASS
NTNV	11G	Ant1	2412	-3.85	-2.35	≤12.14	PASS
NTNV	11G	Ant1	2442	-4.03	-2.53	≤12.14	PASS
NTNV	11G	Ant1	2472	-4.93	-3.43	≤12.14	PASS
NTNV	11N20SISO	Ant1	2412	-4.47	-2.97	≤12.14	PASS
NTNV	11N20SISO	Ant1	2442	-4.46	-2.96	≤12.14	PASS
NTNV	11N20SISO	Ant1	2472	-5.88	-4.38	≤12.14	PASS
NTNV	11N40SISO	Ant1	2422	-6.84	-5.34	≤9.13	PASS
NTNV	11N40SISO	Ant1	2442	-4.88	-3.38	≤9.13	PASS
NTNV	11N40SISO	Ant1	2462	-5.28	-3.78	≤9.13	PASS
NTNV	11AX20SISO	Ant1	2412	-3.80	-2.30	≤12.14	PASS
NTNV	11AX20SISO	Ant1	2442	-3.86	-2.36	≤12.14	PASS
NTNV	11AX20SISO	Ant1	2472	-4.88	-3.38	≤12.14	PASS
NTNV	11AX40SISO	Ant1	2422	-5.15	-3.65	≤9.13	PASS
NTNV	11AX40SISO	Ant1	2442	-4.62	-3.12	≤9.13	PASS
NTNV	11AX40SISO	Ant1	2462	-5.51	-4.01	≤9.13	PASS

Test Condition	Test Mode	Antenna	Frequency [MHz]	Power (mW/MHz)	RatedPower (mW/MHz)	Result (%)	Limit (%)	Verdict
NTNV	11B	Ant1	2412	3.2885	10	-67.12	≤±20	PASS
NTNV	11B	Ant1	2442	2.9717	10	-70.28	≤±20	PASS
NTNV	11B	Ant1	2472	2.4491	10	-75.51	≤±20	PASS
NTNV	11G	Ant1	2412	0.4121	1	-58.79	≤±20	PASS
NTNV	11G	Ant1	2442	0.3954	1	-60.46	≤±20	PASS
NTNV	11G	Ant1	2472	0.3214	1	-67.86	≤±20	PASS
NTNV	11N20SISO	Ant1	2412	0.3573	1	-64.27	≤±20	PASS
NTNV	11N20SISO	Ant1	2442	0.3581	1	-64.19	≤±20	PASS
NTNV	11N20SISO	Ant1	2472	0.2582	1	-74.18	≤±20	PASS
NTNV	11N40SISO	Ant1	2422	0.2070	1	-79.30	≤±20	PASS
NTNV	11N40SISO	Ant1	2442	0.3251	1	-67.49	≤±20	PASS
NTNV	11N40SISO	Ant1	2462	0.2965	1	-70.35	≤±20	PASS
NTNV	11AX20SISO	Ant1	2412	0.4169	1	-58.31	≤±20	PASS
NTNV	11AX20SISO	Ant1	2442	0.4111	1	-58.89	≤±20	PASS
NTNV	11AX20SISO	Ant1	2472	0.3251	1	-67.49	≤±20	PASS
NTNV	11AX40SISO	Ant1	2422	0.3055	1	-69.45	≤±20	PASS
NTNV	11AX40SISO	Ant1	2442	0.3451	1	-65.49	≤±20	PASS
NTNV	11AX40SISO	Ant1	2462	0.2812	1	-71.88	≤±20	PASS

7.2 FREQUENCY ERROR


7.2.1 Applicable Standard

According to Item 19 of Article 2 Paragraph 1.

7.2.2 Conformance Limit

the maximum permit tolerance of frequency is 50ppm.

7.2.3 Test Setup Block Diagram



7.2.4 Test Procedure

1. Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the spectrum analyzer.
2. Set center frequency of spectrum analyzer = operating frequency.
3. Set the spectrum analyzer as RBW, VBW=10KHz, Span = 1MHz.
- 4 'Maximum Hold' mode may be used to accumulate the measurement result over several scans provided emission is repetitive in nature.
5. Repeat above procedures until all frequency measured was complete.


7.2.5 Environmental Conditions

Temperature:	24.1°C
Relative Humidity:	46%
ATM Pressure:	1011 mbar


7.2.6 Test Results

TestCondition	TestMode	Antenna	Frequency[MHz]	CenterFreq [MHz]	Result[ppm]	Limit[ppm]	Verdict
NTNV	11B	Ant1	2412	2411.99	-4.14594	±50	PASS
NTNV	11B	Ant1	2442	2441.995	-2.04750	±50	PASS
NTNV	11B	Ant1	2472	2471.994	-2.42718	±50	PASS
NTNV	11G	Ant1	2412	2411.987	-5.38972	±50	PASS
NTNV	11G	Ant1	2442	2441.986	-5.73301	±50	PASS
NTNV	11G	Ant1	2472	2471.986	-5.66343	±50	PASS
NTNV	11N20SISO	Ant1	2412	2411.986	-5.80431	±50	PASS
NTNV	11N20SISO	Ant1	2442	2441.986	-5.73301	±50	PASS
NTNV	11N20SISO	Ant1	2472	2471.986	-5.66343	±50	PASS
NTNV	11N40SISO	Ant1	2422	2421.986	-5.78035	±50	PASS
NTNV	11N40SISO	Ant1	2442	2441.985	-6.14251	±50	PASS
NTNV	11N40SISO	Ant1	2462	2461.985	-6.09261	±50	PASS
NTNV	11AX20SISO	Ant1	2412	2411.986	-5.80431	±50	PASS
NTNV	11AX20SISO	Ant1	2442	2441.986	-5.73301	±50	PASS
NTNV	11AX20SISO	Ant1	2472	2471.985	-6.06796	±50	PASS
NTNV	11AX40SISO	Ant1	2422	2421.986	-5.78035	±50	PASS
NTNV	11AX40SISO	Ant1	2442	2441.986	-5.73301	±50	PASS
NTNV	11AX40SISO	Ant1	2462	2461.986	-5.68643	±50	PASS


Note: All modes 2.4G 802.11b/g/n/ax have been tested, and the worst result recorded in the report.




NTNV-11B-Ant1-2412-PASS




NTNV-11B-Ant1-2442-PASS




NTNV-11B-Ant1-2472-PASS




NTNV-11G-Ant1-2412-PASS




NTNV-11G-Ant1-2442-PASS





NTNV-11G-Ant1-2472-PASS




NTNV-11N20SISO-Ant1-2412-PASS




NTNV-11N20SISO-Ant1-2442-PASS







NTNV-11N40SISO-Ant1-2442-PASS




NTNV-11N40SISO-Ant1-2462-PASS




NTNV-11AX20SISO-Ant1-2412-PASS




NTNV-11AX20SISO-Ant1-2442-PASS




NTNV-11AX20SISO-Ant1-2472-PASS



NTNV-11AX40SISO-Ant1-2422-PASS



NTNV-11AX40SISO-Ant1-2442-PASS



NTNV-11AX40SISO-Ant1-2462-PASS

7.3 OCCUPIED BANDWIDTH (99%)&SPREADING BANDWIDTH (90%)&SPREAD FACTOR

7.3.1 Applicable Standard


According to Item 19 of Article 2 Paragraph 1.

7.3.2 Conformance Limit

Occupied bandwidth: $FH \leq 83.5 \text{ MHz}$; $DS \leq 26 \text{ MHz}$; $OFDM \leq 38 \text{ MHz}$, Others $\leq 26 \text{ MHz}$

Spread Bandwidth: $\geq 500 \text{ kHz}$ (FH, DS), Spread factor > 5 .

7.3.3 Test Setup Block Diagram



7.3.4 Test Procedure

(1) Spectrum analyzer is set as below

Central Frequency	Test frequency
Sweeping Bandwidth	2 to 3.5 times the allowable value (SPAN=80MHz for 802.11n(HT40), SPAN=50MHz for the others)
Resolution Bandwidth	Lower than 3 % of allowable value (RBW=300kHz)
Video Bandwidth	Equivalent to resolvable bandwidth
Y-Axis Scale	10 dB/Div
Input Level	Carrier level is sufficiently higher than spectrum analyzer noise
Sweep Time	Minimum time to assure the measurement accuracy (In case of burst wave, 1 burst per 1 sample)
Sampling points	More than 400 points
Sweep Mode	Consecutive sweep
Phase-Detection Mode	Positive peak
Trigger Condition	Max-hold

(2) Repeat the sweeping till no change was observed on the display and enter all values of data point to the computer as array variable.

(3) About all data, convert dB value to antilogarithm of electric power dimension.

(4) Add up the electric power of all data and record it as "Sum total of electric power".

(5) Adding up data in order from the lowest frequency to upper frequencies, look for a limit point where the value reaches to 0.5% (5% in case of diffusion bandwidth) of "Sum total of electric power". Convert the limit point to frequency and record as "Lowest limit frequency".

(6) Adding up data in order from the highest frequency to lower frequencies, look for a limit point

where the value reaches to 0.5% (5% in case of diffusion bandwidth) of "Sum total of electric power". Convert the limit point to frequency and record as "Highest limit frequency".

(7) Repeat above procedures until all frequency measured was complete.

(8) Spread Factor=Spread Bandwidth/modulation rate. The modulation rate: MR=1.375 for 802.11b, MR=1.5 for 802.11g/n20, MR=3 for 802.11n40.


7.3.5 Environmental Conditions

Temperature:	24.1°C
Relative Humidity:	46%
ATM Pressure:	1011 mbar


7.3.6 Test Results

Occupied Bandwidth (99% Emission bandwidth)


TestCondition	TestMode	Antenna	Frequency[MHz]	Result [MHz]	Limit [MHz]	Verdict
NTNV	11B	Ant1	2412	12.118	≤26	PASS
NTNV	11B	Ant1	2442	13.170	≤26	PASS
NTNV	11B	Ant1	2472	13.173	≤26	PASS
NTNV	11G	Ant1	2412	16.823	≤26	PASS
NTNV	11G	Ant1	2442	16.852	≤26	PASS
NTNV	11G	Ant1	2472	16.860	≤26	PASS
NTNV	11N20SISO	Ant1	2412	18.084	≤26	PASS
NTNV	11N20SISO	Ant1	2442	18.128	≤26	PASS
NTNV	11N20SISO	Ant1	2472	18.153	≤26	PASS
NTNV	11N40SISO	Ant1	2422	36.169	26-40	PASS
NTNV	11N40SISO	Ant1	2442	36.227	26-40	PASS
NTNV	11N40SISO	Ant1	2462	36.244	26-40	PASS
NTNV	11AX20SISO	Ant1	2412	19.034	≤26	PASS
NTNV	11AX20SISO	Ant1	2442	19.055	≤26	PASS
NTNV	11AX20SISO	Ant1	2472	19.115	≤26	PASS
NTNV	11AX40SISO	Ant1	2422	37.939	26-40	PASS
NTNV	11AX40SISO	Ant1	2442	37.854	26-40	PASS
NTNV	11AX40SISO	Ant1	2462	37.726	26-40	PASS




NTNV-11B-Ant1-2412-PASS



NTNV-11B-Ant1-2442-PASS




NTNV-11B-Ant1-2472-PASS




NTNV-11G-Ant1-2412-PASS




NTNV-11G-Ant1-2442-PASS




NTNV-11G-Ant1-2472-PASS




NTNV-11N20SISO-Ant1-2412-PASS




NTNV-11N20SISO-Ant1-2442-PASS




NTNV-11N20SISO-Ant1-2472-PASS




NTNV-11N40SISO-Ant1-2422-PASS




NTNV-11N40SISO-Ant1-2442-PASS




NTNV-11N40SISO-Ant1-2462-PASS




NTNV-11AX20SISO-Ant1-2412-PASS




NTNV-11AX20SISO-Ant1-2442-PASS




NTNV-11AX20SISO-Ant1-2472-PASS



NTNV-11AX40SISO-Ant1-2422-PASS




NTNV-11AX40SISO-Ant1-2442-PASS




NTNV-11AX40SISO-Ant1-2462-PASS

Spread Bandwidth (90% Emission bandwidth)


TestCondition	TestMode	Antenna	Frequency[MHz]	Result [MHz]	Limit [MHz]	SpreadFactor	Limit	Verdict
NTNV	11B	Ant1	2412	8.235	≥0.5	5.989	>5	PASS
NTNV	11B	Ant1	2442	8.807	≥0.5	6.405	>5	PASS
NTNV	11B	Ant1	2472	8.804	≥0.5	6.403	>5	PASS
NTNV	11G	Ant1	2412	14.398	≥0.5	---	---	PASS
NTNV	11G	Ant1	2442	14.419	≥0.5	---	---	PASS
NTNV	11G	Ant1	2472	14.442	≥0.5	---	---	PASS
NTNV	11N20SISO	Ant1	2412	15.423	≥0.5	---	---	PASS
NTNV	11N20SISO	Ant1	2442	15.528	≥0.5	---	---	PASS
NTNV	11N20SISO	Ant1	2472	15.451	≥0.5	---	---	PASS
NTNV	11N40SISO	Ant1	2422	31.590	≥0.5	---	---	PASS
NTNV	11N40SISO	Ant1	2442	31.722	≥0.5	---	---	PASS
NTNV	11N40SISO	Ant1	2462	31.572	≥0.5	---	---	PASS
NTNV	11AX20SISO	Ant1	2412	16.757	≥0.5	---	---	PASS
NTNV	11AX20SISO	Ant1	2442	16.617	≥0.5	---	---	PASS
NTNV	11AX20SISO	Ant1	2472	16.560	≥0.5	---	---	PASS
NTNV	11AX40SISO	Ant1	2422	32.909	≥0.5	---	---	PASS
NTNV	11AX40SISO	Ant1	2442	32.791	≥0.5	---	---	PASS
NTNV	11AX40SISO	Ant1	2462	32.785	≥0.5	---	---	PASS




NTNV-11B-Ant1-2412-PASS




NTNV-11B-Ant1-2442-PASS




NTNV-11B-Ant1-2472-PASS




NTNV-11G-Ant1-2412-PASS




NTNV-11G-Ant1-2442-PASS




NTNV-11G-Ant1-2472-PASS




NTNV-11N20SISO-Ant1-2412-PASS




NTNV-11N20SISO-Ant1-2442-PASS




NTNV-11N20SISO-Ant1-2472-PASS




NTNV-11N40SISO-Ant1-2422-PASS




NTNV-11N40SISO-Ant1-2442-PASS




NTNV-11N40SISO-Ant1-2462-PASS




NTNV-11AX20SISO-Ant1-2412-PASS




NTNV-11AX20SISO-Ant1-2442-PASS




NTNV-11AX20SISO-Ant1-2472-PASS



NTNV-11AX40SISO-Ant1-2422-PASS



NTNV-11AX40SISO-Ant1-2442-PASS



NTNV-11AX40SISO-Ant1-2462-PASS

7.4 SPURIOUS EMISSIONS OF Tx

7.4.1 Applicable Standard


According to Item 19 of Article 2 Paragraph 1.

7.4.2 Conformance Limit

Permissible mean power of spurious emission of each frequency supplied to a feeder, that is, mean power of spurious emission in the 1 MHz bandwidth at frequency f other than frequency band used shall be as follows:

- (1) Below 2387MHz: 2.5 μ W/MHz (-26dB)
- (2) 2387 to 2400MHz: 25 μ W/MHz (-16dB)
- (3) 2483.5 through 2496.5MHz: 25 μ W/MHz (-16dB)
- (4) Over 2496.5MHz: 2.5 μ W/MHz (-26dB)

7.4.3 Test Setup Block Diagram



7.4.4 Test Procedure

(1) Spectrum analyzer for seeking the spurious emission is set as below

Sweeping Bandwidth	For seeking the spurious emission, from frequency lowest possible to the 5 times the carrier frequency
Resolution Bandwidth	1 MHz
Video Bandwidth	Approx. As same as Resolution bandwidth (1 MHz)
Y-Axis Scale	10 dB/Div
Input Level	Value of maximum dynamic range
Sweep Time	Minimum time to assure the measurement accuracy (Note 1)
Sweep Mode	Single sweep
Phase-Detection Mode	Positive peak

(2) The settings of the spectrum analyzer while conducting spurious amplitude measurements are as follows:

- Central Frequency: Acquired spurious frequencies in (1)
- Sweep Frequency 0 Hz
- Resolution Bandwidth 1 MHz
- Video Bandwidth same as Resolution Bandwidth
- Note: take into account that the requirement limits the power in a bandwidth of 1 MHz.
- If the measurement is carried out with a bandwidth of 100 kHz (for frequencies below 1 GHz), the limit shall be reduced with 10 dB.
- For example 2.5 μ W in 1 MHz = -26 dBm limit, becomes -36 dBm for 100 kHz bandwidth.
- Y-Axis Scale 10 dB/Div
- Input Level: choose input level within the linear range of the SA mixer (so that no additional spurious are generated by the mixer)
- Sweep Time: Minimum amount of time to ensure measurement accuracy. However, in the case of burst waves, time exceeds duration of 1 burst.
- Data Points Over 400 points
- Sweep Mode: Single sweep

- Detection Mode Sample (BIN-Width $\ll$ RBW, so that all spurious emissions are captured) [BIN-width is the frequency difference between 2 adjacent sample points on the display]

(3) Set EUT as occupied bandwidth is measure. That is, Set the EUT on the test frequency and the continuous TX mode or continuous (constant period, constant burst length) burst TX mode. In case of spreading code

used, set on the test spreading code, then the modulation is performed with standard coding test signal. The spectrum analyzer is set as 2 (1). Seek the spurious emission. If the amplitude of the sought spurious emission satisfies the specified value (in case of 2 (2) Note 1, the specified value is -3dB), the measurement of 2 (2) is not performed, then the estimated value is employed as the measured value.

In case the sought spurious emission amplitude exceeds the specified value, seek the spurious frequency by narrowing the sweeping band sequentially as 100 MHz, 10 MHz, 1 MHz for the purpose of higher accuracy of the spectrum analyzer. Set the spectrum analyzer as 2 (2). Estimate the mean value of the spurious amplitude, then employ it as the measured value (In case DSSS as well as OFDM with burst wave, the mean inside of the burst).

Sweep Bandwidth: 30MHz~2387MHz, 2483.5MHz~2496.5MHz, 2496.5MHz~12500MHz

Respectively mark the maximum results in the above sweep bandwidth.

7.4.5 Environmental Conditions

Temperature:	24.1°C
Relative Humidity:	46%
ATM Pressure:	1011 mbar

7.4.6 Test Results

TestCondition	TestMode	Antenna	Frequen cy[MHz]	Freq.Range [MHz]	Freq. [MHz]	Result [dBm]	Limit [dBm]	Result [μW]	Limit [μW]	Verdict
NTNV	11B	Ant1	2412	30~2387	1445.38	-34.53	≤-26	0.35237	≤2.5	PASS
NTNV	11B	Ant1	2412	2387~2400	2388.07	-38.15	≤-16	0.15311	≤25	PASS
NTNV	11B	Ant1	2412	2483.5~2496.5	2489.56	-38.17	≤-16	0.15241	≤25	PASS
NTNV	11B	Ant1	2412	2496.5~13000	5529.01	-34.13	≤-26	0.38637	≤2.5	PASS
NTNV	11B	Ant1	2442	30~2387	1466.89	-34.60	≤-26	0.34674	≤2.5	PASS
NTNV	11B	Ant1	2442	2387~2400	2398.68	-37.57	≤-16	0.17498	≤25	PASS
NTNV	11B	Ant1	2442	2483.5~2496.5	2496.13	-38.19	≤-16	0.15171	≤25	PASS
NTNV	11B	Ant1	2442	2496.5~13000	4884.06	-34.68	≤-26	0.34041	≤2.5	PASS
NTNV	11B	Ant1	2472	30~2387	1484.86	-34.85	≤-26	0.32734	≤2.5	PASS
NTNV	11B	Ant1	2472	2387~2400	2390.62	-37.14	≤-16	0.19320	≤25	PASS
NTNV	11B	Ant1	2472	2483.5~2496.5	2493.80	-36.05	≤-16	0.24831	≤25	PASS
NTNV	11B	Ant1	2472	2496.5~13000	5474.39	-33.93	≤-26	0.40458	≤2.5	PASS
NTNV	11G	Ant1	2412	30~2387	2308.34	-35.47	≤-26	0.28379	≤2.5	PASS
NTNV	11G	Ant1	2412	2387~2400	2399.84	-17.26	≤-16	18.7931 7	≤25	See table below
NTNV	11G	Ant1	2412	2483.5~2496.5	2487.36	-37.40	≤-16	0.18197	≤25	PASS
NTNV	11G	Ant1	2412	2496.5~13000	5932.89	-34.41	≤-26	0.36224	≤2.5	PASS
NTNV	11G	Ant1	2442	30~2387	1468.95	-35.30	≤-26	0.29512	≤2.5	PASS
NTNV	11G	Ant1	2442	2387~2400	2394.38	-38.17	≤-16	0.15241	≤25	PASS
NTNV	11G	Ant1	2442	2483.5~2496.5	2483.68	-38.30	≤-16	0.14791	≤25	PASS
NTNV	11G	Ant1	2442	2496.5~13000	6071.54	-34.37	≤-26	0.36559	≤2.5	PASS
NTNV	11G	Ant1	2472	30~2387	2352.23	-34.73	≤-26	0.33651	≤2.5	PASS
NTNV	11G	Ant1	2472	2387~2400	2393.74	-37.95	≤-16	0.16032	≤25	PASS
NTNV	11G	Ant1	2472	2483.5~2496.5	2483.73	-19.36	≤-16	11.5877 7	≤25	PASS
NTNV	11G	Ant1	2472	2496.5~13000	5842.03	-34.09	≤-26	0.38994	≤2.5	PASS
NTNV	11N20SI SO	Ant1	2412	30~2387	1928.56	-34.74	≤-26	0.33574	≤2.5	PASS
NTNV	11N20SI SO	Ant1	2412	2387~2400	2399.98	-16.97	≤-16	20.0909 3	≤25	See table below
NTNV	11N20SI SO	Ant1	2412	2483.5~2496.5	2492.60	-38.29	≤-16	0.14825	≤25	PASS
NTNV	11N20SI SO	Ant1	2412	2496.5~13000	6039.51	-34.11	≤-26	0.38815	≤2.5	PASS
NTNV	11N20SI SO	Ant1	2442	30~2387	2049.36	-35.25	≤-26	0.29854	≤2.5	PASS
NTNV	11N20SI SO	Ant1	2442	2387~2400	2398.65	-38.00	≤-16	0.15849	≤25	PASS
NTNV	11N20SI SO	Ant1	2442	2483.5~2496.5	2483.60	-37.21	≤-16	0.19011	≤25	PASS
NTNV	11N20SI SO	Ant1	2442	2496.5~13000	5761.68	-34.28	≤-26	0.37325	≤2.5	PASS
NTNV	11N20SI SO	Ant1	2472	30~2387	2374.63	-34.03	≤-26	0.39537	≤2.5	PASS
NTNV	11N20SI SO	Ant1	2472	2387~2400	2391.96	-38.14	≤-16	0.15346	≤25	PASS
NTNV	11N20SI SO	Ant1	2472	2483.5~2496.5	2484.08	-17.72	≤-16	16.9044 1	≤25	See table below
NTNV	11N20SI SO	Ant1	2472	2496.5~13000	6138.77	-33.36	≤-26	0.46132	≤2.5	PASS
NTNV	11N40SI SO	Ant1	2422	30~2387	2094.14	-35.16	≤-26	0.30479	≤2.5	PASS
NTNV	11N40SI SO	Ant1	2422	2387~2400	2399.41	-21.75	≤-16	6.68344	≤25	PASS
NTNV	11N40SI SO	Ant1	2422	2483.5~2496.5	2494.75	-38.77	≤-16	0.13274	≤25	PASS

NTNV	11N40SI SO	Ant1	2422	2496.5~13000	5906.11	-33.99	≤-26	0.39902	≤2.5	PASS
NTNV	11N40SI SO	Ant1	2442	30~2387	2259.72	-35.31	≤-26	0.29444	≤2.5	PASS
NTNV	11N40SI SO	Ant1	2442	2387~2400	2397.89	-37.83	≤-16	0.16482	≤25	PASS
NTNV	11N40SI SO	Ant1	2442	2483.5~2496.5	2485.39	-38.68	≤-16	0.13552	≤25	PASS
NTNV	11N40SI SO	Ant1	2442	2496.5~13000	5742.24	-34.10	≤-26	0.38905	≤2.5	PASS
NTNV	11N40SI SO	Ant1	2462	30~2387	2290.95	-34.99	≤-26	0.31696	≤2.5	PASS
NTNV	11N40SI SO	Ant1	2462	2387~2400	2388.50	-37.64	≤-16	0.17219	≤25	PASS
NTNV	11N40SI SO	Ant1	2462	2483.5~2496.5	2483.51	-19.82	≤-16	10.4231 7	≤25	PASS
NTNV	11N40SI SO	Ant1	2462	2496.5~13000	5955.48	-33.15	≤-26	0.48417	≤2.5	PASS
NTNV	11AX20S ISO	Ant1	2412	30~2387	2337.80	-35.75	≤-26	0.26607	≤2.5	PASS
NTNV	11AX20S ISO	Ant1	2412	2387~2400	2399.89	-16.53	≤-16	22.2331 0	≤25	See table below
NTNV	11AX20S ISO	Ant1	2412	2483.5~2496.5	2488.16	-39.10	≤-16	0.12303	≤25	PASS
NTNV	11AX20S ISO	Ant1	2412	2496.5~13000	6328.37	-33.85	≤-26	0.41210	≤2.5	PASS
NTNV	11AX20S ISO	Ant1	2442	30~2387	2166.33	-35.34	≤-26	0.29242	≤2.5	PASS
NTNV	11AX20S ISO	Ant1	2442	2387~2400	2398.12	-37.67	≤-16	0.17100	≤25	PASS
NTNV	11AX20S ISO	Ant1	2442	2483.5~2496.5	2485.13	-38.43	≤-16	0.14355	≤25	PASS
NTNV	11AX20S ISO	Ant1	2442	2496.5~13000	6120.91	-33.29	≤-26	0.46881	≤2.5	PASS
NTNV	11AX20S ISO	Ant1	2472	30~2387	2298.32	-34.97	≤-26	0.31842	≤2.5	PASS
NTNV	11AX20S ISO	Ant1	2472	2387~2400	2392.73	-37.92	≤-16	0.16144	≤25	PASS
NTNV	11AX20S ISO	Ant1	2472	2483.5~2496.5	2484.58	-16.99	≤-16	19.9986 2	≤25	See table below
NTNV	11AX20S ISO	Ant1	2472	2496.5~13000	6223.33	-33.98	≤-26	0.39994	≤2.5	PASS
NTNV	11AX40S ISO	Ant1	2422	30~2387	2059.97	-35.28	≤-26	0.29648	≤2.5	PASS
NTNV	11AX40S ISO	Ant1	2422	2387~2400	2398.92	-21.58	≤-16	6.95024	≤25	PASS
NTNV	11AX40S ISO	Ant1	2422	2483.5~2496.5	2486.87	-38.62	≤-16	0.13740	≤25	PASS
NTNV	11AX40S ISO	Ant1	2422	2496.5~13000	6978.57	-34.30	≤-26	0.37154	≤2.5	PASS
NTNV	11AX40S ISO	Ant1	2442	30~2387	2242.93	-35.29	≤-26	0.29580	≤2.5	PASS
NTNV	11AX40S ISO	Ant1	2442	2387~2400	2394.69	-32.22	≤-16	0.59979	≤25	PASS
NTNV	11AX40S ISO	Ant1	2442	2483.5~2496.5	2483.84	-34.16	≤-16	0.38371	≤25	PASS
NTNV	11AX40S ISO	Ant1	2442	2496.5~13000	7163.44	-33.49	≤-26	0.44771	≤2.5	PASS
NTNV	11AX40S ISO	Ant1	2462	30~2387	2382.58	-35.08	≤-26	0.31046	≤2.5	PASS

NTNV	11AX40S ISO	Ant1	2462	2387~2400	2392.03	-38.15	≤-16	0.15311	≤25	PASS
NTNV	11AX40S ISO	Ant1	2462	2483.5~2496.5	2483.90	-19.68	≤-16	10.7646 5	≤25	PASS
NTNV	11AX40S ISO	Ant1	2462	2496.5~13000	6956.51	-34.04	≤-26	0.39446	≤2.5	PASS

Step2

TestCondition	TestMode	Antenna	Frequen cy[MHz]	Freq. [MHz]	Result [dBm]	Gain [dBi]	EIRP Result [dBm]	Result [μW]	Limit [μW]	Verdict
NTNV	11G	Ant1	2412	2399.45	-33.91	0	-33.91	0.40644	≤25	PASS
NTNV	11N20SI SO	Ant1	2412	2399.81	-32.42	0	-32.42	0.57280	≤25	PASS
NTNV	11N20SI SO	Ant1	2472	2483.78	-33.69	0	-33.69	0.42756	≤25	PASS
NTNV	11AX20S ISO	Ant1	2412	2399.67	-30.90	0	-30.90	0.81283	≤25	PASS
NTNV	11AX20S ISO	Ant1	2472	2483.78	-33.69	0	-33.69	0.42756	≤25	PASS


複製禁止




Access to the World

複製禁止


複製禁止




NTNV-11B-Ant1-2412-30~2387-PASS





NTNV-11B-Ant1-2412-2387~2400-PASS




NTNV-11B-Ant1-2412-2483.5~2496.5-PASS




NTNV-11B-Ant1-2412-2496.5~13000-PASS







NTNV-11B-Ant1-2442-2483.5~2496.5-PASS




NTNV-11B-Ant1-2442-2496.5~13000-PASS




NTNV-11B-Ant1-2472-30~2387-PASS




NTNV-11B-Ant1-2472-2387~2400-PASS




NTNV-11B-Ant1-2472-2483.5~2496.5-PASS



NTNV-11B-Ant1-2472-2496.5~13000-PASS



NTNV-11G-Ant1-2412-30~2387-PASS



NTNV-11G-Ant1-2412-2387~2400-See table below