



Shenzhen BANTEK Testing Co., Ltd.

Report No.: BTEK260227005A01E01

RF Test Report

For BTEK260227005A01E01

Project No.:	BTEK260227005A01E01
Product Description:	23.8℃, 62%, 101.7kPa
Test Engineer:	Zora
Test Date:	2026-02-28



Shenzhen BANTEK Testing Co., Ltd.

Report No.: BTEK260227005A01E01

Test Summary

Item	Result
Frequency Error	Pass
Occupied Bandwidth	Pass
Spread Bandwidth	Pass
Antenna Power	Pass
Dwell Time	Pass
Spurious Emission Intensity	Pass
Secondary Radiated Emission	Pass



1. Frequency Error

1.1 Test Result


1.1.1 Ant1


Ant1								
ENV	Mode	TX Type	Frequency (MHz)	Packet Type	Measured Frequency (MHz)	Tolerance (ppm)		Verdict
						Result	Limit	
NTNV	Carrier Wave	SISO	2402	DH5	2401.997	-1.25	-50 to 50	Pass
			2441	DH5	2440.995	-2.05	-50 to 50	Pass
			2480	DH5	2479.995	-2.02	-50 to 50	Pass




1.2 Test Graph

1.2.1 Ant1









Shenzhen BANTEK Testing Co., Ltd.

Report No.: BTEK260227005A01E01

2. Occupied Bandwidth

2.1 Test Result


2.1.1 OBW


ENV	Mode	TX Type	Frequency (MHz)	Packet Type	99% Occupied Bandwidth (MHz)		Verdict
					ANT1	Limit	
NTNV	GFSK	SISO	HOPP	DH5	78.741	<=83.5	Pass
	Pi/4DQPSK	SISO	HOPP	2DH5	78.882	<=83.5	Pass
	8DPSK	SISO	HOPP	3DH5	78.873	<=83.5	Pass




2.2 Test Graph

2.2.1 OBW









3. Spread Bandwidth

3.1 Test Result

3.1.1 SPBW

ENV	Mode	TX Type	Frequency (MHz)	Packet Type	Spread Bandwidth (MHz)		Verdict
					ANT1	Limit	
NTNV	GFSK	SISO	HOPP	DH5	71.272	/	Only For Report
	Pi/4DQPSK	SISO	HOPP	2DH5	71.368	/	Only For Report
	8DPSK	SISO	HOPP	3DH5	71.392	/	Only For Report

3.1.2 SpreadFactor


ENV	Mode	TX Type	Frequency (MHz)	Packet Type	Spread Factor		Verdict
					ANT1	Limit	
NTNV	GFSK	SISO	HOPP	DH5	71.272	≥ 5	Only For Report
	Pi/4DQPSK	SISO	HOPP	2DH5	71.368	≥ 5	Only For Report
	8DPSK	SISO	HOPP	3DH5	71.392	≥ 5	Only For Report


Note1: Spread Factor = Spread Bandwidth / Symbol Rate, For Bluetooth, Symbol Rate = 1




3.2 Test Graph

3.2.1 SPBW









4. Antenna Power

4.1 Test Result

4.1.1 Power


ENV	Mode	TX Type	Frequency (MHz)	Packet Type	ANT	Antenna Power (mW/MHz)		Nominal Power (mW/MHz)	Tolerance (%)		Verdict
						Measured	Limit		Measured	Limit	
NTNV	GFSK	SISO	HOPP	DH5	1	0.033	<=3.00	0.033	0.00	-80 to 20	Pass
	PI/4DQPSK	SISO	HOPP	2DH5	1	0.025	<=3.00	0.025	0.00	-80 to 20	Pass
	8DPSK	SISO	HOPP	3DH5	1	0.020	<=3.00	0.020	0.00	-80 to 20	Pass


ENV	Mode	TX Type	Frequency (MHz)	Packet Type	ANT	Antenna Power (dBm)	Gain (dBi)	EIRP (dBm/MHz)		Verdict
								Result	Limit	
NTNV	GFSK	SISO	HOPP	DH5	1	-14.81	2.7	-12.11	<=6.91	Pass
	PI/4DQPSK	SISO	HOPP	2DH5	1	-16.02	2.7	-13.32	<=6.91	Pass
	8DPSK	SISO	HOPP	3DH5	1	-16.99	2.7	-14.29	<=6.91	Pass



4.2 Test Graph

4.2.1 Power







Burst No.	1
Length (ms)	2.888
Power(dBm)	3.75
Power(mW)	2.373
Remark	Max



Pi/4DQPSK_2DH5_HOPP_Ant1_NTNV




Pi/4DQPSK_2DH5_HOPP_Ant1_NTNV




Burst No.	1
Length (ms)	2.894
Power(dBm)	2.50
Power(mW)	1.780
Remark	Max



8DPSK 3DH5_HOPP_Ant1_NTNV



8DPSK 3DH5_HOPP_Ant1_NTNV



Burst No.	1
Length (ms)	0.900
Power(dBm)	1.53
Power(mW)	1.423
Remark	Max



Shenzhen BANTEK Testing Co., Ltd.

Report No.: BTEK260227005A01E01

5. Dwell Time

5.1 Test Result


5.1.1 Ant1


Ant1											
ENV	Mode	TX Type	Frequency (MHz)	Packet Type	Spreading Rate	T_on (ms)	Period (ms)	Hopp Number	Dwell Time (ms)		Verdict
									Result	Limit	
NTNV	GFSK	SISO	2441	DH5	71.272	2.888	3.750	79	277.919	<=400	Pass
	PI/4DQPSK	SISO	2441	2DH5	71.368	2.893	3.750	79	278.775	<=400	Pass
	8DPSK	SISO	2441	3DH5	71.392	0.897	3.750	79	86.466	<=400	Pass




5.2 Test Graph

5.2.1 Ant1









6. Spurious Emission Intensity

6.1 Test Result


6.1.1 TxSe_NTNV


NTNV												
Mode	TX Type	Freq. (MHz)	ANT	Freq. Range		Marker					Limit (uW /MHz)	Verdict
				Start (MHz)	Stop (MHz)	Freq. (MHz)	PK Power (dBm /MHz)	PK Power (uW /MHz)	AV Power (dBm /MHz)	AV Power (uW /MHz)		
GFSK	SISO	HOPP	1	30	2387	2380.5	-45.63	0.027	/	/	2.5	Pass
				2387	2400	2399.61	-34.96	0.319	/	/	25	Pass
				2483.5	2496.5	2496.058	-41.58	0.070	/	/	25	Pass
				2496.5	12500	2499.5	-46.25	0.024	/	/	2.5	Pass
Pi/4DQPSK	SISO	HOPP	1	30	2387	2385.5	-45.39	0.029	/	/	2.5	Pass
				2387	2400	2399.961	-31.87	0.650	/	/	25	Pass
				2483.5	2496.5	2485.489	-40.19	0.096	/	/	25	Pass
				2496.5	12500	5810.5	-47.13	0.019	/	/	2.5	Pass
8DPSK	SISO	HOPP	1	30	2387	2383	-44.04	0.039	/	/	2.5	Pass
				2387	2400	2399.987	-29.85	1.035	/	/	25	Pass
				2483.5	2496.5	2483.617	-40.50	0.089	/	/	25	Pass
				2496.5	12500	9838.5	-46.69	0.021	/	/	2.5	Pass



6.2 Test Graph

6.2.1 TxSe_NTNV







Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	2387	1	1	2380.500	-45.63	/	-26	Pass
2387	2400	1	1	2399.610	-34.96	/	-16	Pass
2483.5	2496.5	1	1	2496.058	-41.58	/	-16	Pass
2496.5	12500	1	1	2499.500	-46.25	/	-26	Pass



Pi/4DQPSK_2DH5_HOPP_Ant1_NTNV




Pi/4DQPSK_2DH5_HOPP_Ant1_NTNV




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	2387	1	1	2385.500	-45.39	/	-26	Pass
2387	2400	1	1	2399.961	-31.87	/	-16	Pass
2483.5	2496.5	1	1	2485.489	-40.19	/	-16	Pass
2496.5	12500	1	1	5810.500	-47.13	/	-26	Pass



8DPSK 3DH5 HOPP_Ant1_NTNV



8DPSK 3DH5 HOPP_Ant1_NTNV



Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	2387	1	1	2383.000	-44.04	/	-26	Pass
2387	2400	1	1	2399.987	-29.85	/	-16	Pass
2483.5	2496.5	1	1	2483.617	-40.50	/	-16	Pass
2496.5	12500	1	1	9838.500	-46.69	/	-26	Pass



7. Secondary Radiated Emission

7.1 Test Result


7.1.1 RxSe_NTNV


NTNV												
Mode	TX Type	Freq. (MHz)	ANT	Freq. Range		Marker					Limit (nW)	Verdict
				Start (MHz)	Stop (MHz)	Freq. (MHz)	PK Power (dBm)	PK Power (nW)	AV Power (dBm)	AV Power (nW)		
GFSK	SISO	2402	1	30	1000	486.25	-78.49	0.014	/	/	4	Pass
				1000	12500	6298	-64.16	0.384	/	/	20	Pass
		2441	1	30	1000	749.35	-78.16	0.015	/	/	4	Pass
				1000	12500	7346.5	-63.62	0.435	/	/	20	Pass
		2480	1	30	1000	520.7	-77.62	0.017	/	/	4	Pass
				1000	12500	5442	-63.91	0.406	/	/	20	Pass
Pi/4DQPSK	SISO	2402	1	30	1000	948.1	-78.20	0.015	/	/	4	Pass
				1000	12500	6386.5	-64.22	0.378	/	/	20	Pass
		2441	1	30	1000	956.55	-78.20	0.015	/	/	4	Pass
				1000	12500	6070.5	-64.17	0.383	/	/	20	Pass
		2480	1	30	1000	936.95	-78.04	0.016	/	/	4	Pass
				1000	12500	5378.5	-64.30	0.372	/	/	20	Pass
8DPSK	SISO	2402	1	30	1000	990.15	-78.07	0.016	/	/	4	Pass
				1000	12500	6374	-63.96	0.402	/	/	20	Pass
		2441	1	30	1000	904.65	-77.98	0.016	/	/	4	Pass
				1000	12500	3174.5	-63.87	0.410	/	/	20	Pass
		2480	1	30	1000	917.1	-77.04	0.020	/	/	4	Pass
				1000	12500	5992	-63.84	0.413	/	/	20	Pass




7.2 Test Graph

7.2.1 RxSe_NTNV






GFSK DH5 2441MHz Ant1 NTN




GFSK DH5 2441MHz Ant1 NTN




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	749.350	-78.16	/	-54	Pass
1000	12500	1	1	7346.500	-63.62	/	-47	Pass

GFSK DH5 2480MHz Ant1 NTN




GFSK DH5 2480MHz Ant1 NTN




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	520.700	-77.62	/	-54	Pass
1000	12500	1	1	5442.000	-63.91	/	-47	Pass



Pi/4DQPSK_2DH5_2402MHz_Ant1_NTNV




Pi/4DQPSK_2DH5_2402MHz_Ant1_NTNV




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	948.100	-78.20	/	-54	Pass
1000	12500	1	1	6386.500	-64.22	/	-47	Pass



Pi/4DQPSK_2DH5_2441MHz_Ant1_NTNV




Pi/4DQPSK_2DH5_2441MHz_Ant1_NTNV




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	956.550	-78.20	/	-54	Pass
1000	12500	1	1	6070.500	-64.17	/	-47	Pass



Pi/4DQPSK_2DH5_2480MHz_Ant1_NTNV




Pi/4DQPSK_2DH5_2480MHz_Ant1_NTNV




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	936.950	-78.04	/	-54	Pass
1000	12500	1	1	5378.500	-64.30	/	-47	Pass



8DPSK 3DH5 2402MHz_Ant1_NTNV




8DPSK 3DH5 2402MHz_Ant1_NTNV




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	990.150	-78.07	/	-54	Pass
1000	12500	1	1	6374.000	-63.96	/	-47	Pass

8DPSK 3DH5 2441MHz Ant1 NTN




8DPSK 3DH5 2441MHz Ant1 NTN




Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	904.650	-77.98	/	-54	Pass
1000	12500	1	1	3174.500	-63.87	/	-47	Pass



8DPSK 3DH5 2480MHz_Ant1_NTNV



8DPSK 3DH5 2480MHz_Ant1_NTNV



Start (MHz)	Stop (MHz)	RBW (MHz)	VBW (MHz)	Freq (MHz)	PK Power (dBm)	AV Power (dBm)	Limit (dBm)	Result
30	1000	0.1	0.1	917.100	-77.04	/	-54	Pass
1000	12500	1	1	5992.000	-63.84	/	-47	Pass