TEST REPORT

Product Name:	Laser Obstacle Remover
Trademark:	redcoast
Model Number:	RFE-500B, RFE-1000B
Prepared For:	SICHUAN RED COAST BASE INTELLIGENT TECHNOLOGY LTD
Address:	Room 909, 9/F, Unit 1, Building 9, No. 1700, North Section of Tianfu Avenue, Chengdu Hi-Tech Industrial Development Zone, China (Sichuan) Pilot Free Trade Zone
Manufacturer:	SICHUAN RED COAST BASE INTELLIGENT TECHNOLOGY LTD
Address:	Room 909, 9/F, Unit 1, Building 9, No. 1700, North Section of Tianfu Avenue, Chengdu Hi-Tech Industrial Development Zone, China (Sichuan) Pilot Free Trade Zone
Prepared By:	Shenzhen CTB Testing Technology Co., Ltd.
Address:	1&2/F., Building A, No.26, Xinhe Road, Xinqiao, Xinqiao Street, Bao'an District, Shenzhen, Guangdong, China
Sample Received Date:	Oct. 15, 2024
Sample tested Date:	Oct. 15, 2024 to Feb. 21, 2025
Issue Date:	Feb. 21, 2025
Report No.:	CTB24101506005RF02
Test Standards	MIC Notice No.88 Appendix No.45 Item 19-3
Test Results	PASS
Remark:	This is 5G WIFI radio test report.

Compiled by:	Reviewed by:	Approved by:
Zhou Kui	Arron Liu	
ZhouKui	Arron Liu	Bin Mei / Director

Note: If there is any objection to the inspection results in this report, please submit a written report to the company within 15 days from the date of receiving the report. The test report is effective only with both signature and specialized stamp. This result(s) shown in this report refer only to the sample(s) tested. Without written approval of Shenzhen CTB Testing Technology Co., Ltd. this report can't be reproduced except in full. The tested sample(s) and the sample information are provided by the client. "*" indicates the testing items were fulfilled by subcontracted lab. "#" indicates the items are not in CNAS accreditation scope.

Table of Contents **Page**

1.Version 5

2.TEST PROCEDURES AND RESULTS 6

3.MEASUREMENT UNCERTAINTY 8

4.GENERAL INFORMATION 9

4.1 GENERAL DESCRIPTION OF EUT 9

4.2 Channel list 10

4.3Table for Filed Antenna 10

4.4 DESCRIPTION OF TEST MODES 10

4.5 TEST CONDITIONS 11

4.6 Block diagram showing the configuration of system tested 11

4.7 DESCRIPTION OF SUPPORT UNITS(CONDUCTEDMODE) 12

4.8 MEASUREMENT INSTRUMENTS LIST 13

5. Antenna Requirement 15

6. Frequency Error 16

6.1 LIMIT 16

6.2 TEST PROCEDURE 16

6.3Test Setup Block Diagram 16

6.4 TEST RESULT 17

7. Occupied Bandwidth (99%) 22

7.1 LIMIT 22

7.2 TEST PROCEDURE 22

7.3 TEST SETUP BLOCK DIAGRAM 22

7.4 TEST RESULT 23

8.Adjacent Channel Emitted Power 35

8.1 LIMIT 35

8.2 TEST PROCEDURE 35

8.3 TEST SETUP Block Diagram 36

8.4 TEST RESULT 36

9Antenna Power and Tolerance 53

9.1 LIMIT 53

9.2 TEST PROCEDURE 53

9.3 Test Setup Block Diagram 53

Table of Contents **Page**

9.4 TEST RESULT 54

10. Unwanted Emissions Strength 55

10.1 LIMIT 55

10.2 TEST PROCEDURE 55

10.3 TEST SETUP Block Diagram 55

10.4 TEST RESULT 56

11 Interference Prevention Function 84

11.1 LIMIT 84

11.2 TEST PROCEDURE 84

11.3 TEST SETUP LAYOUT 84

11.4 TEST RESULT 84

12Carrier sense capability 85

12.1 LIMIT 85

12.2 TEST PROCEDURE 85

12.3 TEST SETUP BLOCK DIAGRAM 85

12.4 TEST RESULT 86

13Construction Protection Confirmation 87

12.1 Requirement 87

13.2 Confirmation method 87

13.3 The photos of construction protection 87

14 Transmission Burst Length 88

14.1 LIMIT 88

14.2 TEST PROCEDURE 88

14.3 TEST SETUP BLOCK DIAGRAM 88

14.4 TEST RESULT 89

15 Secondary Radiated Emitted Power 101

15.1 LIMIT 101

15.2 TEST PROCEDURE 101

15.3 TEST SETUP BLOCK DIAGRAM 101

15.4 TEST RESULT 102

16DYNAMIC FREQUENCY SELECTION (SLAVE) 114

16.1 Standard Applicable 114

Table of Contents **Page**

16.2 TEST PROCEDURE 114
16.3 Summary of Test Results 114
17 EUT TEST PHOTO 115

1.Version

Report No.	Issue Date	Description	Approved
CTB24101506005RF02	Feb. 21, 2025	Original	Valid

2.TEST PROCEDURES AND RESULTS

Test item	Test Requirement	Limit/Severity	Result
Antenna Requirement	Item 19-3 of Article 2 Paragraph 1	Notice 88 Appendix 43,B-1 (1)&(2)	PASS
Frequency Error	Item 19-3 of Article 2 Paragraph 1	+/-20ppm	PASS
Occupied Bandwidth (99%)	Item 19-3 of Article 2 Paragraph 1	W52: Occupied bandwidth: ≤20MHz (20MHz System, OFDM) Occupied bandwidth: ≤40MHz (40MHz System, OFDM) Occupied bandwidth: ≤80MHz (80MHz System, OFDM)	PASS
Adjacent Channel Emitted Power	Item 19-3 of Article 2 Paragraph 1	802.11a/n20/ac20: Fc ± 20MHz±10MHz BW : -25dBc Fc ± 20MHz±10MHz BW : -25dBc 802.11n40/ac40: Fc ± 40MHz±20MHz BW : -25dBc Fc ± 80MHz±20MHz BW : -40dBc 802.11ac80: Fc ± 80MHz ±40MHz BW : -25dBc	PASS
Antenna Power and Tolerance	Item 19-3 of Article 2 Paragraph 1	(1)10mW/MHz(OFDM, DSSS:20MHz system), (2)5mW/MHz(OFDM:40MHz system), (3)2.5mW/MHz(OFDM:80MHz system), (4)10mW/MHz(except above methods), Tolerance : W52: -80%~+20%, W56:-50%~+50%.	PASS
Unwanted Emission Strength	Item 19-3 of Article 2 Paragraph 1	Attachment 1	PASS
Interference Prevention Function	Item 19-3 of Article 2 Paragraph 1	Article 49	PASS
Carrier sense capability	Item 19-3 of Article 2 Paragraph 1	Article 49	PASS
Construction Protection Confirmation	Item 19-3 of Article 2 Paragraph 1	Article 49	PASS
Transmission Burst Length	Item 19-3 of Article 2 Paragraph 1	8ms or less	PASS
Secondary Radiated Emission Strength	Item 19-3 of Article 2 Paragraph 1	(1)Below 1GHz:4nW/100kHz or less (2)1GHz or higher:20nW/MHz or less	PASS

Dynamic Frequency selection(DFS)	Item 19-3 of Article 2 Paragraph 1	WAS/RLAN devices operating in slave mode (slave device) can be operated in a network controlled by aWAN/RLAN device operating in master mode (master device).	N/A

3.MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the Product as specified in CISPR 16-4-2. This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.

Parameter	**Uncertainty**
Frequency error / 99%&90% bandwidth	±54.3Hz
Total RF power, conducted	±1.0dB
Spurious emissions, conducted	±2.8dB
DC and low frequency voltages	±3%
Humidity	±5.3%
Temperature	±0.59℃

4.GENERAL INFORMATION

4.1 GENERAL DESCRIPTION OF EUT

Model(s):	RFE-500B, RFE-1000B
Model Description:	All the model are the same circuit and RF module, only the name and appearance are different. Test sample model: RFE-500BDC
Wi-Fi Specification:	IEEE 802.11a/n/ac
Hardware Version:	V1.0
Software Version:	V5.2.1
Operation Frequency:	IEEE 802.11a/n/ac(20M): 5150MHz ~5250MHz/ 4 channel IEEE 802.11n/ac(40M): 5150MHz ~5250MHz/ 2 channel IEEE 802.11ac(80M): 5150MHz ~5250MHz/ 1 channel
Rate Output power:	802.11a: 8mW/MHz 802.11ac(VHT20): 5mW/MHz, 802.11n(HT20): 5mW/MHz, 802.11n(HT40): 2mW/MHz, 802.11ac(VHT40): 2mW/MHz 802.11ac80: 1mW/MHz
Type of Modulation:	OFDM
Antenna installation:	Internal antenna
Antenna Gain:	ANT1: 3.62dBi, ANT2: 3.62dBi
Ratings:	ADAPTER: Input: AC 180-250V form adapter Output: DC 54.6V ⎓ 5A DC 48V by battery

Note: For a more detailed features description, please refer to the manufacturer's specifications or the User's Manual.

4.2 Channel list

For 802.11a/n/ac(20M) Operation in the 5150MHz ~5250 MHz band			
Channel	Frequency	Channel	Frequency
36	5180MHz	44	5220MHz
40	5200MHz	48	5240MHz
For 802.11n/ac(40M) Operation in the 5150MHz ~5250 MHz band			
Channel	Frequency	Channel	Frequency
38	5190MHz	46	5230MHz
For 802.11ac(80M) Operation in the 5150MHz ~5250 MHz band			
Channel	Frequency	Channel	Frequency
42	5210MHz	NA	NA

4.3Table for Filed Antenna

Ant.	Brand	Model Name	Antenna Type	Gain(dBi)	NOTE
1	N/A	5.2G antenna	Internal antenna	3.62dBi	N/A
2	N/A	5.2G antenna	Internal antenna	3.62dBi	N/A

4.4 DESCRIPTION OF TEST MODES

All test mode(s) and condition(s) mentioned were considered and evaluated respectively by performing full tests, the worst data were recorded and reported.

Test Mode	Tx/Rx	RF Channel		
		Low(L)	Middle(M)	High(H)
802.11a/n/ac(20M)	5150MHz ~5250 MHz	Channel 36	Channel 40	Channel 48
		5180MHz	5200MHz	5240MHz
802.11n/ac(40M)	5150MHz ~5250 MHz	Channel 38	N/A	Channel 46
		5190MHz	N/A	5230MHz
802.11ac(80M)	5150MHz ~5250 MHz	N/A	Channel 42	N/A
		N/A	5210MHz	N/A

4.5 TEST CONDITIONS

Supply Voltage				
	Adapter power V	Module input power V	Rated module power V	Tolerance (%)
Normal	48	3.3	3.3	
+10%	52.8	3.3	3.3	0
-10%	43.2	3.3	3.3	0
Others				
Temperature (°C)		20-25		
Relative humidity		54 %.		
ATM Pressure:		1010 mbar		
Note 1: When the input voltage is reduced or increased by 10%, the regulator voltage changes of less than 1%. So the following test items are conducted in the normal voltage.				

4.6 Block diagram showing the configuration of system tested

Transmitting mode

4.7 DESCRIPTION OF SUPPORT UNITS(CONDUCTEDMODE)

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

Item	Equipment	Mfr/Brand	Model/Type No.	Note
E-1	Laser Obstacle Remover	redcoast	RFE-500B, RFE-1000B	EUT
E-2	Adapter	/	BF0930875001	EUT

Item	Shielded Type	Ferrite Core	Length	Note

Note:

1. The support equipment was authorized by Declaration of Confirmation.
2. For detachable type I/O cable should be specified the length in cm in『Length』column.
3. “YES” is means “shielded” “with core”; “NO” is means “unshielded” “without core”.

4.8 MEASUREMENT INSTRUMENTS LIST

No.	Equipment	Manufacturer	Type No.	Serial No.	Firmware Version	Calibrated until
1	Spectrum Analyzer	Agilent	N9020A	MY52090073	A.14.16	2025/6/28
2	Power Sensor	Agilent	U2021XA	MY56120032	/	2025/6/28
3	Power Sensor	Agilent	U2021XA	MY56120034	/	2025/6/28
4	Communication test set	R&S	CMW500	108058	V3.5.80	2025/6/28
5	Spectrum Analyzer	KEYSIGHT	N9020A	MY51289897	A.14.16	2025/6/28
6	Signal Generator	Agilent	N5181A	MY50140365	A.01.60	2025/6/28
7	Vector signal generator	Agilent	N5182A	MY47420195	A.01.87	2025/6/28
8	Communication test set	Agilent	E5515C	MY50102567	B.19.07 (E1962B)	2025/6/28
9	2.4 GHz Filter	Shenxiang	MSF2400-2483.5MS-1154	20181015001	/	2025/6/30
10	5 GHz Filter	Shenxiang	MSF5150-5850MS-1155	20181015001	/	2025/6/30
11	Filter	Xingbo	XBLBQ-DZA120	190821-1-1	/	2025/6/30
12	BT&WI-FI Automatic test software	Micowave	MTS8310	Ver. 2.0.0.0	/	/
13	Rohde & Schwarz SFU Broadcast Test System	R&S	SFU	101017	/	2025/6/28
14	Temperature humidity chamber	Hongjing	TH-80CH	DG-15174	/	2025/6/28
15	234G Automatic test software	Micowave	MTS8200	Ver. 2.0.0.0	/	/
16	966 chamber	C.R.T.	966	/	/	2027/6/21
17	Receiver	R&S	ESPI	100362	RF_ATTEN_7 (104489/003)	2025/6/28
18	Amplifier	HP	8447E	2945A02747	/	2025/6/28

19	Amplifier	Agilent	8449B	3008A01838	/	2025/6/28
20	TRILOG Broadband Antenna	Schwarzbeck	VULB 9168	00869	/	2025/6/28
21	Double Ridged Broadband Horn Antenna	Schwarzbeck	BBHA9120D	01911	/	2025/6/28
22	EMI test software	Fala	EZ-EMC	FA-03A2 RE	/	/
23	Loop Antenna	Schwarzbeck	FMZB 1519B	1519B-224	/	2025/6/28
24	loop antenna	ZHINAN	ZN30900A	GTS534	/	/
25	40G Horn antenna	A/H/System	SAS-574	588	/	2025/6/28
26	Amplifier	AEROFLEX	Aeroflex	097	/	2025/6/28
27	Power Metter	KEYSIGHT	N1912AP	N/A	A.05.00	2025/6/28

Remark: Calibration institution "Guangzhou Lisai Measurement and Testing Co., LTD."

5. Antenna Requirement

Standard requirement
Applicable for equipment with an antenna terminal, including testing terminals) If an antenna connector is available, all relevant tests will be carried out conducted. If not, tests will be carried out in an anechoic room or with a suitable test-fixture.
EUT Antenna
The best case gain of the antenna is ANT1: 3.62dBi, ANT2: 3.62dBi. Internal antenna
Result: An antenna connector is available; all relevant tests will be carried out conducted.

6. Frequency Error

6.1 LIMIT

Item	Limits
Frequency Error	+/-20ppm

6.2 TEST PROCEDURE

1. Remove the antenna from the EUT and then connect a low loss RF cable from the antenna port to the spectrum analyzer.
2. Set center frequency of spectrum analyzer = operating frequency.
3. Set the spectrum analyzer as RBW=10kHz, VBW=10 kHz, Span = 1MHz.
4 'Maximum Hold'mode may be used to accumulate the measurement result over several scans provided emission is repetitive in nature.
5. Repeat above procedures until all frequency measured was complete.

6.3Test Setup Block Diagram



6.4 TEST RESULT

ANT 1

Test condition	Test Frequency	Measured	Tolerance	Test Result	Limit
	MHz	MHz	MHz	ppm	ppm
NVNT W52	5180	5179.958	-0.042	-8.108	+/-20
	5200	5199.958	-0.042	-8.077	+/-20
	5240	5239.957	-0.043	-8.206	+/-20
	5190	5189.958	-0.042	-8.092	+/-20
	5230	5229.957	-0.043	-8.222	+/-20
	5210	5209.958	-0.042	-8.061	+/-20

ANT 2

Test condition	Test Frequency	Measured	Tolerance	Test Result	Limit
	MHz	MHz	MHz	ppm	ppm
NVNT W52	5180	5179.959	-0.041	-7.915	+/-20
	5200	5199.958	-0.042	-8.077	+/-20
	5240	5239.957	-0.043	-8.206	+/-20
	5190	5189.957	-0.043	-8.285	+/-20
	5230	5229.957	-0.043	-8.222	+/-20
	5210	5209.957	-0.043	-8.253	+/-20

NVNT-ANT 1 W52

Channel(MHz)	Test graph
5180	
5200	
5240	

Channel(MHz)	Test graph
5190	
5230	
5210	

NVNT-ANT 2 W52

Channel(MHz)	Test graph
5180	
5200	
5240	

Channel(MHz)	Test graph
5190	
5230	
5210	

7. Occupied Bandwidth (99%)

7.1 LIMIT

W52:
Occupied bandwidth: ≤18MHz (20MHz System, DSSS)
Occupied bandwidth: ≤20MHz (20MHz System, OFDM)
Occupied bandwidth: ≤40MHz (40MHz System, OFDM)
Occupied bandwidth: ≤80MHz (80MHz System, OFDM)

7.2 TEST PROCEDURE

(1) Set up the spectrum analyzer as the follows:
Center frequency: Test frequency
Sweep bandwidth: 2 to 3.5 times of allowance
Resoluble bandwidth: less than 3% of allowance
Video bandwidth: Equivalent to resoluble bandwidth
Sweep time: Minimum time by which measuring accuracy is assured (In case of burst wave, 1 burst shall be contained per 1 sample)
Sampling points: More than 400 points
Sweep mode: Continuous sweeping
Detection mode: Positive peak
Display mode: Maximum holding

(2) Repeat the sweeping till no change was observed on the display and enter all values of data point to the computer as array variable.

(3) About all data, convert dB value to antilogarithm of electric power dimension.

(4) Add up the electric power of all data and record it as “Sum total of electric power”.

(5) Adding up data in order from the lowest frequency to upper frequencies, look for a limit point where the value reaches to 0.5% (5% in case of diffusion bandwidth) of “Sum total of electric power”. Convert the limit point to frequency and record as “Lowest limit frequency”.

(6) Adding up data in order from the highest frequency to lower frequencies, look for a limit point where the value reaches to 0.5% (5% in case of diffusion bandwidth) of “Sum total of electric power”. Convert the limit point to frequency and record as “Highest limit frequency”.

(7) Repeat above procedures until all frequency measured was complete.

7.3 TEST SETUP BLOCK DIAGRAM



7.4 TEST RESULT

W52 ANT 1

Normal Voltage			
Mode	Channel (MHz)	Occupy Bandwidth (MHz)	Limit (MHz)
802.11a	LCH	16.5379	≤18
	MCH	16.6076	
	HCH	17.5010	
802.11ac(VHT20)	LCH	17.7317	≤20
	MCH	17.7308	
	HCH	18.0014	
802.11ac(VHT40)	LCH	38.7016	≤40
	MCH	/	
	HCH	36.3578	
802.11ac(VHT80)	LCH	/	≤80
	MCH	76.3263	
	HCH	/	
802.11n(HT20)	LCH	17.7076	≤20
	MCH	17.7260	
	HCH	18.2806	
802.11n(HT40)	LCH	39.0316	≤40
	MCH	/	
	HCH	36.3872	
Result	Pass		

W52 ANT 2

Normal Voltage			
Mode	Channel (MHz)	Occupy Bandwidth (MHz)	Limit (MHz)
802.11a	LCH	16.5124	≤18
	MCH	16.7336	
	HCH	17.0112	
802.11ac(VHT20)	LCH	17.7602	≤20
	MCH	18.0572	
	HCH	18.2221	
802.11ac(VHT40)	LCH	36.2263	≤40
	MCH	/	
	HCH	36.3213	
802.11ac(VHT80)	LCH	/	≤80
	MCH	76.3165	
	HCH	/	
802.11n(HT20)	LCH	17.7094	≤20
	MCH	17.8089	
	HCH	18.0466	
802.11n(HT40)	LCH	36.2298	≤40
	MCH	/	
	HCH	36.2667	
Result	Pass		

ANT 1

Channel(MHz)	W52:802.11a
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(HT20)	
5180		
5200		
5240		

Channel(MHz)	W52:802.11ac(VHT40)	
5190		
5230		

Channel(MHz)	W52:802.11ac (VHT80)
5210	
Channel(MHz)	W52:802.11n(HT20)
5180	
5200	

5240		
Channel(MHz)	W52:802.11n(HT40)	
5190		
5230		

ANT 2

Channel(MHz)	W52:802.11a
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(HT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT40)	
5190		
5230		

Channel(MHz)	W52:802.11ac (VHT80)
5210	
Channel(MHz)	W52:802.11n(HT20)
5180	
5200	

5240		
Channel(MHz)	W52:802.11n(HT40)	
5190		
5230		

8.Adjacent Channel Emitted Power

8.1 LIMIT

W52

For system OBW<20MHz

Fc ± 20MHz ±10MHz BW : -25dBc

Fc ± 40MHz ±10MHz BW : -40dBc

For system OBW≤20MHz

Fc ± 20MHz ±10MHz BW : -25dBc

Fc ± 40MHz ±10MHz BW : -40dBc

For system OBW≤40MHz

Fc ± 40MHz±20MHz BW : -25dBc

Fc ± 80MHz±20MHz BW : -40dBc

For system OBW≤80MHz

Fc ± 80MHz ±40MHz BW : -25dBc

For system OBW≤80MHz +80MHz (Not adjacent band)

Fc ± 80MHz ±40MHz BW : -25dBc

For system OBW≤160MHz

N/A

8.2 TEST PROCEDURE

(1) A spectrum In case of conducted measurements, the radio device shall be connected to the measuring equipment via a suitable attenuator.
(2) The measurement equipment shall be set for sample hold mode of operation.
(3) the transmitter shall be operated at the receiving mode.
(4) The resolution bandwidth shall be set to ref. the limits , and the sweep time shall be set to auto mode, to ensure all major modulation products are captured.
(5) When the searched result is less than the specified limit, the maximum one shall be recorded, when the result is more than the specified limit, all measured values shall be recorded.
(6) This measurement shall be repeated with the transmitter in standby mode where applicable.
(7) Repeat above procedures until all frequency measured was complete.

8.3 TEST SETUP Block Diagram



8.4 TEST RESULT

W52 ANT1:

Normal Voltage						
Mode	detuning (MHz)		E.I.R.P (dBm/MHz)			Limit (dBm/MHz)
			LCH	MCH	HCH	
802.11a	20MHz	Lower	-30.85	-30.88	-30.79	-25dBc/20MHz
		Upper	-30.13	-29.69	-28.9	
	40MHz	Lower	-49.29	-49.17	-49.43	-40dBc/40MHz
		Upper	-46.58	-46.33	-43.48	
802.11ac(VHT20)	20MHz	Lower	-33.68	-32.95	-32.63	-25dBc/20MHz
		Upper	-33.87	-33.17	-31.8	
	40MHz	Lower	-50.09	-49.92	-50.06	-40dBc/40MHz
		Upper	-50.7	-50.01	-48.69	
802.11ac(VHT40)	40MHz	Lower	-31.72	/	-30.93	-25dBc/40MHz
		Upper	-30.75	/	-29.26	
	80MHz	Lower	-46.21	/	-46.92	-40dBc/80MHz
		Upper	-46	/	-44.92	
802.11ac(VHT80)	80MHz	Lower	/	-31.82	/	-25dBc/80MHz
		Upper	/	-30.4	/	
	160MHz	Lower	/	-40.54	/	-25dBc/80MHz
		Upper	/	-41.34	/	
802.11n(HT20)	20MHz	Lower	-35.19	-34.82	-36.7	-25dBc/20MHz
		Upper	-35.37	-35.27	-35.04	
	40MHz	Lower	-50.39	-50.32	-50.56	-40dBc/40MHz
		Upper	-50.93	-50.36	-49.01	
802.11n(HT40)	40MHz	Lower	-32.26	/	-32.78	-25dBc/40MHz
		Upper	-32.39	/	-31.59	
	80MHz	Lower	-46.73	/	-46.72	-40dBc/80MHz
		Upper	-46.8	/	-45.64	
Result	Pass					

W52 ANT2:

Normal Voltage						
Mode	detuning (MHz)		E.I.R.P (dBm/MHz)			Limit (dBm/MHz)
			LCH	MCH	HCH	
802.11a	20MHz	Lower	-33.4	-33.02	-32.88	-25dBc/20MHz
		Upper	-32.81	-32.33	-30.88	
	40MHz	Lower	-49.57	-49.43	-50.35	-40dBc/40MHz
		Upper	-48	-47.62	-44.21	
802.11ac(VHT20)	20MHz	Lower	-33.39	-32.06	-32.57	-25dBc/20MHz
		Upper	-33.59	-32.3	-30.91	
	40MHz	Lower	-50.07	-49.86	-49.62	-40dBc/40MHz
		Upper	-50.56	-49.86	-47.77	
802.11ac(VHT40)	40MHz	Lower	-38.31	/	-37.42	-25dBc/40MHz
		Upper	-38.3	/	-36.11	
	80MHz	Lower	-45.84	/	-45.9	-40dBc/80MHz
		Upper	-45.9	/	-46.04	
802.11ac(VHT80)	80MHz	Lower	/	-34.73	/	-25dBc/80MHz
		Upper	/	-34.54	/	
	160MHz	Lower	/	-41.71	/	-25dBc/80MHz
		Upper	/	-41.48	/	
802.11n(HT20)	20MHz	Lower	-33.99	-33.89	-42.48	-25dBc/20MHz
		Upper	-34.33	-33.8	-41.58	
	40MHz	Lower	-50.15	-49.87	-48.42	-40dBc/40MHz
		Upper	-50.58	-49.9	-48.31	
802.11n(HT40)	40MHz	Lower	-41.26	/	-39.17	-25dBc/40MHz
		Upper	-41.34	/	-38.28	
	80MHz	Lower	-45.96	/	-45.99	-40dBc/80MHz
		Upper	-46.02	/	-46.19	
Result	Pass					

W52 MIMO:

Normal Voltage						
Mode	detuning (MHz)		E.I.R.P (dBm/MHz)			Limit (dBm/MHz)
			LCH	MCH	HCH	
802.11a	20MHz	Lower	/	/	/	-25dBc/20MHz
		Upper	/	/	/	
	40MHz	Lower	/	/	/	-40dBc/40MHz
		Upper	/	/	/	
802.11ac(VHT20)	20MHz	Lower	-27.23	-27.36	-26.96	-25dBc/20MHz
		Upper	-25.32	-25.16	-25.48	
	40MHz	Lower	-45.04	-45.88	-47.46	-40dBc/40MHz
		Upper	-43.6	-43.97	-45.68	
802.11ac(VHT40)	40MHz	Lower	-30.61	/	-30.14	-25dBc/40MHz
		Upper	-25.21	/	-25.67	
	80MHz	Lower	-44.38	/	-45.34	-40dBc/80MHz
		Upper	-42.66	/	-43.96	
802.11ac(VHT80)	80MHz	Lower	/	-36.18	/	-25dBc/80MHz
		Upper	/	-26.88	/	
	160MHz	Lower	/	-43.49	/	-25dBc/80MHz
		Upper	/	-42.3	/	
802.11n(HT20)	20MHz	Lower	-28.12	-28.85	-27.45	-25dBc/20MHz
		Upper	-25.46	-25.82	-25.17	
	40MHz	Lower	-45.45	-46.3	-47.3	-40dBc/40MHz
		Upper	-43.64	-44.64	-45.52	
802.11n(HT40)	40MHz	Lower	-31.6	/	-30.49	-25dBc/40MHz
		Upper	-25.72	/	-25.85	
	80MHz	Lower	-45.59	/	-46.42	-40dBc/80MHz
		Upper	-43.8	/	-44.98	
Result	Pass					

ANT1:

Channel(MHz)	W52:802.11a
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT20)	
5180		
5200		
5240		

Channel(MHz)	W52:802.11ac(VHT40)
5190	
5230	
Channel(MHz)	W52:802.11ac(VHT80)
5210	

Channel(MHz)	W52:802.11n(HT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11n(HT40)	
5190		
5230		

ANT2:

Channel(MHz)	W52:802.11a
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT20)		
5180			
5200			
5240			

Channel(MHz)	W52:802.11ac(VHT40)
5190	
5230	
Channel(MHz)	W52:802.11ac(VHT80)
5210	

Channel(MHz)	W52:802.11n(HT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11n(HT40)	
5190		
5230		

MIMO:

Channel(MHz)	W52:802.11ac(VHT20)	
5180		
5200		
5240		

Channel(MHz)	W52:802.11ac(VHT40)
5190	
5230	
Channel(MHz)	W52:802.11ac(VHT80)
5210	

Channel(MHz)	W52:802.11n(HT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11n(HT40)
5190	
5230	

9.Antenna Power and Tolerance

9.1 LIMIT

(1)10mW/MHz(OFDM, DSSS:20MHz system),
(2)5mW/MHz(OFDM:40MHz system),
(3)2.5mW/MHz(OFDM:80MHz system),
(4)1.25mW/MHz(OFDM:160MHz system),
(5)10mW/MHz(except above methods),
Tolerance: W52/W53: -80%~+20%,W56:-50%~+50%.

9.2 TEST PROCEDURE

A spectrum analyzer or similar device shall be used to observe a sample of the modulated transmitter's radio frequency power output.
(a) A sample detector function must be used.
(b) A measurement instrument with an integrated 1MHz power bandwidth function may be used to automate the test process.
(c) Connect the EUT to the RF input of the spectrum analyzer via a 50ohm attenuator.
(d) Set the RBW = 1MHz, VBW = 1MHz, center of frequency = operating frequency, Sweep = Auto.
(e) 'Maximum Hold' mode may be used to accumulate the measurement result over several scans provided emssion is repetitive in nature.
(f) Repeat above procedures until all frequency measured was complete.

9.3 Test Setup Block Diagram



9.4 TEST RESULT

W52

Mode	Channel (MHz)	Average burst power(dBm)	Antenna power (mW/MHz)	E.I.R.P (mW/MHz)	Limit (mW/MHz)	Rated output power (mW/MHz)	Tolerance (%)	Limit
802.11a ANT 1	LCH	5.025	3.181	7.320	10	8	-60.243	-80% ~ +20%
	MCH	4.973	3.143	7.233	10	8	-60.717	
	HCH	5.226	3.331	7.667	10	8	-58.360	
802.11a ANT 2	LCH	4.868	3.068	7.060	10	8	-61.655	
	MCH	5.186	3.301	7.596	10	8	-58.742	
	HCH	5.093	3.231	7.435	10	8	-59.616	

Mode	Channel (MHz)	Average burst power (dBm) ANT 1	Average burst power (dBm) ANT 2	Total Antenna Power (mW/MHz)	Rated power density (mW/MHz)	Antenna Gain (dBi)	EIRP (mW/MHz)	EIRP Limit (mW/MHz)	Tolerance (%)	Limit
802.11n (HT20)	LCH	2.728	3.683	4.209	5	3.62	9.687	10	-15.816	-80% ~ +20 %
	MCH	3.526	2.848	4.179	5	3.62	9.617	10	-16.424	
	HCH	2.946	3.739	4.336	5	3.62	9.979	10	-13.280	
802.11ac (VHT20)	LCH	3.744	2.731	4.244	5	3.62	9.766	10	-15.129	
	MCH	2.482	3.906	4.229	5	3.62	9.733	10	-15.419	
	HCH	3.826	2.856	4.343	5	3.62	9.996	10	-13.131	
802.11n (HT40)	LCH	-0.289	-0.311	1.867	2	3.62	4.296	5	-6.674	
	HCH	-0.602	-0.56	1.750	2	3.62	4.027	5	-12.521	
802.11ac (VHT40)	LCH	-0.128	-0.351	1.893	2	3.62	4.357	5	-5.334	
	HCH	-0.176	-0.432	1.866	2	3.62	4.294	5	-6.720	
802.11ac (VHT80)	MCH	-4.077	-4.323	0.761	1	3.62	1.751	2.5	-23.932	

Note: P= Average burst power, G= Antenna Gain=3.62dBi
EIRP = Conducted Power + Antenna Gain

10. Unwanted Emissions Strength

10.1 LIMIT

W52

20MHz system	
OBW : 18MHz or less	OBW : 18 - 20 MHz
5,142 MHz or less : 2.5 μW/MHz	5,142 MHz or less : 2.5 μW/MHz
5,142 - 5,150 MHz : 15 μW/MHz	5,142 - 5,150 MHz : 15 μW/MHz
	5,250 - 5,250.2 MHz : $10^{1-(8/2)(f-9.75)}$ mW/MHz
5,250 - 5,251 MHz : $10^{1-(f-9)}$ mW/MHz	5,250.2 - 5,251 MHz : $10^{1-(f-9)}$ mW/MHz
5,251 - 5,260 MHz : $10^{-1-(8/90)(f-11)}$ mW/MHz	5,251 - 5,260 MHz : $10^{-1-(8/90)(f-11)}$ mW/MHz
5,260 - 5,266.7 MHz : $10^{-1.8-(6/50)(f-20)}$ mW/MHz	5,260 - 5,266.7 MHz : $10^{-1.8-(6/50)(f-20)}$ mW/MHz
5,266.7 MHz or more : 2.5 μW/MHz	5,266.7 MHz or more : 2.5 μW/MHz
f = MHz, Difference from 5240 (MHz)	f = MHz, Difference from 5240 (MHz)

40MHz system	80MHz system
5,141.6 MHz or less : 2.5 μW/MHz	5,123.2 MHz or less : 2.5 μW/MHz
5,141.6 - 5,150 MHz : 15 μW/MHz	5,123.2 - 5,150 MHz : 15 μW/MHz
5,250 - 5,251 MHz : $10^{-(f-20)+log(1/2)}$ mW/MHz	5,250 - 5,251 MHz : $10^{-(f-40)+log(1/4)}$ mW/MHz
5,251 - 5,270 MHz : $10^{-(8/190)(f-21)-1+\log(1/2)}$ mW/MHz	5,251 - 5,290 MHz : $10^{-(8/290)(f-41)-1+\log(1/4)}$ mW/MHz
5,270 - 5,278.4 MHz : $10^{-(8/50)(f-40)-1.8+\log(1/2)}$ mW/MHz	5,290 - 5,296.7 MHz : $10^{-(8/100)(f-80)-1.8+\log(1/4)}$ mW/MHz
5,278.4 MHz or more : 2.5 μW/MHz	5,296.7 MHz or more : 2.5 μW/MHz
f = MHz, Difference from 5230 (MHz)	f = MHz, Difference from 5210 (MHz)

10.2 TEST PROCEDURE

(1) A spectrumIn case of conducted measurements, the radio device shall be connected to the measuring equipment via a suitable attenuator.
(2) The measurement equipment shall be set for peak hold mode of operation.
(3) the transmitter shall be operated at the highest output power, or, in the case of equipment able to operate at more than one power level, at the lowest and highest output powers;
(4) The resolution bandwidth shall be set to 100kHz from 10MHz to 1GHz, the resolution bandwidth shall be set to 1MHz above 1GHz , and the sweep time shall be set to auto mode, to ensure all major modulation products are captured.
(5) When the searched result is less than the specified limit, the maximum one shall be recorded, when the result is more than the specified limit, all measured values shall be recorded.
(5) This measurement shall be repeated with the transmitter in standby mode where applicable.
(6) Repeat above procedures until all frequency measured was complete.

10.3 TEST SETUP Block Diagram



10.4 TEST RESULT

W52 ANT 1

Test voltage	Test freq.	Test freq. range	Mkr(MHz)	Test result(dBm)	Limit Start(dBm)	Limit Stop (dBm)	Result
Normal Voltage	5180MHz	30MHz–5142MHz	5142	-37.24	-26	-26	PASS
		5142MHz-5150MHz	5148.48	-23.59	-18	-18	PASS
		5250MHz-5251MHz	5250.34	-40.85	0	-10	PASS
		5251MHz-5260MHz	5257.17	-36.38	-10	-18	PASS
		5260MHz-5266.7MHz	5261.43	-40.02	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.86	-26	-26	PASS
	5200MHz	30MHz–5142MHz	5142	-44.28	-26	-26	PASS
		5142MHz-5150MHz	5149.65	-33.9	-18	-18	PASS
		5250MHz-5251MHz	5250.21	-34.25	0	-10	PASS
		5251MHz-5260MHz	5255.26	-33.47	-10	-18	PASS
		5260MHz-5266.7MHz	5262.52	-33.52	-18	-26	PASS
		5266.7MHz-26000MHz	24652.34	-34.54	-26	-26	PASS
	5240MHz	30MHz–5142MHz	2626.9	-44.85	-26	-26	PASS
		5142MHz-5150MHz	5144.13	-42.19	-18	-18	PASS
		5250MHz-5251MHz	5250.01	-21.03	0	-10	PASS
		5251MHz-5260MHz	5251.59	-25.83	-10	-18	PASS
		5260MHz-5266.7MHz	5260.86	-29.72	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.32	-26	-26	PASS

802.11ac

Test voltage	Test freq.	Test freq. range	Mkr(MHz)	Test result	Limit Start(dBm)	Limit Stop (dBm)	Result
Normal Voltage	5180MHz	30MHz–5142MHz	2744.47	-45.37	-26	-26	PASS
		5142MHz-5150MHz	5148.52	-37.3	-18	-18	PASS
		5250MHz-5251MHz	5250.24	-42.63	0	-10	PASS
		5251MHz-5260MHz	5254.38	-42.59	-10	-18	PASS
		5260MHz-5266.7MHz	5261.15	-42.83	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.62	-26	-26	PASS
	5200MHz	30MHz–5142MHz	2637.12	-44.79	-26	-26	PASS
		5142MHz-5150MHz	5146.22	-41.25	-18	-18	PASS
		5250MHz-5251MHz	5250.56	-42.69	0	-10	PASS

		5251MHz-5260MHz	5258.84	-42.51	-10	-18	PASS
		5260MHz-5266.7MHz	5261.29	-42.17	-18	-26	PASS
		5266.7MHz-26000MHz	24673.07	-34.32	-26	-26	PASS
	5240MHz	30MHz-5142MHz	3271.01	-44.91	-26	-26	PASS
		5142MHz-5150MHz	5143.54	-42.19	-18	-18	PASS
		5250MHz-5251MHz	5250	-12.34	0	-10	PASS
		5251MHz-5260MHz	5250.24	-13.69	-10	-18	PASS
		5260MHz-5266.7MHz	5251.47	-14.4	-18	-26	PASS
		5266.7MHz-26000MHz	5261.39	-24.6	-26	-26	PASS
Normal Voltage	5190MHz	30MHz-5141.6MHz	5266.7	-34.47	-26	-26	PASS
		5141.6MHz-5150MHz	5141.6	-36.22	-18	-18	PASS
		5250MHz-5251MHz	5148.48	-26.61	-3	-13	PASS
		5251MHz-5270MHz	5250.51	-35.27	-13	-21	PASS
		5270MHz-5278.4MHz	5253.11	-35.16	-21	-26	PASS
		5278.4MHz-26000MHz	5270.7	-39.67	-26	-26	PASS
	5230MHz	30MHz-5141.6MHz	24632.37	-34.32	-26	-26	PASS
		5141.6MHz-5150MHz	3163.41	-45.35	-18	-18	PASS
		5250MHz-5251MHz	5141.99	-41.56	-3	-13	PASS
		5251MHz-5270MHz	5250.04	-23.63	-13	-21	PASS
		5270MHz-5278.4MHz	5251.95	-26.27	-21	-26	PASS
		5278.4MHz-26000MHz	5270.38	-29.36	-26	-26	PASS
Normal Voltage	5210MHz	30MHz-5123.2MHz	24653.1	-34.42	-26	-26	PASS
		5123.2MHz-5150MHz	5113.01	-43.27	-18	-18	PASS
		5250MHz-5251MHz	5140.65	-37.56	-6	-16	PASS
		5251MHz-5290MHz	5250.02	-17.75	-16	-24	PASS
		5290MHz-5296.7MHz	5251.31	-21.96	-24	-26	PASS
		5296.7MHz-26000MHz	5290.25	-32.19	-26	-26	PASS

802.11n

Test voltage	Test freq.	Test freq. range	Mkr(MHz)	Test result	Limit Start(dBm)	Limit Stop (dBm)	Result
Normal Voltage	5180MHz	30MHz-5142MHz	3260.78	-44.94	-26	-26	PASS
		5142MHz-5150MHz	5148.73	-42.96	-18	-18	PASS
		5250MHz-5251MHz	5250.01	-12.46	0	-10	PASS
		5251MHz-5260MHz	5251.1	-15.91	-10	-18	PASS
		5260MHz-5266.7MHz	5260.03	-22.49	-18	-26	PASS
		5266.7MHz-26000MHz	5266.7	-32.96	-26	-26	PASS
	5200MHz	30MHz-5142MHz	3276.12	-45.02	-26	-26	PASS
		5142MHz-5150MHz	5147.67	-41.23	-18	-18	PASS
		5250MHz-5251MHz	5250.03	-42.21	0	-10	PASS
		5251MHz-5260MHz	5252.84	-42.1	-10	-18	PASS
		5260MHz-5266.7MHz	5264.96	-42.54	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.31	-26	-26	PASS
	5240MHz	30MHz-5142MHz	3306.79	-44.87	-26	-26	PASS
		5142MHz-5150MHz	5147.82	-42.23	-18	-18	PASS
		5250MHz-5251MHz	5250	-12.25	0	-10	PASS
		5251MHz-5260MHz	5251.53	-20.05	-10	-18	PASS
		5260MHz-5266.7MHz	5260.12	-24.06	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.47	-26	-26	PASS
Normal Voltage	5190MHz	30MHz-5141.6MHz	5141.6	-38.67	-26	-26	PASS
		5141.6MHz-5150MHz	5147.76	-26.65	-18	-18	PASS
		5250MHz-5251MHz	5250.33	-35.17	-3	-13	PASS
		5251MHz-5270MHz	5253.87	-36.19	-13	-21	PASS
		5270MHz-5278.4MHz	5271.8	-40.87	-21	-26	PASS
		5278.4MHz-26000MHz	24673.82	-34.33	-26	-26	PASS
	5230MHz	30MHz-5141.6MHz	2667.59	-45.24	-26	-26	PASS
		5141.6MHz-5150MHz	5148.62	-40.01	-18	-18	PASS
		5250MHz-5251MHz	5250.01	-20.35	-3	-13	PASS
		5251MHz-5270MHz	5252.12	-20.12	-13	-21	PASS
		5270MHz-5278.4MHz	5272.15	-23.23	-21	-26	PASS
		5278.4MHz-26000MHz	24632.37	-34.36	-26	-26	PASS

W52 ANT 2

Test voltage	Test freq.	Test freq. range	Mkr(MHz)	Test result(dBm)	Limit Start(dBm)	Limit Stop (dBm)	Result
Normal Voltage	5180MHz	30MHz–5142MHz	3056.3	-45.08	-26	-26	PASS
		5142MHz-5150MHz	5149.62	-34.6	-18	-18	PASS
		5250MHz-5251MHz	5250.02	-42.67	0	-10	PASS
		5251MHz-5260MHz	5258.13	-42.33	-10	-18	PASS
		5260MHz-5266.7MHz	5260.29	-41.05	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.73	-26	-26	PASS
	5200MHz	30MHz–5142MHz	3122.76	-44.96	-26	-26	PASS
		5142MHz-5150MHz	5148.95	-42.25	-18	-18	PASS
		5250MHz-5251MHz	5250.36	-39.37	0	-10	PASS
		5251MHz-5260MHz	5252.76	-40.23	-10	-18	PASS
		5260MHz-5266.7MHz	5262.2	-41.99	-18	-26	PASS
		5266.7MHz-26000MHz	24652.34	-34	-26	-26	PASS
	5240MHz	30MHz–5142MHz	4942.63	-44.51	-26	-26	PASS
		5142MHz-5150MHz	5149.7	-41.04	-18	-18	PASS
		5250MHz-5251MHz	5250.04	-23.16	0	-10	PASS
		5251MHz-5260MHz	5251.34	-31.1	-10	-18	PASS
		5260MHz-5266.7MHz	5260.24	-34.22	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.32	-26	-26	PASS

802.11ac

Test voltage	Test freq.	Test freq. range	Mkr(MHz)	Test result	Limit Start(dBm)	Limit Stop (dBm)	Result
Normal Voltage	5180MHz	30MHz–5142MHz	5142	-45.33	-26	-26	PASS
		5142MHz-5150MHz	5149.15	-36.58	-18	-18	PASS
		5250MHz-5251MHz	5250.5	-42.4	0	-10	PASS
		5251MHz-5260MHz	5254.38	-43.16	-10	-18	PASS
		5260MHz-5266.7MHz	5261.75	-42.41	-18	-26	PASS
		5266.7MHz-26000MHz	24631.6	-34.79	-26	-26	PASS
	5200MHz	30MHz–5142MHz	5111.33	-44.56	-26	-26	PASS
		5142MHz-5150MHz	5146.71	-41.41	-18	-18	PASS
		5250MHz-5251MHz	5250.96	-42.48	0	-10	PASS
		5251MHz-5260MHz	5254.7	-42.15	-10	-18	PASS
		5260MHz-5266.7MHz	5265.86	-42.14	-18	-26	PASS

		5266.7MHz-26000MHz	24673.07	-34.28	-26	-26	PASS
	5240MHz	30MHz-5142MHz	2621.78	-45.39	-26	-26	PASS
		5142MHz-5150MHz	5148.65	-42.47	-18	-18	PASS
		5250MHz-5251MHz	5250	-12.05	0	-10	PASS
		5251MHz-5260MHz	5251.44	-13.68	-10	-18	PASS
		5260MHz-5266.7MHz	5260.09	-22.39	-18	-26	PASS
		5266.7MHz-26000MHz	5266.7	-33.73	-26	-26	PASS
Normal Voltage	5190MHz	30MHz-5141.6MHz	5141.6	-43.26	-26	-26	PASS
		5141.6MHz-5150MHz	5149.94	-35.01	-18	-18	PASS
		5250MHz-5251MHz	5250.06	-39.94	-3	-13	PASS
		5251MHz-5270MHz	5252.77	-41.49	-13	-21	PASS
		5270MHz-5278.4MHz	5276.64	-42.89	-21	-26	PASS
		5278.4MHz-26000MHz	24673.82	-34.36	-26	-26	PASS
	5230MHz	30MHz-5141.6MHz	2590.91	-44.92	-26	-26	PASS
		5141.6MHz-5150MHz	5147.14	-42.25	-18	-18	PASS
		5250MHz-5251MHz	5250.02	-25.28	-3	-13	PASS
		5251MHz-5270MHz	5257.73	-28.7	-13	-21	PASS
		5270MHz-5278.4MHz	5270.24	-30.23	-21	-26	PASS
		5278.4MHz-26000MHz	24632.37	-34.7	-26	-26	PASS
Normal Voltage	5210MHz	30MHz-5123.2MHz	3264.18	-44.9	-26	-26	PASS
		5123.2MHz-5150MHz	5144.56	-41.3	-18	-18	PASS
		5250MHz-5251MHz	5250.05	-21.7	-6	-16	PASS
		5251MHz-5290MHz	5251.08	-25.87	-16	-24	PASS
		5290MHz-5296.7MHz	5294.84	-41.09	-24	-26	PASS
		5296.7MHz-26000MHz	24654.29	-34.3	-26	-26	PASS

802.11n

Test voltage	Test freq.	Test freq. range	Mkr(MHz)	Test result	Limit Start(dBm)	Limit Stop (dBm)	Result
Normal Voltage	5180MHz	30MHz-5142MHz	5142	-44.47	-26	-26	PASS
		5142MHz-5150MHz	5149.02	-35.96	-18	-18	PASS
		5250MHz-5251MHz	5250.07	-42.68	0	-10	PASS
		5251MHz-5260MHz	5255.44	-43.04	-10	-18	PASS
		5260MHz-5266.7MHz	5264.52	-41.97	-18	-26	PASS
		5266.7MHz-26000MHz	24652.34	-34.83	-26	-26	PASS
	5200MHz	30MHz-5142MHz	5142	-44.92	-26	-26	PASS
		5142MHz-5150MHz	5147.46	-39.28	-18	-18	PASS
		5250MHz-5251MHz	5250.14	-42.37	0	-10	PASS
		5251MHz-5260MHz	5252.16	-42.11	-10	-18	PASS
		5260MHz-5266.7MHz	5260.07	-42.08	-18	-26	PASS
		5266.7MHz-26000MHz	24652.34	-34.45	-26	-26	PASS
	5240MHz	30MHz-5142MHz	5116.44	-44.95	-26	-26	PASS
		5142MHz-5150MHz	5145.9	-42.21	-18	-18	PASS
		5250MHz-5251MHz	5250	-15.95	0	-10	PASS
		5251MHz-5260MHz	5250.2	-18.92	-10	-18	PASS
		5260MHz-5266.7MHz	5251.09	-29.92	-18	-26	PASS
		5266.7MHz-26000MHz	5260.22	-36.25	-26	-26	PASS
Normal Voltage	5190MHz	30MHz-5141.6MHz	24652.34	-34.58	-26	-26	PASS
		5141.6MHz-5150MHz	5141.6	-44.52	-18	-18	PASS
		5250MHz-5251MHz	5147.54	-35	-3	-13	PASS
		5251MHz-5270MHz	5250.64	-41.74	-13	-21	PASS
		5270MHz-5278.4MHz	5263.92	-42.51	-21	-26	PASS
		5278.4MHz-26000MHz	5277.01	-42.1	-26	-26	PASS
	5230MHz	30MHz-5141.6MHz	24653.1	-34.6	-26	-26	PASS
		5141.6MHz-5150MHz	3025.4	-44.88	-18	-18	PASS
		5250MHz-5251MHz	5142.66	-41.09	-3	-13	PASS
		5251MHz-5270MHz	5250.03	-23.54	-13	-21	PASS
		5270MHz-5278.4MHz	5251.74	-30.29	-21	-26	PASS
		5278.4MHz-26000MHz	5273.34	-34.06	-26	-26	PASS

ANT 1

Channel (MHz)	W52:802.11a	
5180		
	30MHz-5142MHz	5142MHz-5150MHz
		
	5250MHz-5251MHz	5251MHz-5260MHz
	5260MHz-5266.7	5266.7MHz-26000MHz

5200	 30MHz-5142MHz	 5142MHz-5150MHz
	 5250MHz-5251MHz	 5251MHz-5260MHz
	 5260MHz-5266.7	 5266.7MHz-26000MHz
5240	 30MHz-5142MHz	 5142MHz-5150MHz

5250MHz-5251MHz



5251MHz-5260MHz



5260MHz-5266.7

5266.7MHz-26000MHz

Channel (MHz)	W52:802.11ac(VHT20)

5180

30MHz-5142MHz



5142MHz-5150MHz



	5250MHz~5251MHz	5251MHz-5260MHz
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
		
	30MHz-5142MHz	5142MHz-5150MHz
5200		
	5250MHz~5251MHz	5251MHz-5260MHz
	5260MHz-5266.7MHz	5266.7MHz-26000MHz

5240	 30MHz-5142MHz	 5142MHz-5150MHz
	 5250MHz~5251MHz	 5251MHz-5260MHz
	 5260MHz-5266.7MHz	 5266.7MHz-26000MHz
Channel (MHz)	W52:802.11ac(VHT40)	
5190	 30MHz-5141.6MHz	 5141.6MHz-5150MHz

	 5150MHz-5251MHz	 5251MHz-5270MHz
	 5270MHz-5278.4MHz	 5278.4MHz-26000MHz
5230	 30MHz-5141.6MHz	 5141.6MHz-5150MHz
	 5150MHz-5251MHz	 5251MHz-5270MHz

	5270MHz-5278.4MHz	5278.4MHz-26000MHz
Channel (MHz)	W52:802.11ac(VHT80)	
5210		
	30MHz-5123.2MHz	5123.2MHz-5150MHz
		
	5250MHz-5251MHz	5251MHz-5290MHz
	5290MHz-5296.7MHz	5296.7MHz-26000MHz

Channel (MHz)	W52:802.11n(HT20)	
5180		
	30MHz-5142MHz	5142MHz-5150MHz
		
	5250MHz~5251MHz	5251MHz-5260MHz
		
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
5200		
	30MHz-5142MHz	5142MHz-5150MHz

	 5250MHz~5251MHz	 5251MHz-5260MHz
	 5260MHz-5266.7MHz	 5266.7MHz-26000MHz
5240	 30MHz-5142MHz	 5142MHz-5150MHz
	 5250MHz~5251MHz	 5251MHz-5260MHz

		
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
Channel (MHz)	W52:802.11n(HT40)	
5190		
	30MHz-5141.6MHz	5141.6MHz-5150MHz
		
	5150MHz-5251MHz	5251MHz-5270MHz
		
	5270MHz-5278.4MHz	5278.4MHz-26000MHz

5230	 30MHz-5141.6MHz	 5141.6MHz-5150MHz
	 5150MHz-5251MHz	 5251MHz-5270MHz
	 5270MHz-5278.4MHz	 5278.4MHz-26000MHz

ANT 2

Channel (MHz)	W52:802.11a	
5180		
	30MHz-5142MHz	5142MHz-5150MHz
		
	5250MHz-5251MHz	5251MHz-5260MHz
		
	5260MHz-5266.7	5266.7MHz-26000MHz

5200	 30MHz-5142MHz	 5142MHz-5150MHz
	 5250MHz-5251MHz	 5251MHz-5260MHz
	 5260MHz-5266.7	 5266.7MHz-26000MHz
5240	 30MHz-5142MHz	 5142MHz-5150MHz



5250MHz-5251MHz



5251MHz-5260MHz

5260MHz-5266.7

5266.7MHz-26000MHz

Channel (MHz)	W52:802.11ac(VHT20)
5180	
	30MHz-5142MHz
	
	5142MHz-5150MHz
	
	

	5250MHz~5251MHz	5251MHz-5260MHz
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
		
	30MHz-5142MHz	5142MHz-5150MHz
5200		
	5250MHz~5251MHz	5251MHz-5260MHz
	5260MHz-5266.7MHz	5266.7MHz-26000MHz

5240		
	30MHz-5142MHz	5142MHz-5150MHz
		
	5250MHz~5251MHz	5251MHz-5260MHz
		
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
Channel (MHz)	W52:802.11ac(VHT40)	
5190		
	30MHz-5141.6MHz	5141.6MHz-5150MHz

		
	5150MHz-5251MHz	5251MHz-5270MHz
		
	5270MHz-5278.4MHz	5278.4MHz-26000MHz
5230		
	30MHz-5141.6MHz	5141.6MHz-5150MHz
		
	5150MHz-5251MHz	5251MHz-5270MHz

		
	5270MHz-5278.4MHz	5278.4MHz-26000MHz
Channel (MHz)	W52:802.11ac(VHT80)	
5210		
	30MHz-5123.2MHz	5123.2MHz-5150MHz
	5250MHz-5251MHz	5251MHz-5290MHz
		
	5290MHz-5296.7MHz	5296.7MHz-26000MHz

Channel (MHz)	W52:802.11n(HT20)	
5180		
	30MHz-5142MHz	5142MHz-5150MHz
		
	5250MHz~5251MHz	5251MHz-5260MHz
		
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
5200		
	30MHz-5142MHz	5142MHz-5150MHz

	 5250MHz~5251MHz	 5251MHz-5260MHz
	 5260MHz-5266.7MHz	 5266.7MHz-26000MHz
5240	 30MHz-5142MHz	 5142MHz-5150MHz
	 5250MHz~5251MHz	 5251MHz-5260MHz

		
	5260MHz-5266.7MHz	5266.7MHz-26000MHz
Channel (MHz)	W52:802.11n(HT40)	
5190		
	30MHz-5141.6MHz	5141.6MHz-5150MHz
		
	5150MHz-5251MHz	5251MHz-5270MHz
		
	5270MHz-5278.4MHz	5278.4MHz-26000MHz

5230	 30MHz-5141.6MHz	 5141.6MHz-5150MHz
	 5150MHz-5251MHz	 5251MHz-5270MHz
	 5270MHz-5278.4MHz	 5278.4MHz-26000MHz

11. Interference Prevention Function

11.1 LIMIT

According to Item 19-3 of Article 2 Paragraph 1. The device shall have the function of automatic transmission or reception of identification code.

11.2 TEST PROCEDURE

1. Set the EUT in the usual operation condition
2. The radio equipment with automatic transmitting function of identification code
A. Transmit the assigned identification code from the radio equipment.
B. Confirm the identification code received by the demodulator.
3. The radio equipment with automatic receiving function of identification code
A. Transmit the assigned identification code from the opposite equipment.
B. Confirm that the usual communication is available.
C. Transmit the identification code distinct from the assigned one from the opposite equipment.
D. Confirm that the radio equipment is stopped or an indication is displayed as the identification code is different.
4. The identification function shall be recorded with “Good” or “No”.

11.3 TEST SETUP LAYOUT



11.4 TEST RESULT

Transmitter:
The transmitting mode (the identification code is more than 48 bits) of EUT is on normal operating, the interference prevention function is good.

Receiver:
The transmitting mode of EUT is on normal operating, the interference prevention function is good.

MAC: 9C:A5:25:BA:87:F7

12.Carrier sense capability

12.1 LIMIT

According to ORRE, art 49.20. The device shall have the carrier sensing function.

12.2 TEST PROCEDURE

1. SG adjust the frequency as same as the EUT transmitted signal, unmodulation, power level 0dBm, Then turn off the RF signal
2. EUT have transmitted the maximum modulation signal and fixed channel
3. Setting of the SA following as RBW/VBW: 1/3MHz SPAN: 50MHz Sweep time: Auto continue PK
4. SG Signal on EUT shall be stop the transmitted, Then turn off the SG, The EUT shall be continuous transmitted signal.

12.3 TEST SETUP BLOCK DIAGRAM

(1) Test performed with the radio equipment to be tested only



(2) Test performed using the external radio equipment



12.4 TEST RESULT

EUT Stop RF transmission signal after carrier inject to EUT. Stop carrier inject, EUT will transmitting normal.)

13.Construction Protection Confirmation

13.1Requirement

The high-frequency section and modulation section of the radio equipment except for the antenna system shall not be capable of being opened easily

13.2 Confirmation method

☐	Sealed with special screws.
☐	Plastic chassis is being welded using ultrasonic wavs.
☐	Chassis is glued using a special adhesive.
☐	Metal covers are spot-fused.
☐	Cover is specially interlocked.
☒	RF and Modulation components are covered with shielding case and this shielding case is soldered.
☐	Shield case is welded ant RF and modulations parts, and ID-ROM is welded using BGA Method.
☐	Shield case is welded ant RF and modulations parts, and ID-ROM is glued at its lead with a special adhesive.
☐	Shield case is welded ant RF and modulations parts, and ID-ROM is glued with a non-transparent laminating agent.
☐	Other: All RF and modulation section packet in one IC, and IC is welded using BGA Method, and RF module is welded on the main board, end-User can't open it easily.

13.3 The photos of construction protection

The red circle is welding point.

The RF chip has a terminal distance to less than 1mm and has 7INN6 terminal.



14 Transmission Burst Length

14.1 LIMIT

8ms or less

14.2 TEST PROCEDURE

Enable EUT under transmission mode and connected it to the spectrum analyzer through antenna output port as the block diagram show in TEST CONFIGURATION
Use Spectrum's ACP measurement function and set spectrum analyzer as fellow:
Spectrum Condition:
(1) Frequency: test frequency
(2) Span: 0Hz, RBW: 1MHz, VBW: 3MHz, Sweep time: Auto, Sweep mode: single
(3) Detector mode: Peak, Indication mode: Max hold

14.3 TEST SETUP BLOCK DIAGRAM



14.4 TEST RESULT

W52 ANT 1

Normal Voltage			
Mode	Channel (MHz)	Read Level(ms)	Limit (ms)
802.11a	LCH	0.173	8ms or less
	MCH	0.173	
	HCH	0.173	
802.11ac(VHT20)	LCH	0.165	
	MCH	0.165	
	HCH	0.165	
802.11ac(VHT40)	LCH	0.101	
	MCH	/	
	HCH	0.101	
802.11ac(VHT80)	LCH	/	
	MCH	0.069	
	HCH	/	
802.11n(HT20)	LCH	0.161	
	MCH	0.161	
	HCH	0.161	
802.11n(HT40)	LCH	0.097	
	MCH	/	
	HCH	0.097	

W52 ANT 2

Normal Voltage			
Mode	Channel (MHz)	Read Level(ms)	Limit (ms)
802.11a	LCH	0.173	8ms or less
	MCH	0.173	
	HCH	0.173	
802.11ac(VHT20)	LCH	0.165	
	MCH	0.165	
	HCH	0.165	
802.11ac(VHT40)	LCH	0.101	
	MCH	/	
	HCH	0.101	
802.11ac(VHT80)	LCH	/	
	MCH	0.069	
	HCH	/	
802.11n(HT20)	LCH	0.160	
	MCH	0.161	
	HCH	0.161	
802.11n(HT40)	LCH	0.097	
	MCH	/	
	HCH	0.097	

Test graph

ANT 1

Channel(MHz)	W52:802.11a
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT40)
5190	
5230	

Channel(MHz)	W52:802.11ac(VHT80)
5210	

Channel(MHz)	W52:802.11n(HT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11n(HT40)	
5190		
5230		

ANT 2

Channel(MHz)	W52:802.11a
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11ac(VHT40)
5190	
5230	

Channel(MHz)	W52:802.11ac(VHT80)
5210	

Channel(MHz)	W52:802.11n(HT20)
5180	
5200	
5240	

Channel(MHz)	W52:802.11n(HT40)	
5190		
5230		

15 Secondary Radiated Emitted Power

15.1 LIMIT

According to Item 19-3 of Article 2 Paragraph 1. The receiver spurious emissions shall not exceeded the following limit:
(1) Below 1GHz : 4nW/100kHz or less
(2) 1GHz or more : 20nW/MHz or more

15.2 TEST PROCEDURE

(1) A spectrumIn case of conducted measurements, the radio device shall be connected to the measuring equipment via a suitable attenuator.
(2) The measurement equipment shall be set for peak hold mode of operation.
(3) the transmitter shall be operated at the receiving mode.
(4) The resolution bandwidth shall be set to 100kHz from 10MHz to 1GHz, the resolution bandwidth shall be set to 1MHz above 1GHz , and the sweep time shall be set to auto mode, to ensure all major modulation products are captured.
(5) When the searched result is less than the specified limit, the maximum one shall be recorded, when the result is more than the specified limit, all measured values shall be recorded.
(5) This measurement shall be repeated with the transmitter in standby mode where applicable.
(6) Repeat above procedures until all frequency measured was complete.

15.3 TEST SETUP BLOCK DIAGRAM



15.4 TEST RESULT
W52 ANT 1

Normal Voltage						
Mode	Channel (MHz)	Frequency(MHz)	Mkr(MHz)	Test result(dBm)	Limit (dBm)	Result
802.11a	LCH	30~1000	946.65	-79.52	-54	Pass
		1000~26000	24675	-55	-47	Pass
	MCH	30~1000	891.36	-79.27	-54	Pass
		1000~26000	24650	-54.89	-47	Pass
	HCH	30~1000	869.05	-79.01	-54	Pass
		1000~26000	24625	-54.97	-47	Pass
802.11ac(VHT20)	LCH	30~1000	921.43	-79.34	-54	Pass
		1000~26000	24675	-55.12	-47	Pass
	MCH	30~1000	761.38	-79.45	-54	Pass
		1000~26000	24675	-54.58	-47	Pass
	HCH	30~1000	882.63	-79.13	-54	Pass
		1000~26000	24650	-54.96	-47	Pass
802.11ac(VHT40)	LCH	30~1000	907.85	-79.15	-54	Pass
		1000~26000	24675	-54.62	-47	Pass
	HCH	30~1000	914.64	-79.43	-54	Pass
		1000~26000	24625	-54.81	-47	Pass
802.11ac(VHT80)	MCH	30~1000	933.07	-79.49	-54	Pass
		1000~26000	24650	-54.68	-47	Pass
802.11n(HT20)	LCH	30~1000	760.41	-79.57	-54	Pass
		1000~26000	24675	-54.75	-47	Pass
	MCH	30~1000	836.07	-79.23	-54	Pass
		1000~26000	24625	-54.78	-47	Pass
	HCH	30~1000	910.76	-79.16	-54	Pass
		1000~26000	24650	-54.9	-47	Pass
802.11n(HT40)	LCH	30~1000	902.03	-79.2	-54	Pass
		1000~26000	24650	-54.96	-47	Pass
	HCH	30~1000	840.92	-79.16	-54	Pass
		1000~26000	24625	-54.97	-47	Pass

W52 ANT 2

Normal Voltage						
Mode	Channel (MHz)	Frequency(MHz)	Mkr(MHz)	Test result(dBm)	Limit (dBm)	Result
802.11a	LCH	30~1000	904.94	-79.62	-54	Pass
		1000~26000	24675	-54.9	-47	Pass
	MCH	30~1000	818.61	-79.33	-54	Pass
		1000~26000	24675	-54.65	-47	Pass
	HCH	30~1000	889.42	-78.49	-54	Pass
		1000~26000	24675	-54.81	-47	Pass
802.11ac(VHT20)	LCH	30~1000	833.16	-79.71	-54	Pass
		1000~26000	24675	-54.8	-47	Pass
	MCH	30~1000	775.93	-79.07	-54	Pass
		1000~26000	24650	-54.81	-47	Pass
	HCH	30~1000	973.81	-79.36	-54	Pass
		1000~26000	24625	-55.01	-47	Pass
802.11ac(VHT40)	LCH	30~1000	798.24	-79.47	-54	Pass
		1000~26000	24625	-55	-47	Pass
	HCH	30~1000	893.3	-79.41	-54	Pass
		1000~26000	24675	-54.88	-47	Pass
802.11ac(VHT80)	MCH	30~1000	792.42	-79.36	-54	Pass
		1000~26000	24675	-54.74	-47	Pass
802.11n(HT20)	LCH	30~1000	822.49	-79.25	-54	Pass
		1000~26000	24675	-55.1	-47	Pass
	MCH	30~1000	835.1	-78.83	-54	Pass
		1000~26000	24650	-54.79	-47	Pass
	HCH	30~1000	941.8	-79.48	-54	Pass
		1000~26000	24650	-54.69	-47	Pass
802.11n(HT40)	LCH	30~1000	809.88	-78.84	-54	Pass
		1000~26000	24675	-54.72	-47	Pass
	HCH	30~1000	797.27	-79.51	-54	Pass
		1000~26000	24625	-54.99	-47	Pass

ANT 1

Channel (MHz)	W52:802.11a	
5180		
	30~1000MHz	1000~26000MHz
5200		
	30~1000MHz	1000~26000MHz
5240		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11ac(VHT20)	
5180		
	30~1000MHz	1000~26000MHz
5200		
	30~1000MHz	1000~26000MHz
5240		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11ac(VHT40)	
5190		
	30~1000MHz	1000~26000MHz
5230		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11ac(VHT80)	
5210		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11 n(HT20)	
5180		
	30~1000MHz	1000~26000MHz
5200		
	30~1000MHz	1000~26000MHz
5240		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11n(HT40)	
5190		
	30~1000MHz	1000~26000MHz
5230		
	30~1000MHz	1000~26000MHz

ANT 2

Channel (MHz)	W52:802.11a	
5180		
	30~1000MHz	1000~26000MHz
5200		
	30~1000MHz	1000~26000MHz
5240		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11ac(VHT20)	
5180		
	30~1000MHz	1000~26000MHz
5200		
	30~1000MHz	1000~26000MHz
5240		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11ac(VHT40)	
5190		
	30~1000MHz	1000~26000MHz
5230		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11ac(VHT80)	
5210		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11 n(HT20)	
5180		
	30~1000MHz	1000~26000MHz
5200		
	30~1000MHz	1000~26000MHz
5240		
	30~1000MHz	1000~26000MHz

Channel (MHz)	W52:802.11n(HT40)	
5190		
	30~1000MHz	1000~26000MHz
5230		
	30~1000MHz	1000~26000MHz

16.DYNAMIC FREQUENCY SELECTION (SLAVE)

16.1 Standard Applicable

Article 2 paragraph 1 item (19-3)

16.2 TEST PROCEDURE

Ordinance Regulating Radio Equipment No. 18, Article 49-20
WAS/RLAN devices operating in slave mode (slave device) can be operated in a network controlled by aWAN/RLAN device operating in master mode (master device).

16.3 Summary of Test Results

Can be operated in a network controlled by a WAN/RLAN device operating in master mode.
Pass

17. EUT TEST PHOTO



※※※※※ **END OF REPORT** ※※※※※