



RADIO TEST REPORT-BLE
Article 2 paragraph 1 item (19)
MIC Notice No.88 Appendix No.43

Product: InkPoster Affresco 13.3”

Trade Mark: PocketBook

Model No.: PB1330P1

Family Model: N/A

Report No.: S25033100706002

Prepared for

Pocketbook International SA.

Crocicchio Cortogna 6, 6900, Lugano, Switzerland

Prepared by

Shenzhen NTEK Testing Technology Co., Ltd.

No. 24 Xinfu East Road, Xiangshan Community, Xinqiao Street, Baoan District,
Shenzhen, Guangdong, People's Republic of China

Tel. 0755-23200050 Website: <http://www.ntek.org.cn>

TEST RESULT CERTIFICATION

Applicant's name Pocketbook International SA.
Address Crocicchio Cortogna 6, 6900, Lugano, Switzerland
Manufacturer's Name Pocketbook International SA.
Address Crocicchio Cortogna 6, 6900, Lugano, Switzerland

Test specification:

Standard Article 2 paragraph 1 item (19)
 MIC Notice No.88 Appendix No.43

Test item description

Product name InkPoster Affresco 13.3"

Trade Mark.....: PocketBook

Model and/or type reference PB1330P1

This device described above has been tested by NTEK, and the test results show that the equipment under test (EUT) is in compliance with MIC requirements. And it is applicable only to the tested sample identified in the report.

This report shall not be reproduced except in full, without the written approval of NTEK, this document may be altered or revised by Shenzhen NTEK Testing Technology Co., Ltd. personnel only, and shall be noted in the revision of the document

Test Sample Number S250331007007

Date (s) of performance of tests Mar. 31, 2025 ~ Aug. 15, 2025

Date of Issue Aug. 15, 2025

Test Result..... **Pass**

Prepared By: Kieron Luo
 Kieron Luo
 (Project Engineer)

Reviewed By: Aaron Cheng
 Aaron Cheng
 (Supervisor)

Approved By: Alex Li
 Alex Li
 (Manager)

※※Revision History※※

REV.	REPORT NO.	Page Revised	ISSUED DATE	Contents
Original	S25033100706002	Rev.01	Aug. 15, 2025	N/A
--	--	--	--	--

Table of Contents

	Page
1 . SUMMARY OF TEST RESULTS	7
1.1 TEST FACILITY	8
1.2 MEASUREMENT UNCERTAINTY	8
2 . GENERAL INFORMATION	9
2.1 GENERAL DESCRIPTION OF EUT	9
2.2 DESCRIPTION OF TEST MODES	10
2.3 TEST CONDITIONS	11
2.4 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED	12
2.5 DESCRIPTION OF SUPPORT UNITS (CONDUCTED MODE)	12
2.6 EQUIPMENTS LIST FOR ALL TEST ITEMS	13
3 . TEST RESULT FOR BT	14
3.1 FREQUENCY ERROR	14
3.2 LIMIT	14
3.3 MEASURING INSTRUMENTS AND SETTING	14
3.4 TEST PROCEDURES	14
3.5 TEST SETUP LAYOUT	14
4 . ANTENNA POWER	16
4.1 LIMIT	16
4.2 TEST SETUP LAYOUT	16
4.3 TEST DEVIATION	16
4.4 TEST RESULT	17
5 . OCCUPIED BANDWIDTH	18
5.1 LIMIT	18
5.2 TEST RESULT	19
6 . UNWANTED EMISSION INTENSITY MEASUREMENT	20
6.1 LIMIT	20
6.2 MEASURING INSTRUMENTS AND SETTING	20
6.3 TEST PROCEDURES	20
6.4 TEST SETUP LAYOUT	21
6.5 TEST DEVIATION	21

Table of Contents

	Page
6.6 TEST RESULT	22
7 . IMITATION OF COLLATERAL EMISSION OF RECEIVER MEASUREMENT	23
7.1 LIMIT	23
7.2 MEASURING INSTRUMENTS AND SETTING	23
7.3 TEST PROCEDURES	23
7.4 TEST RESULT	24
8 . TRANSMISSION ANTENNA GAIN (EIRP ANTENNA POWER) MEASUREMENT	25
8.1 LIMIT	25
8.2 TEST SETUP LAYOUT	25
8.3 TEST DEVIATION	25
8.4 EUT OPERATION DURING TEST	25
8.5 RESULTS OF TRANSMISSION ANTENNA GAIN	25
9 . TRANSMISSION RADIATION ANGLE WIDTH (3DB BEAMWIDTH) MEASUREMENT	26
9.1 LIMIT	26
9.2 MEASURING INSTRUMENTS AND SETTING	26
9.3 TEST PROCEDURES	26
9.4 TEST SETUP LAYOUT	27
9.5 TEST DEVIATION	27
9.6 EUT OPERATION DURING TEST	27
9.7 TEST RESULT OF TRANSMISSION RADIATION ANGLE WIDTH (3DB BEAMWIDTH)	27
10 . RADIO INTERFERENCE PREVENTION CAPABILITY MEASUREMENT	28
10.1 LIMIT	28
10.2 MEASURING ID CODE SOFTWARE	28
10.3 TEST PROCEDURES	28
10.4 TEST SETUP LAYOUT	28
10.5 TEST DEVIATION	28
10.6 EUT OPERATION DURING TEST	28
10.7 TEST RESULT OF RADIO INTERFERENCE PREVENTION CAPABILIT	28
11. CARRIER SENSE CAPABILITY	29

Table of Contents

	Page
12. TEST RESULT	30
12.1 1M	30
12.1.1 FREQUENCY ERROR	30
12.1.2 ANTENNA AND EIRP POWER	32
12.1.3 EIRP POWER	32
12.1.4 OCCUPIED CHANNEL BANDWIDTH	32
12.1.5 SPREADING BANDWIDTH	34
12.1.6 TX SPURIOUS EMISSION	36
12.1.7 RX SPURIOUS EMISSION	44
12.2 2M	48
12.2.1 ANTENNA AND EIRP POWER	48
12.2.2 EIRP POWER	48
12.2.3 OCCUPIED CHANNEL BANDWIDTH	48
12.2.4 SPREADING BANDWIDTH	50
12.2.5 TX SPURIOUS EMISSION	52
12.2.6 RX SPURIOUS EMISSION	60
12.2.7 FREQUENCY ERROR	64

1. SUMMARY OF TEST RESULTS

Test procedures according to the technical standards:

Standard	Method	Description of Test	Result
Article 2 paragraph 1 item (19)	MIC Notice No.88 Appendix No.43.3	Frequency Error	Complies
	MIC Notice No.88 Appendix No.43.4	Occupied Bandwidth (99%) and	Complies
	MIC Notice No.88 Appendix No.43.5	Unwanted Emission Intensity	Complies
	MIC Notice No.88 Appendix No.43.6	Antenna Power Error	Complies
	MIC Notice No.88 Appendix No.43.7	Limitation of Collateral Emission of Receiver	Complies
	MIC Notice No.88 Annex No.43.10	Transmission Antenna Gain (EIRP Antenna Power)	N/A
	MIC Notice No.88 Annex No.43.11	Transmission Radiation Angle Width (3dB Beamwidth)	N/A
	MIC Notice No.88 Annex No.43.12	Radio Interference Prevention Capability	Complies
	MIC Notice No.88 Appendix No.43.13	Spreading Factor	N/A
	MIC Notice No.88 Appendix No.43.8	Carrier Sense Capability ^{Note(3)}	N/A
		Carrier Sense Capability ^{Note (4)}	N/A
	Note 2	Construction Protection Confirmation	Please refer to Japan Radio Protection Declaration

NOTE:

(1)" N/A" denotes test is not applicable in this Test Report

(2) MIC Ordinance Regulating Radio Equipment Section 1.A of Article 49.20

(3) Not apply to this device, since EIRP does not require compensation through Antenna Power.

(4) Apply for 802.11n40 which the Occupied bandwidth within 26MHz-40MHz

1.1 TEST FACILITY

Shenzhen NTEK Testing Technology Co., Ltd

Add. : No. 24 Xinfu East Road, Xiangshan Community, Xinqiao Street, Baoan District, Shenzhen, Guangdong, People's Republic of China

FCC RegistrationNo.:463705; IC RegistrationNo.:9270A-1

CNAS Registration No.:L5516

1.2 MEASUREMENT UNCERTAINTY

The reported uncertainty of measurement $y \pm U$, where expanded uncertainty U is based on a standard uncertainty multiplied by a coverage factor of $k=2$, providing a level of confidence of approximately 95%.

No.	Item	Uncertainty
1	Conducted Emission Test	$\pm 3.2\text{dB}$
2	Radiated Emission Test	$\pm 4.7\text{dB}$
3	RF power,conducted	$\pm 0.16\text{dB}$
4	Spurious emissions,conducted	$\pm 0.21\text{dB}$
5	All emissions,radiated(<1G)	$\pm 4.68\text{dB}$
6	All emissions,radiated(>1G)	$\pm 5.0\text{dB}$
7	Radio Frequency	$\pm 1 \times 10^{-6}$

2. GENERAL INFORMATION

2.1 GENERAL DESCRIPTION OF EUT

Equipment	InkPoster Affresco 13.3”	
Trade Mark	N/A	
Model Name.	PB1330P1	
Family Model	N/A	
Model Difference	N/A	
Product Description	The EUT is InkPoster Affresco 13.3”	
	Operation Frequency:	2402~2480MHz
	Modulation Type:	GFSK
	Number Of Channel	40CH
	Antenna Designation:	FPC Antenna
	AntennaGain (dBi)	1.06 dBi
Channel List	Please refer to the Note 2.	
Adapter	Model: UNVUU3030-200015CB	
	Input: 100-240V~50/60Hz 0.9A Output: 5V---3.0A, 9V---3.0A, 12V---2.5A, 15V---2.0A, 20V---1.5A	
Battery	DC 3.85V, 5000mAh, 19.25Wh	
Rating(s)	DC 3.85V from battery or DC 5V from adapter	
Hardware Version	v. 1.0	
Firmware version:	1330.1.1.xxx	
Software Version	N/A	

Note:

1. For a more detailed features description, please refer to the manufacturer's specifications or the User's Manual.

2.

Channel	Frequency (MHz)
00	2402
01	2404
.....	
.....	
...	...
.....	
38	2478
39	2480

2.2 DESCRIPTION OF TEST MODES

To investigate the maximum EMI emission characteristics generates from EUT, the test system was pre-scanning tested base on the consideration of following EUT operation mode or test configuration mode which possible have effect on EMI emission level. Each of these EUT operation mode(s) or test configuration mode(s) mentioned above was evaluated respectively.

Pretest Mode	Description
Mode 1	CH00
Mode 2	CH19
Mode 3	CH39

For Radiated Emission	
Final Test Mode	Description
Mode 1	CH00
Mode 2	CH19
Mode 3	CH39

2.3 TEST CONDITIONS

The EUT was tuned to a low, middle, and high channel for all tests. For all test case pre/scans were completed in all Modes to determine worst case levels.

Power Supply Voltage Fluctuation Test

Voltage Fluctuation Test	Normal Voltage	High Voltage + 10% of Normal Voltage	Low Voltage - 10% of Normal Voltage
DC Power	DC 3.85V	DC 4.24V	DC 3.47V
RF Chip	DC 3.3V	DC 3.3V	DC 3.3V


Note:

Voltage Variation (%)

= (Output high or Low Voltage - Output Normal Voltage) / Output Normal Voltage * 100

During the input supply voltage to the EUT from the external power source is varied by +/- 10%, + / - 10% of the external power change, will not affect the voltage of the RF, so only operated in normal voltage to test all regulations.

2.4 BLOCK DIAGRAM SHOWING THE CONFIGURATION OF SYSTEM TESTED



2.5 DESCRIPTION OF SUPPORT UNITS (CONDUCTED MODE)

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

Item	Equipment	Model/Type No.	Series No.	Note
E-1	InkPoster Affresco 13.3"	PB1330P1	N/A	EUT

Item	Shielded Type	Ferrite Core	Length	Note

Note:

- (1) The support equipment was authorized by Declaration of Confirmation.
- (2) For detachable type I/O cable should be specified the length in cm in 『Length』 column.
- (3) “YES” is means “shielded” “with core”; “NO” is means “unshielded” “without core”.

2.6EQUIPMENTS LIST FOR ALL TEST ITEMS

Test equipment

Item	Kind of Equipment	Manufacturer	Type No.	Serial No.	Last calibration	Calibrated until	Calibration period	Cal.Infor.
								Method
1	SPECTRUM ANALYZER	AGLIENT	E4440A	MY41000130	2024.04.26 2025.04.25	2025.04.25 2026.04.24	1 YEAR	C
2	SPECTRUM ANALYZER	AGILENT	N9020A	MY49100060	2024.04.25 2025.04.17	2025.04.24 2026.04.16	1 YEAR	C
3	TEST RECEIVER	R&S	ESPI7	101318	2024.04.26 2025.04.17	2025.04.25 2026.04.16	1 YEAR	C
4	50Ω COAXIAL SWITCH	ANRITSU	MP59B	6200983705	2024.04.26	2027.04.25	3 YEAR	C
5	HORN ANTENNA	SCHWARZBECK	BBHA 9120 D	2816	2024.05.18	2027.05.17	3 YEAR	C
6	HORN ANT	SCHWARZBECK	BBHA 9170	9170-181	2024.05.12	2027.05.11	3 YEAR	C
7	PRE-AMPLIFIER	EMC	EMC051835SE	980246	2024.04.25 2025.04.17	2025.04.24 2026.04.16	1 YEAR	C
8	POWER METER	DARE	RPR3006W	15I00041SNO84	2024.04.25 2025.04.17	2025.04.24 2026.04.16	1 YEAR	C
9	TEMPORARY ANTENNA CONNECTOR (NOTE)	NTS	R001	N/A	N/A	N/A	N/A	N/A
10	DC POWER SUPPLY	ZHAOXIN	PS-6005D	20170402923	2023.05.06	2026.05.05	3 YEAR	C
11	ESG VETCTOR SIGNAL GENERAROR	AGILENT	E4438C	MY45093347	2024.04.13 2025.04.17	2025.04.12 2026.04.16	1 YEAR	C
12	PSG ANALOG SIGNAL GENERATOR	AGILENT	E8257D	MY51110112	2024.05.30 2025.04.17	2025.05.29 2026.04.16	1 YEAR	C

Note:

Calibration Method:

(a) Calibration conducted by the National Institute of Information and Communications Technology (NICT) or a designated calibration agency under Article 102-18 paragraph (1)

(b) Correction conducted pursuant to the provisions of Article 135 or Article 144 of the Measurement Act (Act No. 51 of 1992)

(c) Calibration conducted in countries except Japan, which shall be equivalent to the calibration conducted by the NICT or a designated calibration agency under Article 102-18 paragraph

(d) Calibration, etc. conducted by using measuring instruments and other equipment listed in the right column of appended table No. 3, which shall have been given any type of calibration, etc. listed above from (a) to (c).

The calibration corresponds to c described above.

All the equipments for Guangzhou Lisai Calibration.

3. TEST RESULT FOR BT

3.1 FREQUENCY ERROR

3.2 LIMIT

Item	Limits
Frequency Error	$\pm 50\text{ppm}$

3.3 MEASURING INSTRUMENTS AND SETTING

The following table is the setting of Spectrum Analyzer.


Spectrum Parameter	Setting
Attenuation	Auto
RB / VB	10/30KHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

3.4 TEST PROCEDURES

- (1) In the case of unmodulated signal (continuous or continuous burst), measure the frequency directly by a frequency meter.
- (2) In the case of burst waves, the measurement shall be done for enough time in order to obtain the enough measuring accuracy, and the average of the measured values becomes the final value.
- (3) In the case of a test mode with a specific frequency spectrum, measure the frequency of the specific spectrum by a spectrum analyzer.
- (4) In the cases above, if the frequency equivalent to the test frequency is not directly measured in principle, it shall be obtained by necessary calculation.

In the case of modulated signal, if there is no specific spectrum measurable by a spectrum analyzer but a specific dip is observed, it is allowed to measure the frequency with the signal generator (synthesized). That is, observe a signal of the signal generator concurrently (or alternately) with the tested signal using the spectrum analyzer while setting the frequency of the signal generator to the position of the dip on the screen of the spectrum analyzer, and determine the frequency of the signal generator at the time as a measured value.

3.5 TEST SETUP LAYOUT



4.1.5. EUT OPERATION DURING TEST

The EUT was placed on the test table and programmed in un-modulation function.

3.5.1 TEST RESULT

EUT :	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	Kieron Luo
Humidity:	55 % RH	Test Voltage	DC 3.85V
Operation Mode:	unmodulated		

Test data reference attachment

4. ANTENNA POWER


4.1 LIMIT

Modulation	Frequency band	Antenna power	Max EIRP		Antenna power Tolerance
			Non-directional	Beam directional ^{Note1}	
DS	2,400-2,483.5MHz	10mW/MHz	12.14dBm/MHz	22.14dBm/MHz	+20% No lower limit
OFDM1 ^{Note2}	2,400-2,483.5MHz	10mW/MHz	12.14dBm/MHz	22.14dBm/MHz	
OFDM2	2,400-2,483.5MHz	5mW/MHz	9.13dBm/MHz	19.13dBm/MHz	
FH,DS-FH,FH-OFDM	2,400-2,483.5MHz	3mW/MHz	6.91dBm/MHz	16.91dBm/MHz	
	2,427-2,470.75MHz	10mW/MHz	12.14dBm/MHz	22.14dBm/MHz	
Other than those above	2,400-2,483.5MHz	10mW	12.14dBm	22.14dBm	

Note 1: The half-value angle of the beam directivity must be less than $360 \div A$ degrees. A shall be the rate at which the EIRP exceeds the upper limit of the omnidirectional EIRP.

Note 2: OFDM 1 in the modulation method column indicates that the occupied frequency band width is 26 MHz or less, and OFDM 2 indicates the occupied frequency bandwidth exceeding 26 MHz and 40 MHz or less.

4.2 TEST SETUP LAYOUT



4.3 TEST DEVIATION

There is no deviation with the original standard.

4.4 TEST RESULT

EUT :	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	Kieron Luo
Humidity:	55 % RH	Test Voltage	DC 3.85V
Operation Mode:	Transmit-GFSK		

Test data reference attachment

5. OCCUPIED BANDWIDTH

5.1 LIMIT

Item	Limits
Occupied Band Width:	FH 83.5MHz; OFDM1,DS $\leq$ 26MHz; 26MHz $\leq$ OFDM 40MHz system $\leq$ 40MHz.; Others $\leq$ 26MHz

6.1.2. MEASURING INSTRUMENTS AND SETTING


6.1.3. TEST PROCEDURES

Set the spectrum analyzer as follows :

Center frequency:	Test frequency
Frequency sweep width:	About 2~3.5 times of the Nominal bandwidth
Resolution bandwidth:	3% or less of the Nominal bandwidth
Video bandwidth:	Equal to RBW
Sweep time:	Minimum time to ensure the measuring accuracy (In the case of burst wave, one burst shall be included per data point.)
Sweep mode:	Continuous sweep
Detection mode:	Positive peak
Display mode:	Maximum hold

Note: 1. Spread Spectrum Factor = Spread Spectrum Bandwidth / modulation rate of EUT.

6.1.4. TEST SETUP LAYOUT



6.1.5. TEST DEVIATION

There is no deviation with the original standard.

6.1.6. EUT OPERATION DURING TEST

The EUT was programmed to be in continuously transmitting mode.

5.2 TEST RESULT

EUT:	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	Kieron Luo
Humidity:	55 % RH	Test Voltage	DC 3.85V
Operation Mode:	Transmit-GFSK		

Test data reference attachment

6. UNWANTED EMISSION INTENSITY MEASUREMENT

6.1 LIMIT

Item	Limits
TX Spurious Emission	$\leq 2.5 \mu\text{W/ MHz}$ ($30\text{MHz} \leq f \leq 1000\text{MHz}$)
	$\leq 2.5 \mu\text{W/ MHz}$ ($1000\text{MHz} < f \leq 2387\text{MHz}$)
	$\leq 25 \mu\text{W/ MHz}$ ($2387\text{MHz} < f \leq 2400\text{MHz}$)
	$\leq 25 \mu\text{W/ MHz}$ ($2483.5\text{MHz} \leq f < 2496.5\text{MHz}$)
	$\leq 2.5 \mu\text{W/ MHz}$ ($2496.5\text{MHz} \leq f < 12500\text{MHz}$)

6.2 MEASURING INSTRUMENTS AND SETTING


Please refer to section 5 in this report. The following table is the setting of Spectrum Analyzer.

Spectrum Parameter	Setting
Attenuation	Auto
RB / VB	1 MHz
Detector	Average
Trace	Max Hold
Sweep Time	Auto

6.3 TEST PROCEDURES

- EUT have transmitted the maximum modulation signal and fixed channelize.
- Setting of SA is following as: Below 1GHz RB:1MHz / VB:1MHz
Above 1GHz RB:1MHz / VB:1MHz / AT: Auto Ref: Auto / Sweep time: Auto
Sweep Mode: Continuous sweep / Detect mode: Average
Trace mode: Max hold
- Setting of SA is following as 30MHz and stop frequency 1000MHz Then to mark peak reading value + cable loss shall be less than 2.5μW.
- Setting of SA is following as 1000MHz and stop frequency 2387MHz Then to mark peak reading value + cable loss shall be less than 2.5μW.
- SA adjusted to start frequency 2387MHz and stop frequency 2400MHz. Then to mark peak reading value + cable loss shall be less than 25μW.
- SA adjusted to start frequency 2483.5MHz and stop frequency 2496.5MHz Then to mark peak reading value + cable loss shall be less than 25μW
- SA adjusted to start frequency 2496.5MHz and stop frequency 12500MHz Then to mark peak reading value + cable loss shall be less than 2.5μW
- Measure side band spurious as follows: For 2.4GHz band: 2374MHz~2400MHz and 2483.5MHz~2509.5MHz RBW = VBW = 30kHz, Result_Value = Measured_Value + 15.2 [dBm]
- If the Result_Value is over the requirement, take total sum of 1MHz band centered at the spur frequency like ACLP measurement as Result_Value.

6.4 TEST SETUP LAYOUT



6.5 TEST DEVIATION

There is no deviation with the original standard.

6.6 TEST RESULT

EUT :	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	Kieron Luo
Humidity:	55 % RH	Test Voltage	DC 3.85V
Operation Mode:	Transmit-GFSK (CH00, CH19,CH39)		

Test data reference attachment

7. IMITATION OF COLLATERAL EMISSION OF RECEIVER MEASUREMENT

7.1 LIMIT

Item	Limits
RX Spurious Emission:	$\leq 4\text{nW}$ ($f < 1\text{GHz}$)
	$\leq 20\text{nW}$ ($1\text{GHz} \leq f$)

7.2 MEASURING INSTRUMENTS AND SETTING

Please refer to section 5 in this report. The following table is the setting of Spectrum Analyzer.

Spectrum Parameter	Setting
Attenuation	Auto
RB	100 kHz (below 1GHz emissions) 1 MHz (above 1GHz emissions)
VB	100 kHz (below 1GHz emissions) 1 MHz (above 1GHz emissions)
Detector	Average
Trace	Max Hold
Sweep Time	Auto

7.3 TEST PROCEDURES

- EUT have the continuous reception mode and fixed only one channelize.
- Setting of SA is following as RB / VB: 100 kHz (below 1GHz emissions) / 1 MHz (above 1GHz emissions) /
AT: Auto / Ref: Auto / Sweep time: Auto / Sweep Mode: Continuous sweep / Detect mode: Average / Trace mode: Max hold
- SA set RB: 100kHz and VB: 100kHz. Then adjust to start frequency 30MHz and stop frequency 1000MHz. Search to mark peak reading value + cable loss shall be less than 4nW
- SA set RB: 1MHz and VB: 1MHz. Then adjust to start frequency 1000MHz and stop frequency 12500MHz. Search to mark peak reading value + cable loss shall be less than 20nW
- If power level of lower emissions are more than 1/10 of limit (.0.4nW for $f < 1\text{GHz}$, 2nW for $f \geq 1\text{GHz}$), all those are to be indicated in the 2nd and 3rd lines. If others are 1/10 or less more of the limit, no necessary to be indicated.

7.4 TEST RESULT

EUT :	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	Kieron Luo
Humidity:	55 % RH	Test Voltage	DC 3.85V
Operation Mode:	Receiver-GFSK (CH00, CH19,CH39)		

Test data reference attachment

8. TRANSMISSION ANTENNA GAIN (EIRP ANTENNA POWER) MEASUREMENT


8.1 LIMIT

Modulation	Frequency band	Antenna power	Max EIRP	
			Non-directional	Beam directional ^{Note1}
DS	2,400-2,483.5MHz	10mW/MHz	12.14dBm/MHz	22.14dBm/MHz
OFDM1 ^{Note2}	2,400-2,483.5MHz	10mW/MHz	12.14dBm/MHz	22.14dBm/MHz
OFDM2	2,400-2,483.5MHz	5mW/MHz	9.13dBm/MHz	19.13dBm/MHz
FH,DS-FH,FH-OFDM	2,400-2,483.5MHz	3mW/MHz	6.91dBm/MHz	16.91dBm/MHz
	2,427-2,470.75MHz	10mW/MHz	12.14dBm/MHz	22.14dBm/MHz
Other than those above	2,400-2,483.5MHz	10mW	12.14dBm	22.14dBm

Note 1: The half-value angle of the beam directivity must be less than $360 \div A$ degrees. A shall be the rate at which the EIRP exceeds the upper limit of the omnidirectional EIRP.

Note 2: OFDM 1 in the modulation method column indicates that the occupied frequency band width is 26 MHz or less, and OFDM 2 indicates the occupied frequency bandwidth exceeding 26 MHz and 40 MHz or less.

8.2 TEST SETUP LAYOUT



8.3 TEST DEVIATION

There is no deviation with the original standard.

8.4 EUT OPERATION DURING TEST

The EUT was programmed to be in continuously transmitting mode.

8.5 RESULTS OF TRANSMISSION ANTENNA GAIN

EUT :	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	Kieron Luo
Humidity:	55 % RH	Test Voltage	N/A
Operation Mode:	N/A		

Note: This test item will not be applied to the transmission antenna which has a gain of 2.14dBi or less.

Note: EIRP= Peak Output Power+ ANT Gain

9. TRANSMISSION RADIATION ANGLE WIDTH (3DB BEAMWIDTH) MEASUREMENT

9.1 LIMIT

Item	Limits
3dB antenna beam width	$360/A$ (If $A < 1$; then $A = 1$) $A = \{\text{EIRP Power [mW]} / 16.36 \text{ for DS, OFDM}\}$ or $A = \{\text{EIRP Power [mW]} / 4.9 \text{ for FH}\}$
Note: This test item is not applied for radio equipment with equivalent isotropic radiation power lower than 12.14dBm/MHz, but Antenna Power(Conducted) limit is 10 mW/MHz (10 dBm/MHz), So the test item will not be applied to the transmission antenna which has a gain of 2.14dBi or less	


9.2 MEASURING INSTRUMENTS AND SETTING

Spectrum Parameter	Setting
Attenuation	Auto
Span Frequency	0 MHz
RB	1 MHz
VB	1 kHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

9.3 TEST PROCEDURES

- Set EUT and measuring antenna at the same height and roughly facing each other.
- Set spectrum analyzer with condition in section 4.7.2 and tune reference level to observe receiving signal position.
- Rotate directions of the EUT horizontally and vertically to find the maximum receiving power.
- Move the measuring antenna height up and down within $\pm 50\text{cm}$ of EUT height and swing it to find the maximum output of measuring antenna. The output level at the spectrum analyzer is read as "E"
- Calculate permitted radiation angle in horizontal and vertical using EIRP measured in another test method.
- Calculate 3dB antenna beam width by the formula below $360/A$ (If $A < 1$; then $A = 1$).
 $A = \{\text{EIRP Power [mW]} / 16.36 \text{ for DS, OFDM}\}$ or
 $A = \{\text{EIRP Power [mW]} / 4.9 \text{ for FH}\}$

9.4 TEST SETUP LAYOUT



9.5 TEST DEVIATION

There is no deviation with the original standard.

9.6 EUT OPERATION DURING TEST

The EUT was programmed to be in continuously transmitting mode.

9.7 TEST RESULT OF TRANSMISSION RADIATION ANGLE WIDTH (3DB BEAMWIDTH)

EUT :	InkPoster Affresco 13.3"	Model:	PB1330P1
Temperature:	25°C	Tested by:	N/A
Humidity:	55 % RH	Test Voltage	N/A
Operation Mode:	N/A		

Note: This item is not applicable, when EIRP power is lower than the limit of 12.14dBm.

10. RADIO INTERFERENCE PREVENTION CAPABILITY MEASUREMENT

10.1 LIMIT

Item	Limits
Identification code	≥ 48 bits


10.2 MEASURING ID CODE SOFTWARE

Item	Limits
MAC IP List	MAC Scan

10.3 TEST PROCEDURES

- In the case that the EUT has the function of automatically transmitting the identification code: a. Transmit the predetermined identification codes from EUT. b. Check the transmitted identification codes with the demodulator.
- In the case of receiving the identification code: a. Transmit the predetermined identification codes from the counterpart. b. Check if communication is normal. c. Transmit the signals other than predetermined ID codes from the counterpart. d. Check if the EUT stops the transmission, or if it displays that identification codes are different from the predetermined ones.

10.4 TEST SETUP LAYOUT



10.5 TEST DEVIATION

There is no deviation with the original standard.

10.6 EUT OPERATION DURING TEST

The EUT was programmed to be in normal transmitting mode.

10.7 TEST RESULT OF RADIO INTERFERENCE PREVENTION CAPABILITY

	Normal voltage	Low voltage	High voltage
Result	OK	N/A	N/A

Mac address: 17:29:88:d8:20:2d

Result: OK


11. CARRIER SENSE CAPABILITY

Limit

EUT stop RF transmission signal after carrier inject to EUT

Test Procedure

Measurement System Diagram



1. SG adjusted the frequency as same as the EUT transmitted signal and emitted the absence of modulation from SG and power level is $(-22.79 + G - 20 \cdot \log(f) \text{ dBm})$ (G is the antenna gain, f is the test frequency).
2. turn off the RF signal of the SG.
3. EUT have transmitted the maximum modulation signal and fixed channelize.
4. Setting of SA :RBW/VBW=1MHz/1MHz, Span=50MHz, Sweep time=auto, Sweep mode=continuous, Detect mode=positive peak
5. SG RF signal on.
6. EUT shall be stop the transmitted any signal and SG RF signal off, the EUT will be continuous transmitted signal.
7. Result:
not applicable


12. TEST RESULT

12.1 1M


12.1.1 FREQUENCY ERROR

Condition	Mode	Frequency (MHz)	Antenna	Measured Frequency (MHz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	Un-modulation	2402	Ant1	2401.967	-13.74	50	Pass
NVNT	Un-modulation	2440	Ant1	2439.966	-13.93	50	Pass
NVNT	Un-modulation	2480	Ant1	2479.965	-14.11	50	Pass


Freq. Error NVNT BLE 2402MHz Ant1



Freq. Error NVNT BLE 2440MHz Ant1



Freq. Error NVNT BLE 2480MHz Ant1



12.1.2 ANTENNA AND EIRP POWER

Condition	Mode	Frequency (MHz)	Antenna	Antenna Power (mW)	Declared Power (mW)	Tolerance (%)	Upper Limit (%)	Verdict
NVNT	BLE	2402	Ant1	2.32	3	-22.58	20	Pass
NVNT	BLE	2440	Ant1	2.28	3	-23.99	20	Pass
NVNT	BLE	2480	Ant1	2.86	3	-4.53	20	Pass


12.1.3 EIRP POWER

Condition	Mode	Frequency (MHz)	Antenna	Antenna Power (mW)	Gain (dBi)	EIRP Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE	2402	Ant1	2.32	1.06	4.72	12.14	Pass
NVNT	BLE	2440	Ant1	2.28	1.06	4.64	12.14	Pass
NVNT	BLE	2480	Ant1	2.86	1.06	5.63	12.14	Pass


12.1.4 OCCUPIED CHANNEL BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	99% OBW (MHz)
NVNT	BLE	2402	Ant1	1.038
NVNT	BLE	2440	Ant1	1.041
NVNT	BLE	2480	Ant1	1.039


OBW NVNT BLE 2402MHz Ant1



OBW NVNT BLE 2440MHz Ant1




OBW NVNT BLE 2480MHz Ant1




12.1.5 SPREADING BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	90% OBW (MHz)	Verdict
NVNT	BLE	2402	Ant1	0.676	Pass
NVNT	BLE	2440	Ant1	0.677	Pass
NVNT	BLE	2480	Ant1	0.674	Pass


Spreading Bandwidth NVNT BLE 2402MHz Ant1



Spreading Bandwidth NVNT BLE 2440MHz Ant1




Spreading Bandwidth NVNT BLE 2480MHz Ant1




12.1.6 TX SPURIOUS EMISSION

Condition	Mode	Frequency (MHz)	Antenna	Range (MHz)	Emission Frequency (MHz)	Max Value (dBm)	Max Value (uW)	Limit Start(uW)	Limit Stop (uW)	Verdict
NVNT	BLE	2402	Ant1	30-1000	518.88	-61.34	0.0007	2.5	2.5	Pass
NVNT	BLE	2402	Ant1	1000-2387	2366.19	-62.2	0.0006	2.5	2.5	Pass
NVNT	BLE	2402	Ant1	2387-2400	2400	-34.04	0.3945	25	25	Pass
NVNT	BLE	2402	Ant1	2483.5-2496.5	2486.75	-60.09	0.001	25	25	Pass
NVNT	BLE	2402	Ant1	2496.5-13000	12642.88	-63.31	0.0005	2.5	2.5	Pass
NVNT	BLE	2440	Ant1	30-1000	193.93	-61.5	0.0007	2.5	2.5	Pass
NVNT	BLE	2440	Ant1	1000-2387	1997.25	-62.09	0.0006	2.5	2.5	Pass
NVNT	BLE	2440	Ant1	2387-2400	2388.38	-59.43	0.0011	25	25	Pass
NVNT	BLE	2440	Ant1	2483.5-2496.5	2484.21	-59.61	0.0011	25	25	Pass
NVNT	BLE	2440	Ant1	2496.5-13000	12495.83	-63.36	0.0005	2.5	2.5	Pass
NVNT	BLE	2480	Ant1	30-1000	947.62	-60.08	0.001	2.5	2.5	Pass
NVNT	BLE	2480	Ant1	1000-2387	2377.29	-61.96	0.0006	2.5	2.5	Pass
NVNT	BLE	2480	Ant1	2387-2400	2397.71	-59.31	0.0012	25	25	Pass
NVNT	BLE	2480	Ant1	2483.5-2496.5	2483.9	-56.87	0.0021	25	25	Pass
NVNT	BLE	2480	Ant1	2496.5-13000	12611.37	-63.2	0.0005	2.5	2.5	Pass


Tx. Spurious NVNT BLE 2402MHz Ant1 @ 30MHz-1000MHz




Tx. Spurious NVNT BLE 2402MHz Ant1 @ 1000MHz-2387MHz




Tx. Spurious NVNT BLE 2402MHz Ant1 @ 2387MHz-2400MHz




Tx. Spurious NVNT BLE 2402MHz Ant1 @ 2483.5MHz-2496.5MHz




Tx. Spurious NVNT BLE 2402MHz Ant1 @ 2496.5MHz-13000MHz




Tx. Spurious NVNT BLE 2440MHz Ant1 @ 30MHz-1000MHz




Tx. Spurious NVNT BLE 2440MHz Ant1 @ 1000MHz-2387MHz




Tx. Spurious NVNT BLE 2440MHz Ant1 @ 2387MHz-2400MHz




Tx. Spurious NVNT BLE 2440MHz Ant1 @ 2483.5MHz-2496.5MHz




Tx. Spurious NVNT BLE 2440MHz Ant1 @ 2496.5MHz-13000MHz




Tx. Spurious NVNT BLE 2480MHz Ant1 @ 30MHz-1000MHz




Tx. Spurious NVNT BLE 2480MHz Ant1 @ 1000MHz-2387MHz




Tx. Spurious NVNT BLE 2480MHz Ant1 @ 2387MHz-2400MHz



Tx. Spurious NVNT BLE 2480MHz Ant1 @ 2483.5MHz-2496.5MHz




Tx. Spurious NVNT BLE 2480MHz Ant1 @ 2496.5MHz-13000MHz




12.1.7 RX SPURIOUS EMISSION

Condition	Mode	Frequency (MHz)	Antenna	Range (MHz)	Emission Frequency (MHz)	Max Value (dBm)	Max Value (nW)	Limit (nW)	Verdict
NVNT	BLE	2402	Ant1	30-1000	948.59	-93.96	0.0004	4	Pass
NVNT	BLE	2402	Ant1	1000-13000	3460	-84.19	0.0038	20	Pass
NVNT	BLE	2440	Ant1	30-1000	948.59	-95.85	0.0003	4	Pass
NVNT	BLE	2440	Ant1	1000-13000	2428	-75.1	0.0309	20	Pass
NVNT	BLE	2480	Ant1	30-1000	948.59	-95.37	0.0003	4	Pass
NVNT	BLE	2480	Ant1	1000-13000	2428	-77.55	0.0176	20	Pass


Rx. Spurious NVNT BLE 2402MHz Ant1 @ 30MHz-1000MHz




Rx. Spurious NVNT BLE 2402MHz Ant1 @ 1000MHz-13000MHz




Rx. Spurious NVNT BLE 2440MHz Ant1 @ 30MHz-1000MHz




Rx. Spurious NVNT BLE 2440MHz Ant1 @ 1000MHz-13000MHz



Rx. Spurious NVNT BLE 2480MHz Ant1 @ 30MHz-1000MHz



Rx. Spurious NVNT BLE 2480MHz Ant1 @ 1000MHz-13000MHz



12.2 2M

12.2.1 ANTENNA AND EIRP POWER

Condition	Mode	Frequency (MHz)	Antenna	Antenna Power (mW)	Declared Power (mW)	Tolerance (%)	Upper Limit (%)	Verdict
NVNT	BLE 2M	2402	Ant1	2.19	3	-26.91	20	Pass
NVNT	BLE 2M	2440	Ant1	2.27	3	-24.34	20	Pass
NVNT	BLE 2M	2480	Ant1	2.72	3	-9.24	20	Pass


12.2.2 EIRP POWER

Condition	Mode	Frequency (MHz)	Antenna	Antenna Power (mW)	Gain (dBi)	EIRP Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 2M	2402	Ant1	2.19	1.06	4.47	12.14	Pass
NVNT	BLE 2M	2440	Ant1	2.27	1.06	4.62	12.14	Pass
NVNT	BLE 2M	2480	Ant1	2.72	1.06	5.41	12.14	Pass


12.2.3 OCCUPIED CHANNEL BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	99% OBW (MHz)
NVNT	BLE 2M	2402	Ant1	2.07
NVNT	BLE 2M	2440	Ant1	2.069
NVNT	BLE 2M	2480	Ant1	2.093


OBW NVNT BLE 2M 2402MHz Ant1



OBW NVNT BLE 2M 2440MHz Ant1




OBW NVNT BLE 2M 2480MHz Ant1




12.2.4 SPREADING BANDWIDTH

Condition	Mode	Frequency (MHz)	Antenna	90% OBW (MHz)	Limit (MHz)	Verdict
NVNT	BLE 2M	2402	Ant1	1.344	/	/
NVNT	BLE 2M	2440	Ant1	1.342	/	/
NVNT	BLE 2M	2480	Ant1	1.344	/	/


Spreading Bandwidth NVNT BLE 2M 2402MHz Ant1



Spreading Bandwidth NVNT BLE 2M 2440MHz Ant1




Spreading Bandwidth NVNT BLE 2M 2480MHz Ant1




12.2.5 TX SPURIOUS EMISSION

Condition	Mode	Frequency (MHz)	Antenna	Range (MHz)	Emission Frequency (MHz)	Max Value (dBm)	Max Value (uW)	Limit Start(uW)	Limit Stop (uW)	Verdict
NVNT	BLE 2M	2402	Ant1	30-1000	775.93	-60.64	0.0009	2.5	2.5	Pass
NVNT	BLE 2M	2402	Ant1	1000-2387	2373.13	-60.44	0.0009	2.5	2.5	Pass
NVNT	BLE 2M	2402	Ant1	2387-2400	2400	-19.22	11.9674	25	25	Pass
NVNT	BLE 2M	2402	Ant1	2483.5-2496.5	2494.25	-59.66	0.0011	25	25	Pass
NVNT	BLE 2M	2402	Ant1	2496.5-13000	12548.35	-63.06	0.0005	2.5	2.5	Pass
NVNT	BLE 2M	2440	Ant1	30-1000	892.33	-61.06	0.0008	2.5	2.5	Pass
NVNT	BLE 2M	2440	Ant1	1000-2387	2144.28	-62.05	0.0006	2.5	2.5	Pass
NVNT	BLE 2M	2440	Ant1	2387-2400	2391.03	-58.81	0.0013	25	25	Pass
NVNT	BLE 2M	2440	Ant1	2483.5-2496.5	2490.13	-58.73	0.0013	25	25	Pass
NVNT	BLE 2M	2440	Ant1	2496.5-13000	12695.4	-63.32	0.0005	2.5	2.5	Pass
NVNT	BLE 2M	2480	Ant1	30-1000	480.08	-61.8	0.0007	2.5	2.5	Pass
NVNT	BLE 2M	2480	Ant1	1000-2387	2352.32	-61.2	0.0008	2.5	2.5	Pass
NVNT	BLE 2M	2480	Ant1	2387-2400	2398.62	-59.27	0.0012	25	25	Pass
NVNT	BLE 2M	2480	Ant1	2483.5-2496.5	2483.55	-49.73	0.0106	25	25	Pass
NVNT	BLE 2M	2480	Ant1	2496.5-13000	12642.88	-63.18	0.0005	2.5	2.5	Pass


Tx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 30MHz-1000MHz




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 1000MHz-2387MHz




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 2387MHz-2400MHz




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 2483.5MHz-2496.5MHz




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 2496.5MHz-13000MHz




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 30MHz-1000MHz




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 1000MHz-2387MHz




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 2387MHz-2400MHz




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 2483.5MHz-2496.5MHz




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 2496.5MHz-13000MHz




Tx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 30MHz-1000MHz




Tx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 1000MHz-2387MHz




Tx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 2387MHz-2400MHz



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 2483.5MHz-2496.5MHz




Tx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 2496.5MHz-13000MHz




12.2.6 RX SPURIOUS EMISSION

Condition	Mode	Frequency (MHz)	Antenna	Range (MHz)	Emission Frequency (MHz)	Max Value (dBm)	Max Value (nW)	Limit (nW)	Verdict
NVNT	BLE 2M	2402	Ant1	30-1000	948.59	-95.73	0.0003	4	Pass
NVNT	BLE 2M	2402	Ant1	1000-13000	2476	-80.2	0.0095	20	Pass
NVNT	BLE 2M	2440	Ant1	30-1000	948.59	-95.07	0.0003	4	Pass
NVNT	BLE 2M	2440	Ant1	1000-13000	2476	-83.57	0.0044	20	Pass
NVNT	BLE 2M	2480	Ant1	30-1000	948.59	-97.05	0.0002	4	Pass
NVNT	BLE 2M	2480	Ant1	1000-13000	2428	-84.04	0.0039	20	Pass


Rx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 30MHz-1000MHz




Rx. Spurious NVNT BLE 2M 2402MHz Ant1 @ 1000MHz-13000MHz




Rx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 30MHz-1000MHz




Rx. Spurious NVNT BLE 2M 2440MHz Ant1 @ 1000MHz-13000MHz



Rx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 30MHz-1000MHz




Rx. Spurious NVNT BLE 2M 2480MHz Ant1 @ 1000MHz-13000MHz




12.2.7 FREQUENCY ERROR

Condition	Mode	Frequency (MHz)	Measured Frequency (MHz)	Deviation (ppm)	Limit (ppm)	Verdict
NVNT	Un-modulation	2402	2401.969	-12.91	50	Pass
NVNT	Un-modulation	2440	2439.968	-13.11	50	Pass
NVNT	Un-modulation	2480	2479.967	-13.31	50	Pass


Freq. Error NVNT BLE 2402MHz Ant1



Freq. Error NVNT BLE 2440MHz Ant1



Freq. Error NVNT BLE 2480MHz Ant1



REPORT IS FINISHED.