

TEST REPORT

Report No.: BCTC2606859847E

Applicant: SANWA SUPPLY INC.

Product Name: Wireless receiver

Test Model: SANWA RC2E3

Tested Date: 2026-06-25 to 2026-07-07

Issued Date: 2026-07-07



Shenzhen **BCTC** Testing Co., Ltd.




Product Name: Wireless receiver
Trademark: Sanwa Supply
Model/Type Reference: SANWA RC2E3
Prepared For: SANWA SUPPLY INC.
Address: 1-10-1, TAMACHI, KITA-KU, OKAYAMA PREF, 700-0825, JAPAN
Manufacturer: Dongguan Newmen Electronics Technology Co.,Ltd.
Address: No.5, Xifa Road, Lin Village, Tangxia Town, Dongguan City, 523711 Guangdong, China
Prepared By: Shenzhen BCTC Testing Co., Ltd.
Address: 1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Sample Received Date: 2026-06-25
Sample Tested Date: 2026-06-25 to 2026-07-07
Issue Date: 2026-07-07
Report No.: BCTC2606859847E
Test Standards: Article 2 paragraph 1 of item 19
MIC Notice No.88 Appendix No.43
Test Results: PASS
Remark: This is JAPAN RADIO test report.

Prepared by:



Yukin Liang

Reviewed By:



Shanshan Zhang

Approved by:



Zero Zhou

The test report is effective only with both signature and specialized stamp. This result(s) shown in this report refer only to the sample(s) tested. Without written approval of Shenzhen BCTC Testing Co., Ltd, this report can't be reproduced except in full. The tested sample(s) and the sample information are provided by the client.


Table Of Content

Test Report Declaration	Page
1. Version	5
2. Test Summary	6
3. Measurement Uncertainty	7
4. Product Information And Test Setup	8
4.1 Product Information	8
4.2 Block Diagram Parameters Of Test Software Setting	9
4.3 Description Of Support Units (Conducted Mode)	9
4.4 Channel List	9
4.5 Test Mode	9
4.6 Test Conditions	10
4.7 Table Of Parameters Of Test Software Setting	10
5. Test Facility And Test Instrument Used	11
5.1 Test Facility	11
5.2 Test Instrument Used	11
6. RF Shielding Method	12
7. Frequency Error	13
7.1 Block Diagram Of Test Setup	13
7.2 Limit	13
7.3 Measuring Instruments And Setting	13
7.4 Test procedure	13
7.5 Test Result	14
8. Antenna Power	20
8.1 Block Diagram Of Test Setup	20
8.2 Limit	20
8.3 Test procedure	20
8.4 Test Result	21
9. Occupied Bandwidth	22
9.1 Block Diagram Of Test Setup	22
9.2 Limit	22
9.3 Test procedure	22
9.4 Test Result	22
10. Unwanted Emission Intensity Measurement	33
10.1 Block Diagram Of Test Setup	33
10.2 Limit	33
10.3 Measuring Instruments And Setting	33
10.4 Test procedure	33
10.5 Test Result	34
11. Imitation Of Collateral Emission Of Receiver Measurement	59
11.1 Block Diagram Of Test Setup	59
11.2 Limit	59
11.3 Measuring Instruments And Setting	59
11.4 Test procedure	59
11.5 Test Result	60
12. Transmission Antenna Gain (EIRP Antenna Power) Measurement	70
12.1 Block Diagram Of Test Setup	70
12.2 Limit	70

12.3	Measuring Instruments And Setting	71
12.4	Test procedure	71
12.5	Test Result	71
13.	Transmission Radiation Angle Width (3db Beamwidth) Measurement	72
13.1	Block Diagram Of Test Setup	72
13.2	Limit	72
13.3	Measuring Instruments And Setting	72
13.4	Test procedure	72
13.5	Test Result	72
14.	Radio Interference Prevention Capability Measurement	73
14.1	Block Diagram Of Test Setup	73
14.2	Limit	73
14.3	Measuring Instruments And Setting	73
14.4	Test procedure	73
14.5	Test Result	73
15.	EUT Photographs	74
16.	EUT Test Setup Photographs	75


(Note: N/A Means Not Applicable)

TE
TC
OVE
t Sea



1. Version

Report No.	Issue Date	Description	Approved
BCTC2606859847E	2026-07-07	Original	Valid



2. Test Summary


Test procedures according to the technical standards:

Article 2 paragraph 1 of item 19		
Description of Test	Result	Test by
Frequency Error	Complies	Hui he Long
Occupied Bandwidth (99%) and Spread-spectrum Bandwidth (90%)	Complies	Hui he Long
Unwanted Emission Intensity	Complies	Hui he Long
Antenna Power Error	Complies	Hui he Long
Limitation of Collateral Emission of Receiver	Complies	Hui he Long
Transmission Antenna Gain (EIRP Antenna Power)	N/A	/
Transmission Radiation Angle Width (3dB Beamwidth)	N/A	/
Radio Interference Prevention Capability	Complies	Hui he Long
Construction Protection Confirmation	Complies	Hui he Long

NOTE:

(1)" N/A" denotes test is not applicable in this Test Report


CO., LTD.



3. Measurement Uncertainty

The reported uncertainty of measurement $y \pm U$, where expanded uncertainty U is based on a standard uncertainty multiplied by a coverage factor of $k=2$, providing a level of confidence of approximately 95 %.

No.	Item	Uncertainty
1	Conducted Emission Test	$\pm 3.2\text{dB}$
2	Radiated Emission Test	$\pm 4.7\text{dB}$
3	RF power,conducted	$\pm 0.16\text{dB}$
4	Spurious emissions,conducted	$\pm 0.21\text{dB}$
5	All emissions,radiated(<1G)	$\pm 4.68\text{dB}$
6	All emissions,radiated(>1G)	$\pm 5.0\text{dB}$
7	frequency error ppm	$\pm 0.5\text{ppm}$



4. Product Information And Test Setup

4.1 Product Information

Model/Type Reference: SANWA RC2E3

Model Differences: N/A

Hardware Version: V1.0

Software Version: V1.0

Operation Frequency: 2402-2480MHz

Type of Modulation: GFSK1Mbps

Number Of Channel: 40 CH

Antenna installation: PCB antenna

Antenna Gain: -1.66 dBi


Remark:

☒ The antenna gain of the product comes from the antenna report provided by the customer, and the test data is affected by the customer information. The laboratory assumes no responsibility for its authenticity.


☐ The antenna gain of the product is provided by the customer, and the test data is affected by the customer information. The laboratory assumes no responsibility for its authenticity.

Ratings:

DC 5V



4.2 Block Diagram Parameters Of Text Software Setting



4.3 Description Of Support Units (Conducted Mode)

Item	Equipment	Mfr/Brand	Model/Type No.	Series No.	Note
E-1	Wireless receiver	Sanwa Supply	SANWA RC2E3	N/A	EUT

Notes:

1. The support equipment was authorized by Declaration of Confirmation.
2. For detachable type I/O cable should be specified the length in cm in 『Length』 column
3. “YES” is means “shielded” “with core”; “NO” is means “unshielded” “without core”.

4.4 Channel List

Channel List					
Channel	Frequency (MHz)	Channel	Frequency (MHz)	Channel	Frequency (MHz)
01	2402	11	2422	21	2442
02	2404	12	2424	22	2444
03	2406	13	2426	23	2446
~	~	~	~	~	~
09	2418	19	2438	39	2478
10	2420	20	2440	40	2480

4.5 Test Mode

To investigate the maximum EMI emission characteristics generates from EUT, the test system was pre-scanning tested base on the consideration of following EUT operation mode or test configuration mode which possible have effect on EMI emission level. Each of these EUT operation mode(s) or test configuration mode(s) mentioned above was evaluated respectively.

For All Mode	Description	Modulation Type
Mode 1	CH01	GFSK(1Mbps)
Mode 2	CH20	
Mode 3	CH40	
Mode 4	RX	GFSK

4.6 Test Conditions

The EUT module was tested while in a continuous transmitter/receiver mode.

The EUT was tuned to a low, middle, and high channel for all tests. For all test case pre/scans were completed in all Modes to determine worst case levels.

Power Supply Voltage Fluctuation Test

Voltage Fluctuation Test	Normal Voltage	High Voltage +10% of Normal Voltage	Low Voltage -10% of Normal Voltage
Input DC Power	5V	5.5	4.5V
Voltage Variation (%)	0%	+10%	-10%

Note:

Voltage Variation (%)= (Output high or Low Voltage - Output Normal Voltage)/ Output Normal Voltage* 100.

4.7 Table Of Parameters Of Test Software Setting

During testing channel & power controlling software provided by the customer was used to control the operating channel as well as the output power level. The RF output power selection is for the setting of RF output power expected by the customer and is going to be fixed on the firmware of the final end product power parameters

Test software Version	KehwinWirelessConfigToolV2		
Frequency	2402 MHz	2440 MHz	2480 MHz
Parameters	DEF	DEF	DEF

5. Test Facility And Test Instrument Used

5.1 Test Facility

All measurement facilities used to collect the measurement data are located at Shenzhen BCTC Testing Co., Ltd. Address:1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China. The site and apparatus are constructed in conformance with the requirements of ANSI C63.4 and CISPR 16-1-1 other equivalent standards.

5.2 Test Instrument Used

Item	Equipment	Manufacturer	Type No.	Serial No.	Last calibration	Calibrated until
1.	Power Meter	Keysight	E4419	A00065	May 09, 2026	May 08, 2027
2.	Power Sensor	Keysight	E9300A	US39211659	May 09, 2026	May 08, 2027
3.	Signal Analyzer 20Hz-26.5GHz	Agilent	N9020A	MY54230579	Oct. 31, 2025	Oct. 30, 2026
4.	D.C. Power Supply	LongWei	TPR-6405D	\	May 09, 2026	May 08, 2027
5.	Signal Generator	Keysight	N5182B	MY56200519	May 09, 2026	May 08, 2027
6.	Pulse limiter	Schwarzbeck	VTSD 9561-F	01323	May 09, 2026	May 08, 2027
7.	Hygrothermograph	Thermo	HTC-1	\	May 09, 2026	May 08, 2027
8.	Software	MTS	8310E	V3.0.0.0	\	\

Calibration laboratory: CCIC(Shenzhen) Co., Ltd


● Calibration Information (Article 24-2, Paragraph 4 of the Radio Act)	
☐	a) Calibration conducted by the National Institute of Information and Communications Technology (NICT) or a designated calibration agency under Article 102-18-1 of the Radio Act
☐	b) Calibration conducted based on the regulations of Article 135 or 144 of the Measurement Act
☒	c) Calibration conducted in foreign countries, which is equivalent to calibration conducted by the NICT or a designated calibration agency under Article 102-18-1 of the Radio Act
☐	d) Calibration, etc. conducted by using measuring instruments and other facilities listed at the bottom of appended table 3 of the Radio Act, which is to have been calibrated as described in (a) through (c) above

6. RF Shielding Method

Chipset:


The product structure is uses SMD patch process.

As shown in the picture, If the will be open so the product be damage.



7. Frequency Error

7.1 Block Diagram Of Test Setup



7.2 Limit

Item	Limits
Frequency Error	±50ppm

7.3 Measuring Instruments And Setting

The following table is the setting of Spectrum Analyzer.

Spectrum Parameter	Setting
Attenuation	Auto
RB / VB	10KHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto


7.4 Test procedure


- (1) In the case of unmodulated signal (continuous or continuous burst), measure the frequency directly by a frequency meter.
- (2) In the case of burst waves, the measurement shall be done for enough time in order to obtain the enough measuring accuracy, and the average of the measured values becomes the final value.
- (3) In the case of a test mode with a specific frequency spectrum, measure the frequency of the specific spectrum by a spectrum analyzer.
- (4) In the cases above, if the frequency equivalent to the test frequency is not directly measured in principle, it shall be obtained by necessary calculation.
In the case of modulated signal, if there is no specific spectrum measurable by a spectrum analyzer but a specific dip is observed, it is allowed to measure the frequency with the signal generator (synthesized). That is, observe a signal of the signal generator concurrently (or alternately) with the tested signal using the spectrum analyzer while setting the frequency of the signal generator to the position of the dip on the screen of the spectrum analyzer, and determine the frequency of the signal generator at the time as a measured value.



7.5 Test Result



Temperature:	26°C		
Humidity:	54%RH	Test Voltage	DC 5V
Test Mode:	GFSK		

Condition	Frequency	Measured Frequency	Frequency Error	Limit	Verdict
NVNT	MHz	MHz	ppm	(ppm)	
	2402	2401.979	-8.74	±50	Pass
	2440	2439.979	-8.61	±50	Pass
	2480	2479.978	-8.87	±50	Pass
LVNT	2402	2401.976	-9.99	±50	Pass
	2440	2439.975	-10.25	±50	Pass
	2480	2479.974	-10.48	±50	Pass
HVNT	2402	2401.976	-9.99	±50	Pass
	2440	2439.975	-10.25	±50	Pass
	2480	2479.974	-10.48	±50	Pass












STING
ED



CO. LTD



SHENZHEN

8. Antenna Power

8.1 Block Diagram Of Test Setup



8.2 Limit

Item	Limits
Antenna Power Density	(1) $\leq 3\text{mW/MHz}$ (FH, FH+DS, FH+OFDM form 2400 - 2483.5 MHz) (2) $\leq 10\text{mW/MHz}$ (OFDM OBW < 26MHz, DS, FH other than (1)) (3) $\leq 5\text{mW/MHz}$ (OFDM OBW 26-38MHz) (4) $\leq 10\text{mW/MHz}$ (Other than (1) & (2)& (3))
Antenna Power Error	+20%, No Lower Limit (Base on manufacturer declare antenna power density)

Item	Limits
EIRP Power Density	$\leq 16.91\text{dBm/MHz}$ (FH form 2427 - 2470.75 MHz) $\leq 22.14\text{dBm/MHz}$ (OFDM, DS from 2400~2483.5MHz) $\leq 22.14\text{dBm}$ (Other from 2400~2483.5MHz)
Note: This test item is not applied for radio equipment with equivalent isotropic radiation power lower than 12.14dBm/MHz, but Antenna Power(Conducted) limit is 10 mW/MHz (10 dBm/MHz), So the test item will not be applied to the transmission antenna which has a gain of 2.14dBi or less	

8.3 Test procedure

- 1: Measure the total power by Power Meter in a state of hopping mode or non-hopping mode (with Average Sensor)
 - 2: If it's the burst wave, please measure the burst ratio. Then calculate the real total power by burst ratio.
 - 3: Calculate the mean power.
- Output Power Density (mW) = Total Output Power (mW) / Duty cycle

8.4 Test Result


Temperature:	26°C		
Humidity:	54%RH	Test Voltage	DC 5V
Test Mode:	GFSK		

Condition	Test Frequency (MHz)	Antenna Power (dBm)	Antenna Power (mW)	Rated output power (mW)	Antenna Power Error (%)	Limit (mW)	Verdict
NVNT	2402	-3.97	0.40	0.5	-20	10	PASS
	2440	-3.80	0.42		-17		
	2480	-4.37	0.37		-27		
LVNT	2402	-4.08	0.39		-22		
	2440	-3.88	0.41		-18		
	2480	-4.35	0.37		-27		
HVNT	2402	-4.10	0.39		-22		
	2440	-3.87	0.41		-18		
	2480	-4.34	0.37		-26		

Limit: +20%, -80% (Base on manufacturer declare antenna power density)

9. Occupied Bandwidth

9.1 Block Diagram Of Test Setup



9.2 Limit

Item	Limits
Occupied Band Width:	FH 83.5MHz; OFDM,DS ≤ 26 MHz; Others ≤ 26 MHz


9.3 Test procedure



- Setting of SA is following as: RB: 300kHz / VB:300kHz / SPAN: 3MHz / AT: 20dB Ref: 10dBm / Sweep time: Auto / Sweep Mode: Continuous sweep / Detect mode: Positive peak / Trace mode: Max hold
- EUT have transmitted the maximum modulation signal and fixed channelize (For DSSS or OFDM Device) or continuous maximum power of hopping mode(For FHSS Device). SA set to 99% of occupied bandwidth to measure occupied bandwidth. The limit is less than 26MHz (For DSSS or OFDM Device) or 83.5MHz (For FHSS Device).
- SA set to 90% of occupied bandwidth to measure Spread Spectrum Bandwidth.
- Spread Spectrum Factor = Spread Spectrum Bandwidth / modulation rate of EUT.
- Spread Spectrum Factor limit is greater than 5

9.4 Test Result



Temperature:	26°C		
Humidity:	54%RH	Test Voltage	DC 5V
Test Mode:	GFSK		


Condition	Frequency	99%Occupied bandwidth MHz	90%Spread bandwidth MHz	Occupied Bandwidth Limit MHz	Verdict
NVNT	2402	1.232	0.824	≤ 26	Pass
	2440	1.218	0.827	≤ 26	Pass
	2480	1.221	0.822	≤ 26	Pass
LVNT	2402	1.232	0.821	≤ 26	Pass
	2440	1.225	0.826	≤ 26	Pass
	2480	1.224	0.825	≤ 26	Pass
HVNT	2402	1.240	0.819	≤ 26	Pass
	2440	1.218	0.824	≤ 26	Pass
	2480	1.222	0.816	≤ 26	Pass







CO. LTD.














BCTC
BCTC
PPR
Report












10. Unwanted Emission Intensity Measurement

10.1 Block Diagram Of Test Setup



10.2 Limit

Item	RB / VB	Limits
TX Spurious Emission	100KHz	$\leq 2.5 \mu\text{W/MHz}$ (-36dBm) ($30\text{MHz} \leq f \leq 1000\text{MHz}$)
	1 MHz	$\leq 2.5 \mu\text{W/MHz}$ (-26dBm) ($1000\text{MHz} < f \leq 2387\text{MHz}$)
	1 MHz	$\leq 25 \mu\text{W/MHz}$ (-16dBm) ($2387\text{MHz} < f \leq 2400\text{MHz}$)
	1 MHz	$\leq 25 \mu\text{W/MHz}$ (-16dBm) ($2483.5\text{MHz} \leq f < 2496.5\text{MHz}$)
	1 MHz	$\leq 2.5 \mu\text{W/MHz}$ (-26dBm) ($2496.5\text{MHz} \leq f < 12500\text{MHz}$)

10.3 Measuring Instruments And Setting

Please refer to section 5 in this report. The following table is the setting of Spectrum Analyzer.

Spectrum Parameter	Setting
Attenuation	Auto
RB / VB	1 MHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

10.4 Test procedure

1. EUT have transmitted the maximum modulation signal and fixed channelize.
2. Setting of SA is following as: Below 1GHz RB:100KHz / VB:100KHz
Above 1GHz RB:1MHz / VB:1MHz / AT: 20dB Ref: 10dBm / Sweep time: Auto
Sweep Mode: Continuous sweep / Detect mode: Positive peak
Trace mode: Max hold
3. Setting of SA is following as 30MHz and stop frequency 1000MHz Then to mark peak reading value + cable loss shall be less than $0.25 \mu\text{W/MHz}$.
4. Setting of SA is following as 1000MHz and stop frequency 2387MHz Then to mark peak reading value + cable loss shall be less than $2.5 \mu\text{W/MHz}$.
5. SA adjusted to start frequency 2387MHz and stop frequency 2400MHz. Then to mark peak reading value + cable loss shall be less than $25 \mu\text{W/MHz}$.
6. SA adjusted to start frequency 2483.5MHz and stop frequency 2496.5MHz Then to mark peak reading value + cable loss shall be less than $25 \mu\text{W/MHz}$.
7. SA adjusted to start frequency 2496.5MHz and stop frequency 12500MHz Then to mark peak reading value + cable loss shall be less than $2.5 \mu\text{W/MHz}$.

10.5 Test Result


Temperature:	26°C		
Humidity:	54%RH	Test Voltage	DC 5V

Condition	Mode	Frequency (MHz)	Range (MHz)	Emission Frequency (MHz)	Max Value (dBm)	Max Value (μW/MHz)	Limit (μW/MHz)	Verdict
NVNT	GFSK 1Mbps	2402	30-1000	30	-47.95	0.0160	2.5	Pass
NVNT		2402	1000-2387	2382.84	-46.86	0.0206	2.5	Pass
NVNT		2402	2387-2400	2397.97	-33.04	0.4966	25	Pass
NVNT		2402	2483.5-2496.5	2485.45	-55.08	0.0031	25	Pass
NVNT		2402	2496.5-13000	4807.27	-35.02	0.3148	2.5	Pass
NVNT		2440	30-1000	30.97	-48.29	0.0148	2.5	Pass
NVNT		2440	1000-2387	2377.29	-55.6	0.0028	2.5	Pass
NVNT		2440	2387-2400	2395.37	-51.82	0.0066	25	Pass
NVNT		2440	2483.5-2496.5	2483.76	-52.2	0.0060	25	Pass
NVNT		2440	2496.5-13000	4880.79	-34.8	0.3311	2.5	Pass
NVNT		2480	30-1000	30	-47.92	0.0161	2.5	Pass
NVNT		2480	1000-2387	2380.07	-56.23	0.0024	2.5	Pass
NVNT		2480	2387-2400	2395.84	-54.86	0.0033	25	Pass
NVNT		2480	2483.5-2496.5	2483.58	-33.12	0.4875	25	Pass
NVNT		2480	2496.5-13000	4964.82	-34.71	0.3381	2.5	Pass
LVNT		2402	30-1000	30	-48.11	0.0155	2.5	Pass
LVNT		2402	1000-2387	2374.52	-50.77	0.0084	2.5	Pass
LVNT		2402	2387-2400	2397.93	-33.14	0.4853	25	Pass
LVNT		2402	2483.5-2496.5	2489.75	-54.29	0.0037	25	Pass
LVNT		2402	2496.5-13000	4807.27	-35.73	0.2673	2.5	Pass
LVNT		2440	30-1000	30	-47.89	0.0163	2.5	Pass
LVNT		2440	1000-2387	2135.95	-57.09	0.0020	2.5	Pass
LVNT		2440	2387-2400	2399.39	-51.31	0.0074	25	Pass
LVNT		2440	2483.5-2496.5	2487.69	-52.07	0.0062	25	Pass
LVNT		2440	2496.5-13000	4880.79	-35.09	0.3097	2.5	Pass
LVNT		2480	30-1000	30	-47.65	0.0172	2.5	Pass
LVNT		2480	1000-2387	2342.62	-55.9	0.0026	2.5	Pass
LVNT		2480	2387-2400	2395.61	-54.93	0.0032	25	Pass
LVNT		2480	2483.5-2496.5	2483.76	-33.02	0.4989	25	Pass
LVNT		2480	2496.5-13000	4964.82	-35.01	0.3155	2.5	Pass
HVNT		2402	30-1000	30	-48.01	0.0158	2.5	Pass
HVNT		2402	1000-2387	2387	-46.14	0.0243	2.5	Pass
HVNT		2402	2387-2400	2397.82	-33.1	0.4898	25	Pass
HVNT		2402	2483.5-2496.5	2485.63	-54.75	0.0033	25	Pass
HVNT		2402	2496.5-13000	4807.27	-35.37	0.2904	2.5	Pass
HVNT		2440	30-1000	30.97	-47.84	0.0164	2.5	Pass
HVNT		2440	1000-2387	2349.55	-54.78	0.0033	2.5	Pass
HVNT		2440	2387-2400	2399.9	-51.15	0.0077	25	Pass



HVNT		2440	2483.5-2496.5	2483.72	-52.56	0.0055	25	Pass
HVNT		2440	2496.5-13000	4880.79	-35.07	0.3112	2.5	Pass
HVNT		2480	30-1000	30	-48.06	0.0156	2.5	Pass
HVNT		2480	1000-2387	2165.08	-56.93	0.0020	2.5	Pass
HVNT		2480	2387-2400	2388.11	-54.83	0.0033	25	Pass
HVNT		2480	2483.5-2496.5	2483.71	-33.16	0.4831	25	Pass
HVNT		2480	2496.5-13000	4964.82	-34.92	0.3221	2.5	Pass



When the RB=100kHz, RB factor = $10\log(RB0/RB1) = 10\log(1M/100K) = 10dB$





















































































11. Imitation Of Collateral Emission Of Receiver Measurement

11.1 Block Diagram Of Test Setup



11.2 Limit

Item	Limits
RX Spurious Emission:	$\leq 4\text{nW}$ (-54dBm) ($f < 1\text{GHz}$)
	$\leq 20\text{nW}$ (-47dBm) ($1\text{GHz} \leq f$)

11.3 Measuring Instruments And Setting

Please refer to section 5 in this report. The following table is the setting of Spectrum Analyzer.

Spectrum Parameter	Setting
Attenuation	Auto
RB	100 kHz (below 1GHz emissions) 1 MHz (above 1GHz emissions)
VB	100 kHz (below 1GHz emissions) 1 MHz (above 1GHz emissions)
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

11.4 Test procedure


- EUT have the continuous reception mode and fixed only one channelize.
- Setting of SA is following as RB / VB: 100 kHz (below 1GHz emissions) / 1 MHz (above 1GHz emissions) / AT: 6dB / Ref: -20dBm / Sweep time: Auto / Sweep Mode: Continuous sweep / Detect mode: Positive peak / Trace mode: Max hold
- SA set RB: 100kHz and VB: 100kHz. Then adjust to start frequency 30MHz and stop frequency 1000MHz. Search to mark peak reading value + cable loss shall be less than 4nW
- SA set RB: 1MHz and VB: 1MHz. Then adjust to start frequency 1000MHz and stop frequency 12500MHz. Search to mark peak reading value + cable loss shall be less than 20nW
- If power level of lower emissions are more than 1/10 of limit (.0.4nW for $f < 1\text{GHz}$, 2nW for $f \geq 1\text{GHz}$), all those are to be indicated in the 2nd and 3rd lines. If others are 1/10 or less more of the limit, no necessary to be indicated.



11.5 Test Result



Temperature:	26°C		
Humidity:	54%RH	Test Voltage	DC 5V



Condition	Frequency (MHz)	Range (MHz)	Emission Frequency (MHz)	Max Value (dBm)	Max Value (nW)	Limit (nW)	Verdict
NVNT	2402	30-1000	112.45	-66.23	0.2382	4	Pass
NVNT	2402	1000-13000	5188	-57.23	1.8923	20	Pass
NVNT	2440	30-1000	112.45	-66.74	0.2118	4	Pass
NVNT	2440	1000-13000	3412	-51.23	7.5336	20	Pass
NVNT	2480	30-1000	112.45	-65.98	0.2523	4	Pass
NVNT	2480	1000-13000	2464	-61.61	0.6902	20	Pass
LVNT	2402	30-1000	112.45	-66.46	0.2259	4	Pass
LVNT	2402	1000-13000	3748	-63.1	0.4898	20	Pass
LVNT	2440	30-1000	335.55	-64.69	0.3396	4	Pass
LVNT	2440	1000-13000	3724	-63.44	0.4529	20	Pass
LVNT	2480	30-1000	112.45	-66.37	0.2307	4	Pass
LVNT	2480	1000-13000	5632	-63.23	0.4753	20	Pass
HVNT	2402	30-1000	335.55	-66.05	0.2483	4	Pass
HVNT	2402	1000-13000	3736	-63.46	0.4508	20	Pass
HVNT	2440	30-1000	112.45	-66.66	0.2158	4	Pass
HVNT	2440	1000-13000	2440	-62.99	0.5023	20	Pass
HVNT	2480	30-1000	112.45	-66.36	0.2312	4	Pass
HVNT	2480	1000-13000	5764	-62.12	0.6138	20	Pass



CO., LTD.





























12. Transmission Antenna Gain (EIRP Antenna Power) Measurement

12.1 Block Diagram Of Test Setup

For EUT radiation measurement



For standard antenna measurement



12.2 Limit

Item	Limits
EIRP Power Density	$\leq 16.91 \text{ dBm/MHz}$ (FH form 2427 - 2470.75 MHz) $\leq 22.14 \text{ dBm/MHz}$ (OFDM, DS from 2400~2483.5MHz) $\leq 22.14 \text{ dBm}$ (Other from 2400~2483.5MHz)
Note: This test item is not applied for radio equipment with equivalent isotropic radiation power lower than 12.14dBm/MHz, but Antenna Power(Conducted) limit is 10 mW/MHz (10 dBm/MHz), So the test item will not be applied to the transmission antenna which has a gain of 2.14dBi or less	

12.3 Measuring Instruments And Setting

Please refer to section 5 in this report. The following table is the setting of spectrum analyzer.

Spectrum Parameter	Setting
Attenuation	Auto
RB/VB	1 MHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

12.4 Test procedure


1. Set EUT and measuring antenna at the same height and roughly facing each other.
2. Move the measuring antenna height up and down within ± 50 cm of EUT height and swing it to find the maximum output of the measuring antenna. The output level at the spectrum analyzer is read as "E".
3. Remove the EUT from the turn table and put the replacing antenna facing to measuring antenna at same height. Set the standard signal generator (SSG) at same frequency and transmit on then receive the signal
4. Swing the replacing antenna give a maximum receiving level.
5. Move the measuring antenna height up and down within ± 50 cm of replacing antenna height and swing it to find the maximum receiving level.
6. Set SSG output power at Pt to give the equivalent output level of "E" or calculate Pt with SSG output which gives the nearest of "E" and difference (± 1 dB). Record the Pt.
7. Calculate EIRP by the formula below $EIRP = G_t - L + P_t$.
Gt: gain of replacing antenna (dBi)
L: feeder loss between SSG and replacing antenna
Pt: Output power of the SSG
8. If the antenna for the EUT has circular polarization, sum of V-field and H-field will be result if measuring antenna is linear polarization.

12.5 Test Result

The test item will not be applied to the transmission antenna which has a gain of 2.14dBi or less.

13. Transmission Radiation Angle Width (3db Beamwidth) Measurement

13.1 Block Diagram Of Test Setup



13.2 Limit

Item	Limits
3dB antenna beam width	360/A (If A<1; then A=1)
Note: A = E.I.R.P. / (2.14dBi + "Antenna Power (limit)" of each modulation method (*3mW/MHz, 10mW/MHz, etc.))	

13.3 Measuring Instruments And Setting

Spectrum Parameter	Setting
Attenuation	Auto
Span Frequency	0 MHz
RB	1 MHz
VB	1 kHz
Detector	Peak
Trace	Max Hold
Sweep Time	Auto

13.4 Test procedure


1. Set EUT and measuring antenna at the same height and roughly facing each other.
2. Set spectrum analyzer with condition in section 4.7.2 and tune reference level to observe receiving signal position.
3. Rotate directions of the EUT horizontally and vertically to find the maximum receiving power.
4. Move the measuring antenna height up and down within $\pm 50\text{cm}$ of EUT height and swing it to find the maximum output of measuring antenna. The output level at the spectrum analyzer is read as "E".
5. Calculate permitted radiation angle in horizontal and vertical using EIRP measured in another test method.
6. Calculate 3dB antenna beam width by the formula below $360/A$ (If $A < 1$; then $A = 1$).

13.5 Test Result

N/A

14. Radio Interference Prevention Capability Measurement

14.1 Block Diagram Of Test Setup



14.2 Limit

Item	Limits
Identification code	≥ 48 bits

14.3 Measuring Instruments And Setting

Item	Limits
MAC IP List	MAC Scan

14.4 Test procedure

1. In the case that the EUT has the function of automatically transmitting the identification code:
 - a. Transmit the predetermined identification codes form EUT.
 - b. Check the transmitted identification codes with the demodulator.
2. In the case of receiving the identification ocde:
 - a. Transmit the predetermined identification codes form the counterpart.
 - b. Check if communication is normal.
 - c. Transmit the signals other than predetermined ID codes form the counterpart.
 - d. check if the EUT stops the transmission, or if it displays that idnetification codes are different from the predetermined ones.


14.5 Test Result

Temperature:	26 °C		
Humidity:	54%RH	Test Voltage:	DC 5V
Operation Mode:	GFSK	Test result:	PASS

Bluetooth Device Address: E6:5B:90:11:E8:01

15. EUT Photographs



EUT Photo



NOTE: Appendix-Photographs Of EUT Constructional Details
(SANWA RC2E3 _External & Internal Photos)

16. EUT Test Setup Photographs

Measurement Photos



TEST
TC
OVED
t Seal

STATEMENT

1. The equipment lists are traceable to the International System of Units (SI).
2. The test report can not be partially copied unless prior written approval is issued from our lab.
3. The test report is invalid without the "special seal for inspection and testing".
4. The test report is invalid without the signature of the approver.
5. The test process and test result is only related to the Unit Under Test.
6. Sample information is provided by the client and the laboratory is not responsible for its authenticity.
7. The quality system of our laboratory is in accordance with ISO/IEC 17025:2017.
8. If there is any objection to this test report, the client should inform issuing laboratory within 15 days from the date of receiving test report.

Address:

1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China

TEL: 400-788-9558

P.C.: 518103

FAX: 0755-33229357

Website: <http://www.chnbctc.com>

Consultation E-mail: bctc@bctc-lab.com.cn

Complaint/Advice E-mail: advice@bctc-lab.com.cn

***** END *****

