EXHIBIT 8A – FCC MPE PART 15

See Attached

Transmitters do not simultaneously transmit

©2019 Celltech Labs Inc. This document is not to be reproduced in whole or in part without the expressed written permission of Celltech Labs Inc.

Prediction of MPE Limit
47 CFR § 2.1091/ § 2.1093

$$S_{20} = \frac{P_A G_N}{4\pi R_{20}^2} \qquad S_C = \frac{P_A G_N}{4\pi R_C^2} \qquad R_C = \sqrt{\frac{P_A G_N}{4\pi S_L}}$$

$$S_L = \frac{f}{1500} \text{ (mW/cm}^2\text{)}$$

S_{20} = Power Density of the Device at 20cm
S_L = Power Density Limit
S_C = Power Density of the Device at the Compliance Distance R_C
R_{20} = 20cm
R_c = Minimum Distance to the Radiating Element to Meet Compliance
P_T = Power Input to Antenna
P_A = Adjust Power
G_N = Numeric Gain of the Antenna
f = Transmit Frequency

Transmit Duty Cycle = 100%

Use Group = General Popuation

Transmit Duty Cycle:	100.00	(%)
Tx Frequency (f):	433.50	(MHz)
RF Power at Antenna Input Port (P_T):	11.00	(mW)
Antenna Gain:	-2.50	(dBi)
Numeric Antenna Gain (G_N):	0.56	(numeric)
Cable or Other Loss:	0.00	(dB)
Duty Cycle/Loss Adjusted Power (P_A):	11.00	(mW)

S_L =	0.289	(mW/cm^2)
S_{20} at 20cm =	0.001	(mW/cm^2)
R_C =	1.3	(cm)
S_C =	0.29	(mW/cm^2)

RESULT **PASS**

Art Voss		Senior Engineer	Celltech Labs Inc.