
Circuit descriptions

Figure B-1 shows the circuit interface diagram for the Tait Orca handportable radio.

The Tait Orca handportable has been designed to be totally electronically tuned using the *Calibration System for Tait Orca Radios*. The titles in parentheses below refer to tests available in the calibration system. Consult the calibration system *User's Manual* for more information on specific calibration tests.

Transmitter

The RF power amplifier amplifies transmit RF from the VCO to the output power level (4W UHF/5W VHF). The PA output is fed to the PIN switch, which provides isolation between the transmit and receive paths.

A LPF follows the PIN switch and provides attenuation of unwanted high frequency signals.

Following the LPF, the signal is fed to the antenna.

The output power level is controlled by the microprocessor and associated circuitry, and is initially set by calibrating the radio (**Power Level test**).

Transmit (Tx) audio

Tx audio from the microphone is processed into two modulation signals, one required by the TCXO in the synthesiser and the other by the VCO.

A digital pot is used to set the overall deviation and modulation balance; these are controlled by calibration (**Maximum Deviation and Modulation Balance tests**).

Receiver

RF from the antenna is fed via the LPF and PIN switch into the receiver. The RF passes through the front end tuning circuit, which selects the desired frequency. The front end is tuned during calibration (**Front End Tuning test**).

The output of the front end tuning stage is fed to the first mixer, and the VCO provides the local oscillator input. The output of the mixer is at the first IF frequency (45.1 MHz UHF/21.4 MHz VHF).

The IF signal passes through a crystal filter and onto the IF amplifier. From there it goes through a second crystal filter and into the Demod IC.

In the Demod IC, the first IF passes through the second mixer, producing the second IF (455 kHz). The second IF passes through a band pass filter and IF amp, which are external to the IC. The second IF is then fed back into the Demod IC for another amplification stage, then through another external band pass filter. The final stage is the phase lock loop (PLL) discriminator in the Demod IC, which produces detected audio.

A squelch detect circuit uses high frequency audio noise to control the threshold at which the radio mutes and unmutes. This threshold is set up by the microprocessor and can be set during calibration (**Squelch Thresholds test**).

The RSSI output of the detector circuit provides an analogue indication of the received signal strength. RSSI thresholds are set during calibration (**RSSI Thresholds test**).

The receiver can operate on wide/medium or narrow band (TOP-x2xxx radios), or wide or medium band (TOP-x1xxx radios), which is programmable on a per channel basis.