
Circuit descriptions

Circuit interface diagrams for the Tait Orca handportable radios are shown in Figure A-1 (TOP B, C, G, H, I, J and K) and Figure A-2 (TOP A only).

The Tait Orca handportable has been designed to be totally electronically tuned using the *Calibration Application*. The titles of tests referred to below are tests available in the calibration system, e.g. **Power Level** test refers to the **Power Level** screen in the calibration system. Consult the Calibration Application online help or User's Manual for more information on specific calibration tests.

Transmitter

The RF power amplifier amplifies transmit RF from the VCO to the output power level (3W 800/900 MHz, 4W UHF/5W VHF). The PA output is fed to the PIN switch, which provides isolation between the transmit and receive paths.

An LPF follows the PIN switch and provides attenuation of unwanted high frequency signals.

Following the LPF, the signal is fed to the antenna.

The output power level is controlled by the microprocessor and associated circuitry, and is initially set by calibrating the radio (**Power Level** test).

Transmit (Tx) audio

Tx audio from the microphone is processed by the DSP and associated circuitry into two modulation signals, one required by the TCXO in the synthesiser and the other by the VCO.

A digital pot is used to set the overall deviation and modulation balance; these are controlled by calibration (**Maximum Deviation** and **Modulation Balance** tests).

Receiver

RF from the antenna is fed via the LPF and PIN switch into the receiver. The RF passes through the front end tuning circuit, which rejects unwanted frequencies. The front end is electronically tuned, and the front end tuning voltage that sets the centre of the bandpass filter is determined during calibration (**Front End Tuning** test).

The output of the front end tuning stage is fed to the first mixer, and the VCO provides the local oscillator input. The output of the mixer is at the first IF frequency (45.1 MHz UHF/ 21.4 MHz VHF).

The IF signal passes through two crystal filters, separated by the IF amplifier.

In the Demod IC, the signal passes through the second mixer, producing the second IF (455 kHz). The second IF passes through a ceramic band pass filter and IF amp, which are external to the IC. The second IF is then fed back into the Demod IC for another amplification stage, then through another ceramic band pass filter. The final stage is the phase lock loop (PLL) discriminator in the Demod IC, which produces detected audio.

A squelch detect circuit detects high frequency audio noise and compares it with a threshold, which is set up by the microprocessor and can be set during calibration (**Squelch Thresholds** test).

The RSSI output of the detector circuit provides an analogue indication of the received signal strength. RSSI thresholds are set during calibration (**RSSI Thresholds** test).

Receive (Rx) audio

The detected audio is processed by the DSP, amplified and fed to an internal speaker, whose selection is controlled by a line from the

microprocessor. The speaker output is always available on the accessory connector, to drive an external speaker.

The unprocessed audio from the output of the Demod IC (RX-DET-AF) is also available at the accessory connector.

All signalling, such as Selcall, CTCSS, DCS, DTMF and FFSK, and all confidence tones are generated by the DSP.

The DSP operates in half-duplex mode. That is, its CODEC input and output is switched between the Tx and Rx audio paths, according to whether the radio is transmitting or receiving.

Synthesiser and VCO

The synthesiser receives channel frequency information from the microprocessor. It then sets the VCO to the required frequency and maintains its stability using a phase-locked loop. There are one or two VCOs, depending on the radio type. Some bands have one VCO that covers the whole tuning range of the radio plus the IF offset, with its output switched to Tx or Rx. Other bands have a dedicated Tx and Rx VCO.

A lock detect output from the synthesiser (LCK-DET) indicates whether the VCO is producing the correct frequency (the radio is in lock). If the frequency is incorrect, the lock detect status prevents the transmitter from operating, and informs the control microprocessor.

The reference frequency for the synthesiser is provided by the TCXO (temperature compensated crystal oscillator), which is initially set on frequency using a DC voltage at calibration (**TCXO Calibration** test).

Power supplies

+5V-DIG

The +5V-DIG supply provides regulated 5 V to the microprocessor and its associated circuitry. It is controlled by the on/off switch and a line from the microprocessor.

It provides 5 V to all circuitry that requires power when the radio is in economy mode.

+5V-AN

The +5V-AN supply provides the power to all circuitry that requires 5 V when the radio is not in economy mode, mainly all analog circuitry in the receiver, synthesiser and audio modules. It is controlled by a line from the microprocessor and is a regulated supply.

+5V-TX

The +5V TX supply provides power for the exciter stage of the transmitter when the radio is in transmit mode. It is controlled by a line from the microprocessor and is a regulated supply.

+7V5-BATT

The +7V5-BATT supply is the unregulated voltage supplied to the radio from the battery.

+7V5-ACC

The +7V5-ACC supply is supplied to the accessory connector from the battery through a switch and with some current limiting.

+7V5-SW

The +7V5-SW switched supply is unregulated voltage supplied to the radio from the battery through a switch.

+14V

The +14V regulated supply provides the 14 V required by the loop filter in the synthesiser.

A switch mode regulator produces this voltage from the +7V5-SW and +5V-AN supplies.

+4V3-DEC

The +4V3-DEC supply is derived from the +5V-AN voltage. It is used to power the transmit and receive VCOs in conjunction with the transmit control line from the processor. It also provides the loop filter reference in the synthesiser.

Accessory connector interface

The accessory connector interface is described in *Part F: Accessories*.

Universal band versus wideband IF filtering

The IF filtering for the universal band is designed in a way such that it functionally meets specifications for both narrowband as well as wideband systems.

The Deviation and Receive Audio Processing are selectable per channel, which enables the radio to inter-operate between narrowband and wideband channels.