

EXHIBIT B

[FCC Ref. 2.1033(b)(4)]

"Description of Circuit Functions"

21006A Circuit Description :

The following circuit description for model 21006A is base on the circuit diagram and block diagram of 21006A.

21006A Handset :

1. Receiving Path

The receiving path is established by below sections.

Low Noise Amplifier (LNA), Mixer, Demodulator

The RF signal filtering by the Band Pass filter 2.457MHz , and input to LNA of IC T2082 transceiver IC . Then though mixer and GFSK data output from demodulator .

GFSK data demodulate

The GFSK data is output from IC T2082 transceiver IC, then go to DECT controller chip W93511AF/W93513AF for decode to audio and output on pin 85. And audio signal before output to the handset speaker though audio amplifier .

2. Transmitting Path

The transmitting path is established by below sections.

Mic amplifier and encoder

Audio pick up by handset microphone is amplified by internal mic amplifier of U2 of WDCT controller chip W93511AF/W93513F , then go to encoding .

Modulator and RF power amplifier

The GFSK data output from WDCT controller chip, then input to transceiver IC T2802. The modulated signal go to power amplifier T7024, then though band pass filter to antenna

21006A Base Unit :

1. Receiving Path

The receiving path is established by below sections.

Low Noise Amplifier (LNA), Mixer, Demodulator

The RF signal filtering by the Band Pass filter 2.457MHz , and input to LNA of IC T2082 transceiver IC . Then through mixer and GFSK data output from demodulator .

GFSK data demodulate

The GFSK data is output from IC T2082 transceiver IC, then go to DECT controller chip W93510AF/W93523AF for decode to audio and output on pin 85. And audio signal before output to the line interface through audio amplifier .

2. Transmitting Path

The transmitting path is established by below sections.

Audio amplifier and encoder

Audio pick up by line interface is amplified by internal audio amplifier of U1 of WDCT controller chip W93510AF/W93523F , then go to encoding .

Modulator and RF power amplifier

The GFSK data output from WDCT controller chip, then input to transceiver IC T2802. The modulated signal go to power amplifier T7024, then through band pass filter to antenna

3. Telephone line interface

The telephone line interface circuit is established by below sections.

Audio power amplifier

Q3, Q4 & Q12 are built as a power amplifier , according to high current output requirement for line interface.

Line relay & isolation transformer

T1 is the line isolation transformer , both audio input and output is through this transformer . RL1 is the reed relay for line seize , which is controlled Q2.

Ring detect circuit

U5B and U5C are used as a differential amplifier for picks up the ring signal , which is input though two 20M ohm resistor (R16 and R65) as an isolation from the line.

21006A digital security coding system :

The handset and base unit of 21006A will registration on both 20 bit digital random generated security code with manufacturer ID code . This is pass to FCC Part 15.214(d) requirement.

21006A CID system :

The CID signal through R79, R80, C48 and C49 input U13 CID chip to amplifier and go to WDCT W95310AF/W95323F to demodulate the CID data then displayed on Handset LCD display.

21006A CW system :

The CW signal through line isolation transformer input U5A to amplifier and go to WDCT W93510AF/W93523F to demodulate the CW data then displayed on Handset LCD display.