

O44JR1800F447 Circuit Descriptions

Block1 : The buttons of this product.

When Being pressed this remote starts to work.

Block2 : The battery supply the power of 6volts to the circuits.

Block3 : This is the micro-controller.

U1(Micro-controller)reads the button and make the radio transmission circuits work.

Block4 : This is the real time circuit.

XT2 supply the real time clock to the U1.

Block5 : This is the radio power control circuit by U1.

U1 make radio frequency circuits(B7,B9) enable by Block5.

Block6 : U1 can make the modulation by this block.

By switching(between 0V and 4.7V) at VD1 the frequency modulation is done.

Block7 : This is the basic oscillation circuit to radiate the radio frequency.

Q3 oscillates 447.7(MHz) by XT1, L7, C19.

Block8 : Besides 447.7(MHz) will be removed by filter(L6,C17).

Block9 : The third harmonic frequency 447(MHz) of block7 will be amplified at this by Q2.

Block10 : Besides 447.7(MHz) will be removed by filter(L4, C11).

Block11 : The third harmonic frequency 447.7(MHz) of block9 will be amplified at this by Q1

Block12 : Besides 447.7(MHz) will be removed by filter(L1,C1,C2).