

Operation description

BTA-804

1. **Purpose:** The purpose of this document is to describe key component operations on Bluetooth.
2. **Key components:** BTM-001, GlobalSat Bluetooth Module class II, XC6209B332MR High Speed LDO Regulators,
3. **Operation Principle:** GlobalSat BTM-001 Module class II, it provides a fully compliant Bluetooth system for data and voice communications.
Operation at 2.7 ~ 3.3V supply.
Operation clock is provided by 16MHz oscillator.

Key Features

Radio

- Operation with common TX/RX terminals simplifies external matching circuitry and eliminates external antenna switch
- Extensive built-in self-test minimizes production test time
- No external trimming is required in production
- Full RF reference designs are available

Transmitter

- Up to 0dBm RF transmit power with level control from the on-chip 6-bit DAC over a dynamic range greater than 30dB
- Supports Class 2 and Class 3 radios without the need for an external power amplifier or TX/RX switch

Receiver

- Integrated channel filters
- Digital demodulator for improved sensitivity and co-channel rejection
- Digitized RSSI available in real time over the HCI interface
- Fast AGC for enhanced dynamic range

Synthesizer

- Fully integrated synthesizer, no external VCO varactor diode or resonator
- Compatible with crystals between 8 and 32MHz (in multiples of 250KHz) or an external clock

Auxiliary Features

- Crystal oscillator with built-in digital trimming
- Power management includes digital shut down and wake up commands and an integrated low power oscillator for ultra-low Park/Sniff/Hold mode power consumption
- Devices can be used with an external Master oscillator and provides a clock request signal. To control external clock source.
- Uncommitted 8-bit ADC and 8-bit DAC are available to application programs

Baseband and software

- External 8Mbit flash for complete system solution and application flexibility
- 32kbyte on-chip RAM allows full speed Bluetooth data transfer, mixed voice and data, plus full 7 slaves Pico net operation
- Dedicated logic for forward error correction, header error control, access code correlation, demodulation, cyclic redundancy check, encryption bit-stream generation, whitening and transmit pulse shaping

-Transponders for A-law, μ -law and linear voice from host and A-law, μ -law and CVSD voice over air

Physical Interfaces

- Synchronous serial interface up to 4MBaud
- UART interface with programmable Baud rate up to 1.5MBaud
- Full speed USB interface supports OHCI and UHCI host interfaces. Compliant with USB v1.1
- Synchronous bi-directional serial programmable audio interface
- Operational I-CTM Compatible interface

Bluetooth Stack Running on an Internal Micro-controller

CSR's Bluetooth Protocol Stack runs on-chip in a variety of configurations:

- Standard HCI (UART or USB)
- Fully embedded to RFCOMM, thus reducing host CPU load

XC6209B332MR, High Speed LDO Regulators

The XC6209 series are highly precise, low noise, positive voltage LDO regulators. **Maximum Output Current:** 200mA manufactured using CMOS processes. The series achieves high ripple rejection. **Dropout Voltage:** 200mV ($I_{OUT} = 100mA$) and low dropout and consists of a standard voltage source, an error correction, **Maximum Operation Voltage:** 10V current limiter and a phase compensation circuit plus a driver transistor. **Output Voltage Range:** 0.9V - 6.0V in 50mV increments. Output voltage is selectable in 50mV increments within a range of 0.9V ~ 6.0V. **Highly Accurate:** $\pm 2\%$ the series is also compatible with low ESR ceramic capacitors which give added **Low Power Consumption:** TYP 25 μA output stability. This stability can be maintained even during load fluctuations due **Standby Current:** less than 0.1 μA to the excellent transient response of the series. **High ripple Rejection:** 70dB (10kHz). The Current limiter's feedback circuit also operates as a short protect for the output. **Low Output Noise:** 30 μV_{rms} current limiter and the output pin. **Operating Temperature Range:** $-40^{\circ}C \sim +85^{\circ}C$. The CE function enables the output to be turned off, resulting in greatly reduced **Low ESR Capacitor Compatible:** Ceramic capacitor power consumption.