

Low Energy Consuming
Mini WiFi Camera

Instruction Manual

Thank you for your choosing, please follow the Instruction Manual to use the camera. Please follow the Instruction Manual Step-by-Step to setup the camera successfully.

Related operation videos can be found on YouTube or Anlork website.

www.anlork.com
Home > Support > F1-Smallest WiFi Camera

YouTube
discover tecs

Note:Only support 2.4G WiFi
Most routers have 2.4G/5G dual signal options, please choose 2.4G network.

Catalog

Features..... Page 1
Interface description..... Page 2
Interface use..... Page 3
Start to use..... Page 4
APP installation..... Page 5
Hotspot setting..... Page 7
WiFi setting..... Page 15
APP interface Page 18
Function setting Page 19
Specifications..... Page 20
Package Page 21
Notes..... Page 22
After sales service Page 23
Installation method..... Back cover

Features

- ◆ The camera can be used while charging.
- ◆ Support Hotspot, WiFi and 4G mobile network to view.
- ◆ Built-in 850mA lithium battery.
- ◆ Continuous recording time: 6 hours.
- ◆ Supports night vision mode, built-in infrared light.
- ◆ SD card max capacity 128Gb(Not included).
- ◆ Built-in Microphone.
- ◆ Supportst motion detection.
- ◆ Supports multiple users to connect and view at the same time.
- ◆ Built-in magnet, the camera can be attached on any magnetic surface easily.
- ◆ Supports IOS and Android smart phones.
- ◆ USB charging cable can be used for reading SD card file.

Note:
Please charging the camera for 1 to 3 hours before your first using.

Interface description

Signal lights ON/OFF Force Shutdown RESET

Micro SD Micro USB : Charging interface

Interface use

- ◆ Turn ON:
Hold the ON/OFF button for 2 seconds until the red and blue lights flash together. Wait until the blue light bright and the camera hotspot powers on.
- ◆ Turn OFF:
Hold the ON/OFF button for 5 seconds until the red and blue lights flashes turn off together. the device will power off.
- ◆ Force Shutdown:
Press the small hole between ON / OFF and RESET using a thin object.
- ◆ Reset to factory setting:
Hold the RESET button for 2 seconds wait until the red and blue lights flashes turn off, the camera will power off.

Note:
During the connection process, please observe the color and status of the indicator light (The above is the indicator color display without SD card).

Start to use

APP installation

Connect to camera hotspot

Add camera

Get real-time video in hotspot mode

Connect to router, Configure camera WIFI

Get real-time video in WIFI mode

APP installation

IOS: Search “Video0” in App Store.
Android: Search “Video0” in Android market.
You can also scan the below QR code to install.

IOS

Android

Video0

Note:
Camera App Video0, the last Digit is Zero-0, not letter-o, please note this when download the camera App.

Note:
In order to ensure the normal use of APP functions, please agree to the relevant authorization.

Note:

There are two ways to add a camera , auto mode and manual mode.

Auto Mode:
When the phone WIFI selects the camera ID, the APP will automatically detect and add the camera.

Manual Mode:
Due to the mobile phone system and version, the APP cannot automatically detect and add a camera. At this time, You need to add cameras in manual mode.

In order to use the camera quickly, after the hotspot mode connection is successful, we will connect to the WIFI.

Thank you for your understanding.

Hotspot setting(Auto Mode)

Hotspot mode:
Without internet access, you can also use the hotspot working mode of the wireless camera for short-distance viewing.

Step1:Hold the ON/OFF button for 2 seconds until the red and blue lights flash together. Wait until the blue light bright and the camera hotspot powers on.

Step2:Enter“Wi-Fi” setting, connecting hotspot in “JS-XXXXXX”.

Note:
In auto mode, Need to open the location services of the phone.

Step3: Open “Video0”

At this time, The APP will prompt whether to connect to the router.

Choose "Cancel"First enter the hotspot mode to watch the video, and then connect to WIFI.

Step4: Click “Cancel” ,Get real-time video in hotspot mode.

At this time, the hotspot mode connection is successful, and you can watch real-time video in a short distance.

Next step, please check page 15, how to set up WiFi.

Hotspot setting(Manual Mode)

Step1:Hold the ON/OFF button for 2 seconds until the red and blue lights flash together. Wait until the blue light bright and the camera hotspot powers on.

Step2:Enter“Wi-Fi” setting, connecting hotspot in “JS-XXXXXX”.

Note:
Please confirm that the mobile phone WIFI has been connected to the camera ID (JS-XXXXXX).
◆ If you cannot find the camera ID, please reset the camera.

Step3: Open “Video0” , click

At this time, The APP will prompt whether to connect to the router.

Choose "Cancel"First enter the hotspot mode to watch the video, and then connect to WIFI.

Step4: Click “Been connected to the router”.

At this time, the hotspot mode connection is successful, and you can watch real-time video in a short distance.

Next step, please check page 15, how to set up WiFi.

Step5:Click the information display area.

9WS5EG/TWLHBDHP111A
92-H0-BE11

UID 9WS5EG/TWLHBDHP111A
Device Password hk123456
Device Name Camera

The camera's UID, Device Password and Device Name are default(No changes needed).

Password default:hk123456

Step6: Click to save parameters, add camera.

System display:“Camera successfully added”

Step7: Click image to view

At this time, the hotspot mode connection is successful, and you can watch real-time video in a short distance.

Step8: Click to enter live image viewing

At this time, the hotspot mode connection is successful, and you can watch real-time video in a short distance.

Note: Hotspot mode is complete.

At this time, the hotspot mode connection is successful, and you can watch real-time video in a short distance.

WiFi setting

Please set the hotspot before setting up the WiFi network.

Step1: Click to enter WIFI setting.

Step2: Click“WiFi setting” to enter the setting.

Step3: Select the router name and password, and click “Connect” ,the WiFi connection will begin.

The red and blue lights flash together. wait Until the red light is on, the WiFi connection is successful(without SD card)

Note:
◆ WiFi name cannot include spaces.
◆ Most router have 2.4G/5G dual signal options, please choose 2.4G network.
◆ The camera connect to WiFi at the first time, please close to router and mobile phone.

Step4: Touch the image viewing area to view Real-time video.

WiFi mode is complete.

Note:
If you go out or switch networks on your phone, The camera may not be online. Because the app is Disconnected from the camera, the monitor does not display Online; refresh the device or restart the APP.

If you replace the router, you need to do the following:
1. Reset the camera.
2. Connect the camera to the new WiFi.

APP interface

Online mode Date/Time display Video button View video and alarm pictures in SD card Monitor ON/OFF Day/Night mode switch Image display Full screen Shoot the picture button Flip images vertically Resolution selection

Function setting

Change camera password Detection ON/OFF Signal lights ON/OFF Product model/version Sync phone date and time WiFi setting SD card storage Reset default password Remove this device

Specifications

- Resolution: 1080P/720P
- Viewing angle: 120 degree
- Number of frames: 25fps
- Video format: AVI
- Picture format: JPEG
- Battery capacity: 850mA lithium battery
- Continuous recording time: 6 hours
- Charging Time:3-5hours
- Maximum SD card capacity: 128Gb
- Infrared night vision distance:18ft
- Microphone: Yes
- Motion detection:Yes
- Connection method: Hotspot/WiFi/4G
- Access method: Phone/Tablet PC
- Smart Phone: IOS/Android
- Voltage input: DC5V/1A
- Interface: Micro USB
- Product size: 1.6 x1.6 x 0.5Inch
- Product weight: 1.1oz

Package

- 1x Mini Camera
- 1x Magnetic Bracket
- 1x User Manual
- 1x Double-sided Tape
- 1x Flexible Rigid Cable
- 1x USB Charging Cables

Note:
◆ The USB charging Cable has a data transmission function. When the charging cable is connected to a computer,the information on the SD card can be read.
◆ Flexible rigid cable just for charging.
◆ The infrared light is turned off, battery can work for 6 hours.

Notes

- ◆ Please turn off the camera before inserting or removing the SD card. Otherwise, the SD card will be damaged.
- ◆ The camera does not has PC software, you can view the contents of the SD card on the computer.
- ◆ The camera connect to WiFi at the first time, please close to router and mobile phone.
- ◆ Please adjust the camera angle to avoid infrared light reflection, so as not to cause the image to become white.
- ◆ The accuracy of motion detection will be affected by light, angle, target size and network, etc.
- ◆ To ensure the stability of the camera, the Day / Night mode is manual switching.
- ◆ If the camera hotspot name cannot be found, please press the RESET to restart.
- ◆ The yellow indicator light is always on during charging. When it is off, the battery is fully charged.

After sales Service

E-mail : discovertecs@gmail.com

Video Guide:
How to setting Hotspot and WiFi

YouTube
discover tecs

Related operation videos can be found on YouTube or Anlork website.

www.anlork.com
Home > Support > F1-Smallest WiFi Camera

Dear customers,

To those who are really interested in our product Anlork wifi cameras,We are very grateful for your choice !

We sincerely apologize but wish you all could give us the chance to help you with the problems you meet while using our cameras. It is normal to have issues with Hi-tech products, and please keep patient to ask for our help.

Thank you in advance for your kindness. God will always bless those heart-kind mans.

We highly recommend you to read the manual attached in the package before setting up the camera. If you find it too small to read, you can ask for PDF document via email.

Best wishes,
Anlork

Flexible Installation

Can be placed in standing position for video recording 0.5in 1.0in Double-sided Tape Magnet Bracket Flexible Rigid Cable With Back Magnetic

Application:
You can place it anywhere, it is small enough, very convenient to install and hide, such as doorways, garages, gardens, courtyards, rooms, offices, apartments, rental houses, cars, camping, etc., as well as your temporary monitoring needs because of it Small, it has a battery, which is very suitable for your needs!

V1.0-20211109

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.